

[manuals.plus](#) /

› [MOOKA](#) /

› [MOOKA Air Purifiers M01 & M02 User Manual](#)

MOOKA M01, M02

MOOKA Air Purifiers M01 & M02 User Manual

Models: M01, M02

1. INTRODUCTION

Thank you for choosing MOOKA Air Purifiers M01 and M02. These devices are designed to improve your indoor air quality by effectively removing various airborne contaminants. This manual provides essential information for the safe and efficient operation, maintenance, and troubleshooting of your air purifier.



Image: MOOKA Air Purifiers M01 (left) and M02 (right) demonstrating their compact design and air purification capabilities.

2. PRODUCT OVERVIEW

2.1 Key Features

- **High-Efficiency Filtration:** Both models feature a 4-stage filtration system including a protective shell, pre-filter, true H13 HEPA filter, and high-efficiency activated carbon filter to capture pollen, pet hair, dander, smoke, odor, and dust particles.
- **Wide Coverage:** Model M01 covers up to 430 sq.ft., while Model M02 covers up to 1095 sq.ft., suitable for various room sizes from bedrooms to large living areas.
- **Quiet Operation:** Operates at a low noise level of 20dB in sleep mode, ensuring undisturbed rest or work.
- **Adjustable Settings:** Offers 4 fan speeds (Low, Medium, High, Sleep) and 4 timer settings (2H, 4H, 6H, 8H) for customized air purification.
- **Night Light Function:** Integrated night light feature with the option to turn off all lights for a dark sleeping environment.
- **Filter Replacement Reminder:** An indicator light flashes after approximately 2160 hours of use, signaling the need for filter replacement.

- **Ozone-Free & Certified:** Does not produce ozone or use UV-light. Complies with California Air Resources Board (CARB), FCC, and ETL certifications.

2.2 Product Components

Familiarize yourself with the main components of your MOOKA Air Purifier:

- Air Outlet Grille
- Control Panel
- Air Quality Indicator Light
- Main Body
- Air Inlet
- Filter Compartment (located at the bottom)
- USB-C Power Port (M01) / AC Power Port (M02)



Image: The compact MOOKA M01 air purifier, highlighting its USB-C power compatibility for use with laptops, car chargers, and power banks, making it suitable for various environments.

3. SETUP

- 1. Unpack:** Carefully remove the air purifier from its packaging.
- 2. Remove Filter Packaging:** Before first use, open the filter compartment (usually at the bottom of the unit) and remove the plastic packaging from the HEPA filter. Reinsert the filter and close the compartment securely.
- 3. Placement:** Place the air purifier on a flat, stable surface. Ensure there is at least 6 inches (15 cm) of space around all sides for optimal air circulation.
- 4. Power Connection:**
 - For Model M01: Connect the provided USB cable to the USB-C port on the unit and plug the other end into a compatible 5V/2A USB power adapter (not included), laptop, car charger, or power bank.
 - For Model M02: Connect the power cord to the AC power port on the unit and plug it into a standard electrical outlet.

4. OPERATING INSTRUCTIONS

Your MOOKA Air Purifier features an intuitive control panel for easy operation.



Image: Detailed view of the MOOKA M01 control panel, illustrating the functions of each button and indicator for user

convenience.

4.1 Control Panel Functions

- **Power Button ()**: Press to turn the unit ON or OFF.
- **Fan Speed Button (Ξ)**: Press repeatedly to cycle through fan speeds: Low (I), Medium (II), High (III), and Sleep mode (fan icon with crescent moon).
- **Timer Button ()**: Press repeatedly to set the operating timer for 2, 4, 6, or 8 hours. The unit will automatically turn off after the selected time.
- **Night Light Button ()**: Press to turn the night light ON or OFF.
- **Child Lock Button ()**: Press and hold for 3 seconds to activate or deactivate the child lock. When activated, other buttons will not respond.
- **Filter Reset Button (:=)**: After replacing the filter, press and hold this button for 3 seconds to reset the filter life indicator.

4.2 Adding Fragrances (M01 Only)

The M01 model includes a fragrance sponge compartment for adding essential oils or other liquid fragrances.

1. Locate the fragrance sponge compartment on the top of the unit, near the control panel.
2. Open the cover of the compartment.
3. Add a few drops of your desired essential oil onto the sponge. Do not pour liquid directly into the unit.
4. Close the compartment cover securely.

Add Fragrances



Image: Illustrates the process of adding essential oils to the dedicated fragrance sponge compartment on the MOOKA M01 air purifier, allowing for a pleasant aroma in the purified air.

5. MAINTENANCE

5.1 Filter Replacement

The filter life indicator light will flash after approximately 2160 hours of operation, signaling that the filter needs to be replaced to maintain optimal performance.

- 1. Power Off:** Unplug the air purifier from the power source.
- 2. Access Filter:** Turn the unit upside down. Twist the base cover counter-clockwise to unlock and remove it.
- 3. Remove Old Filter:** Pull out the old filter.
- 4. Install New Filter:** Insert a new MOOKA H13 HEPA replacement filter (ensure plastic packaging is removed) into the unit.
- 5. Secure Base:** Replace the base cover and twist clockwise to lock it securely.
- 6. Reset Filter Indicator:** Plug the unit back in. With the unit powered on, press and hold the "RESET" button on the control panel for 3 seconds until the indicator light turns off.

Note: Filter life may vary depending on air quality and usage. Replace the filter every 3-6 months for best results.

5.2 Cleaning

- **Exterior:** Wipe the exterior of the air purifier with a soft, dry cloth. Do not use abrasive cleaners or solvents.
- **Pre-filter:** The pre-filter (outer layer of the composite filter) can be gently vacuumed to remove large dust particles and pet hair between filter replacements. Do not wash the HEPA or activated carbon filter.
- **Fragrance Sponge (M01):** If using the fragrance sponge, clean or replace it periodically to prevent residue buildup.

6. TROUBLESHOOTING

If you encounter any issues with your air purifier, please refer to the following table:

Problem	Possible Cause	Solution
Unit does not turn on.	Not plugged in correctly; Power adapter issue (M01); Power outlet issue; Child lock activated.	Ensure power cable is securely connected. Try a different power outlet. For M01, ensure power adapter is 5V/2A. Deactivate child lock by pressing and holding the lock button for 3 seconds.
Airflow is weak or noise increases.	Filter is dirty or clogged; Air inlets/outlets are blocked.	Check and replace the filter if the filter indicator is flashing or if it appears visibly dirty. Ensure nothing is obstructing the air inlets or outlets.
Odor coming from the unit.	New filter odor; Filter needs replacement.	A slight odor may be present with a new filter, which will dissipate. If odor persists, replace the filter.
Filter reset light remains on after filter change.	Filter reset button not pressed correctly.	With the unit powered on, press and hold the "RESET" button for 3 seconds until the light turns off.

7. SPECIFICATIONS

Feature	Specification
Brand	MOOKA
Models	M01, M02
Filtration System	4-Stage (Pre-filter, H13 HEPA, Activated Carbon)
Coverage Area (M01)	Up to 430 Sq.Ft.

Feature	Specification
Coverage Area (M02)	Up to 1095 Sq.Ft.
Noise Level (Sleep Mode)	20 dB
Controller Type	Button Control
Wattage	1 Milliwatts (M01)
Certifications	CARB Certified, FCC Certified, ETL Listed

8. WARRANTY AND SUPPORT

MOOKA provides the following assurances for your product:

- **Return Policy:** 90-days return period from the date of purchase.
- **Exchange Policy:** 2-year exchange policy for manufacturing defects.

For any questions, concerns, or support needs, please contact MOOKA customer service through the retailer's platform or the official MOOKA website. Please have your purchase details and product model number ready when contacting support.