

[Manuals.plus](#) /

> [UGREEN](#) /

> UGREEN Nexode Power Bank 25000mAh 200W Laptop Portable Charger PD 3.1 Fast Charging 90Wh 3-Port Battery Pack with TFT Smart Display User Manual

## UGREEN 35525

# UGREEN Nexode Power Bank 25000mAh 200W User Manual

Model: 35525 | Brand: UGREEN

## INTRODUCTION

Thank you for choosing the UGREEN Nexode Power Bank 25000mAh 200W. This portable charger is designed to provide high-speed power delivery for a wide range of devices, including laptops, smartphones, and tablets. With its large capacity and advanced features like the TFT smart display, it ensures reliable and efficient charging on the go. Please read this manual carefully before use to ensure proper operation and maintenance.

## SAFETY INFORMATION

- Do not expose the power bank to extreme temperatures (above 60°C/140°F) or direct sunlight.
- Avoid dropping, disassembling, or attempting to repair the device yourself.
- Keep away from water, moisture, and flammable materials.
- Use only certified charging cables and adapters.
- Keep out of reach of children.
- Dispose of the power bank responsibly according to local regulations.

## PACKAGE CONTENTS

- UGREEN Nexode Power Bank 25000mAh 200W
- USB-C to USB-C Charging Cable
- User Manual

## PRODUCT OVERVIEW

The UGREEN Nexode Power Bank features a compact, power-column design with multiple ports and an intuitive TFT smart display for real-time information.



Image: The UGREEN Nexode Power Bank in its sleek grey finish, shown alongside its accompanying USB-C to USB-C charging cable.

# 25000mAh

## Large Capacity

iPad Pro 11"  
**2.6**  
Charges

iPhone 15  
**5.2**  
Charges

MacBook Pro 14"  
**0.94**  
Charges

Galaxy S24 Ultra  
**3.6**  
Charges

\*All data are theoretical estimated values obtained by Ugreen's lab. The actual performance may vary.



Image: A close-up view of the power bank's TFT smart display, illustrating the real-time battery level, remaining time, and individual port output/input power, voltage, and current readings.

# TFT Smart Display



Image: A user on a train charging a laptop, smartphone, and wireless earbuds case simultaneously using the UGREEN Nexode Power Bank, demonstrating its multi-device charging capability.

# 65 Fast Recharging

Enjoy Quick Recharging  
for On-the-go Convenience



\*Data comes from UGREEN's lab tests conducted under particular conditions. The actual performance may vary.

Image: The power bank connected to a wall charger, with the display indicating a 65W fast recharging input, highlighting its quick recharge feature.

## SETUP

1. **Initial Charge:** For optimal performance, fully charge the power bank before first use. Connect the included USB-C to USB-C cable to the power bank's input port and a compatible 65W (or higher) USB-C power

adapter. The TFT display will show the charging progress. A full charge from 0% to 100% takes approximately 2.5 hours with a 65W charger.

2. **Check Battery Level:** The TFT display provides real-time battery percentage and estimated remaining time.

## OPERATING INSTRUCTIONS

---

### Charging Your Devices

The UGREEN Nexode Power Bank features two USB-C ports and one USB-A port, allowing you to charge up to three devices simultaneously with a total output of 200W.

- **Connect Devices:** Use appropriate charging cables to connect your devices to the power bank's USB-C (C1/C2) or USB-A (A) ports.
- **Automatic Detection:** The power bank will automatically detect the connected device and deliver the optimal charging speed.
- **TFT Display:** The display will show the real-time output power (in Watts) for each connected port, along with voltage and current.

Your browser does not support the video tag.

Video: A short demonstration of the power bank's fast recharging capability, showing the display updating with charging wattage.

### Recharging the Power Bank

To recharge the power bank, connect it to a wall charger using the provided USB-C cable. For the fastest recharge (approximately 2 hours), use a 65W USB-C PD charger.

Your browser does not support the video tag.

Video: A brief clip showcasing the portability of the power bank, emphasizing its ability to charge devices anywhere, anytime.

### TFT Smart Display Functions

The TFT display provides comprehensive real-time information:

- **Battery Level:** Shows the current percentage of charge remaining.
- **Remaining Time:** Estimates the time until the power bank is fully charged or depleted.
- **Output/Input Power:** Displays the wattage being delivered to or received from each port.
- **Voltage & Current:** Provides real-time voltage and current readings for precise monitoring.
- **Power Curve:** Visual representation of power flow.

### Trickle Charging Mode

For low-power devices like smartwatches or Bluetooth earbuds, the power bank supports a trickle charging mode to prevent overcharging and protect the device's battery. This mode is automatically engaged when a low-power device is connected.

Your browser does not support the video tag.

Video: A quick demonstration of the power bank's fast charging capabilities for various devices.

## MAINTENANCE

---

- **Cleaning:** Wipe the power bank with a soft, dry cloth. Do not use liquid cleaners or aerosols.
- **Storage:** Store in a cool, dry place away from direct sunlight and extreme temperatures. For long-term storage, it is recommended to keep the power bank charged to around 50-70% to preserve battery health.
- **Battery Life:** The power bank is designed to retain over 80% capacity after 1000 charge-discharge cycles.

## TROUBLESHOOTING

---

Problem	Possible Solution
Power bank not charging	Ensure the charging cable and wall adapter are working correctly. Use a 65W or higher PD charger for optimal input. Check if the cable is securely connected to both the power bank and the adapter.
Devices not charging	Verify that the power bank has sufficient charge. Try a different charging cable or port. Ensure your device is compatible with the power bank's output specifications.
Slow charging	Check if your device supports fast charging protocols (PD 3.1). Ensure you are using a high-quality, compatible cable. The total output is shared among multiple devices; charging fewer devices may increase individual charging speeds.
Display not working	Ensure the power bank is not completely depleted. If the issue persists, contact customer support.

## SPECIFICATIONS

---

- **Model Number:** 35525
- **Battery Capacity:** 25000mAh
- **Max Output:** 200W
- **Input:** USB Type C (PD 3.1)
- **Output Ports:** 2 x USB Type C, 1 x USB Type A
- **Dimensions:** 6.1 x 2.13 x 1.97 inches
- **Item Weight:** 1.12 pounds
- **Battery Type:** Lithium Polymer
- **Special Features:** PD 3.1 Fast Charging, TFT Smart Display, Power-column Design

## WARRANTY AND SUPPORT

---

UGREEN products come with a standard warranty. For detailed warranty information, technical support, or customer service inquiries, please visit the official UGREEN website or contact their customer support team directly. Keep your purchase receipt for warranty claims.

For more information, visit: [www.ugreen.com](http://www.ugreen.com)