

[manuals.plus](#) /› [Gyration](#) /› [Gyration Cyberview 2000 2 Megapixel Indoor Full HD Network Camera User Manual](#)

Gyration Cyberview 2000

Gyration Cyberview 2000 Indoor Full HD Network Camera User Manual

Model: Cyberview 2000

1. INTRODUCTION AND OVERVIEW

This manual provides comprehensive instructions for the installation, operation, and maintenance of your Gyration Cyberview 2000 Indoor Full HD Network Camera. Please read this manual thoroughly before using the product to ensure proper functionality and safety.

Key Features:

- High-quality 2 Megapixel image sensor (1920x1080 at 15fps).
- 3X Digital Zoom for detailed viewing.
- Pan and Tilt functionality for wide area coverage (355° Pan, 90° Tilt).
- Two-way audio with built-in microphone and speaker.
- Infrared night vision with a range of 7 meters for 24-hour monitoring.
- Motion detection with intelligent push notifications.
- Supports Micro SD card storage (up to 128 GB) and cloud storage.
- Wi-Fi connectivity for easy setup and remote access.
- Compatible with Amazon Alexa and Google Assistant.

2. SETUP GUIDE

2.1 What's in the Box

Please verify that all components are present before proceeding with installation.

- Gyration Cyberview 2000 Camera
- Power Adapter (Corded Electric)
- Mounting Accessories (if applicable, for tabletop mount)
- User Manual (this document)

2.2 Physical Installation

The Cyberview 2000 camera is designed for indoor use and supports tabletop mounting. Place the camera on a stable, flat surface in the desired monitoring area. Ensure the camera has a clear line of sight and is within range of your Wi-Fi network.



Image 1: Front view of the Gyration Cyberview 2000 camera.

2.3 Power Connection

Connect the provided power adapter to the camera's power input port and then plug it into a standard electrical outlet. The camera will power on automatically.

2.4 App Installation and Account Creation

To operate the camera, download the "CyberView Plus" app from your mobile device's app store (available for Android and iOS). Follow the in-app instructions to create an account and log in.

2.5 Wi-Fi Connection

Within the CyberView Plus app, select "Add Device" and follow the on-screen prompts to connect your camera to your home Wi-Fi network. This typically involves scanning a QR code displayed on your phone with the camera or entering your Wi-Fi credentials.

3. OPERATING INSTRUCTIONS

3.1 Live View and Remote Monitoring

Once connected, open the CyberView Plus app to access the live video feed from your camera. You can monitor your space remotely from anywhere with an internet connection.



Image 2: Screenshot of the mobile app showing remote monitoring and notifications.

3.2 Pan and Tilt Control

Within the live view interface of the app, use the directional controls to pan the camera horizontally (355°)

and tilt it vertically (90°) to adjust the viewing angle as needed. The 3X digital zoom can be activated by pinching the screen.



Image 3: Diagram illustrating the 355° pan and 90° tilt capabilities of the camera.

3.3 Two-Way Audio and Call Button

The camera features a built-in microphone and speaker, enabling two-way communication. Tap the microphone icon in the app to speak through the camera. The physical call button on the camera allows someone at the camera's location to initiate a call to your connected mobile device.

With the built-in waterproof and dustproof microphone and Hi-Fi speaker, you can warn remotely to stop the loss in case of an emergency. For family and friends, live chat to experience intimate interactions, regardless of time and location.



CALL BUTTON FOR TWO WAY AUDIO

Image 4: Close-up of the camera showing the call button, highlighting two-way audio functionality.

3.4 Night Vision

The Cyberview 2000 automatically switches to infrared night vision in low-light conditions, providing clear black and white video up to 7 meters. The IR-CUT filter ensures accurate color representation during the day.



FULL COLOR INFRARED NIGHT VISION

Image 5: Split image demonstrating the clarity of night vision compared to a scene without it.

3.5 Motion Detection and Alerts

Configure motion detection settings within the app to receive instant alerts on your mobile device when activity is detected. You can define specific activity zones to reduce false alarms.



MOTION DETECTION & REAL-TIME ALERT

Image 6: Illustrates the camera detecting motion and sending an alert.

3.6 Storage Options (Cloud and Micro SD)

The camera supports local storage via a Micro SD card (up to 128 GB, not included). Insert the Micro SD card into the designated slot on the camera. Additionally, the camera supports cloud streaming and storage, with a free 3-day rolling cloud storage for 2 years.



Image 7: Depicts the cloud storage feature and an event timeline within the app.

4. MAINTENANCE

4.1 Cleaning the Camera

To maintain optimal image quality, periodically clean the camera lens and body. Use a soft, dry cloth to wipe away dust. For stubborn marks, slightly dampen the cloth with water. Avoid using harsh chemicals or abrasive cleaners.

4.2 Firmware Updates

Ensure your camera's firmware is up to date for the best performance and security. The CyberView Plus app will typically notify you of available firmware updates. Follow the in-app instructions to perform updates. Do not power off the camera during a firmware update.

5. TROUBLESHOOTING

Refer to the table below for common issues and their solutions.

Problem	Solution
---------	----------

Problem	Solution
Camera not powering on.	Ensure the power adapter is securely connected to both the camera and a working electrical outlet. Try a different outlet.
Unable to connect to Wi-Fi.	Verify your Wi-Fi network name and password are correct. Ensure the camera is within range of your Wi-Fi router. Restart your router and the camera. The camera supports 2.4GHz Wi-Fi networks only.
No live video feed.	Check your internet connection. Ensure the camera is powered on and connected to Wi-Fi. Restart the app and the camera.
Motion alerts not received.	Check app notification settings on your phone and within the CyberView Plus app. Ensure motion detection is enabled and activity zones are correctly configured.
Micro SD card not recording.	Ensure the Micro SD card is inserted correctly and is not full. Format the SD card through the app if it's new or causing issues. The camera supports up to 128GB.
Poor image quality.	Clean the camera lens. Ensure adequate lighting. Check your internet speed for streaming issues.

6. TECHNICAL SPECIFICATIONS

Feature	Detail
Model Name	CyberView 2000
Image Sensor	2 Megapixel, 1/2.3" CMOS
Video Resolution	1920x1080 @ 15fps (Full HD)
Video Compression	H.264, MJPEG
Digital Zoom	3X
Pan/Tilt Range	Pan 355°, Tilt 90°
Night Vision	Infrared, up to 7m distance
Audio	Built-in Mic & Speaker (Two-way audio)
Storage	Micro SD card (max 128 GB), Cloud Storage
Connectivity	Wi-Fi (2.4GHz)
Power Source	Corded Electric, 5 Volts
Compatible Devices	Smartphone (Android/iOS), Amazon Alexa, Google Assistant

Feature	Detail
Indoor/Outdoor Usage	Indoor
Dimensions (L x W x H)	6.2 x 3.7 x 3.4 inches
Item Weight	12.7 ounces
UPC	744390953460

7. WARRANTY AND SUPPORT

Gyration products are manufactured to high-quality standards. This product comes with a limited warranty against defects in materials and workmanship. Please refer to the warranty card included with your purchase or visit the official Gyration website for detailed warranty terms and conditions.

For technical support, troubleshooting assistance, or warranty claims, please contact Gyration Customer Service:



- Website:** www.gyration.com (Placeholder, actual website not provided in data)
- Email:** support@gyration.com (Placeholder, actual email not provided in data)
- Phone:** 1-800-XXX-XXXX (Placeholder, actual phone number not provided in data)

Please have your product model number (Cyberview 2000) and purchase date ready when contacting support.

© 2024 Gyration. All rights reserved.

Related Documents - Cyberview 2000

 <p>GYRATION® Cyberview3020 Smart PTZ Battery Camera Solar Recharging Kit User manual</p>	<p>Gyration Cyberview3020 Smart PTZ Battery Camera Solar Recharging Kit User Manual User manual for the Gyration Cyberview3020 Smart PTZ Battery Camera with Solar Recharging Kit. Learn about setup, installation, features, and troubleshooting for this wireless security camera.</p>
 <p>GYRATION® Cyberview2000 Smart PTZ Camera User manual</p>	<p>Gyration Cyberview2000 Smart PTZ Camera User Manual - Setup, Installation, Specifications Comprehensive user manual for the Gyration Cyberview2000 Smart PTZ Camera. Covers setup, Wi-Fi binding, installation, sharing features, product specifications, and regulatory compliance. Includes app download information.</p>

 <p>GYRATION® Cyberview3000 Smart Video Doorbell kit User manual</p>	<p>Gyration Cyberview3000 Smart Video Doorbell User Manual Comprehensive user manual for the Gyration Cyberview3000 Smart Video Doorbell kit, detailing installation, setup, features, and troubleshooting.</p>
 <p>AIR MOUSE® VOICE Quick Start Guide Gyration</p>	<p>Gyration Air Mouse Voice Quick Start Guide A comprehensive quick start guide for the Gyration Air Mouse Voice, detailing setup, features like In-Air and Voice modes, MotionTools software customization, and warranty information.</p>
 <p>GYRATION® Cyberview3020 Smart PTZ Battery Camera Solar Recharging Kit User manual</p>	<p>Gyration Cyberview3020 Smart PTZ Battery Camera Solar Recharging Kit User Manual User manual for the Gyration Cyberview3020 Smart PTZ Battery Camera with Solar Recharging Kit. Learn about setup, installation, features, and troubleshooting for this wireless security camera.</p>
 <p>Yacht Devices User Manual NMEA 2000 Wi-Fi Router YDNR-02N Version 1.0 2022-01-01</p>	<p>Yacht Devices NMEA 2000 Wi-Fi Router YDNR-02N User Manual Comprehensive user manual for the Yacht Devices NMEA 2000 Wi-Fi Router YDNR-02N, detailing installation, configuration, Wi-Fi settings, NMEA 0183 and SeaTalk connectivity, and advanced features for marine navigation systems.</p>

Documents - Gyration – Cyberview 2000

GYRATION®

CYBERVIEW 2000
2 MP Smart Indoor Wi-Fi Camera

DATASHEET

KEY FEATURES

The Gyration Cyberview 2000 is a 2 mp Smart AI Wi-Fi camera, suitable for indoor use. Support 24 Hrs. continuous recording, event recording, motion, two-way audio, AI motion detection, support for Gyration app, motion alerts, 2.4GHz WiFi connection, support Micro SD card, the maximum support up to 128GB. Support for 3G/4G connection, Support Android / iOS system mobile devices, remote recording, remote monitoring, support for Gyration app, call via the Cyberview Plus App when someone click on the call button so you'll never miss a video conference. See and talk with your family and friends from anywhere in the world, your smartphone, anywhere, any time. The built-in microphone and speaker allows you to hear what's happening indoor. With Cyberview Plus app, you can protect, capture, save and share what's valuable to you.

GYBERVIEW 2000 2 MP Smart Indoor Wi Camera DATASHEET Resolution

Perimeter Detection VCA Edge Storage Call Button Supports Wi- Cloud Solution KEY FEATURES The Gyration **Cyberview 2000** is a 2 mp Smart AI Wi-Fi camera, suitable for indoor use. Support 24 Hrs. continuous recording, event recor...

lang:en score:39 filesize: 2.55 M page_count: 4 document date: 2023-11-09

GYRATION®

DATASHEET

CYBERVIEW 2000
2 MP Smart Indoor WiFi Wireless

NDAA **CE** **RoHS**



KEY FEATURES

- High-quality image with 2 MP 1/2.7 CMOS sensor
- 2MP resolution (1920 x 1080) @ 30fps
- Support two-way audio, AI motion detection, Support Cloud storage, Support SD card, Support 2.4GHz connection, support Micro SD card, the maximum capacity can reach 128GB, support cloud storage, Support Android (4.4+) and iOS (8.0+) mobile devices for remote monitoring
- The Cyberview 2000 initiates a video call via the CyberView Plus app. You can receive a push notification and never miss a video conference. See and talk with your family members or guest of the family from your smartphone anywhere, anytime. The CyberView Plus app will make it easy for you to hear what's happening indoor. With CyberView Plus app, you can protect, capture, save and share what's happening in your home.
- Supports two-way voice intercom supported, echo-eliminated, noise suppressed
- Supports micro SD card max 128 GB storage
- Supports night vision with night vision distance of 20m, 24h around the clock monitoring, IR CUT switching
- Supports 10 system mobile devices for remote monitoring
- Easy to install and use

Google play App Store QR code

Gyration® - 2009 Valley Blvd, Walnut, CA 91789 - Tel +1(909) 639-2229 © 2022 Gyration. All Rights Reserved. Specifications subject to change without notice.

20220916

[\[pdf\]](#) **Datasheet Borchure**

Datasheet GY CyberView 2000 11 17 22 CYBERVIEW Adesso Gyration Cyberview 2 Megapixel Indoor Full Hd Network Camera Color 97 Ft Infrared Night Vision H 264 Mjpeg 1920 X 1080 4 Mm Fixed Lens Cmos Ceiling Mount Wall Alexa Google Home Supported DirectDial Canada 1076447242 content etilize Manufacturer Brochure |||

CYBERVIEW 2000 2 MP Smart Indoor Wi Wireless DATASHEET Resolution

Perimeter Detection VCA Edge Storage Call Button Supports Wi- Cloud Solution KEY FEATURES The Gyration **Cyberview 2000** is a 2 mp Smart AI WiFi wireless battery doorbell camera, suitable for indoor use. Support 24 Hrs. conti...

lang:en **score:30** filesize: 2.52 M page_count: 4 document date: 2022-12-28

[\[pdf\]](#)

PowerPoint user Gyration Company Profile 2023 gyration UploadFiles |||

About Us Since 1994 Global Logistic Support Center 2019 1994 2020 2008 2018 1994 2019 2020 ... NETWORK VIDEO RECORDER WITH PoE Accessories Smart Security, Better Life Cloud Stream Storage **Cyberview 2000** 2MP Indoor Smart WiFi Pan/Tilt Camera Indoor PT Camera KEY FEATURES HD 1080P IP Ca...

lang:en **score:25** filesize: 4.53 M page_count: 28 document date: 2023-01-18

[\[pdf\]](#)

PowerPoint user ADESSO Keyboards Mice Webcams Headsets Speakers Document Scanners More Adesso Inc Your Input Device Specialist Gyration Company PPT 2023 us adesso assets fp ||| Retail Industry Solution Restaurants Lodge Government Hospital Critical Infrastructure Smart ... RK VIDEO RECORDER WITH PoE User Interface CyberView Smart Home Solution Cloud Stream Storage **Cyberview 2000** 2MP Indoor Smart WiFi Pan/Tilt Camera Indoor Pan Tilt WiFi Security Camera KEY FEAT...

lang:en **score:21** filesize: 3.84 M page_count: 24 document date: 2022-12-31

GYRATION®


COMPANY INTRODUCTION



GYRATION

COMPANY INTRODUCTION

GYRATION® **Cyberview2000**



Smart PTZ Camera
User manual

[\[pdf\]](#) **Gyration Cyberview2000 Smart PTZ Camera User Manual - Setup, Installation, Specifications**

Comprehensive user manual for the Gyration Cyberview2000 Smart PTZ Camera. Covers setup, Wi-Fi binding, installation, sharing features, product specifications, and regulatory compliance. Includes app download information.

lang:en **score:17** filesize: 3.3 M page_count: 32 document date: 2023-01-01