

[Manuals.plus](#) /

› [ZIYOU LANG](#) /

› ZIYOU LANG M96 Wireless Gaming Keyboard User Manual

ZIYOU LANG M96

ZIYOU LANG M96 Wireless Gaming Keyboard User Manual

Model: M96

1. INTRODUCTION

The ZIYOU LANG M96 is a versatile wireless gaming keyboard designed for a quiet and responsive typing experience. It features dual-mode connectivity (Bluetooth and 2.4Ghz), an integrated display screen, a multimedia control knob, and customizable rainbow backlighting. The keyboard is equipped with durable PBT keycaps and an ergonomic design for extended use.



Image 1.1: Overview of the ZIYOU LANG M96 Wireless Gaming Keyboard, highlighting its compact design and key features.

2. PACKAGE CONTENTS

Please check the package for the following items:

- ZIYOU LANG M96 Wireless Gaming Keyboard
- USB to Type-C Charging Cable
- 2.4Ghz USB Receiver (may be stored in the keyboard's receiver slot)
- User Manual (this document)

3. SETUP

3.1 Charging the Keyboard

Before initial use, fully charge the keyboard using the provided USB to Type-C cable. Connect the Type-C end to the keyboard's charging port and the USB-A end to a power source (e.g., computer USB port, USB wall adapter).



Image 3.1: The ZIYOU LANG M96 keyboard features a built-in 2000mAh rechargeable battery, providing long-lasting power for extended use.

3.2 Connecting the Keyboard

The M96 keyboard supports three connection modes: 2.4Ghz wireless, Bluetooth 1 (BT1), and Bluetooth 2 (BT2). Use the switch located on the side of the keyboard to select your desired mode.



Image 3.2: Side view of the keyboard showing the power switch, Type-C charging port, and the mode switching toggle for BT2, BT1, and 2.4Ghz connections.

3.2.1 2.4Ghz Wireless Connection

1. Locate the 2.4Ghz USB receiver, usually stored in a compartment on the keyboard.
2. Plug the USB receiver into an available USB port on your computer.
3. Slide the mode switch on the keyboard to the "2.4G" position.

4. The keyboard should automatically connect. The display screen will indicate the 2.4G connection status.

3.2.2 Bluetooth Connection (BT1 / BT2)

1. Slide the mode switch on the keyboard to either "BT1" or "BT2" position.
2. For BT1, press and hold **FN + Q** for 3-5 seconds until the keyboard's display screen shows a blinking Bluetooth icon, indicating pairing mode.
3. For BT2, press and hold **FN + W** for 3-5 seconds until the keyboard's display screen shows a blinking Bluetooth icon, indicating pairing mode.
4. On your device (computer, laptop, tablet, smartphone), open Bluetooth settings and search for new devices.
5. Select "ZIOU LANG M96" from the list of available devices to pair.
6. Once connected, the Bluetooth icon on the keyboard's display screen will stop blinking.



Image 3.3: The M96 keyboard supports multi-device connection via Bluetooth 5.0 and 2.4Ghz wireless, allowing seamless switching between up to three devices.

4. OPERATING INSTRUCTIONS

4.1 Display Screen Functions

The integrated LED display screen provides real-time information about the keyboard's status:

- **Battery Level:** Shows the current battery percentage.
- **Connection Mode:** Indicates whether 2.4G, BT1, or BT2 is active.
- **Caps Lock Indicator:** Lights up when Caps Lock is active.
- **Num Lock Indicator:** Lights up when Num Lock is active.
- **Win/Mac Mode:** Displays the current operating system mode.



Image 4.1: Close-up of the M96 keyboard's LED display screen, showing indicators for battery level, connection status, Caps Lock, Num Lock, and Win/Mac mode.

4.2 Multimedia Control Knob

The knob located on the top right of the keyboard offers quick control over multimedia and backlight settings:

- **Volume Control:** Rotate clockwise to increase volume, counter-clockwise to decrease volume. Press the knob to mute/unmute audio.
- **Backlight Brightness:** Press and hold the knob for 5 seconds to switch to backlight control mode. Rotate clockwise to increase brightness, counter-clockwise to decrease brightness. Press the knob to cycle through backlight effects.



Image 4.2: The multi-functional knob on the M96 keyboard allows for intuitive adjustment of volume and backlight settings.

4.3 Multimedia Hot Keys

The keyboard includes 12 dedicated multimedia keys (F1-F12) accessible via the **FN** key for quick access to common functions:

- **FN + F1:** Media Player
- **FN + F2:** Volume Down
- **FN + F3:** Volume Up
- **FN + F4:** Mute
- **FN + F5:** Stop
- **FN + F6:** Previous Track
- **FN + F7:** Play/Pause
- **FN + F8:** Next Track
- **FN + F9:** Email
- **FN + F10:** Web Browser
- **FN + F11:** My Computer
- **FN + F12:** Calculator

4.4 Backlight Control

The M96 keyboard features a rainbow LED backlight. You can adjust its settings using FN key combinations:

- **FN + Right Arrow:** Increase backlight speed.
- **FN + Left Arrow:** Decrease backlight speed.
- **FN + Up Arrow:** Increase backlight brightness.
- **FN + Down Arrow:** Decrease backlight brightness.
- **FN + DEL:** Cycle through backlight modes (static, breathing, off).



Image 4.3: Visual guide for controlling the rainbow backlight effects and brightness on the M96 keyboard.

5. MAINTENANCE

5.1 Cleaning the Keyboard

To maintain optimal performance and appearance:

- Disconnect the keyboard from all devices and turn it off before cleaning.
- Use a soft, lint-free cloth slightly dampened with water or a mild cleaning solution to wipe the keycaps and surface.
- For stubborn dirt between keycaps, use compressed air or a small brush.
- Avoid using harsh chemicals, abrasive cleaners, or excessive moisture.

5.2 Battery Care

- Avoid fully discharging the battery frequently.
- Store the keyboard in a cool, dry place when not in use for extended periods.
- Charge the keyboard regularly to maintain battery health.

5.3 Keycap Care

The M96 keyboard features durable PBT keycaps. While PBT is resistant to shine and wear, proper care can extend their lifespan:

- Avoid exposing keycaps to direct sunlight for prolonged periods.
- If removing keycaps for cleaning, use a keycap puller to prevent damage.



Image 5.1: The M96 keyboard is equipped with durable OEM profile PBT keycaps, known for their resistance to wear and comfortable feel.

6. TROUBLESHOOTING

If you encounter issues with your ZIYOU LANG M96 keyboard, refer to the following common solutions:

- **Keyboard not responding:** Ensure the keyboard is turned on and fully charged. Check the connection mode switch (2.4G, BT1, BT2) is set correctly. For 2.4G, ensure the USB receiver is properly inserted. For Bluetooth, ensure the keyboard is paired and within range.
- **Connection drops frequently:** Ensure there are no strong interference sources nearby (e.g., other wireless devices, large metal objects). Try moving closer to your device. Re-pair the Bluetooth connection or re-insert the 2.4G receiver.
- **Backlight not working or incorrect:** Check the backlight settings using the FN key combinations (FN + arrows, FN + DEL) or the multimedia knob. Ensure the keyboard has sufficient battery charge.
- **Keys not registering or double-typing:** Clean the keycaps and switches to remove any debris. Ensure the keyboard is fully charged. If the issue persists, contact customer support.
- **Display screen not showing information:** Ensure the keyboard is powered on. If the screen is blank, try charging the keyboard.

7. SPECIFICATIONS

Feature	Detail
Brand	ZIYOU LANG
Model	M96
Connectivity Technology	2.4Ghz, Bluetooth
Keyboard Description	Membrane
Number of Keys	94
Keycap Material	PBT
Special Features	Backlit, Hotkeys and Media Keys, Rechargeable, Volume Roller, Display Screen

Keyboard Backlighting	Rainbow RGB
Battery Capacity	2000mAH
Compatible Devices	Gaming Console, Laptop, PC, Smartphone, Tablet (Windows/Mac/Linux/iOS/Android)
Product Dimensions	15.75"L x 6.46"W x 1.77"H

8. OFFICIAL PRODUCT VIDEO

Your browser does not support the video tag.

Video 8.1: An official product video demonstrating the ZIYOU LANG M96 keyboard's Bluetooth/2.4G dual-mode connectivity, display screen, and multimedia knob features.

9. WARRANTY AND SUPPORT

For warranty information, please refer to the documentation provided with your purchase or visit the official ZIYOU LANG website. If you require further assistance or have questions not covered in this manual, please contact ZIYOU LANG customer support through their official channels.

You can visit the ZIYOU LANG Store for more information:[ZIYOU LANG Store on Amazon](#)

ASK A QUESTION ABOUT THIS MANUAL

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Email

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. [Privacy details](#).

Question

Details

Submit question

