Saved from manuals.plus.
Open the live page for links to other documents and user manuals.

SCS Sentinel AAM0131

SCS Sentinel SimplyControl 2-Channel Remote Control (Model AAM0131)

User Manual

Introduction

This manual provides comprehensive instructions for the SCS Sentinel SimplyControl 2-Channel Remote Control, Model AAM0131. This device is designed for efficient and convenient remote operation of compatible alarm systems and automatic gate openers. It features a 40-meter operating range and utilizes a 433.92 MHz frequency. The remote control is powered by an included CR2032 lithium battery.

Product Features

- **Efficient and Convenient Remote Control:** Offers efficient and convenient remote operation for your alarm system or compatible gate opener with a 40-meter range.
- **Enhanced Security Features:** Includes activation, deactivation, and partial arming modes for customized security. Features an SOS emergency call function for immediate assistance.
- **Wide Compatibility:** Compatible with various automatic gate openers, including SimplyOpen, OpenGate, Prim' by SCS Sentinel, SG 1/2/3, CarGate 800 TRIO, and CarOne 600.
- **Compact Design:** Designed for easy portability and comfortable use.

Product Overview



The SimplyControl 2-Channel Remote Control, featuring a fuchsia button and 'Made in France' quality.



A hand using the SimplyControl remote to open a garage door, demonstrating its practical application.



The compact SimplyControl remote control resting on a table alongside everyday items like keys and sunglasses.



A close-up view of a hand pressing one of the two buttons on the SimplyControl remote control.



The retail packaging for the SimplyControl remote control, highlighting its features and model number.

Setup & Programming

Remote Control Programming (Self-Learning)

The SimplyControl remote control features a self-learning function to duplicate codes from an existing remote. Follow these steps for programming:

1. **Position Remotes:** Place the new SimplyControl remote and the original remote control within 5mm of each other.
2. **Initiate Learning on SimplyControl:** Press and hold the button on the SimplyControl remote where you wish to store the code. The LED will flash once, then begin to flash slowly.
3. **Transmit Code from Original Remote:** While still holding the button on the SimplyControl remote, press and hold the corresponding button on the original remote control.
4. **Confirm Learning:** The LED on the SimplyControl remote will emit rapid flashes. Wait approximately 3 seconds, then release both buttons. The code is now stored.
5. **Repeat for Other Buttons:** Use the same procedure to program other buttons on the SimplyControl remote.

Resetting and Deleting Codes

To reset the SimplyControl remote and delete all stored codes:

1. **Press Both Buttons:** Simultaneously press and hold both buttons (A and B) on the SimplyControl remote.
2. **Observe LED:** After approximately 10 seconds, the LED will remain lit and then emit rapid flashes.
3. **Release Buttons:** Release both buttons. All codes are now deleted.

Video Tutorials for Programming

▶ **Watch video online**
Configurazione del telecomando.

Video: Remote Control Configuration. This video demonstrates the programming steps for the remote control, including how to duplicate codes from an existing remote.

▶ **Watch video online**
Product Operation Video

Video: Product Operation. This video provides a visual guide on how to operate the remote control and its various functions.

▶ **Watch video online**
WHY EVO - Radiocomando Universale Apricancello - Ampio Raggio - Multifrequenza da 300 a 868Mhz - ...

Video: Universal Gate Opener Remote Control Programming. This tutorial covers programming a universal remote for various gate openers, which may be applicable to the SimplyControl.

▶ **Watch video online**
Come duplicare un trasmettitore TTS a codice fisso

Video: How to Duplicate a Fixed Code Transmitter. This video demonstrates the process of duplicating a fixed code remote, a common method for programming.

Operating Instructions

Once programmed, the SimplyControl remote is ready for use. Each button corresponds to a specific function or device as programmed during the setup process.

- **Activation/Deactivation:** Press the programmed button once to activate or deactivate your alarm system or open/close your gate.

- **Partial Arming:** If configured, use the designated button for partial arming of your security system.
- **SOS Emergency Call:** Press and hold the designated SOS button (if configured) for immediate assistance.

Maintenance

Battery Replacement (CR2032)

The SimplyControl remote control uses a CR2032 lithium battery. If the remote's range decreases or the LED indicator does not light up, the battery may need replacement.

1. **Open the Casing:** Carefully open the remote control casing using a small screwdriver or similar tool.
2. **Remove Old Battery:** Gently remove the old CR2032 battery.
3. **Insert New Battery:** Insert a new CR2032 lithium battery, ensuring the positive (+) side faces upwards.
4. **Close Casing:** Close the remote control casing securely.

Troubleshooting

- **Remote Not Responding:**
  - Check the battery: Ensure the CR2032 battery is correctly inserted and has sufficient charge. Replace if necessary.
  - Verify programming: Re-check the programming steps to ensure the remote is correctly paired with your device.
- **Reduced Range:**
  - Replace the battery: A weak battery is the most common cause of reduced range.
  - Check for interference: Ensure there are no strong radio frequency sources (e.g., other wireless devices, large metal objects) blocking the signal.
- **Inconsistent Operation:**
  - Reprogram the remote: Sometimes, re-programming can resolve inconsistent behavior.
  - Check the receiver: Ensure the receiver unit of your gate opener or alarm system is functioning correctly and is not obstructed.

Specifications

Brand	SCS Sentinel
Model	AAM0131 (SimplyControl)
Number of Buttons	2
Connectivity Technology	Radio Frequency (RF)
Frequency	433.92 MHz
Maximum Range	40 Meters
Battery Type	CR2032 Lithium
Batteries Included	Yes
Additional Features	SOS Emergency Call

Item Weight	0.1 g

Warranty and Support

The SCS Sentinel SimplyControl remote control comes with a 2-year warranty, ensuring its quality and durability. For any technical assistance or personalized advice regarding product installation or operation, please contact the SCS Sentinel technical support team based in France. Your satisfaction is our priority.

Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

Open the live page

https://manuals.plus/asin/B0D311P3PG

More documents and user manuals: **https://manuals.plus/**