Saved from manuals.plus.
Open the live page for links to other documents and user manuals.

RAWM MH01

RAWM Wireless 8K Lightweight Gaming Mouse

MODEL: MH01

Brand: RAWM

INTRODUCTION

This manual provides comprehensive instructions for the RAWM Wireless 8K Lightweight Gaming Mouse (Model MH01). It covers setup, operation, maintenance, and troubleshooting to ensure optimal performance and longevity of your device. This high-performance gaming mouse is designed for competitive esports, offering precision, speed, and customization.





The RAWM Wireless 8K Lightweight Gaming Mouse MH01 in white.

What's in the Box

The RAWM MH01 gaming mouse comes with a comprehensive set of accessories to enhance your gaming experience and allow for customization. Below is a video detailing the package contents, followed by a list of included items.

▶ **Watch video online**
What is in the package?

Official video demonstrating the unboxing and contents of the RAWM MH01 gaming mouse package.

- RAWM MH01 Wireless Gaming Mouse (White)
- Additional Mouse Shell (Black, hollow design)
- Type-C Charging Cable (6.5 ft)
- 8K Wireless Receiver Dongle
- 3 Sets of Replaceable Micro Switches (HUANO and MANBA)
- Screwdriver for disassembly
- User Manual

- PTFE Foot Patch (x1)
- Extra Screws (x2)
- Disassembly Tool (x1)
- Anti-slip Sticker Kit (x2)

Setup and Connection

Tri-mode Connectivity

The RAWM MH01 offers versatile connection options to suit your needs:

- **2.4G Wireless:** For maximum performance and 8K compatibility, use the included 8K wireless receiver dongle.
- **Bluetooth 5.3:** For general use and portability, connect via Bluetooth to compatible devices.
- **Wired Mode:** Connect directly using the Type-C cable for a stable 1K polling rate connection and simultaneous charging.



Illustration of the mouse's tri-mode connection capabilities: Type-C wired, Wireless USB 2.4G, and Bluetooth 5.3.

Initial Setup

To get started, select your preferred connection mode using the switch on the bottom of the mouse. For wireless modes, ensure the dongle is plugged into your computer or Bluetooth is enabled and paired. The mouse is plug-and-play for basic functionality, but for advanced customization, install the RAWM Dual Driver software.

Key Features

Hot Swappable Design

The RAWM MH01 features a unique hot-swappable switch design, allowing you to easily change the main click switches without soldering. This enables customization of click feel and responsiveness. The mouse supports 3-pin switches, and extra HUANO and MANBA switches are included in the package.

▶ **Watch video online**

How to open RAWM SA-MH01 gaming mouse?

Official video demonstrating the disassembly process of the RAWM MH01 mouse to access and replace the hot-swappable switches.



Diagram illustrating the hot-swappable switch mechanism and included switch types (HUANO Pink Dots, Kailh GM8.0 Black Mamba, HUANO Silent micro switch).

Dual Driver Software

Customize your RAWM MH01 mouse with the dedicated dual-driver software, available as both an application and a web hub from the RAWM website. This software allows for continuous upgrades and provides extensive control over mouse settings.



Screenshot of the RAWM Dual Driver software interface, showing options for DPI, polling rate, lighting, and button assignments.

Ergonomic Design for Optimal Grip

The RAWM MH01 features a symmetrical design with an hourglass shape, a wide back, and a high curved top (40.1mm hump) to provide a comfortable experience and prevent finger cramps. It is particularly suitable for palm grip users but also accommodates claw and fingertip grips, making it versatile for various hand sizes and preferences.



Visual representation of the RAWM MH01 mouse being used with palm, claw, and fingertip grip styles.

Long Battery Life

Equipped with a 600mAh rechargeable battery, the RAWM MH01 provides extended usage, offering up to 165 hours of continuous game play on a single charge. A full charge takes approximately 2.5 to 3 hours.



Graphic highlighting the 165-hour battery life and 3-hour full charging time of the RAWM MH01 mouse.

Operating Instructions

DPI Adjustment

The mouse features an on-the-fly adjustable DPI setting, ranging from 50 to 26000 DPI. Use the dedicated DPI button (typically located near the scroll wheel) to cycle through preset DPI levels or customize them via the software.

Programmable Buttons

The RAWM MH01 has 7 programmable buttons. Utilize the dual-driver software to customize button assignments, create macros, and fine-tune settings like polling rate and lift-off distance to match your gaming style. Configurations can be saved directly to the mouse's onboard memory for quick access.

Maintenance

Cleaning

To maintain optimal performance, regularly clean your mouse. Use a soft, dry cloth to wipe the surface. For the optical sensor, use a cotton swab lightly dampened with isopropyl alcohol, ensuring no liquid enters the mouse's interior.

Switch Replacement

Thanks to the hot-swappable design, replacing switches is straightforward. Refer to the

Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

Open the live page

https://manuals.plus/asin/B0D3LQGH9W

More documents and user manuals: **https://manuals.plus/**