

## CHUYI Wireless Bluetooth Mouse

# CHUYI Wireless Mouse Instruction Manual

Model: Wireless Bluetooth Mouse

## PRODUCT OVERVIEW

The CHUYI Wireless Mouse offers versatile connectivity with both 2.4G USB and dual Bluetooth modes (BT5.0 & BT3.0), allowing connection to up to three devices simultaneously. It features three adjustable DPI levels (800/1200/1600) for precise cursor control and an ergonomic design for comfortable use. The mouse is rechargeable via a Type-C port, providing extended battery life.

### Key Features:

- Dual-Mode Connectivity: 2.4G USB and Bluetooth (BT5.0 & BT3.0)
- Connects to up to 3 devices
- 3 Adjustable DPI Levels: 800, 1200, 1600
- Ergonomic Design for comfort
- Rechargeable with Type-C charging cable
- Wide Compatibility: Windows, Mac OS, iOS 13+, Linux, etc.

## PACKAGE CONTENTS

Verify that all items are present in the package:

- 1 x CHUYI Wireless Mouse
- 1 x USB Receiver (stored inside the mouse)
- 1 x Type-C Charging Cable

## MOUSE COMPONENTS



Image: Detailed diagram showing the mouse's left click, right click, scroll wheel, DPI button, back/forward keys, Type-C charging port, switch button, optical sensor, ON/OFF switch, and USB receiver storage. Dimensions are also indicated.

1. Left Click Button
2. Right Click Button
3. Scroll Wheel
4. DPI Button (800/1200/1600)
5. Back Key
6. Forward Key
7. Type-C Charging Port
8. Switch Button (for mode selection)
9. Optical Sensor
10. ON/OFF Switch
11. USB Receiver Storage

## SETUP AND CONNECTION

The mouse supports two connection modes: 2.4G Wireless via USB receiver and Bluetooth (BT1/BT2).

### 1. 2.4G Wireless Mode

1. Locate the USB receiver: The USB receiver is stored in the compartment at the bottom of the mouse.
2. Insert the receiver: Plug the USB receiver into an available USB-A port on your computer.
3. Power on the mouse: Slide the ON/OFF switch at the bottom of the mouse to the "ON" position.
4. Switch to 2.4G mode: Press the mode switch button on the bottom of the mouse until the 2.4G indicator light (often red or green, refer to mouse markings) illuminates briefly.
5. The mouse should now be connected and ready for use.



*Image: Illustration demonstrating how to connect the 2.4G USB receiver and switch the mouse to 2.4G mode.*

### 2. Bluetooth Mode (BT1 / BT2)

The mouse supports two separate Bluetooth channels (BT1 and BT2) for connecting to different devices.

1. Power on the mouse: Slide the ON/OFF switch at the bottom of the mouse to the "ON" position.
2. Select Bluetooth channel: Press the mode switch button on the bottom of the mouse to select either BT1 or BT2. The corresponding indicator light (e.g., blue for BT1, green for BT2) will flash slowly.
3. Enter pairing mode: Press and hold the mode switch button for 3-5 seconds until the selected Bluetooth indicator light starts flashing rapidly. This indicates the mouse is in pairing mode.
4. Enable Bluetooth on your device:
  - **For Windows:** Go to Settings > Devices > Bluetooth & other devices. Click "Add Bluetooth or other device" and select "Bluetooth".
  - **For Mac OS:** Go to System Preferences > Bluetooth.
  - **For iPad/iOS:** Go to Settings > Bluetooth.

- Select the mouse: In your device's Bluetooth list, look for "BT5.0 Mouse" or "BT3.0 Mouse" (or similar, depending on the channel selected) and click to connect.
- Once connected, the indicator light on the mouse will stop flashing and remain solid for a few seconds, then turn off.



Image: Visual representation of the mouse connecting to a laptop via BT3.0, a desktop via 2.4G, and a tablet via BT5.0, highlighting the easy switching capability.

**Switching Between Devices:** To switch between connected devices (2.4G, BT1, BT2), simply press the mode switch button on the bottom of the mouse. The corresponding indicator light will briefly illuminate to confirm the active mode.

## OPERATING INSTRUCTIONS

### DPI Adjustment

The mouse features three adjustable DPI (Dots Per Inch) levels to control cursor sensitivity and speed. Press the DPI button located on the top of the mouse, behind the scroll wheel, to cycle through the settings:

- 800 DPI:** Slower cursor movement, suitable for precise tasks.

- **1200 DPI:** Standard cursor movement, suitable for general use.
- **1600 DPI:** Faster cursor movement, suitable for quick navigation or gaming.



Image: Diagram showing the three DPI settings (800, 1200, 1600) and how they affect cursor sensitivity.

## Back/Forward Buttons

The mouse is equipped with convenient Back and Forward buttons on the left side. These buttons allow for quick navigation in web browsers, file explorers, and other applications, such as switching between documents or browsing web pages.

## CHARGING AND BATTERY LIFE

The CHUYI Wireless Mouse has a built-in rechargeable battery. When the battery is low, the mouse may exhibit erratic behavior or stop responding. Charge the mouse using the provided Type-C charging cable.

1. Connect the Type-C end of the charging cable to the charging port on the front of the mouse.
2. Connect the USB-A end of the charging cable to a USB power source (e.g., computer USB port, USB wall

adapter).

3. A charging indicator light (if present) will illuminate during charging and typically turn off or change color when fully charged.
4. A full charge takes approximately 3-4 hours and provides up to 40 hours of battery life.



Image: Illustration of the mouse connected to a laptop via its Type-C charging cable, indicating charging time and battery life.

## TROUBLESHOOTING

### Frequently Asked Questions

**Q: Where is the USB receiver for the mouse?**

A: The receiver is generally located at the bottom of the mouse, often in a small compartment. You may need to open a cover to access it.

**Q: Is this mouse compatible with MacBook or Chromebook?**

A: This mouse uses a USB-A receiver for 2.4G mode, which is suitable for computers with a USB-A interface. For devices with only a Type-C interface (like some MacBooks or Chromebooks), you will need a USB-A to

USB-C adapter (not included) to use the 2.4G mode. The Bluetooth mode offers wider compatibility with devices supporting Bluetooth connectivity, including Mac OS and iOS 13 and above.

## General Troubleshooting Tips

- **Mouse not responding:**
  - Ensure the mouse is powered on.
  - Check battery level and charge if necessary.
  - For 2.4G mode, ensure the USB receiver is securely plugged in and the mouse is in 2.4G mode.
  - For Bluetooth mode, ensure Bluetooth is enabled on your device and the mouse is correctly paired to the selected BT channel. Try re-pairing if connection is lost.
  - Try connecting the mouse to a different USB port or a different device to rule out port or device issues.
- **Erratic cursor movement:**
  - Clean the optical sensor at the bottom of the mouse.
  - Ensure you are using the mouse on a suitable surface (not highly reflective or transparent).
  - Adjust the DPI setting to a lower value if the cursor is too sensitive.
- **Connection drops frequently:**
  - Ensure the mouse is within the effective operating range (up to 10 meters).
  - Minimize interference from other wireless devices.
  - Recharge the mouse battery.

## SPECIFICATIONS

Feature	Detail
Product Dimensions	4.01 x 2.32 x 0.04 inches
Item Weight	2.36 ounces
Connectivity Technology	Bluetooth (BT5.0 & BT3.0), 2.4GHz USB
DPI Levels	800 / 1200 / 1600
Movement Detection Technology	Optical
Battery Type	1 Lithium Polymer battery (included)
Charging Port	Type-C
Charging Time	3-4 hours
Battery Life	Up to 40 hours
Compatibility	Windows XP/Vista/2000/Win7/Win8/Win10/ME/NT/Linux/Mac OS, iOS 13 and above

## WARRANTY AND SUPPORT

---

This product comes with a standard return policy, typically 30 days from the date of purchase. For specific warranty details, returns, or technical support, please refer to your purchase documentation or contact CHUYI customer service through the retailer where the product was purchased.

## OFFICIAL PRODUCT VIDEO

---

Your browser does not support the video tag.

*Video: An official product video demonstrating the CHUYI Dual Mode Wireless Bluetooth Mouse in use, highlighting its features and functionality.*