

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

[manuals.plus](#) /

› [Newmight](#) /

› [USB C Docking Station Dual HDMI Monitor, Newmight 7 in 1 USB C to Dual HDMI Adapter for Dell, HP, MacBook, iPhone 15 \(Silver\) - User Manual](#)

Newmight B0D5XT6MM3

Newmight 7-in-1 USB C Docking Station Dual HDMI Monitor User Manual

Model: B0D5XT6MM3

Brand: Newmight

1. INTRODUCTION

Thank you for choosing the Newmight 7-in-1 USB C Docking Station Dual HDMI Monitor. This versatile hub is designed to expand the connectivity of your USB-C enabled devices, providing dual HDMI display outputs, multiple USB 3.0 ports for data transfer, and powerful 100W Power Delivery charging. This manual provides detailed instructions for setup, operation, maintenance, and troubleshooting to ensure optimal performance and a seamless user experience.



Image 1.1: The Newmighthub 7-in-1 USB C Docking Station, showcasing its compact design and multiple connectivity options including USB-A, USB-C, and HDMI ports.

2. PRODUCT FEATURES

The Newmighthub 7-in-1 USB C Docking Station offers a comprehensive set of features to enhance your productivity and connectivity:

- **Dual HDMI Ports:** Supports resolutions up to 4K@30Hz for a high-definition visual experience.
- **3 x USB 3.0 Ports:** Provides high-speed data transfer up to 5Gbps, ideal for external drives, keyboards, and mice.
- **1 x USB C 3.0 Port:** Offers additional USB-C connectivity for data transfer.
- **100W Power Delivery (PD) Charging Port:** Allows for fast charging of your host device while using the hub.
- **Plug and Play:** No driver installation required for most operating systems.
- **Durable Construction:** Made from aluminum alloy for wear resistance, durability, and efficient heat dissipation.

- **Compact and Portable:** Lightweight design for easy transport and use in various environments.



Image 2.1: A visual breakdown of the Newmighthub 7-in-1 USB C Hub's ports and their respective functions, highlighting its expansion capabilities.

3. PACKAGE CONTENTS

Upon opening the package, please verify that all items are present and in good condition:

- 1 x Newmighthub 7-in-1 USB C Docking Station

- 1 x User Manual (this document)

4. SETUP GUIDE

4.1. Connecting to Host Device

Connect the integrated USB-C cable of the docking station directly to a compatible USB-C port on your laptop, tablet, or smartphone. Ensure your device's USB-C port supports video output (DisplayPort Alternate Mode) and/or Power Delivery for full functionality.

Check Your Laptop Before Purchase

Please check your laptop's USB C port is support Charging, Data, Video transfer or not

Thunderbolt 3/4 Full Function	Support Data Video Transfer	Support Video Transfer
		
Only Data Transfer	Only Charging	Only Data Transfer
		

Image 4.1: Important information on checking your laptop's USB-C port capabilities to ensure compatibility with video, data, and charging functions.

4.2. Connecting Displays

Use standard HDMI cables to connect your external monitors to the two HDMI ports on the docking station. The docking station supports resolutions up to 4K@30Hz. For optimal display quality, ensure your monitors and HDMI cables also support 4K@30Hz.

4k Ultra HD Display



Image 4.2: A user demonstrating the 4K Ultra HD display capability with a laptop connected to dual monitors through the docking station.

4.3. Connecting USB Peripherals

Plug your USB devices such as keyboards, mice, USB flash drives, or external hard drives into the three USB 3.0 ports or the USB C 3.0 port on the docking station. These ports support data transfer speeds of up to 5Gbps.



Super Fast Data Transfer

3 * USB 3.0 / 5Gbps



Image 4.3: Depiction of high-speed data transfer, illustrating how the USB 3.0 ports enable quick file transfers between devices and the host laptop.

4.4. Power Delivery (PD) Charging

To charge your host device through the docking station, connect your original USB-C power adapter to the PD 100W charging port on the docking station. This allows you to power your laptop or tablet while simultaneously using the hub's other functions.



100W Fast Charging



Image 4.4: The 100W PD charging feature in action, showing the docking station providing power to a laptop from a wall outlet.

4.5. Compatibility

The Newmight 7-in-1 USB C Docking Station is widely compatible with most Type-C laptops featuring Thunderbolt 3/4, or USB-C ports that support DisplayPort Alternate Mode and Power Delivery. Supported operating systems include macOS, Windows, Linux, Android, and iOS.

- **Compatible Host Devices:** MacBook Pro/Air (2023/2022/2021/2020/M1/M2, etc.), iPad Pro 2020/2021, iMac models from 2017 onwards, iPhone 15 Series, Samsung Chromebook Pro, Dell XPS 13/15, HP Spectre X360, Surface Book 2, Huawei P20 Pro, Google Chromebook Pixel, and more.

Wide Compatibility



Image 4.5: A visual guide to the wide range of devices and operating systems compatible with the Newmnight USB C Docking Station.

5. OPERATING INSTRUCTIONS

5.1. Multiple Display Modes (Windows)

For Windows operating systems, the docking station supports various display modes across multiple monitors:

- **Mirror Mode:** Displays the same content on all connected monitors (A-A-A).
- **Extend Mode 1:** Extends your desktop across two external monitors, showing different content on each (A-B-B).
- **Extend Mode 2:** Extends your desktop across two external monitors, showing different content on each, distinct from the laptop display (A-B-C).



Image 5.1: Visual representation of the different display configurations available for Windows users with dual monitors.

5.2. Multiple Display Modes (macOS)

For macOS devices, due to system limitations, the docking station supports the following display modes:

- **Mirror Mode:** Displays the same content on all connected monitors (A-A-A).
- **Extend Mode:** While it extends your desktop, both external monitors will display the same content (A-B-

B). macOS does not support MST (Multi-Stream Transport) for displaying different content on each external monitor.



Image 5.2: Visual guide to macOS display configurations, highlighting the limitation where extended monitors will mirror each other.

6. MAINTENANCE

To ensure the longevity and optimal performance of your Newmight 7-in-1 USB C Docking Station, please follow these maintenance guidelines:

- **Cleaning:** Use a soft, dry cloth to wipe the surface of the docking station. Avoid using liquid cleaners or abrasive materials.
- **Storage:** When not in use, store the docking station in a cool, dry place away from direct sunlight and extreme temperatures. The compact design allows for easy storage or transport in a laptop bag.
- **Heat Dissipation:** The aluminum alloy casing is designed for efficient heat dissipation. Ensure the docking station is placed on a flat, stable surface with adequate airflow to prevent overheating during prolonged use.
- **Cable Care:** Avoid bending or twisting the integrated USB-C cable excessively to prevent internal damage.

7. TROUBLESHOOTING

If you encounter any issues while using your Newmight 7-in-1 USB C Docking Station, please refer to the following common troubleshooting steps:

- **No Display Output:**
 - Ensure your host device's USB-C port supports DisplayPort Alternate Mode (video output).
 - Check that HDMI cables are securely connected to both the docking station and the monitors.
 - Verify that your monitors are set to the correct HDMI input source.

- Try restarting your host device.
- **Monitors Displaying Same Content (macOS):**
 - This is a known limitation of macOS. macOS devices do not support MST (Multi-Stream Transport) mode, meaning both external monitors will mirror each other when extended. This is not a defect of the docking station.
- **No Power Delivery (Charging):**
 - Ensure your host device's USB-C port supports Power Delivery.
 - Verify that your original USB-C power adapter is connected to the PD port on the docking station and is functioning correctly.
 - Check if the power adapter provides sufficient wattage (e.g., 100W).
- **USB Devices Not Recognized:**
 - Ensure USB devices are properly inserted into the ports.
 - Try connecting the USB device directly to your host device to confirm it is working.
 - Restart your host device.
- **Intermittent Connection:**
 - Ensure all connections are firm and stable.
 - Avoid placing the docking station near strong electromagnetic interference sources.

8. SPECIFICATIONS

Feature	Specification
Product Dimensions	5.91 x 1.34 x 0.51 inches
Item Weight	2.12 ounces
ASIN	B0D5XT6MM3
Brand	Newmight
Color	Silver
Hardware Interface	HDMI, Thunderbolt, USB 3.0
Total USB Ports	4 (3 x USB 3.0, 1 x USB C 3.0)
Data Transfer Rate	5 Gigabits Per Second
Power Delivery	Up to 100W
HDMI Resolution	Up to 4K@30Hz
Manufacturer	Newmight
Date First Available	June 3, 2024

9. WARRANTY AND SUPPORT

Newmight provides a **24-month warranty period** for this product, ensuring your long-term satisfaction with your purchase. During this period, if you encounter any product-related problems, please do not hesitate to contact our friendly customer service team. We are committed to resolving your issues in a timely manner.

For support, please refer to the contact information provided with your purchase or visit the official Newmight website.