

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

manuals.plus /

- › [Gurexl](#) /
- › [Gurexl 3-in-1 Vanity Desk User Manual](#)

Gurexl Dressing Tables

Gurexl 3-in-1 Vanity Desk User Manual

MODEL: DRESSING TABLES

Brand: Gurexl

1. Product Overview

The Gurexl 3-in-1 Vanity Desk is a versatile furniture piece designed to function as a vanity, a nightstand, and an office table. It features a human sensor LED light, a convenient charging station, and ample storage solutions, making it ideal for bedrooms and compact spaces.



Figure 1: Gurexl 3-in-1 Vanity Desk in a bedroom. This image shows the vanity desk with its flip-up mirror, integrated lighting, and accompanying cushioned stool, positioned next to a bed.

2. Safety Information

Please read and understand all safety warnings before assembly and use. Failure to follow these instructions may result in injury or damage to the product.

- Assembly may involve sharp edges and pinch points. Exercise caution during handling.
- Always unplug electrical components before assembly, cleaning, or maintenance.
- Do not exceed the weight limit of the vanity or its components. Refer to the specifications for details.
- Keep electrical components dry and away from heat sources to prevent fire or electric shock.
- Ensure all connections are secure before using the product.
- Always follow the instructions provided in the assembly manual for safe and correct setup.

3. Package Contents

Before beginning assembly, verify that all parts listed below are present and undamaged. If any parts are missing or damaged, please contact Gurexl customer service.

- Vanity Desk Main Frame Components
- Flip-up Mirror Assembly
- LED Light Strip and Human Sensor Module
- Integrated Power Strip (AC Outlets, USB, Type-C)
- Drawers and Cabinet Doors
- Cushioned Stool Components
- Hardware Pack (screws, dowels, cam locks, etc.)
- Assembly Tools (screwdriver, wrench, if applicable)
- Instruction Manual

4. Assembly Instructions

Assembly of the Gurexl 3-in-1 Vanity Desk requires careful attention to detail. Please follow the step-by-step instructions provided in the separate assembly manual included with your product. Organize all parts and hardware before you begin to ensure a smooth process.

1. **Unpack and Identify:** Carefully unpack all components and lay them out on a clean, soft surface to prevent scratches. Identify each part using the diagrams in the assembly manual.
2. **Hardware Check:** Verify all hardware pieces are present against the parts list.
3. **Follow Step-by-Step:** Adhere strictly to the sequence of steps outlined in the assembly manual. Do not overtighten screws unless specified.
4. **Electrical Connections:** Connect the LED light and charging station components as instructed. Ensure power is off during this step.
5. **Final Checks:** Once assembled, ensure all connections are secure and the unit is stable before use.



Figure 2: Product Dimensions. This diagram illustrates the height, width, and depth of the vanity desk, providing essential measurements for placement and assembly.

5. Operating Instructions

5.1. Human Sensor LED Light

The vanity desk features an integrated LED light with a human sensor for convenience and energy saving.

- **Light Adjustment:** The LED light offers 3 dimmable colors: blue, white, and warm white.
- **Color Change:** Short press the light control button to cycle through the three color temperatures.
- **Brightness Adjustment:** Long press the light control button to adjust the brightness from 10% to 100%.
- **Human Sensor Function:** When activated, the light automatically turns on when a person approaches within 3-4 meters and turns off approximately 30 seconds after you leave the area.

SMART HUMAN INDUCTION

When the human body sensor function is on, the light will automatically turn on when you approach the buffet within 3-4 meters. After leaving the buffet for 30 seconds, the light will then automatically turn off.



Figure 3: Adjustable LED Lights. This image demonstrates the three available light colors (blue, white, warm white) and their dimmable range, highlighting the versatility of the integrated lighting.



Figure 4: Smart Human Induction. This diagram illustrates how the human sensor detects presence within 1-2 meters, automatically activating the light for convenience.

5.2. Convenient Charging Station

The vanity desk is equipped with a built-in charging station to power your electronic devices.

- **AC Outlets:** Features 2 standard 120V/12A AC outlets for powering hair dryers, curling irons, or other small appliances.

- **USB Port:** Includes 1 USB port (5V/2A) for charging smartphones, tablets, and other USB-powered devices.
- **Type-C Port:** Includes 1 Type-C port for modern devices requiring USB-C connectivity.



Figure 5: Recessed Power Strip. This image provides a detailed view of the integrated power strip, showing the two AC outlets, one USB port, and one Type-C port, ready for device charging.

5.3. Flip-up Mirror

The vanity desk includes a flip-up mirror that transforms the unit from a nightstand/desk into a functional vanity.

- **Operation:** Gently lift the top panel to reveal the mirror and the integrated jewelry organizer.
- **Conversion:** When the mirror is flipped down, the unit functions as a flat-top nightstand or a compact desk.

DIMENSION



Figure 6: Flip-up Mirror in Use. This image shows the vanity desk with its mirror flipped up, demonstrating its use for makeup application.

5.4. Storage Features

The vanity desk offers multiple storage options to keep your items organized.

- **Flip-top Jewelry Organizer:** Located beneath the flip-up mirror, ideal for small items like rings, earrings, and necklaces.
- **Main Drawer:** A spacious drawer below the mirror for cosmetics or personal items.
- **Two-tier Cabinet:** Features height-adjustable shelves for storing taller bottles or various beauty products.
- **Cushioned Stool with Drawer:** The accompanying stool includes a large organizer drawer, providing additional hidden storage.



Figure 7: Adjustable Shelf. This close-up shows the adjustable shelving within the vanity's upper cabinet, allowing for customized storage of various-sized items.



Figure 8: Jewelry Box. A detailed view of the integrated jewelry organizer, showcasing its partitioned compartments designed for rings, bracelets, and other small accessories.

6. Maintenance

Proper maintenance will ensure the longevity and optimal performance of your Gurexl Vanity Desk.

- **Cleaning:** Wipe surfaces with a soft, damp cloth. Avoid harsh chemicals or abrasive cleaners that may damage the finish.
- **Mirror Care:** Clean the mirror with a glass cleaner and a lint-free cloth.
- **Electrical Components:** Ensure the power strip and LED lights are kept dry. Do not spray liquids directly onto electrical parts.
- **Hardware:** Periodically check and tighten any loose screws or fittings to maintain stability.
- **Stool Cushion:** Spot clean the cushioned stool with a mild fabric cleaner as needed.

7. Troubleshooting

If you encounter any issues with your vanity desk, refer to the common problems and solutions below.

Problem	Possible Cause	Solution
LED light not turning on.	Power cord not plugged in; loose connection; sensor obstructed.	Ensure power cord is securely plugged into a working outlet. Check all internal connections. Clear any obstructions from the human sensor.
Charging station not working.	Power cord not plugged in; device not compatible; overloaded circuit.	Verify the main power cord is connected. Ensure your device is compatible with the USB/Type-C port. Avoid plugging in too many high-power devices simultaneously.
Vanity feels wobbly after assembly.	Loose screws or fittings; uneven floor.	Retighten all screws and hardware according to the assembly manual. Place the vanity on a level surface or use furniture pads to stabilize.
Mirror does not flip up smoothly.	Hinges need lubrication; obstruction.	Apply a small amount of silicone lubricant to the hinges. Check for any items obstructing the mirror's movement.

8. Specifications

Feature	Detail
Brand	Gurexl
Model Number	Dressing Tables
Color	Led Grey
Product Dimensions (D x W x H)	15.7"D x 19.6"W x 66.9"H (approx. 15.75 x 19.69 x 35.43 inches for main unit)
Frame Material	Wood
Seat Material Type	Engineered Wood
LED Light Features	3 Dimmable Colors (Blue, White, Warm White), Human Body Sensing (3-4m distance)
Charging Station	2 AC Outlets (120V/12A), 1 USB Port (5V/2A), 1 Type-C Port
Storage Features	Flip-top Jewelry Organizer, 1 Drawer, Two-tier Cabinet with Adjustable Shelves, Cushioned Stool with Drawer

9. Warranty and Support

Gurexl products are designed for quality and durability. For information regarding warranty coverage, technical support, or replacement parts, please refer to the warranty card included with your purchase or contact Gurexl customer service directly through their official website or the retailer where the product was purchased.

Please have your model number (Dressing Tables) and purchase date available when contacting support.

