

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

manuals.plus /

› [TECKNET](#) /

› [TECKNET Multi-Device Wireless Keyboard User Manual](#)

TECKNET TK-KB006

TECKNET Multi-Device Wireless Keyboard User Manual

Model: TK-KB006

INTRODUCTION

Thank you for choosing the TECKNET Multi-Device Wireless Keyboard. This manual provides detailed instructions on how to set up, operate, and maintain your keyboard, ensuring optimal performance and longevity. Please read this manual thoroughly before using the product.



Image: The TECKNET Multi-Device Wireless Keyboard, showcasing its slim design and the included USB receiver.

PACKAGE CONTENTS

- 1 x TECKNET Multi-Device Wireless Keyboard (Model: TK-KB006)
- 1 x USB Receiver

- 1 x USB-C Charging Cable
- 1 x User Manual

SETUP

Charging the Keyboard

Before first use, fully charge the keyboard. Connect the supplied USB-C charging cable to the keyboard's charging port and the other end to a USB power source (e.g., computer USB port, USB wall adapter). The charging indicator light will show the charging status.

- A full charge takes approximately 2 hours.
- A full charge can last up to 180 days based on 2 hours of daily use.

Connecting to Devices (4-Mode Connection)

The TECKNET keyboard supports connection via 2.4G USB receiver and three Bluetooth channels (BT1, BT2, BT3). You can connect up to four different devices simultaneously and switch between them.

2.4G USB Receiver Connection

1. Locate the USB receiver, usually stored in a compartment on the keyboard.
2. Plug the USB receiver into an available USB port on your computer or device.
3. Turn on the keyboard. The keyboard should automatically connect to the device via the 2.4G mode.
4. Press **Fn + 2.4G** (often indicated by a specific key or LED) to switch to 2.4G mode if you are currently in a Bluetooth mode.

Bluetooth Connection (BT1, BT2, BT3)

1. Turn on the keyboard.
2. Press and hold **Fn + BT1** (or **Fn + BT2**, **Fn + BT3**) for 3-5 seconds until the corresponding Bluetooth indicator light flashes rapidly. This indicates the keyboard is in pairing mode.
3. On your device (PC, laptop, tablet, smartphone, Smart TV), go to Bluetooth settings.
4. Search for new devices. You should see "TECKNET Keyboard" or a similar name appear in the list.
5. Select the keyboard to pair. Follow any on-screen prompts, such as entering a pairing code.
6. Once paired, the indicator light will stop flashing and remain solid for a few seconds before turning off, indicating a successful connection.
7. Repeat these steps for BT2 and BT3 to connect up to two additional Bluetooth devices.

OPERATING INSTRUCTIONS

Switching Between Connected Devices

To switch between your connected devices, simply press the corresponding function key:

- **Fn + 2.4G**: Switch to the device connected via the USB receiver.
- **Fn + BT1**: Switch to the device connected via Bluetooth channel 1.
- **Fn + BT2**: Switch to the device connected via Bluetooth channel 2.
- **Fn + BT3**: Switch to the device connected via Bluetooth channel 3.

Operating System Compatibility

The keyboard is compatible with Windows, iOS, macOS, and Android. To optimize key functions for your operating system, use the following combinations:

- **Fn + Q:** Switch to Android layout.
- **Fn + W:** Switch to Windows layout.
- **Fn + E:** Switch to iOS/macOS layout.

Multimedia Keys

The keyboard features 12 multimedia keys (F1-F12) that provide quick access to various functions. These functions are typically accessed by pressing the **Fn** key simultaneously with the desired F-key.

Key Combination	Function
Fn + F1	Home
Fn + F2	Search
Fn + F3	Brightness Down
Fn + F4	Brightness Up
Fn + F5	Previous Track
Fn + F6	Play/Pause
Fn + F7	Next Track
Fn + F8	Mute
Fn + F9	Volume Down
Fn + F10	Volume Up
Fn + F11	Lock Screen
Fn + F12	Screenshot

Power Saving Mode

The keyboard automatically enters sleep mode after 30 minutes of inactivity to conserve battery. To wake it up, simply press any key. The keyboard will reconnect to the last active device.

MAINTENANCE

Cleaning the Keyboard

- Turn off the keyboard before cleaning.
- Use a soft, lint-free cloth slightly dampened with water or a mild cleaning solution.
- Do not use harsh chemicals, abrasives, or solvents.
- Avoid getting moisture into the keycaps or internal components.
- For dust and debris between keys, use compressed air.

Battery Care

- Recharge the keyboard when the low battery indicator lights up.

- Avoid fully discharging the battery frequently to prolong its lifespan.
- If storing the keyboard for an extended period, charge it to about 50% before storage and recharge every few months.
- Do not expose the keyboard to extreme temperatures.

TROUBLESHOOTING

Problem	Possible Cause / Solution
Keyboard not connecting via 2.4G.	<ul style="list-style-type: none"> ◦ Ensure the USB receiver is securely plugged into a working USB port. ◦ Make sure the keyboard is turned on and in 2.4G mode (Fn + 2.4G). ◦ Try plugging the receiver into a different USB port. ◦ Reboot your device.
Keyboard not connecting via Bluetooth.	<ul style="list-style-type: none"> ◦ Ensure the keyboard is in the correct Bluetooth pairing mode (Fn + BT1/BT2/BT3, flashing light). ◦ Make sure Bluetooth is enabled on your device. ◦ Remove any previous pairings of the keyboard from your device's Bluetooth list and try pairing again. ◦ Ensure the keyboard is within the 15m operating range. ◦ Check if the keyboard battery is low.
Keys are not responding or typing incorrectly.	<ul style="list-style-type: none"> ◦ Check the battery level and recharge if necessary. ◦ Ensure the keyboard is connected to the correct device/mode. ◦ Try switching the operating system layout (Fn + Q/W/E). ◦ Restart the keyboard and your device.
Keyboard frequently disconnects.	<ul style="list-style-type: none"> ◦ Move the keyboard closer to the device. ◦ Avoid sources of strong electromagnetic interference (e.g., Wi-Fi routers, other wireless devices). ◦ Ensure the battery is sufficiently charged.

SPECIFICATIONS


- **Model:** TK-KB006
- **Brand:** TECKNET
- **Connectivity:** 2.4G Wireless, Bluetooth (BT1, BT2, BT3)
- **Operating Range:** Up to 15 meters (49 feet)
- **Battery Capacity:** 500 mAh (Rechargeable)
- **Charging Time:** Approximately 2 hours
- **Battery Life:** Up to 180 days (based on 2 hours/day usage)
- **Key Lifespan:** Up to 10 million keystrokes
- **Key Travel:** 2 mm
- **Compatibility:** Windows, iOS, macOS, Android
- **Special Features:** 4-mode connection, Quiet keys, Ergonomic design, Adjustable tilt stand, 12 Multimedia keys, Auto-sleep function.

WARRANTY AND SUPPORT

TECKNET offers comprehensive support for your product. The keyboard comes with a 36-month (3-year) support period upon registration. For any issues or inquiries, please contact TECKNET customer service. For further assistance, please visit the official TECKNET website or contact their support team directly. Details can usually be found on the product packaging or the TECKNET website.

© 2024 TECKNET. All rights reserved.

Related Documents - TK-KB006

	<p>TECKNET TK-CP005 Laptop Cooling Pad User Manual</p> <p>Comprehensive user manual for the TECKNET TK-CP005 Laptop Cooling Pad, covering package contents, product overview, specifications, usage instructions, precautions, FAQs, warranty information, and EU declaration of conformity.</p>
	<p>TECKNET Wireless Doorbell TK-WD895/TK-WD896 User Manual</p> <p>User manual for the TECKNET Wireless Doorbell models TK-WD895 and TK-WD896. This guide provides instructions on package contents, specifications, installation of the push button and receiver, usage, pairing, and safety information.</p>
	<p>TeckNet TK-MS009 Wireless Rechargeable Mouse User Manual</p> <p>User manual for the TeckNet TK-MS009 Wireless Rechargeable Mouse, including setup, features, and safety instructions.</p>
	<p>TECKNET Wireless Doorbell TK-WD995/TK-WD996 User Manual & Installation Guide</p> <p>Comprehensive user manual for the TECKNET wireless doorbell models TK-WD995 and TK-WD996. Includes installation instructions, operation guide, safety information, specifications, and warranty details.</p>
	<p>TeckNet TK-MS001 Wireless Rechargeable Silent Mouse User Manual</p> <p>User manual for the TeckNet TK-MS001 Wireless Rechargeable Silent Mouse, detailing setup, 2.4GHz and Bluetooth connectivity, DPI settings, charging, safety precautions, warranty, and disposal instructions.</p>
	<p>TECKNET TK-MS317 Wireless Rechargeable Mouse User Manual</p> <p>User manual for the TECKNET TK-MS317 Wireless Rechargeable Mouse, covering setup, usage, charging, specifications, safety instructions, and warranty information.</p>