

AQQA AQ061

AQQA LED Aquarium Light User Manual

Model: AQ061

1. INTRODUCTION

Thank you for choosing the AQQA LED Aquarium Light. This manual provides detailed instructions for the safe and efficient operation of your new aquarium light. Designed for optimal plant growth and vibrant aquatic environments, this light offers advanced features including 24/7 natural light simulation, DIY customization, and a convenient memory function. Please read this manual thoroughly before installation and use.



Figure 1.1: Overview of the AQQA LED Aquarium Light and its components.

2. SAFETY INSTRUCTIONS

To ensure safe operation and prevent damage, please observe the following precautions:

- Always disconnect the power supply before performing any maintenance or installation.
- This product is designed for indoor use with aquariums only. Do not use it for purposes other than its intended use.
- Ensure your hands are dry when handling the power plug or controller.
- Do not immerse the controller or power adapter in water. The light fixture itself is IP68 waterproof.
- Keep out of reach of children.
- Do not operate if any part of the light or power cord is damaged. Contact customer support for assistance.
- Ensure the light is securely clipped to the aquarium before powering on.

3. PACKAGE CONTENTS

Verify that all items are present in the package:

- 1 x AQQA Aquarium Light
- 1 x Controller

4. PRODUCT FEATURES

The AQQA LED Aquarium Light is equipped with advanced features to enhance your aquatic environment:

- **High Quality Construction:** Features a widened and thickened aluminum shell for durability and efficient heat dissipation. Utilizes premium 5050 and 2835 LEDs for optimal plant growth.
- **DIY Mode:** Allows simultaneous adjustment of brightness, color, and timing. Offers 5 levels of brightness (10%-100%), 3 timer settings (6H/10H/12H), and 7 light colors plus full spectrum and auto color cycle.
- **24/7 Default Mode:** Simulates natural light cycles, transitioning from warm orange at sunrise to bright full-spectrum at noon, and starry blue at night. Default on/off times are 6 AM and 10:58 PM, which can be adjusted.
- **Flexible Adjustable Design:** A 7-inch 360° flexible gooseneck tube allows for easy angle and direction adjustment. The aluminum alloy clip with tightening screws ensures secure mounting on framed or frameless aquariums up to 0.9 inches thick.
- **Memory Function:** Retains previous settings (color, brightness, timing) after a power outage, eliminating the need for re-setup.

26W FULL SPECTRUM AQUARIUM LIGHT

Perfect for Plant Growth

DC 12V

Output

72PCS

LED quantity (PCS)

AC 100-240V

Input

24-32inches

Application tank size

Premium 5050 and 2835 LEDS




Figure 4.1: Detailed view of the full spectrum LED array, optimized for plant growth.

5. SETUP GUIDE

Follow these steps to install your AQQA LED Aquarium Light:

1. **Attach the Clip:** Secure the aluminum alloy clip to the edge of your aquarium. Ensure the clip is firmly tightened using the screws provided, suitable for tank thickness up to 0.9 inches.
2. **Position the Light:** Insert the flexible gooseneck tube into the clip. Adjust the gooseneck to position the light fixture directly over your aquarium. The 360° flexibility allows for precise placement.
3. **Connect Power:** Plug the light's power cord into the controller, and then plug the controller's power adapter into a suitable electrical outlet.

FLEXIBLE CLIP ON AQUARIUM LIGHTS



Figure 5.1: Illustration of the flexible clip-on installation method.

6. OPERATING MODES

Your AQQA LED Aquarium Light offers two primary operating modes: DIY Mode for custom settings and 24/7 Default Mode for automated light cycles.

6.1. DIY Mode

The DIY mode allows you to manually set the timer, color, and brightness. Use the inline controller to navigate these settings.

- **Timer Setting:** Press the 'TIMER' button to cycle through 6H, 10H, or 12H lighting durations.
- **Color Adjustment:** Press the 'C/M' button to change between 7 individual colors (Red, Green, Blue, Orange, Yellow, Cyan Blue, Purple), full spectrum white, or an auto color cycle. Press and hold for 3 seconds to exit color mode.
- **Brightness Control:** Press the '%' button to adjust brightness levels (10%, 25%, 50%, 75%, 100%).
Note: Brightness cannot be adjusted in 24/7 mode.

DIY Mode

Time + color + brightness can be set simultaneously

Timer

Three lighting time setting choices: 6H、10H、12H



6H



10H



12H

Color

(Press and hold for 3 seconds to close)

(7 lighting modes + full spectrum + auto color cycle)



Brightness

5 levels light brightness(10%-25%-50%-75%-100%)



10%

25%

50%

75%

100%



Please note

The automatic dimming mode and the 24/7 mode are not able to adjust the brightness.




Figure 6.1: The inline controller for DIY mode settings.

8 LIGHTING MODES + AUTO COLOR CYCLY

7 Colors + full spectrum + color cycle



Figure 6.2: Visual representation of the 8 available lighting modes.

6.2. 24/7 Default Mode

This mode simulates a natural 24-hour light cycle, automatically adjusting light intensity and color throughout the day. The default cycle starts at 6 AM and ends at 10:58 PM.

- **Activation:** Press the '24/7' button on the controller to activate this mode.
- **Light Cycle:** The light will gradually transition from warm orange (sunrise) to bright full-spectrum (noon), then to a dimmer blue light (moonlight) before turning off.
- **Time Adjustment:** The overall default time period can be postponed or advanced to better suit your schedule.

24/7 DEFAULT MODE

Simulates natural living environments




Figure 6.3: The 24/7 default mode light cycle simulation.

7. MAINTENANCE

Regular maintenance ensures the longevity and optimal performance of your aquarium light:

- **Cleaning:** Periodically wipe the light fixture with a soft, damp cloth to remove water spots, dust, and algae buildup. Ensure the light is unplugged before cleaning.
- **Inspect Cables:** Regularly check the power cord and controller for any signs of damage, fraying, or kinks.
- **LED Surface:** Avoid scratching the LED surface. Do not use abrasive cleaners.

8. TROUBLESHOOTING

If you encounter issues with your AQQA LED Aquarium Light, refer to the following common problems and solutions:

Problem	Possible Cause	Solution
---------	----------------	----------

Problem	Possible Cause	Solution
Light does not turn on.	No power supply; loose connection; damaged power adapter/controller.	Check power outlet; ensure all connections are secure; test with another outlet; if still not working, contact support.
Light flickers or dims unexpectedly.	Unstable power supply; loose connection; internal fault.	Ensure stable power; check connections; if problem persists, discontinue use and contact support.
Controller buttons are unresponsive.	Controller malfunction; temporary software glitch.	Unplug the light for 30 seconds and plug it back in to reset. If unresponsive, contact support.
Light does not retain settings after power cycle.	Memory function error (rare).	Ensure the light was powered off correctly (not just unplugged). If the issue persists, contact support.

9. TECHNICAL SPECIFICATIONS











Specification	Detail
Model Number	AQ061
Wattage	26 Watts
Input Voltage	AC 100-240V
Output Voltage	DC 12V
LED Quantity	72 PCS
Material	Aluminum, Stainless Steel
Finish Type	Brushed
Light Source Type	Light Emitting Diode (LED)
Mounting Type	Clip Mount
IP Rating	IP68 (Light fixture only)
Product Dimensions	1"L x 1"W x 1"H (Approximate, as per product data)
Item Weight	2.25 pounds
Compatible Tank Size	24-32 inches
Max Tank Thickness for Clip	0.9 inches


10. WARRANTY AND SUPPORT

AQQA products are manufactured to high-quality standards. For warranty information, technical support, or any inquiries regarding your AQQA LED Aquarium Light, please refer to the contact information provided with your purchase or visit the official AQQA brand store on Amazon.

Online Support: [Visit the AQQA Store on Amazon](#)

Related Documents - AQ061


<div><p>AQ147 USER MANUAL AQQA Full Spectrum COB LED Aquarium Light</p><p><small>AQQA Full Spectrum COB LED Aquarium Light adopts full spectrum imported lamp beads and advanced light control technology, providing high-quality lighting for your aquarium. Please read the instruction manual carefully before using the light to ensure the best lighting effect. The light should be used in a well-ventilated area and should not be used for a long time. Please refer to the AQQA brand manual.</small></p></div>	<p>AQQA AQ147 Full Spectrum COB LED Aquarium Light User Manual</p> <p>User manual for the AQQA AQ147 Full Spectrum COB LED Aquarium Light, detailing product features, parameters, functions, installation, safety precautions, warranty, and disposal.</p>
<div><p>MINI DESKTOP FISH TANK USER MANUAL AQ030</p><p><small>Thank you for choosing AQQA products. The AQQA mini desktop fish tank is an all-in-one style aquarium tank kit. Perfect for home decoration, office or gift.</small></p><p><small>ATTENTION: Glass, fish, plants and decor are not included.</small></p></div>	<p>AQQA AQ030 Mini Desktop Fish Tank User Manual</p> <p>User manual for the AQQA AQ030 mini desktop fish tank, detailing product features, setup instructions, troubleshooting, maintenance, specifications, cautions, and warranty information.</p>
<div><p>AQ-032 USER MANUAL AQQA Aquarium Magnet Cleaner Brush</p><p><small>AQQA aquarium magnet cleaner brush used as scrubber and scraper, suitable for freshwater and saltwater tanks. Please read this user manual carefully before use and follow strictly in accordance with the manual.</small></p><p><small>Do not put your fingers between the magic brush and the ferris brush, be careful of your fingers being pinched by the cleaner.</small></p></div>	<p>AQQA AQ-032 Aquarium Magnet Cleaner Brush User Manual</p> <p>User manual for the AQQA AQ-032 Aquarium Magnet Cleaner Brush, detailing product features, parameters, application methods, safety precautions, package contents, and warranty information.</p>
<div><p>AQ087 USER MANUAL AQQA Aquarium Submersible Pump</p><p><small>The AQQA submersible pump provides a quiet water flow. The submersible pump is suitable for aquariums, ponds, fish tanks, fountains, waterfalls, hydroponics, aerators, humidifiers, misters, and more.</small></p><p><small>CAUTION: Please note that the pump must be completely submerged in water before operating. Please refer to the manual for more details. The pump is not suitable for use outdoors.</small></p><p><small>Please read the manual carefully before using the product and follow the instructions to ensure proper operation.</small></p></div>	<p>AQQA AQ087 Aquarium Submersible Pump User Manual</p> <p>User manual for the AQQA AQ087 Aquarium Submersible Pump, detailing product features, parameters, packing list, diagram, warnings, maintenance, troubleshooting, disposal, and warranty information.</p>
<div><p>AQ121 AQQA MULTI-FUNCTIONAL FISH TANK STAND INSTALLATION PROCEDURE MANUAL</p><p><small>Installation Instructions:</small> Don't tighten screws completely at first, just to close parts when assembled. Adjust and then tighten screws. Tighten screws at last when all parts are put together.</p></div>	<p>AQ121 AQQA Multi-Functional Fish Tank Stand Installation Manual</p> <p>Step-by-step installation guide for the AQ121 AQQA Multi-Functional Fish Tank Stand, including a detailed parts list and assembly instructions for easy setup.</p>



AQQA AQ157 User Manual: Multifunctional Electric Gravel Cleaner

User manual for the AQQA AQ157 DC Multifunctional Electric Gravel Cleaner, detailing its 6-in-1 features for aquarium maintenance, including gravel cleaning, water changes, and filtration. Covers specifications, assembly, operation, troubleshooting, safety, and warranty.

Documents - AQQA – AQ061




[\[pdf\]](#) User Manual

AQ061 User Manual Download Now AQQA Make fish keeping easier! aqqa aq061 aqqapet user manual
 USER MANUAL Aquarium clip light Aluminum Alloy Clip The aluminum alloy is equipped with screws for
 tightening and are safe to use on framed or frameless aquariums up 0 98 inches thick |||

• • •

lang: score:27 filesize: 7.59 M page_count: 8 document date: 2025-05-27



[\[pdf\]](#) User Manual

AQ061 cdr Administrator Download Now Manual AQQA Make fish keeping easier! AQ061 aqqapet
2024 12 Untitled |||

...

lang: **score:25** filesize: 12.41 M page_count: 1 document date: 2023-12-08