Saved from manuals.plus.
Open the live page for links to other documents and user manuals.

KQLKJ KQ-36A

KQLKJ Air Purifier KQ-36A User Manual

Model: KQ-36A

1. Introduction

Thank you for choosing the KQLKJ Air Purifier KQ-36A. This manual provides essential information for the safe and efficient operation, maintenance, and troubleshooting of your new air purifier. Please read it thoroughly before use and retain it for future reference.

The KQLKJ KQ-36A is designed to improve indoor air quality in large rooms, covering up to 2100 square feet. It features a 3-stage filtration system, intelligent air quality detection, and multiple operating modes for a comfortable and healthy environment.

2. Important Safety Instructions

To reduce the risk of fire, electric shock, or injury, please observe the following safety precautions:

- Always unplug the air purifier before moving, cleaning, or performing any maintenance.
- Do not operate the unit with a damaged cord or plug. If the cord is damaged, it must be replaced by the manufacturer or a qualified service agent.
- Keep the power cord away from heated surfaces.
- Do not use the air purifier in wet or damp environments, such as bathrooms or laundry rooms.
- Do not insert fingers or foreign objects into any openings.
- Ensure the air inlet and outlet are not blocked.
- This appliance is not intended for use by persons (including children) with reduced physical, sensory, or mental capabilities, or lack of experience and knowledge, unless they have been given supervision or instruction concerning use of the appliance by a person responsible for their safety.
- Children should be supervised to ensure that they do not play with the appliance.
- Use only KQLKJ genuine replacement filters.



Figure 2.1: The KQLKJ Air Purifier is designed to address common indoor air pollutants such as allergens, dust, smoke, odors, pet hair, and dander. It also features a child lock for enhanced safety.

3. Package Contents

Carefully unpack your air purifier and check that all items are included:

- KQLKJ Air Purifier Unit (Model KQ-36A)
- 3-in-1 HEPA Filter
- Power Adapter
- User Manual (this document)



Figure 3.1: Included components: the KQLKJ Air Purifier KQ-36A unit and its 3-in-1 HEPA filter. The image also illustrates the approximate dimensions of the unit.

4. Product Overview

Familiarize yourself with the main components of your air purifier:

- **Control Panel:** Touch-sensitive interface for all functions.
- **Air Inlet:** Where air enters the purifier for filtration.
- **Air Outlet:** Where purified air is released.
- **Filter Compartment:** Houses the 3-in-1 HEPA filter.
- **Power Port:** For connecting the power adapter.
- **Air Quality Sensor:** Detects airborne particle levels.



Figure 4.1: Front view of the KQLKJ Air Purifier KQ-36A, showcasing its sleek design and control panel.

5. Setup Guide

5.1. Filter Installation

The filter may come pre-installed or wrapped separately. If wrapped, remove all packaging before use.

1. Place the air purifier on a flat, stable surface.
2. Turn the unit upside down and twist the base cover counter-clockwise to unlock and remove it.
3. Remove the plastic packaging from the 3-in-1 HEPA filter.
4. Insert the filter into the unit with the pull tabs facing outwards.
5. Replace the base cover and twist clockwise to lock it securely.

5.2. Placement

For optimal performance, place the air purifier in a central location within the room, ensuring at least 6 inches (15 cm) of clearance from walls or furniture to allow for proper airflow.



Figure 5.1: The KQLKJ Air Purifier is suitable for large rooms, capable of purifying air up to 5 times per hour in a 2100 sq ft space.

5.3. Power Connection

Connect the power adapter to the power port on the back of the unit, then plug the adapter into a standard electrical outlet.

6. Operating Instructions

The air purifier features a touch control panel. Refer to the control panel diagram in Section 4 for button locations.

6.1. Power On/Off

- Touch the **Power Button** to turn the unit on or off.

- When powered on, the unit will start in its default mode or the last used setting.

6.2. Fan Speed Adjustment

- Touch the **Fan Speed Button** repeatedly to cycle through fan speeds: Low, Medium, High, Turbo.

6.3. Auto Mode

In Auto Mode, the built-in PM0.3 air quality sensor detects the surrounding air quality and automatically adjusts the fan speed accordingly.

- Touch the **Auto Mode Button** to activate this feature.
- The display will show the current air quality level (Good, Moderate, Bad) and the fan speed will adjust automatically.



Figure 6.1: The air purifier's intelligent sensor provides real-time air quality detection, categorizing it as Good (0-35 ug/m³), Moderate (36-75 ug/m³), or Bad (>76 ug/m³), and adjusts operation in Auto Mode.

6.4. Sleep Mode

Sleep Mode operates the purifier at the lowest fan speed and dims all indicator lights to ensure a quiet and undisturbed sleeping environment (noise level as low as 20dB).

- Touch the **Sleep Mode Button** to activate or deactivate Sleep Mode.



Figure 6.2: The KQLKJ Air Purifier features an ultra-quiet Sleep Mode, operating at approximately 20dB, and includes a timer function for a restful night.

6.5. Timer Function

Set the purifier to operate for a specific duration before automatically turning off.

- Touch the **Timer Button** repeatedly to cycle through timer settings: 4H, 8H, 12H, 16H, 24H.
- To cancel the timer, cycle through all settings until no timer duration is displayed.

6.6. Child Lock

The Child Lock feature prevents accidental changes to settings by disabling the control panel.

- Press and hold the **Child Lock Button** (or a combination of buttons as indicated on the unit) for 3 seconds to activate or deactivate the Child Lock.
- When active, a lock icon may appear on the display.

6.7. Ambient Lighting

The air purifier includes 7 RGB color-changing lights to enhance the room's ambiance.

- Touch the **Light Button** to cycle through different light colors or turn the lighting off.



Figure 6.3: The KQLKJ Air Purifier offers 7 RGB color-changing ambient lights, providing a dynamic atmosphere while purifying the air.

7. Maintenance

Regular maintenance ensures optimal performance and extends the lifespan of your air purifier.

7.1. Filter Replacement

The 3-in-1 HEPA filter should be replaced every 6-8 months, depending on usage and air quality. A filter indicator light on the control panel will illuminate when it's time for replacement.

1. Unplug the air purifier from the power outlet.
2. Turn the unit upside down and twist the base cover counter-clockwise to unlock and remove it.
3. Remove the old filter by pulling on its tabs.
4. Insert a new KQLKJ genuine 3-in-1 HEPA filter (ensure all packaging is removed) with the pull tabs facing outwards.
5. Replace the base cover and twist clockwise to lock it securely.
6. Plug in the air purifier. Press and hold the**Filter Reset Button** (or Power Button for 5 seconds, refer to unit's specific instructions) until the filter indicator light turns off, resetting the filter timer.



Figure 7.1: The 3-stage filtration system efficiently captures 99.997% of particles as small as 0.1 microns, including allergens, dust, and pet dander.

7.2. Cleaning the Unit

- Always unplug the unit before cleaning.

- Wipe the exterior of the air purifier with a soft, dry cloth.
- Do not use abrasive cleaners or solvents.
- Periodically vacuum the air inlet and outlet grilles to remove dust buildup.

8. Troubleshooting

If you encounter issues with your air purifier, refer to the following table for common problems and solutions.

Problem	Possible Cause	Solution
Unit does not turn on.	Not plugged in; power outage; damaged cord/plug.	Ensure power cord is securely plugged in. Check power outlet. Contact customer support if cord is damaged.
Weak airflow or no purification.	Filter clogged; filter packaging not removed; air inlets/outlets blocked.	Check and replace filter if necessary. Ensure filter packaging is removed. Clear any obstructions from air inlets/outlets.
Unusual noise.	Unit not on a flat surface; foreign object inside; filter not installed correctly.	Place unit on a flat, stable surface. Unplug and check for foreign objects. Reinstall filter correctly.
Filter indicator light remains on after replacement.	Filter timer not reset.	Press and hold the Filter Reset Button (or Power Button for 5 seconds) to reset the filter timer.
Child Lock is active, controls unresponsive.	Child Lock feature is engaged.	Press and hold the Child Lock Button (or specified combination) for 3 seconds to deactivate.

9. Specifications

Feature	Detail
Model Number	KQ-36A
Brand	KQLKJ
Coverage Area	Up to 2100 sq ft
Purification Rate	5 times/hour (in turbo mode)
Filtration System	3-in-1 (Pre-Filter, True H13 HEPA, Activated Carbon)
Noise Level	As low as 20dB (Sleep Mode)
Control Method	Touch Control
Power Source	DC
Timer Settings	4H, 8H, 12H, 16H, 24H

Feature	Detail
Dimensions (W x D x H)	Approx. 12.4" x 6.5" x 16.14"
Item Weight	7.5 Pounds
Certifications	CARB, EPA, FCC, RoHS, UL Certified

10. Warranty and Customer Support

KQLKJ provides 24/7 customer support for your air purifier. For any questions, concerns, or warranty claims, please contact our support team through the retailer's platform or the contact information provided with your purchase. Please retain your proof of purchase for warranty purposes.

© 2025 KQLKJ. All rights reserved.

Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

Open the live page

https://manuals.plus/asin/B0DFVYG9QV

More documents and user manuals: **https://manuals.plus/**