

[Manuals.plus](#) /

› [SZHLUX](#) /

› SZHLUX PT6000 600W LED Grow Light Instruction Manual

SZHLUX PT6000

SZHLUX PT6000 600W LED Grow Light Instruction Manual

Model: PT6000 | Brand: SZHLUX

INTRODUCTION

Thank you for choosing the SZHLUX PT6000 600W LED Grow Light. This manual provides essential information for the safe and efficient operation of your new grow light. Please read these instructions carefully before installation and use to ensure optimal performance and plant growth.

PRODUCT OVERVIEW AND KEY FEATURES

The SZHLUX PT6000 LED Grow Light is designed for indoor plant cultivation, offering a full spectrum light output to support all stages of plant growth from seedling to bloom. Its advanced features ensure high efficiency and user-friendly control.

- **High Efficiency and Low Energy Consumption:** Utilizes the latest LED technology with 1728 diodes, achieving an energy efficiency of 2.9 $\mu\text{mol/J}$. Delivers powerful light output and uniform canopy penetration for maximum yields over a 4 x 6 ft effective footprint. Actual power consumption is 600W.
- **Temperature Control and Timer Modes:** Features an upgraded PT series with a built-in temperature sensor, temperature button, and timer button. The auto-setting temperature is 85°F. The light adjusts output based on temperature: 7 light bars on at 86°F, 5 light bars on at 91°F, and the light turns off at 96°F to prevent overheating.
- **Sunlight Full Spectrum:** Provides a spectrum infinitely close to natural sunlight, ensuring over 95% light energy absorption by plants. Includes white (3000K, 5000K), blue, red (660nm), and IR (730nm) light. 5000K blue light promotes seedling growth, while 660nm red and 730nm IR light are crucial for photosynthesis, flowering, fruiting, and overall crop quality.
- **Trapezoid Tube and Fanless Design:** Features an innovative trapezoid-shaped LED tube for a larger luminous area compared to traditional T5 and T8 LED tubes. The premium aluminum shell with a fanless design ensures faster heat dissipation, providing quiet operation and allowing plants to receive more energy without burning.
- **Cost-Effective Upgraded Grow Lamp:** Offers significant energy savings compared to HPS lights. The upgraded PT series incorporates a modern drive with temperature control and timing design buttons, replacing traditional dimming knobs for more scientific control throughout all plant growth stages.

WHAT'S IN THE BOX

Verify that all components are present upon unpacking:

- SZHLUX PT6000 LED Grow Light Unit x1

- Power Cord x1
- Hanging Rope with Pulley x2
- Steel Hanging Cable x2
- Temperature Sensor x1




Figure 1: Product Dimensions and Included Accessories. This image displays the grow light's dimensions (47.2"L x 23.6"W x 2.55"H) and lists the included accessories: power cord, hanging ropes with pulleys, steel hanging cables, and a temperature sensor.

SETUP INSTRUCTIONS

1. **Unpack Components:** Carefully remove all items from the packaging and verify against the 'What's in the Box' list.
2. **Choose Location:** Select an indoor location with adequate space for the 4x6 ft effective footprint. Ensure proper ventilation.
3. **Install Hanging System:** Attach the hanging ropes with pulleys or steel hanging cables to sturdy support structures above your plants. Ensure the hanging system can safely support the weight of the grow light (approximately 19.16 pounds).
4. **Mount Grow Light:** Securely attach the grow light to the installed hanging system. Adjust the height according to the recommended hanging heights for your plant's growth stage (refer to 'Recommended Hanging Height' section).
5. **Connect Temperature Sensor:** Plug the temperature sensor into the designated port on the grow light unit. Position the sensor near your plants for accurate temperature readings.
6. **Connect Power:** Plug the power cord into the grow light unit, then plug the other end into a standard 120V AC power outlet.

Timing and Temp Control Integrated

Auto-cycle modes by different temperature instead of normal dimming button, reduce the loss of light, more scientifically promote the growth of plants from seedling to fruiting.



Figure 2: SZHLUX PT6000 LED Grow Light. This image shows the overall design of the grow light, ready for installation.

OPERATING INSTRUCTIONS

The SZHLUX PT6000 features an integrated control panel and can also be operated via a remote control (if included with your specific package).

Integrated Control Panel

The top of the grow light unit features a digital display and control buttons for direct operation.

- **Power Button:** Press to turn the light ON or OFF.
- **Timer Button:** Press to set the desired operating duration. The light will automatically turn off after the set time.
- **Temperature Button:** Activates the temperature control mode. The light will adjust its output based on the ambient temperature detected by the sensor.
- **+/- Buttons:** Use these buttons to adjust temperature settings or timer duration.

Remote Control (if applicable)

For convenient operation, use the remote control to manage the grow light's functions from a distance.

- **Power Button:** Turns the light ON/OFF.
- **Lock Button:** Locks the current settings to prevent accidental changes.
- **Timer Button:** Sets the operating timer.
- **Temperature Button:** Activates temperature-based light adjustment.
- **+/- Buttons:** Adjust temperature or timer settings.



Figure 3: Integrated Timing and Temperature Control Panel. This image illustrates the auto-cycle modes based on temperature, showing how the number of active light bars changes to manage heat and optimize plant growth.

TEMPERATURE CONTROL AND TIMER MODES

The grow light's intelligent temperature control system helps maintain an optimal environment for your plants and prevents overheating.

- The auto-setting temperature is preset to 85°F (29.4°C).
- If the ambient temperature reaches 86°F (30°C), the light will automatically reduce its output to 7 active light bars.
- If the temperature further rises to 91°F (32.8°C), the light will reduce output to 5 active light bars.
- Should the temperature reach 96°F (35.6°C), the light will automatically turn off to protect itself and your plants from excessive heat.
- Use the timer function to set specific operating hours, ensuring your plants receive consistent light cycles without manual intervention.

RECOMMENDED HANGING HEIGHT

Adjusting the hanging height of your grow light is crucial for delivering the correct light intensity (PPFD) to your plants at different growth stages. The integrated temperature sensor allows for proper height adjustment to optimize PPF value.

- **Seedling Stage:** 24-30 inches above canopy (16-18 hours/day)
- **Growth Stage:** 18-24 inches above canopy (14-16 hours/day)
- **Blooming Stage:** 12-18 inches above canopy (12-14 hours/day)
- **Fruiting Stage:** 8-14 inches above canopy (10-12 hours/day)

Recommended Hanging Height




Figure 4: Recommended Hanging Heights for Plant Growth Stages. This diagram illustrates optimal hanging distances and corresponding PPFD values for seedlings, growth, blooming, and fruiting stages.




Figure 5: PPFD Distribution Map in a 4x4ft Grow Tent. This map shows the Photosynthetic Photon Flux Density (PPFD) values at various heights (11.8", 19.89", 39.87") within a 4x4ft (120x120cm) grow tent, demonstrating light uniformity.

SPECIFICATIONS

Brand	SZHLUX
Model Name	PT6000
Wattage	600 watts
Number of Light Sources	1728 LEDs
Energy Efficiency	2.9 Umol/J
Effective Footprint	4 x 6 ft
Light Color	White (3000K, 5000K), Blue, Red (660nm), IR (730nm)

Product Dimensions	47.2"L x 23.6"W x 2.55"H
Item Weight	19.16 pounds
Material	Aluminum
Installation Type	Suspended
Control Method	Remote, Push Button
Special Features	Dimmable, Energy Efficient, Full Spectrum, Temperature Control, Timer
Indoor/Outdoor Usage	Indoor
Voltage	120 Volts
Light Output (Lumen)	84000 Lumens
Water Resistance Level	Not Water Resistant






Figure 8: Full Spectrum Light Output and Efficiency. This graph demonstrates the spectral distribution of the grow light, showing the balance of white, blue, red, and IR light for comprehensive plant development.

MAINTENANCE

To ensure the longevity and optimal performance of your SZHLUX PT6000 LED Grow Light, follow these maintenance guidelines:

- **Cleaning:** Regularly wipe the light bars and housing with a soft, dry cloth to remove dust and debris. Ensure the unit is unplugged before cleaning. Do not use liquid cleaners directly on the light.
- **Ventilation:** Ensure adequate airflow around the grow light to facilitate heat dissipation. Avoid blocking the ventilation slots.
- **Cable Inspection:** Periodically check the power cord and hanging cables for any signs of wear or damage. Replace immediately if any damage is found.

TROUBLESHOOTING

If you encounter issues with your grow light, refer to the following common troubleshooting steps:

- **Light Not Turning On:** Check if the power cord is securely plugged into both the light unit and the power outlet. Verify that the power outlet is functional.
- **Temperature Control Issues:** Ensure the temperature sensor is properly connected and positioned. Check for any obstructions around the sensor that might affect readings.
- **Inconsistent Light Output:** Verify that the light is not in a temperature-triggered auto-adjustment mode. Check timer settings to ensure it's not scheduled to dim or turn off.
- **Overheating:** Ensure the grow light has sufficient clearance for airflow. Reduce ambient room temperature if consistently high. The light's auto-shutdown feature will activate at 96°F (35.6°C).

For further assistance or issues not covered here, please contact SZHLUX customer support.

WARRANTY AND SUPPORT

For information regarding product warranty, returns, or technical support, please refer to the warranty card included with your product or visit the official SZHLUX website. Keep your purchase receipt as proof of purchase for warranty claims.

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. [Privacy details](#).

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question