Saved from manuals.plus.
Open the live page for links to other documents and user manuals.

BelFone BF-SC500UV

BelFone BF-SC500UV Ham Radio Walkie Talkie Instruction Manual

Model: BF-SC500UV

1. Introduction

Thank you for choosing the BelFone BF-SC500UV Ham Radio Walkie Talkie. This professional outdoor two-way radio is designed for reliable communication in various environments. It features a robust, waterproof, and dustproof design, a long-lasting 2600mAh battery, and advanced functions such as UV dual-band operation, fast teaming, monitoring, and encrypted calls. This manual provides essential information for proper setup, operation, and maintenance of your device.



The BelFone BF-SC500UV is designed for outdoor communication.

2. Package Contents

Please check the box for the following items:

- 1 x BelFone BF-SC500UV Walkie Talkie
- 1 x Charger
- 1 x USB Cable
- 1 x Li-ion Battery (2600mAh)
- 1 x Back Clip

- 1 x Lanyard
- 1 x User Manual



Contents of the BelFone BF-SC500UV package.

3. Product Overview

The BelFone BF-SC500UV features a user-friendly design with a keypad, LCD display, and essential control buttons and knobs. Its robust ABS+PC casing ensures durability and protection against environmental elements.



Front view of the BelFone BF-SC500UV walkie talkie.

4. Setup

4.1 Attaching the Antenna

Carefully screw the provided antenna onto the connector at the top of the walkie talkie until it is finger-tight. Do not overtighten.

4.2 Installing the Battery

Ensure the battery is correctly aligned with the battery compartment on the back of the walkie talkie. Slide it into place until it clicks securely. To remove, press the release latch and slide the battery out.

4.3 Initial Charging

Before first use, fully charge the walkie talkie battery. Refer to the 'Charging Instructions' section for details.

5. Basic Operation

5.1 Power On/Off

To power on, rotate the power/volume knob clockwise until you hear a click and the display illuminates. To power off, rotate the knob counter-clockwise until it clicks and the display turns off.

5.2 Volume Adjustment

Adjust the volume by rotating the power/volume knob. Clockwise increases volume, counter-clockwise decreases it.

5.3 Channel Selection

Use the up/down arrow keys on the keypad to navigate through available channels. The current channel number will be displayed on the screen.

5.4 Transmitting and Receiving

To transmit, press and hold the Push-To-Talk (PTT) button on the side of the device and speak clearly into the microphone. Release the PTT button to receive.

6. Advanced Features

The BF-SC500UV includes several advanced functions to enhance your communication experience:

- **VOX Voice-Activated Mode:** Allows hands-free transmission by detecting your voice.
- **Fast Teaming:** Quickly connect with other compatible walkie talkies.
- **Monitoring:** Listen to channels without transmitting.
- **Scanning:** Automatically scan through channels to find active transmissions.
- **Multiple Voice Encryption (CTCSS/CDCSS):** Reduces crosstalk and interference, ensuring private calls.
- **FM Radio Function:** Listen to local FM radio stations.
- **UV Dual Band & Writeable DIY:** Supports dual-band operation and manual FM tuning for advanced users.
- **One-Key Alarm:** Activates an emergency alarm.
- **Torch:** Built-in flashlight for convenience.



Overview of the BF-SC500UV's multiple functions.

6.1 Safety Intercom and Encryption


The walkie talkie utilizes CTCSS/CDCSS encryption to minimize interference and ensure call privacy. You can superimpose scrambling settings for enhanced security. Devices without the same scrambling value will only hear static.



Enhanced call security with scrambling settings.

6.2 FM Radio Function

Activate the integrated FM radio function to listen to local radio stations, including weather forecasts and music. This feature provides entertainment and information when not actively communicating.



The walkie talkie includes an FM radio function.

6.3 UV Dual Band and Writeable DIY

The UV dual-band capability allows for more flexible frequency usage. The 'Writeable DIY' feature supports manual FM tuning, offering advanced users greater control and customization.



Manual tuning options for advanced users.

7. Charging Instructions

The BF-SC500UV features a 2600mAh Li-ion battery, providing approximately 96 hours of average life. It supports convenient USB charging, allowing you to charge the device using various power sources:

- Direct power charge (using the included charger and USB cable)
- Computer USB port
- Mobile device power banks
- In-car charging adapters

The battery can also be charged separately. A low battery alert will notify you when charging is needed.



Multiple convenient charging options for the 2600mAh battery.

8. Maintenance

8.1 Waterproof and Dustproof

The BF-SC500UV has an IP54 waterproof rating, making it resistant to splashes and dust. While it can withstand rain, it is not designed for submersion. Ensure all ports are securely covered when exposed to moisture.



The BF-SC500UV features an IP54 waterproof and dustproof rating.

8.2 General Care

- Clean the device with a soft, damp cloth. Do not use harsh chemicals or solvents.
- Avoid exposing the walkie talkie to extreme temperatures or direct sunlight for prolonged periods.
- Store the device in a dry, cool place when not in use.

9. Troubleshooting

Problem	Possible Cause	Solution
No power	Battery depleted or not installed correctly.	Charge the battery. Ensure the battery is securely installed.
Cannot transmit or receive	Incorrect channel, low battery, or out of range.	Verify channel settings. Charge battery. Move closer to other units.
Poor audio quality	Low signal strength, interference, or incorrect volume.	Adjust antenna. Move to a clearer area. Adjust volume. Check squelch level.
Keypad locked	Keypad auto-lock activated.	Refer to the full user manual for specific unlock instructions.

For more detailed troubleshooting, please consult the complete user manual or contact BelFone customer support.

10. Specifications

Feature	Detail
Brand	BelFone
Model Number	BF-SC500UV
Color	BLACK
Number of Channels	255
Special Features	IP54 waterproof, Long Range, UV, Ham Radio

Feature	Detail
Talking Range Maximum	2 Miles
Water Resistance Level	Waterproof (IP54)
Product Dimensions	1.4"D x 2.3"W x 4.9"H
Number of Batteries	1 Lithium Ion (included)
Compatible Devices	Other BelFone walkie talkies, USB charging accessories
Temperature Range	-20°C to +60°C
Battery Average Life	96 Hours
Tuner Type	UV
Connectivity Protocol	Two-Way Radio
UPC	762730340800

11. Warranty and Support

11.1 Warranty Information

The BelFone BF-SC500UV Ham Radio Walkie Talkie comes with a **1-year warranty** from the date of purchase. This warranty covers manufacturing defects and malfunctions under normal use. Please retain your proof of purchase for warranty claims.

11.2 Customer Support

For technical assistance, troubleshooting, or warranty inquiries, please contact BelFone customer support through their official website or the contact information provided with your purchase. Our team is dedicated to providing prompt and helpful service.

© 2025 BelFone. All rights reserved.

Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

Open the live page

https://manuals.plus/asin/B0DKTJ4HYZ

More documents and user manuals: **https://manuals.plus/**