

[Manuals.plus](#) /

› [JAZAVA](#) /

› JAZAVA ZCPL101BK-3C 3-Light Cluster Globe Pendant Instruction Manual

JAZAVA ZCPL101BK-3C

JAZAVA ZCPL101BK-3C 3-Light Cluster Globe Pendant Instruction Manual

Model: ZCPL101BK-3C

1. INTRODUCTION

Thank you for purchasing the JAZAVA ZCPL101BK-3C 3-Light Cluster Globe Pendant. This modern lighting fixture features three clear glass globes and a matte black finish, designed to provide ample illumination and enhance the aesthetic of various indoor spaces. This manual provides essential information for safe installation, operation, and maintenance of your new pendant light. Please read these instructions carefully before beginning installation and retain them for future reference.



Image 1: JAZAVA ZCPL101BK-3C 3-Light Cluster Globe Pendant in a living room setting.

2. SAFETY INFORMATION

- **WARNING:** Risk of electric shock. Disconnect power at the circuit breaker or fuse box before installation or servicing.
- All electrical connections must be in accordance with local codes, ordinances, or the National Electric Code (NEC). Contact a qualified electrician if you are unfamiliar with proper electrical wiring connections.
- This fixture is intended for indoor use only. Do not expose to water or moisture.
- Ensure the mounting surface can support the weight of the fixture.
- Use only E26 A19 / G16.5 LED Edison bulbs, with a maximum wattage of 60W per bulb. Do not exceed the recommended wattage.
- Handle glass components with care to prevent breakage.
- Do not connect this fixture to an ungrounded electrical system.

3. PACKAGE CONTENTS

Verify that all components are present before beginning installation. If any parts are missing or damaged, contact JAZAVA customer support.

- 1 x 3-Light Pendant Light Fixture
- Mounting Hardware (screws, wire nuts, mounting bracket)
- Instruction Manual

4. SPECIFICATIONS

Brand	JAZAVA
Model Number	ZCPL101BK-3C
Color	Matte Black & Clear Glass
Material	Glass, Metal
Light Fixture Form	Pendant
Number of Light Sources	3
Bulb Base	E26 Medium
Max Wattage per Bulb	60 Watts
Voltage	110 Volts (AC)
Overall Max Height	70 inches
Overall Min Height	15 inches
Ceiling Canopy Diameter	11.75 inches
Lamp Shade Diameter	6.5 inches
Special Features	Adjustable Height, Dimmable (with compatible bulb/dimmer)
Installation Type	Semi Flush Mount

DIMENSIONS

Modern Globe Glass Pendant Lights



Adjustable Length



SPECIFIC BULB:
A19/G16.5 TYPE BULB
(Bulbs are not included)

Voltage

110-120V

Finish

Matte Black

Wattage

Max to 60W

Material

Metal & Glass

Image 2: Detailed dimensions and bulb specifications for the pendant light.

5. SETUP AND INSTALLATION

This fixture is designed for hardwired installation. It is recommended to have a qualified electrician perform the installation if you are not experienced with electrical wiring.

1. **Turn off Power:** Before starting, ensure the power to the circuit is completely off at the main circuit breaker or fuse box.

2. **Prepare Mounting Surface:** Attach the mounting bracket to the junction box in the ceiling using the provided screws. Ensure the bracket is securely fastened.
3. **Adjust Cord Length:** The pendant cords are adjustable. Loosen the set screws on the canopy to adjust each pendant's hanging length to your desired height. Tighten the set screws once the desired length is achieved.
4. **Make Electrical Connections:**
 - Connect the fixture's black wire to the house's black (live) wire.
 - Connect the fixture's white wire to the house's white (neutral) wire.
 - Connect the fixture's ground wire to the house's ground wire (bare copper or green).
 - Secure all connections with wire nuts and wrap with electrical tape for added safety.
5. **Mount the Canopy:** Carefully tuck the wires into the junction box and align the canopy with the mounting bracket. Secure the canopy to the bracket using the provided screws.
6. **Install Glass Shades:** Carefully attach each clear glass globe to its respective lamp holder.
7. **Install Bulbs:** Screw in three E26 A19 / G16.5 LED Edison bulbs (not included) into the sockets. Do not overtighten.
8. **Restore Power:** Once installation is complete and all connections are secure, restore power at the circuit breaker.



Image 3: Product details showing flat/sloped ceiling compatibility, matte black finish, and clear glass.



Image 4: Illustration of adjustable cord length for customization.

Your browser does not support the video tag.

Video 1: Official JAZAVA product video demonstrating the Cluster Light ZCPL101BK3C.

6. OPERATING INSTRUCTIONS

Once installed and powered, the JAZAVA ZCPL101BK-3C pendant light operates like any standard light fixture.

- **Turning On/Off:** Use your wall switch to turn the light fixture on or off.
- **Dimming Functionality:** If you have installed dimmable E26 A19 / G16.5 LED Edison bulbs and connected the fixture to a compatible dimmer switch (sold separately), you can adjust the light intensity to create your desired ambiance.

7. MAINTENANCE

Regular maintenance will help preserve the appearance and functionality of your pendant light.

- **Cleaning:** Always turn off the power before cleaning. Wipe the fixture with a soft, dry cloth. Do not use abrasive cleaners, solvents, or polishes as they may damage the finish or glass.
- **Glass Shades:** The clear glass shades can be carefully removed for more thorough cleaning if necessary. Wash with mild soap and water, rinse thoroughly, and dry completely before reattaching.
- **Bulb Replacement:** Ensure the power is off and the bulbs have cooled before attempting to replace them. Use only E26 A19 / G16.5 LED Edison bulbs, maximum 60W.

8. TROUBLESHOOTING

If you experience issues with your pendant light, refer to the following common problems and solutions:

Problem	Possible Cause	Solution
Light does not turn on.	◦ Power is off at the circuit breaker. ◦ Loose wire connections. ◦ Faulty bulb.	◦ Check the circuit breaker and ensure power is on. ◦ Verify all wire connections are secure (ensure power is off first). ◦ Replace the bulb with a new, working one.
Light flickers or dims unexpectedly.	◦ Loose bulb. ◦ Incompatible dimmer switch or bulb. ◦ Loose wire connection.	◦ Tighten the bulb. ◦ Ensure dimmable bulbs are used with a compatible dimmer. ◦ Check wire connections (ensure power is off first).
Glass shade is loose.	◦ Shade not properly secured.	◦ Carefully re-secure the glass shade to the fixture.

If the problem persists after trying these solutions, please contact JAZAVA customer support.

9. WARRANTY

The JAZAVA ZCPL101BK-3C 3-Light Cluster Globe Pendant comes with a **1-year limited manufacturer's warranty** from the date of purchase. This warranty covers defects in materials and workmanship under normal use. It does not cover damage resulting from improper installation, accident, misuse, abuse, or unauthorized modifications. Please retain your proof of purchase for warranty claims.

10. CUSTOMER SUPPORT

For any questions, assistance with setup, installation, or troubleshooting, please contact JAZAVA customer support.

Phone Support: Available during business hours (Monday-Friday PT).

Email Support: For non-urgent inquiries.



Image 5: JAZAVA customer support contact details.

