

## Irfora D1015TAM-D

# Irfora Cordless Expandable Phone System D1015TAM-D User Manual

Model: D1015TAM-D

## 1. INTRODUCTION

This manual provides detailed instructions for the installation, operation, and maintenance of your Irfora Cordless Expandable Phone System D1015TAM-D. Please read this manual thoroughly before using the phone system to ensure proper functionality and to prevent damage.

## 2. SAFETY INFORMATION

- Use only the provided power adapters and batteries.
- Do not expose the phone system to water or excessive moisture.
- Avoid placing the base unit or handsets near heat sources or direct sunlight.
- Keep the phone system away from strong electromagnetic fields.
- The distance between the main unit and the handset should not exceed 80 meters for optimal performance.

## 3. PACKAGE CONTENTS

Verify that all items are present in the package:

- 2 x Handsets
- 2 x Charging Cradles
- 1 x Phone Line Cord
- 4 x 1.2V 400MAh Ni-MH AAA Batteries
- 2 x Power Adapters

## 4. PRODUCT OVERVIEW

The Irfora Cordless Expandable Phone System features large buttons and a clear display for ease of use. It includes an integrated answering machine and supports multiple handsets.



## Big Button & Large Screen

1.8 inch LCD screen with 3 lines display & backlight function

Friendly for Elders

**Figure 4.1:** Handset with large buttons and a 1.8-inch LCD screen, designed for clear visibility and ease of use.



**Figure 4.2:** Handset keypad layout, showing M1, M2, M3 for speed dialing and the standard numeric keys.



**Figure 4.3:** The phone system features an integrated telephone answering machine for message recording.

**Phone:**

- Ø LCD 3 lines display, backlight function
- Ø Maximum 5 handsets can be registered to the same base unit, and maximum 4 bases per handset
- Ø Pre-dial and edit, redial and pause function
- Ø 30 incoming numbers memories and 10 outgoing numbers memories
- Ø 50 phone book memories with 12 characters & 20 digits maximum
- Ø Call transfer to other handset and intercom call between 2 handsets
- Ø Conference call between external call and 2 handsets
- Ø Alarm clock function
- Ø Tone/Pulse dialing mode can be set
- Ø Flash time 100/300/600/1000ms for selection
- Ø Auto and manual answering function

**TAM:**

- Ø The base has 2 digit LCD display to indicator
- Ø The base can play and record message
- Ø Digital Answering machine with max. 60 minutes messages
- Ø ICM recording
- Ø 2 groups OGM can be recorded by user
- Ø Memo recording with max. 120 seconds
- Ø Voice prompt in English, Spanish, French and German



**Figure 4.4:** Overview of phone and answering machine features, including LCD display, handset registration, call memories, and recording capabilities.



**Figure 4.5:** The base unit and handset feature an incoming call indicator.



**Figure 4.6:** The phone system supports 16 interface languages, including Spanish, English, French, German, Italian, Portuguese, Dutch, Hungarian, Greek, Polish, Danish, Norwegian, Swedish, Turkish, Russian, and Ukrainian.

## 5. SETUP

### 5.1 Battery Installation

1. Open the battery compartment cover on the back of each handset.
2. Insert the two 1.2V 400MAh Ni-MH AAA batteries, ensuring correct polarity.
3. Close the battery compartment cover.
4. Place the handset in its charging cradle to charge for at least 12 hours before first use.

### 5.2 Connecting the Base Unit

1. Connect one end of the phone line cord to the LINE jack on the base unit.
2. Connect the other end of the phone line cord to your telephone wall jack.
3. Plug the power adapter into the DC IN jack on the base unit.
4. Plug the power adapter into a standard electrical outlet.
5. For the second charging cradle, plug its power adapter into a standard electrical outlet.

### 5.3 Handset Registration

The system supports a maximum of 5 handsets registered to the same base unit. Refer to the on-screen menu for specific registration steps if additional handsets need to be registered or re-registered.

## 6. OPERATING INSTRUCTIONS

---

### 6.1 Basic Call Functions

- **Making a Call:** Enter the phone number and press the **Call** button.
- **Answering a Call:** When the phone rings, press the **Call** button. The system supports auto/manual answering.
- **Ending a Call:** Press the **End Call** button or place the handset back in the cradle.
- **Redial:** Press the **Redial** button to call the last dialed number.
- **Pause:** Use the pause function during dialing as needed.
- **Mute:** Press the **Mute** button during a call to temporarily disable your microphone.
- **Audio Boost:** Use the dedicated key for audio boost during a call to increase volume.

### 6.2 Answering Machine (TAM)

- The digital answering machine can record up to 60 minutes of messages.
- The base unit has a 2-digit LCD display to indicate messages.
- **Memo Recording:** Record memos up to 2 minutes in length.
- **Outgoing Message (OGM):** Two groups of OGM can be recorded by the user.
- Voice prompts are available in English, Spanish, French, and German.

### 6.3 Phone Book and Call Memories

- **Phone Book:** Store up to 50 entries with a maximum of 12 characters and 20 digits.
- **Incoming Call Memories:** Stores up to 30 incoming numbers.
- **Outgoing Call Memories:** Stores up to 10 outgoing numbers.
- **Speed Dial:** Utilize M1, M2, M3 buttons for quick access to frequently called numbers.

### 6.4 Intercom and Conference Calls

- **Intercom:** Initiate calls between two registered handsets.
- **Call Transfer:** Transfer an external call to another handset.
- **Conference Call:** Conduct a three-way conference call involving an external call and two handsets.

### 6.5 Settings and Features

- **Interface Languages:** Select from 16 languages including Spanish, English, French, German, Italian, Portuguese, Dutch, Hungarian, Greek, Polish, Danish, Norwegian, Swedish, Turkish, Russian, and Ukrainian.
- **Flash Time:** Adjustable settings for 100/300/600/1000ms.
- **Ringing Tones:** 10 selectable ringing tones. Adjustable ringing tone, earpiece, and hands-free volume. Different melodies can be set for different calls.
- **Keypad Lock:** Function to lock the keypad to prevent accidental dialing.
- **Dialing Barring:** Function to restrict certain outgoing calls.
- **LCD Backlight:** The LCD screen features a backlight function.
- **Alarm Clock:** An alarm clock function is available.

## 7. MAINTENANCE

- Clean the phone system with a soft, damp cloth. Do not use abrasive cleaners or solvents.
- Ensure the charging contacts on the handset and cradle are clean for proper charging.
- Replace batteries when they no longer hold a charge effectively.

## 8. TROUBLESHOOTING

- **No Dial Tone:**
  - Check if the phone line cord is securely connected to both the base unit and the wall jack.
  - Ensure the power adapter is properly connected and plugged into a working outlet.
- **Handset Not Charging:**
  - Verify the handset is correctly seated in the charging cradle.
  - Clean the charging contacts on both the handset and cradle.
  - Check if the charging cradle's power adapter is connected.
- **Poor Call Quality or Range Issues:**
  - Ensure the handset is within 80 meters of the base unit.
  - Relocate the base unit away from other electronic devices that may cause interference.
- **Base Unit and Handset Ring Simultaneously, Cannot Answer Both:**
  - This is normal operation. When a call comes in, both the main unit and handset will ring. You can only choose one of them to answer the call, not both simultaneously.

## 9. SPECIFICATIONS

<b>Model</b>	D1015TAM-D
<b>Handset Dimensions</b>	19 x 5.7 x 2.7 cm (7.48 x 2.24 x 1.06 inches)
<b>Cradle Dimensions</b>	16.8 x 12.5 x 6 cm (6.61 x 4.92 x 2.36 inches) and 10 x 11.2 x 7 cm (3.94 x 4.41 x 2.76 inches)
<b>Batteries</b>	4 x 1.2V 400MAh Ni-MH AAA batteries
<b>LCD Screen</b>	1.8 inches, 3 lines display, backlight function
<b>Expandability</b>	Max. 5 handsets per base unit, Max. 4 bases per handset
<b>Phone Book Memory</b>	50 entries (12 characters & 20 digits max)
<b>Call Memories</b>	30 incoming, 10 outgoing
<b>Answering Machine Recording Time</b>	Max. 60 minutes
<b>Memo Recording Time</b>	Max. 120 seconds
<b>Flash Time Settings</b>	100/300/600/1000ms

<b>Interface Languages</b>	16 options (Spanish, English, French, German, Italian, Portuguese, Dutch, Hungarian, Greek, Polish, Danish, Norwegian, Swedish, Turkish, Russian, Ukrainian)
<b>Manufacturer</b>	Irfora
<b>ASIN</b>	B0DRG4WSDY