

[manuals.plus](#) /› [Mount-It!](#) /› [Mount-It! MI-1882BLK Dual Monitor Desk Mount Instruction Manual](#)**Mount-It! MI-1882BLK**

Mount-It! MI-1882BLK Dual Monitor Desk Mount Instruction Manual

INTRODUCTION

This manual provides comprehensive instructions for the installation, operation, and maintenance of your Mount-It! MI-1882BLK Dual Monitor Desk Mount. Designed for monitors ranging from 13 to 32 inches and supporting up to 17.6 lbs per arm, this mount offers full motion adjustability to enhance your workspace ergonomics and efficiency. Please read all instructions carefully before assembly and use.



Image: The Mount-It! MI-1882BLK Dual Monitor Desk Mount, shown with two monitors mounted, illustrating its sleek design and space-saving capabilities.

SAFETY INFORMATION

- Ensure all components are present and undamaged before assembly. Do not use if any parts are missing or faulty.
- Verify that your desk surface is strong enough to support the combined weight of the mount and your monitors.
- Do not exceed the maximum weight capacity of 17.6 lbs (8 kg) per arm.
- Always apply pressure to the arm and hold it in a horizontal position before adjusting the gas spring tension to avoid injury.
- Keep children and pets away during assembly.

SETUP AND INSTALLATION

Desk Compatibility

This monitor mount is compatible with desks between 0.4 inches (10mm) and 1.97 inches (50mm) thick.

Mounting Options

The MI-1882BLK offers two installation methods: C-clamp and Grommet base.



Image: Illustration of the C-clamp and grommet mounting options, detailing how the mount attaches to desks of varying thicknesses.

C-Clamp Installation

1. Attach the C-clamp bracket to the main pole.
2. Position the mount at the desired location on your desk edge.
3. Tighten the C-clamp screw until the mount is securely fastened to the desk.

Grommet Base Installation

1. If your desk has an existing grommet hole, ensure it is between 0.4"-2.4" (10-60mm) in diameter and the desk thickness is 0.4"-1.6" (10-40mm). If not, drill a 3/8" (10mm) hole in your desired location.
2. Assemble the grommet base components as per the included hardware instructions.
3. Insert the grommet bolt through the desk hole from underneath.
4. Attach the main pole to the grommet bolt on top of the desk and tighten the hand knob from underneath until secure.

Attaching Monitors

This mount supports VESA 75x75mm and 100x100mm patterns.

1. Attach the VESA plate to the back of each monitor using the appropriate screws and washers provided. Ensure a secure fit without overtightening.
2. Slide the VESA plates onto the ends of the monitor arms.
3. Secure the monitors by tightening the knob on the height adjustment peg.

Installation Video

Your browser does not support the video tag.

Video: A general