

## Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

manuals.plus /

- > [Fanvil](#) /
- > [Linkvil W610D DECT Wireless Phone User Manual](#)

## Fanvil W610D

# Linkvil W610D DECT Wireless Phone User Manual

Model: W610D

## INTRODUCTION

This manual provides instructions for the setup, operation, and maintenance of the Linkvil W610D DECT Wireless Phone. The W610D is a professional wireless handset designed for reliable communication in various environments, featuring Bluetooth 5.0, a 3.5 mm headphone jack, Push to Talk functionality, and enhanced durability.



Image: The Linkvil W610D DECT Wireless Phone, black in color, resting in its matching black charging cradle. The phone features a clear color display showing time, date, and menu options, along with a full numeric keypad and navigation buttons. The "LINKVIL" brand name is visible on the front of the charging cradle.

## PACKAGE CONTENTS

---

Ensure all items are present in the package:

- Linkvil W610D DECT Wireless Handset
- Charging Cradle
- Power Adapter for Charging Cradle
- Rechargeable Lithium-Ion Battery (pre-installed or separate)

## SETUP

---

### 1. Charging the Handset

1. Connect the power adapter to the charging cradle and plug it into a power outlet.
2. Place the W610D handset into the charging cradle. Ensure the charging contacts on the handset align with those on the cradle.
3. The handset display will indicate charging status. For first-time use, charge the handset for at least 4 hours to ensure full battery capacity.

### 2. Pairing with W710D Base Station

The W610D handset is designed to be paired with the Linkvil W710D DECT Base Station (sold separately). Refer to the W710D base station manual for detailed pairing instructions. General steps typically include:

1. Put the W710D base station into pairing mode (usually by pressing a button on the base).
2. On the W610D handset, navigate to the "Registration" or "Pairing" menu option.
3. Select the option to register a new handset. The handset will search for available base stations.
4. Once the W710D base station is detected, follow the on-screen prompts to complete the pairing process. You may need to enter a PIN (default is often 0000 or 1234).

## OPERATING INSTRUCTIONS

---

### 1. Making and Receiving Calls

- **Making a Call:** Dial the desired number using the keypad and press the **Call** button (green phone icon).
- **Receiving a Call:** When the phone rings, press the **Call** button to answer.
- **Ending a Call:** Press the **End Call** button (red phone icon).
- **Adjusting Volume:** Use the side volume buttons during a call.

### 2. Using Bluetooth 5.0

The W610D supports Bluetooth 5.0 for connecting wireless headsets or other compatible devices.

1. Navigate to the "Bluetooth" menu on the handset.
2. Enable Bluetooth and select "Pair New Device".
3. Put your Bluetooth headset or device into pairing mode.
4. Select your device from the list on the W610D and follow any on-screen prompts to complete pairing.

### 3. Using the 3.5 mm Headphone Jack

For wired audio accessories, plug your 3.5 mm headset directly into the headphone jack located on the side of the handset.

### 4. Push to Talk (PTT) Function

The integrated Push to Talk functionality allows for instant communication, similar to a walkie-talkie, when configured with a compatible system.

- To initiate PTT, press and hold the dedicated PTT button (refer to handset layout for exact location, typically a side button).
- Speak clearly into the microphone.
- Release the PTT button to listen.
- Ensure your system administrator has configured PTT channels and groups for proper operation.

### 5. Keypad and Navigation

- **Numeric Keypad:** Used for dialing numbers and entering text.
- **Navigation Keys:** Use the directional pad (up, down, left, right) to navigate through menus and options.
- **OK/Select Button:** The center button of the navigation pad confirms selections.
- **Soft Keys:** Context-sensitive buttons directly below the display, their function changes based on the current screen (e.g., Dsskey, CallLog, Menu).

## MAINTENANCE

---

### 1. Cleaning

To clean the handset and charging cradle:

- Disconnect the charging cradle from power before cleaning.
- Use a soft, dry, lint-free cloth to wipe surfaces.
- For stubborn marks, slightly dampen the cloth with water. Avoid using harsh chemicals, abrasive cleaners, or excessive moisture.
- Ensure all ports and openings are dry before reconnecting power or using the device.

### 2. Battery Care

- Use only the original or approved replacement battery.
- Avoid exposing the battery to extreme temperatures.
- If the handset will not be used for an extended period, fully charge it before storage and recharge every few months to maintain battery health.

### 3. Drop Resistance

The W610D is built to withstand drops from up to 1.8 meters. While durable, repeated severe impacts can still cause damage. Handle the device with care to prolong its lifespan.

## TROUBLESHOOTING

---

Problem	Possible Cause / Solution
Handset does not power on.	Battery is depleted. Place handset in charging cradle. Ensure power adapter is connected and outlet is active.
No dial tone / Cannot make calls.	Handset is out of range of the base station. / Handset is not registered to a base station. / Base station is not powered on or connected to the network.
Poor call quality / Static.	Interference from other electronic devices. / Handset is too far from the base station. / Low battery on handset.
Bluetooth device not pairing.	Ensure Bluetooth is enabled on both devices. / Ensure the Bluetooth device is in pairing mode. / Move devices closer together.
Push to Talk not working.	PTT feature may not be configured on the base station or server. / Handset not registered to a PTT group. Contact your system administrator.

## SPECIFICATIONS

Feature	Description
Model	W610D
Brand	Fanvil (Linkvil)
Technology	DECT Wireless
Bluetooth	Bluetooth 5.0
Headphone Jack	3.5 mm
Durability	1.8 m Drop Resistant
Display	Color display, 5" / 13 cm visible screen diagonal
Keypad	Ergonomic numeric keypad
Alerts	Vibration alert feature
Power Source	Power supply (via charging cradle)
Battery	1 Lithium Ion battery (included)
Product Dimensions	15 x 5 x 15 cm
Item Weight	0.44 Kilograms
Material	Plastic
Color	Black
Compatible Base Station	W710D (sold separately)

## WARRANTY AND SUPPORT

For warranty information and technical support, please refer to the documentation provided with your purchase or

visit the official Fanvil (Linkvil) website. Keep your proof of purchase for warranty claims.



© 2024 Fanvil. All rights reserved.