

Itari M102

Itari M102 Label Maker Machine User Manual

Model: M102

1. INTRODUCTION

This manual provides detailed instructions for the setup, operation, and maintenance of your Itari M102 Label Maker Machine. Please read this manual thoroughly before using the device to ensure proper function and longevity.

2. PACKAGE CONTENTS

Verify that all items are present in your package:

- Itari M102 Label Maker Machine
- 3 Rolls of Thermal Labels (1.57" x 1.18" / 40mm x 30mm)
- USB Type-C Charging Cable
- User Manual (this document)



Image 2.1: The Itari M102 Label Maker Machine shown with the included label rolls.

3. PRODUCT OVERVIEW

Familiarize yourself with the components of your label maker.



Image 3.1: Detailed view highlighting the dimensions, safe built-in paper ripper, removable protective laminates, and Type-C charging port.

Key Features:

- **Power Button:** Used to turn the device on/off.
- **Label Compartment:** Holds the label roll.
- **Adjustable Guide:** Ensures proper alignment for various label widths (supports 20-50mm wide labels).
- **Paper Exit Slot:** Where printed labels emerge.
- **Built-in Paper Ripper:** For cleanly detaching printed labels.

- **Type-C Charging Port:** For recharging the internal battery.

4. SETUP

4.1. Charging the Device

Before first use, fully charge the label maker. Connect the provided USB Type-C cable to the charging port on the device and a compatible USB power adapter (not included). A full charge takes approximately 2 hours and provides up to 1 month of typical usage.

4.2. Loading Labels

1. Open the label compartment cover.
2. Insert a roll of thermal labels into the compartment, ensuring the labels feed from the bottom and the printing side faces upwards.
3. Adjust the label guides to fit the width of your label roll snugly. The device supports labels from 20mm to 50mm wide.
4. Pull a small portion of the label paper out through the paper exit slot.
5. Close the label compartment cover securely.

Suitable Various Style Label

Support **20-50mm** wide label



Image 4.1: The label compartment open, illustrating how to insert a label roll and adjust the width guides.

4.3. App Installation and Connectivity

The Itari M102 Label Maker connects wirelessly via Bluetooth to your smartphone or tablet, and via USB to computers. Download the dedicated label editing application from your device's app store (e.g., Apple App Store for iOS, Google Play Store for Android).

1. For Bluetooth Connection:

- Turn on the label maker.
- Enable Bluetooth on your mobile device.
- Open the Itari label app and follow the in-app instructions to search for and pair with your M102 device. Pairing typically takes less than 2 seconds.

2. For USB Connection:

- Connect the label maker to your computer using the USB Type-C cable.
- Install the necessary drivers or software for your operating system (Windows, macOS, Chrome OS, Linux) as prompted or available on the Itari support website.



Image 4.2: Illustrates wireless Bluetooth connectivity for iOS and Android, and USB connectivity for Chrome OS, Windows, Mac OS, and Linux.

5. OPERATING INSTRUCTIONS

5.1. Creating and Customizing Labels

The Itari label app provides extensive customization options:

- **Templates:** Access over 300 free label templates for various uses (address, price, food, clothing,

cable, jewelry, folder labels, etc.).

- **Fonts & Symbols:** Choose from over 100 fonts and 1000 symbols to personalize your labels.
- **Images:** Embed images into your label designs.
- **Text Editing:** Adjust text size, style, alignment, and add multiple lines.
- **Barcodes & QR Codes:** Generate and print various types of barcodes and QR codes.

5.2. Printing Labels

1. Ensure the label maker is powered on and connected to your device (Bluetooth or USB).
2. Open the Itari label app and create or select your desired label design.
3. Confirm the label size in the app matches the loaded label roll.
4. Tap the 'Print' button in the app.
5. The label maker will print the label. Use the built-in paper ripper to cleanly detach the label from the roll.

6. MAINTENANCE

6.1. Cleaning

To maintain print quality and device longevity:

- Turn off the label maker before cleaning.
- Gently wipe the print head with a soft, lint-free cloth moistened with isopropyl alcohol. Allow it to dry completely before use.
- Clean the exterior of the device with a soft, dry cloth. Do not use harsh chemicals or abrasive cleaners.

6.2. Label Storage

Store thermal labels in a cool, dry place away from direct sunlight and heat to prevent premature fading or damage to the thermal coating.

Wireless Bluetooth Label Maker

Support for IOS, Android, Windows, Mac, etc



Image 6.1: Itari thermal label rolls, highlighting the 1.57" x 1.18" (40mm x 30mm) size, 230 sheets per roll, and high-quality thermal paper.

7. TROUBLESHOOTING

If you encounter issues with your Itari M102 Label Maker, refer to the following common problems and solutions:

Problem	Possible Cause	Solution
Device does not turn on	Low battery	Charge the device using the provided USB Type-C cable.

Problem	Possible Cause	Solution
No print or faint print	<ul style="list-style-type: none"> Label roll inserted incorrectly Print head dirty Incorrect label type 	<ul style="list-style-type: none"> Re-insert the label roll, ensuring the printing side faces up. Clean the print head as described in Section 6.1. Ensure you are using thermal labels.
Bluetooth connection failure	<ul style="list-style-type: none"> Bluetooth off on mobile device Device out of range App not recognizing printer 	<ul style="list-style-type: none"> Ensure Bluetooth is enabled. Move the label maker closer to your mobile device. Restart the app and the label maker. Try re-pairing.
Labels jam	<ul style="list-style-type: none"> Label roll not properly aligned Foreign object in paper path 	<ul style="list-style-type: none"> Open the compartment and re-align the label roll and guides. Carefully remove any obstructions.

8. SPECIFICATIONS

- **Model:** M102
- **Printing Technology:** Thermal (Inkless)
- **Supported Label Width:** 20mm - 50mm
- **Included Label Size:** 1.57" x 1.18" (40mm x 30mm)
- **Connectivity:** Bluetooth, USB Type-C
- **Battery Life:** Up to 1 month of typical use (2 hours full charge)
- **Dimensions:** Approximately 4.37" (H) x 3.39" (W) x 2.32" (D)
- **Weight:** Approximately 0.43 lbs (0.195 kg)

9. WARRANTY AND SUPPORT

For warranty information and technical support, please refer to the contact details provided with your purchase or visit the official Itari website. Keep your purchase receipt as proof of purchase for warranty claims.