

## FOSCAM BP4

# Foscam BP4 2K Solar Security Camera User Manual

Model: BP4

## 1. INTRODUCTION

The Foscam BP4 is a 2K (4MP) wireless outdoor security camera designed for comprehensive home surveillance. It features a 10,000mAh rechargeable battery and a 5W solar panel for continuous power, eliminating the need for frequent manual charging. Key functionalities include advanced PIR human detection, two-way audio communication, color night vision, and IP66 weather resistance. This manual provides detailed instructions for setting up, operating, and maintaining your Foscam BP4 camera to ensure optimal performance and security.

## 2. PACKAGE CONTENTS

Verify that all items listed below are included in your package:

- Foscam BP4 Camera Body
- 5W Solar Panel
- Mounting Screws and Anchors
- Instruction Manual (Quick Setup Guide)
- USB Charging Cable
- Mounting Brackets for Camera and Solar Panel



Image: The Foscam BP4 camera body shown alongside its accompanying 5W solar panel, illustrating the complete package contents.

### 3. SETUP

---

#### 3.1 Initial Charging

Before initial use, fully charge the camera's built-in 10,000mAh battery using the provided USB cable and a DC 5V/2A power adapter (not included). Alternatively, connect the camera to the solar panel and place the panel in direct sunlight for several hours. Ensure the charging port is securely sealed after connecting the solar panel cable to maintain weather resistance.

# Full Duplex Two-Way Audio

Welcome or warn—anywhere





Image: The Foscam BP4 camera connected to its solar panel, demonstrating how the solar panel provides continuous power to the camera's battery.

## 3.2 App Installation and Camera Connection

1. Download the Foscam app from your smartphone's app store (iOS or Android).
2. Create an account or log in if you already have one.
3. Follow the in-app instructions to add your BP4 camera. This typically involves scanning a QR code on the camera or manually entering its details.
4. Connect the camera to your 2.4GHz Wi-Fi network as prompted by the app.

## 3.3 Mounting the Camera and Solar Panel



Use the provided mounting template to mark drill holes for the camera and solar panel. Securely attach the mounting brackets to your desired outdoor location using the screws and anchors. Ensure the solar panel is positioned to receive maximum direct sunlight throughout the day for optimal charging. The camera and solar panel are designed for outdoor use with an IP66 waterproof rating.

## 2K Clarity & Smart Full-Color Night Vision




Image: The Foscam BP4 camera and its solar panel are shown mounted on an exterior wall, illustrating a typical installation for continuous power and surveillance.

Your browser does not support the video tag.

Video: An official Foscam video demonstrating the features and outdoor capabilities of the Foscam BP4 2K Solar Security Camera, including its solar power and wireless operation.

## 4. OPERATING INSTRUCTIONS

### 4.1 Live View and Video Quality

Access the live video feed through the Foscam app. The BP4 camera provides crystal clear 2K (2560x1440) resolution at 20 frames per second, ensuring sharp and detailed images. Utilize the 20X digital zoom feature to get a closer look at specific areas within the 110-degree wide-angle view.



Image: A visual representation of the Foscam BP4's 2K QHD video quality, highlighting its 20X digital zoom capability for detailed surveillance.



Image: The Foscam BP4 camera capturing a broad 110-degree wide-angle view, ideal for monitoring large outdoor areas like driveways or yards.

### 4.2 Two-Way Audio

The camera features a built-in microphone and speaker for two-way audio communication. Use this function via the Foscam app to speak with visitors, delivery personnel, or deter unwanted individuals on your property.



## IP66 Weatherproof

Protect your security in every extreme weather



Image: A family enjoying their pool while using the Foscam BP4's full duplex two-way audio to communicate, demonstrating real-time voice interaction.

### 4.3 Motion Detection and Alerts

The BP4 utilizes advanced PIR (Passive Infrared) human detection to minimize false alarms. It can distinguish between humans, animals, vehicles, and packages. When motion is detected, you will receive instant notifications on your smartphone. The camera can also trigger a sound and light alarm (6500K spotlight and 110dB siren) to deter intruders.




Image: The Foscam BP4 camera's Smart AI PIR Detection feature in action, accurately identifying and categorizing objects such as pets, packages, humans, and vehicles within its view.

### Smart Full Color Night Vision

Built-in 2pcs IR LED and 6500K spotlights, distance up to 33ft





Image: The Foscam BP4 camera activating its instant notification system, including flashing spotlights and a siren, while sending an alert to a smartphone.

#### 4.4 Night Vision

The camera offers full-color night vision up to 33 feet (10m) using its 2 IR LEDs and 6500K spotlight. It can automatically or manually switch between full-color and IR (infrared) modes, providing clear visibility in low-light conditions.




Image: Comparison of Foscam BP4's night vision capabilities, showing IR Mode (black and white), Color Mode (full color with spotlights), and Smart Mode (motion-triggered color night vision).

#### 4.5 Recording and Storage

Recordings can be stored locally on a Micro SD card (up to 256GB, not included) or via Foscam's secure cloud storage service (7 days free, subscription required for extended periods). The app allows for easy playback and management of recorded events.




Image: An illustration detailing the Foscam BP4's flexible storage solutions, including support for a Micro SD card up to 256GB and a 7-day free cloud service.

#### 4.6 Smart Home Integration

The Foscam BP4 camera is compatible with Amazon Alexa and Google Assistant, allowing for voice-controlled security and live monitoring. This integration enhances convenience by allowing you to manage your camera using simple voice commands.



## Multi-User Shared Viewing

Sharing it with your family group to keep track of what's happening at home from anywhere, at any time.



Image: A user interacting with smart home devices, demonstrating the Foscam BP4's compatibility with Amazon Alexa and Google Assistant for voice-controlled security.

### 4.7 Additional App Features

- **One-Click Settings:** Easily enable or disable common settings for all cameras, such as siren linkage or sleep mode, with a single tap.
- **AI Search:** (Requires cloud service) Search for specific events using keywords, simplifying the review of historical recordings.
- **Custom Monitoring Zones:** Define specific areas for detection to reduce false alerts and focus on critical zones.
- **Multi-User Sharing:** Share camera access with family members, allowing multiple users to view and monitor the property simultaneously.

## Full Duplex Two Way Audio

Built-in microphone and speaker, to achieve real-time two-way voice communication convenience for your life



Image: A smartphone screen displaying the Foscam app's interface for one-click enabling or disabling of common settings across multiple cameras, such as 'Leave Home Mode' and 'Back Home Mode'.






Image: A series of smartphone screens illustrating the Foscam app's AI search functionality, allowing users to quickly find relevant alarm videos using keywords.

## 5. MAINTENANCE

- **Cleaning:** Regularly clean the camera lens and solar panel with a soft, damp cloth to ensure clear image quality and efficient solar charging. Avoid abrasive cleaners.
- **Battery Check:** Monitor the battery level via the Foscam app. While the solar panel provides continuous charging, extreme weather or prolonged periods of low sunlight may affect battery performance.
- **Firmware Updates:** Keep the camera's firmware updated through the Foscam app to ensure optimal performance, security, and access to new features.
- **Weather Protection:** Despite its IP66 rating, periodically inspect the camera and solar panel for any signs of wear or damage, especially after severe weather conditions.



Image: The Foscam BP4 camera shown enduring various extreme weather conditions, including rain, snow at -20°C (-4°F), and heat at 60°C (140°F), highlighting its IP66 weatherproof durability.

## 6. TROUBLESHOOTING

- **Camera Not Powering On:** Ensure the battery is charged. If using the solar panel, verify it's receiving direct sunlight. Connect via USB for direct charging to confirm battery function.
- **No Wi-Fi Connection:** Confirm your Wi-Fi network is 2.4GHz. Ensure the camera is within range of your router. Restart both the camera and router.
- **Poor Image Quality:** Clean the camera lens. Check for obstructions in the camera's field of view. Ensure adequate lighting for

night vision modes.

- **False Motion Alerts:** Adjust motion detection sensitivity settings in the app. Utilize custom monitoring zones to exclude areas with frequent non-threatening movement (e.g., trees swaying).
- **Two-Way Audio Issues:** Check your smartphone's microphone and speaker settings. Ensure the camera's microphone and speaker are not obstructed.
- **App Not Responding:** Close and reopen the Foscam app. Ensure your app is updated to the latest version.

For more detailed troubleshooting or technical support, please visit the official Foscam support website.







## 7. SPECIFICATIONS

Feature	Specification
Model Name	BP4
Video Capture Resolution	2K (2560x1440)
Effective Still Resolution	4 MP
Frame Rate	20 frames per second
Digital Zoom	20X
Viewing Angle	110 Degrees
Night Vision Range	33 Feet (10m)
Night Vision Type	Color Night (with 2 IR LEDs and 6500K spotlight)
Power Source	Solar Powered (5W Solar Panel) & Battery (10,000mAh)
Connectivity Technology	Wireless (Wi-Fi 2.4GHz)
Weather Resistance	IP66 Waterproof
Audio	2-Way Audio
Motion Detection	PIR Human Detection (AI recognition for human, animal, vehicle, package)
Storage Options	Micro SD Card (up to 256GB), Cloud Storage
Smart Home Compatibility	Amazon Alexa, Google Assistant
Dimensions (L x W x H)	2.64 x 7.99 x 2.64 inches
Item Weight	1.21 pounds


## 8. WARRANTY AND SUPPORT

The Foscam BP4 camera comes with a standard manufacturer's warranty. For specific warranty details, registration, and to access comprehensive technical support, FAQs, and additional resources, please visit the official Foscam website: [www.foscam.com](http://www.foscam.com)

Foscam is committed to providing reliable products and customer service. If you encounter any issues or have questions, please refer to the online support channels or contact Foscam customer service directly.

	<p><a href="#">FOSCAM Security Camera Quick Setup Guide   Installation &amp; Configuration</a></p> <p>Comprehensive quick setup guide for FOSCAM security cameras. Learn how to install, connect via the Foscam App, access your camera, and find technical support.</p>
	<p><a href="#">Foscam R3/R5 Indoor IP Security Camera Quick Setup Guide   Installation &amp; Configuration</a></p> <p>Get your Foscam R3 or R5 Indoor IP Security Camera up and running quickly with this comprehensive setup guide. Learn about hardware installation, app connection, Foscam VMS, and important safety tips.</p>
	<p><a href="#">FOSCAM FI8906W Outdoor Wireless IP Camera User Manual</a></p> <p>User manual for the FOSCAM FI8906W Outdoor Wireless IP Camera. Covers installation, setup, software interface, advanced network and camera settings, firmware updates, and troubleshooting for this wireless surveillance device.</p>
	<p><a href="#">FOSCAM SD8P Outdoor IP Security Camera User Manual</a></p> <p>Comprehensive user manual for the FOSCAM SD8P Outdoor IP Security Camera, covering key features, installation, specifications, and default parameters.</p>
	<p><a href="#">Foscam Battery-Powered Security Camera Quick Setup Guide   Installation &amp; Wi-Fi Setup</a></p> <p>Get started with your Foscam battery-powered security camera. This guide covers unboxing, camera installation, Wi-Fi connection via the Foscam app, solar panel setup, and troubleshooting tips for a secure home.</p>
	<p><a href="#">FOSCAM Indoor FHD IP Camera User Manual</a></p> <p>This user manual provides comprehensive instructions for setting up, configuring, and operating the FOSCAM Indoor FHD IP Camera (Models R2, R4, R2C, R2E). It covers wired and wireless connections, remote access, software usage, advanced settings, troubleshooting, and specifications.</p>





[Foscam Battery-Powered Security Camera Quick Setup Guide | Installation & Wi-Fi Setup](#)

Get started with your Foscam battery-powered security camera. This guide covers unboxing, camera installation, Wi-Fi connection via the Foscam app, solar panel setup, and troubleshooting tips for a secure home.

lang:en **score:36** filesize: 8.29 M page\_count: 1 document date: 2024-12-11

Foscam BP4 batteriebetriebene 2K 4 MP WLAN-Überwachungskamera inkl. Solarpanel

EAN: 6954836019351

Die batteriebetriebene Kamera Foscam BP4 liefert gestochen scharfe Bilder mit einer Auflösung von bis zu 2560 x 1440 Pixeln bei 20 Bildern pro Sekunde.

Sie erhöht den Präzisionsgrad und die Detailgenauigkeit der Sicherheitsaufnahmen, so dass sich wichtige Informationen besser erkennen und aufnehmen lassen.

Zusätzlich zu den grundlegenden Funktionen, wie z.B. die Bewegungserkennung, bietet die Foscam BP4 auch eine PIR-Personenerkennung, die in der Lage ist, Personen von anderen sich bewegenden Objekten zu unterscheiden und einen Alarm zu senden, um Ihnen eine schnelle Reaktion zu ermöglichen und eine unbedingte Zufriedenheit zu erreichen.

Bei Erkennung eines Eindringlings wird das Spritzlicht aktiviert und ein Alarmton ertönt, um potenzielle Täter abzuwehren. Das Spritzlicht kann auch manuell aktiviert werden.

Dank der zwei integrierten Spritzlicht-LEDs bietet die Foscam BP4 Nachsichtreichweite von bis zu 10 Metern. Leuchtend gelbe Farbtöne sind auch in der Dunkelheit möglich.

Als wiederaufladbare Batterie- und Solarpanel bietet die Kamera jederzeit einstrahlendes Licht. Mit einem Leistungsgesamtwert von 10.000mAh Akku und 18000mAh Solarpanel und dem Foscam Solarpanel ist die BP4 vollständig kabellos und unabhängig von Steckdosen. Ein vollständiges System bereit für maximale Flexibilität.

Die Foscam BP4 ist mit integriertem Mikrofon und einem Lautsprecher ausgestattet und unterstützt darüber hinaus Zwei-Wege-Audio in Echtzeit. Sie können Sie mit Ihren Gästen kommunizieren und eine ruhige Atmosphäre schaffen, unabhängig von Ihrem Standort.

Die Foscam Mobile App ist die ideale Lösung, mit der Sie die Live-Übertragungen ansehen, über die batteriebetriebene Kamera sprechen und zentralisieren. Schließungen auf dem Smartphone ermöglichen und vieles mehr. Die Foscam PC App ist eine kabellos nachgeladene (MMS) mit einer intuitiven Benutzeroberfläche, die es ermöglicht, Videos auf dem Computer, Laptop zu speichern, zu teilen, zu löschen und zu verschieben.

Die Kamera kann dort aufgestellt werden, wo sie ein gutes WLAN-Signal empfangen kann. Da keine Steckdose oder ein Stromkabel angeschlossen werden muss, ist die Kamera flexibel einsetzbar.

Die Foscam BP4 ist nach IP68 geschützt und hält extremen Wetterbedingungen stand. Ob vor der Haustür, in der Garage oder im Lager – diese Kamera funktioniert zuverlässig bei Temperaturen von -20°C bis 60°C.

Die Aufnahmen können auch lokal auf einer Micro-SD-Karte (bis zu 256 GB) gespeichert werden.

Diese WLAN-Überwachungskamera unterstützt Alexa & Google Home.

Highlights

- Hochauflösendes 2K-Video bei Tag und Nacht
- PIR-Erkennung von Personen
- Wiederaufladbare Batterie und Solarpanel
- Nachtsicht in Farbe
- Zwei-Wege-Audio mit integriertem Mikrofon und Lautsprecher
- Integrierte 2-fache Schwenkbildschirm und 2K-LED
- Unterstützt SD-Karten mit bis zu 256 GB zum Speichern der Videos
- IP68 Wasserdicht
- Unterstützung von Alexa & Google Home

[\[pdf\] User Manual](#)

IV kd Tehnični podatki 3387299 Foscam BP4 WLAN ip nadzorna kamera 2560 x 1440 piksel MegaShop spletna trgovina Megashop si tehnicni foscam bp4 wlan asset conrad media10 add 160267 c1 de 003387299DS00 |||

Foscam **BP4** batteriebetriebene 2K 4 MP WLAN-berwachungskamera inkl. Solarpanel EAN: 6954836019351 Die batteriebetriebene Kamera Foscam **BP4** liefert gestochen scharfe Bilder mit einer Auflösung von bis zu 2560 x 1440 Pixeln bei 20 Bildern pro Sekunde. Sie erhöht den Präzisionsgrad und die Detailgenauigkeit...

lang:de **score:32** filesize: 135.75 K page\_count: 2 document date: 2025-02-06

EMTEK

TEST REPORT

Product Name : 2K Battery Security Camera

Model Number : BP4, BP4W, BP4C

FCC ID : ZDEBP4

Prepared for : ShenZhen Foscam Intelligent Technology Co., Ltd

Address : Room 902, Building 1B, Shenzhen International Innovation Valley, Xingke 1st Street, Nanshan District, Shenzhen, Guangdong, China, 518055

Prepared by : EMTEK (DONGGUAN) CO., LTD.

Address : 142/F, Building 2, Zone A, Zhongda Marine Biotechnology Research and Development Base, No.3, Xinghe Avenue, Songshanhu High-technology Industrial Development Zone, Dongguan, Guangdong, China

TEL: +86-0769-22807078

FAX: +86-0769-22807079

Report Number : ED02411200113E00402R

Date(s) of Test(s) : November 20, 2024 to December 19, 2024

Date of Issue : December 19, 2024

Report No. ED02411200113E00402R

Page 1 of 7

Ver 1.0

[\[pdf\] Specifications Test Report SAR Rating](#)

abc RF Exposure ShenZhen Foscam Intelligent Technology Co Ltd BP4 ZDEBP4 bp4

TEST REPORT Product Name 2K Battery Security Camera Model Number **BP4**, **BP4W**, **BP4C** FCC ID ZDEBP4 Prepared for Address Prepared by Address : ShenZhen Foscam Intelligent Technology Co., Ltd : Room 902, Building 1B, Shenzhen International Innovation Valley, Xingke 1st Street, Nanshan District, Shenzhen...

lang:en **score:31** filesize: 413.64 K page\_count: 7 document date: 2025-01-02

[\[pdf\]](#) User Manual Datasheet

IV kd Buy Foscam BP4 Wi Fi IP CCTV camera 2560 x 1440 p Conrad Electronicdatasheet 3387299

foscam bp4 wi fi ip cctv passet conrad media10 add 160267 c1 de 003387299DS00 datasheet

batteriebetriebene 2K 4 MP WLANDie Kamera liefert gestochen scharfe Bilder mit einer Auflösung von

bis zu Pixeln bei 20 Bildern pro Sekunde

pikseldatasheet podatkovna pikselasset ||| ||| Foscam BP4 batteriebeitriebene 2K 4 MP WLAN-

berwachungskamera inkl. Solarpanel EAN: 6954836019351 Die batteriebetriebene Kamera Foscam BP4

liefert gestochen scharfe Bilder mit einer Auflösung von bis zu 2560 x 1440 Pixeln bei 20 Bildern pro S



## Foscam **BP4** batteriebetriebene 2K 4 MP WLAN-berwachungskamera inkl. Solarpanel

EAN: 6954836019351 Die batteriebetriebene Kamera Foscam **BP4** liefert gestochen

scharfe Bilder mit einer Auflösung von bis zu 2560 x 1440 Pixeln bei 20 Bildern pro

Sekunde. Sie erhöht den Präzisionsgrad und die Detailgenauigkeit...

lang:de **score:31** filesize: 135.76 K page\_count: 2 document date: 2025-02-06



[\[pdf\]](#) Decleration of Conformity

abc Declaration on model difference ShenZhen Foscam Intelligent Technology Co Ltd BP4 ZDEBP4 bp4

Declaration on model difference We the undersigned hereby confirm that these

models are identical, and all models have the same RF module, PCB layout ,

Antenna, schematics and component. Only different on model name. Production

name Trademark Battery Security Camera FOSCAM FCC ZDEBP4 Model no. ...

lang:de **score:29** filesize: 116.14 K page\_count: 1 document date: 2025-01-02

[\[pdf\]](#) Test Report

2 4G WIFI Test Report 1 ShenZhen Foscam Intelligent Technology Co Ltd BP4 ZDEBP4 bp4

TEST REPORT Product Name 2K Battery Security Camera Model Number **BP4**,

**BP4W, BP4C** FCC ID **ZDEBP4** Prepared for Address Prepared by Address :

ShenZhen Foscam Intelligent Technology Co., Ltd : Room 902,Building 1B, Shenzhen

International innovationValley, Xingke 1st Street, Nanshan District, Shenzh...

lang:en score:28 filesize: 4.54 M page count: 38 document date: 0000-00-00

[\[pdf\]](#) Agent Authorization

Tim Payne US AGENT Letter ShenZhen Foscam Intelligent Technology Co Ltd BP4 ZDEBP4 bp4


ShenZhen Foscam Intelligent Technology Co., Ltd Room 902, Building 1B, Shenzhen

International Innovation Valley, Xingke 1st Street, Nanshan Dist Date: 2025.01.02

Federal Communications Commission Authorization and Evaluation Division 7435

Oakland Mills Road Columbia, MD 21046 FCC ID: ZDEBP4 FRN: 0022...

lang:en score:23 filesize: 127.98 K page count: 1 document date: 2025-01-02



[pdf] Declaration of Conformity

Lu Bian FCC SDOC Attestation Letter ShenZhen Foscam Intelligent Technology Co Ltd BP4 ZDEBP4 bp4

ShenZhen Foscam Intelligent Technology Co., Ltd Federal Communications Commission Authorization and Evaluation Division 7435 Oakland Mills Road Columbia, MD 21046 Date: 2024.12.26 SUBJECT: FCC ID: ZDEBP4 To Whom It May Concern: I, the undersigned, hereby states this equipment has been tested and fou...

lang:en score:22 filesize: 117.64 K page\_count: 1 document date: 2025-01-02



[pdf]

APPLICANT S LETTERHEAD Sid Sanders Attestation Statements 2 911 d 5 ShenZhen Foscam Intelligent Technology Co Ltd BP4 ZDEBP4 bp4

ShenZhen Foscam Intelligent Technology Co., Ltd Federal Communications Commission Authorization and Evaluation Division 7435 Oakland Mills Road Columbia, MD 21046 USA Date: 12-25-2024 Ref: Attestation Statements Part 2.911 d 5 i Filing FCC IDZDEBP4 ShenZhen Foscam Intelligent Technology Co., L...

lang:en score:22 filesize: 102.93 K page\_count: 2 document date: 2025-01-02




[pdf] Confidentiality Request Letter

APPLICANT S LETTERHEAD Sid Sanders Confidentiality Letter ShenZhen Foscam Intelligent Technology Co Ltd BP4 ZDEBP4 bp4

ShenZhen Foscam Intelligent Technology Co., Ltd Federal Communications Commission Authorization and Evaluation Division Confidentiality Request regarding application for certification of FCC ID: ZDEBP4 Pursuant to Sections 0.457 and 0.459 of the Commission s Rules, we hereby request confidential tr...

lang:en score:21 filesize: 90.6 K page\_count: 1 document date: 2025-01-02




[pdf]

TIMCO Engineering Inc Valued Sony Customer Authority Letter ShenZhen Foscam Intelligent Technology Co Ltd BP4 ZDEBP4 bp4

ShenZhen Foscam Intelligent Technology Co., Ltd Federal Communications Commission Authorization and Evaluation Division 7435 Oakland Mills Road Columbia, MD 21046 Date:2024.12.26 SUBJECT: FCC Application for FCC ID: ZDEBP4 To Whom It May Concern: We, the undersigned, hereby authorize Sam Lv. at EMTE...

lang:en score:21 filesize: 71.88 K page\_count: 1 document date: 2025-01-02






## [\[pdf\]](#) User Manual Instructions

305503001109 BP4 140×105mm V2 0 k User Manual ShenZhen Foscam Intelligent Technology Co Ltd ZDEBP4 bp4

Warning To assure continued compliance, any changes or modifications not expressly approved by the party. Responsible for compliance could void the user's authority to operate this equipment. FCC Statement This equipment complies with Part 15 of the FCC Rules. Operation is subject to the following two...

lang:en score:18 filesize: 2.07 M page\_count: 1 document date: 2024-11-26



## [\[pdf\]](#) Declaration of Conformity

Germany EC Declaration B4 BP4 Foscam of Conformity System foscam Images ce |||

...

lang:en score:15 filesize: 470.53 K page\_count: 2 document date: 2024-12-24



## [\[pdf\]](#) Product Photos Teardown

abc Internal Photos ShenZhen Foscam Intelligent Technology Co Ltd BP4 ZDEBP4 bp4

FCC ID: ZDEBP4 Report No. EDG2411200113E004 Page 1 of 6 Ver.1.0 Report No. EDG2411200113E004 Page 2 of 6 Ver.1.0 Report No. EDG2411200113E004 Page 3 of 6 Ver.1.0 Report No. EDG2411200113E004 Page 4 of 6 Ver.1.0 Report No. EDG2411200113E004 Page 5 of 6 Ver.1.0 Report No. EDG24112...

lang:en score:14 filesize: 1.82 M page\_count: 6 document date: 2025-01-06




[pdf] Product Photos

abc External Photos ShenZhen Foscam Intelligent Technology Co Ltd BP4 ZDEBP4 bp4  
FCC ID: ZDEBP4 Report No.EDG2411200113E004 Page 1 of 6 Ver.1.0 Report  
No.EDG2411200113E004 Page 2 of 6 Ver.1.0 ANT Report No.EDG2411200113E004  
Page 3 of 6 Ver.1.0 Report No.EDG2411200113E004 Page 4 of 6 Ver.1.0 Report  
No.EDG2411200113E004 Page 5 of 6 Ver.1.0 Report No.EDG241120...  
lang:en score:14 filesize: 2.05 M page\_count: 6 document date: 2025-01-06



[pdf] Confidentiality Request Letter

yy Antenna Specification ShenZhen Foscam Intelligent Technology Co Ltd BP4 ZDEBP4 bp4  
SPECIFICATION Shenzhen Guandetong Electronic Limited QR/ RD-P01-06B  
Shenzhen Guandeong Electronics Co., Ltd. Shenzhen Guandetong Electronic C o.,  
Ltd. External antenna: 2.4 G 3 dBi white-small lower seat antenna Feeder L: 150mm /  
-3mm specification client Wire name Customer material number Co...  
lang:en score:14 filesize: 291.32 K page\_count: 10 document date: 2025-01-03



[pdf] Label

EMC Label Location ShenZhen Foscam Intelligent Technology Co Ltd BP4 ZDEBP4 bp4  
...  
lang:en score:14 filesize: 513.83 K page\_count: 1 document date: 2025-01-02



[pdf] Product Photos

abc Test Setup Photos ShenZhen Foscam Intelligent Technology Co Ltd BP4 ZDEBP4 bp4  
FCC ID: ZDEBP4 Report No. EDG2411200113E004 Page 1 of 2 Ver.1.0 Report No.  
EDG2411200113E004 Page 2 of 2 Ver.1.0 ...  
lang:en score:13 filesize: 544.67 K page\_count: 2 document date: 2025-01-02

EMTEK  
ENTER TO THE WORLD

TestMode	Antenna	Frequency(MHz)	Result(dBm/3-100kHz)	Limit(dBm/3kHz)	Usage
11B	Ant1	2412	-17.56	-18.00	PASS
11B	Ant1	2417	-18.00	-18.00	PASS
11B	Ant1	2422	-17.53	-18.00	PASS
11G	Ant1	2437	-19.72	-18.00	PASS
11G	Ant1	2442	-19.82	-18.00	PASS
11G	Ant1	2447	-20.24	-18.00	PASS
11N20SISO	Ant1	2412	-20.24	-18.00	PASS
11N20SISO	Ant1	2417	-20.27	-18.00	PASS
11N20SISO	Ant1	2422	-19.82	-18.00	PASS

Report No. EDG2411200113E0041R Page 31 of 77 Ver.1.0

[pdf] Test Report

2 4G WIFI Test Report ShenZhen Foscam Intelligent Technology Co Ltd BP4 ZDEBP4 bp4  
TestMode 11B 11B 11B 11G 11G 11G 11N20SISO 11N20SISO 11N20SISO  
Antenna Ant1 Ant1 Ant1 Ant1 Ant1 Ant1 Ant1 Ant1 Ant1 Frequency MHz 2412 2437  
2462 2412 2437 2462 2412 2437 2462 Result dBm/3-100kHz -17.56 -18.00 -17.53 -  
19.72 -20.24 -19.82 -20.24 -20.97 -20.48 Limit dBm/3kHz 8.00 8.00 8.00 8.00 ...  
lang:en score:13 filesize: 5.35 M page\_count: 39 document date: 0000-00-00