

[manuals.plus](#) /

› [Perlegear](#) /

› [Perlegear 10U Open Frame Network Rack Instruction Manual \(Model PGSER02B\)](#)

Perlegear PGSER02B

Perlegear 10U Open Frame Network Rack Instruction Manual

MODEL: PGSER02B

Brand: Perlegear

1. INTRODUCTION

This manual provides detailed instructions for the assembly, installation, and operation of your Perlegear 10U Open Frame Network Rack (Model PGSER02B). Please read this manual thoroughly before installation to ensure proper setup and safe use. Keep this manual for future reference.



Figure 1: Perlegear 10U Open Frame Network Rack with shelves.

2. SAFETY INFORMATION

Observe the following safety precautions during assembly and use:

- Ensure all components are present and undamaged before assembly.
- Do not exceed the maximum load capacity of 200 lbs for the rack and 22 lbs for the top panel.
- When wall-mounting, ensure the mounting surface (e.g., wood studs, concrete wall) can safely support the rack's weight and its contents. Do not mount on drywall alone.
- Use appropriate tools and follow all installation steps carefully.
- Keep children and pets away from the assembly area.

3. PACKAGE CONTENTS

Verify that all parts are included in your package:

Complete Package




Figure 2: Complete Package Contents.

- Rack Frame (x2)
- Shelf (x2)
- Back Brace (x2)
- Front Brace (x2)
- M6 Bolt (x40)
- Cage Nut (x8)
- M6 Nut (x12)
- Wall Anchor (x6)
- Lag Screw (x6)
- Wall Plate Template (x1)

4. SPECIFICATIONS

Feature	Specification
Model Number	PGSER02B
Rack Units (U)	10U
Product Dimensions (D x W x H)	20.12" x 20.5" x 19.39" (51.1cm x 52.1cm x 49.2cm)
Item Weight	30.5 lbs (13.8 kg)
Material	Cold-rolled Steel
Color	Black
Max Load Capacity (Rack)	200 lbs (90.7 kg)
Max Load Capacity (Top Panel)	22 lbs (10 kg)
Compatibility	19-inch networking, AV, and IT equipment

Product Dimensions



Figure 3: Product Dimensions and Hardware Kit Overview.

5. SETUP AND INSTALLATION

The Perlegear 10U Open Frame Network Rack offers flexible installation options: wall-mounted or floor-standing. Follow these steps for assembly and installation.

5.1. Assembly Overview

Keep Your Equipment Cool

Open rack and vented shelves help improve airflow



Figure 4: Simple Setup Overview.

5.2. Detailed Assembly Steps

For a visual guide, please refer to the official installation video below:

Your browser does not support the video tag.

Video 1: Perlegear 10U Network Rack Installation Tutorial. This video demonstrates the step-by-step assembly and installation process for the rack.

1. Assemble the Frame:

- Identify the Left and Right Frames, Back Braces, and Front Braces.
- Attach the Back Braces to the bottom of the Left and Right Frames using M6 Bolts and M6 Nuts. Ensure the side with three holes on the frame faces the front.
- Attach the Front Braces to the top of the Left and Right Frames, again ensuring the side with three holes faces the front. The 'PERLEGEAR' logo on the front brace should be visible.
- Tighten all M6 Nuts using a PH2 or PZ2 screwdriver and a 10mm wrench for secure assembly.

2. Install Shelves:

- Insert the two 1U vented shelves into the desired rack unit positions.
- Utilize the provided shelf reinforcement brackets to support the shelves and prevent sagging, especially for heavier equipment. These brackets can be installed on one shelf or across two different shelves for added stability.

Shelf Reinforcement



01



Install both
brackets on one shelf

02



Install brackets on
two different shelves

Figure 5: Shelf Reinforcement Options.

3. Mounting Options:

- **Floor-Standing:** Place the assembled rack on a stable, level surface. The rack includes caster holes at the bottom for optional mobility (casters not included).
- **Wall-Mounted:** Use the provided drilling template to mark pilot holes. Mount the rack to 16-inch wood studs (without anchors) or concrete walls (with anchors) using the lag screws. Ensure the rack is securely fastened before loading equipment.

Flexible Setup



Wall-mounted

Floor-standing



Figure 6: Flexible Setup - Wall-mounted and Floor-standing configurations.

6. OPERATING INSTRUCTIONS

Once assembled and installed, the Perlegear 10U Open Frame Network Rack is ready for use.

6.1. Equipment Installation

- Install your 19-inch rack-mounted networking, AV, and IT equipment into the rack units.
- Utilize the two 1U vented shelves for non-rack-mountable devices such as smaller switches, storage devices, or UPS units.
- Ensure proper cable management to maintain airflow and prevent obstruction.

Large 10U Rack Space

10U



Compatible with

- Holds 19" networking & AV gear
- Fits 16" wood studs

Figure 7: Rack with 10U Space and Equipment.

6.2. Airflow and Cooling

The open frame design and vented shelves promote optimal airflow, which is crucial for keeping your networking, audio, and video equipment cool and preventing overheating.



Figure 8: Enhanced Airflow for Equipment Cooling.

6.3. Expandability

This server rack features an expandable design. You can stack two 10U racks to create a 20U rack, doubling your storage capacity for growing equipment needs. Ensure to remove the top panel of the bottom rack when stacking.

Simple Setup



Figure 9: Stackable Design for Increased Capacity.

Store More on Top



Figure 10: Utilizing the Top Surface for Additional Storage.

7. MAINTENANCE

Regular maintenance ensures the longevity and optimal performance of your network rack:

- **Cleaning:** Wipe the rack surfaces with a soft, dry cloth to remove dust. For stubborn marks, use a mild, non-abrasive cleaner.
- **Inspection:** Periodically check all bolts and nuts to ensure they remain tight. Re-tighten if necessary.
- **Load Check:** Verify that the total weight of equipment does not exceed the maximum load capacity.

8. TROUBLESHOOTING

If you encounter any issues, consider the following:

- **Rack Instability:** Ensure all bolts and nuts are securely tightened. If wall-mounted, confirm the mounting hardware is correctly installed into appropriate structural supports.
- **Equipment Overheating:** Check for proper cable management that might obstruct airflow. Ensure the rack is not placed in an enclosed space without adequate ventilation.
- **Difficulty Installing Equipment:** Verify that your equipment is 19-inch rack-mountable. Ensure cage nuts are correctly inserted into the square holes before attaching equipment with M6 bolts.

9. WARRANTY AND SUPPORT

Perlegear products are designed for durability and performance. For warranty information, technical support, or to purchase replacement parts, please visit the official Perlegear website or contact customer service through your retailer.

Related Documents - PGSER02B

 <p>PERLEGEAR SERVER COMPUTER RACK INSTRUCTION MANUAL PGSER02</p> <p>Thank you for choosing this Perlegear product. We strive to provide you with the best instructions and support possible. If you have any questions or concerns about this product or any of our other products, please contact us at the number below.</p>	<p>Perlegear PGSER02 Server Computer Rack Instruction Manual</p> <p>Detailed instruction manual for assembling and installing the Perlegear PGSER02 Server Computer Rack. Includes parts list, tools required, safety warnings, and step-by-step installation guides for wood stud and solid concrete walls.</p>
 <p>取扱説明書 PGTVMC04 Perlegear</p> <p>テレビスタンド</p> <p>www.perlegear.com</p>	<p>Perlegear PGTVMC04 TV Stand Instruction Manual</p> <p>Comprehensive assembly and safety guide for the Perlegear PGTVMC04 mobile TV stand with casters. This manual provides detailed instructions, parts lists, hardware specifications, and step-by-step procedures for securely mounting televisions and shelves.</p>
 <p>PERLEGEAR FREQUENTLY ASKED QUESTIONS</p>	<p>Perlegear TV Wall Mount Frequently Asked Questions (FAQ)</p> <p>Find answers to common questions about Perlegear TV wall mounts, including VESA patterns, wall types, installation challenges, and troubleshooting steps.</p>

<p>INSTRUCTION MANUAL Rev00A</p> <p>Perlegear</p> <p>PGFS06</p>  <p>Floor TV Stand</p> <p>© 2023 Perlegear.com 1-800-424-0988 www.perlegear.com</p>	<p>Perlegear PGFS06 Floor TV Stand Instruction Manual</p> <p>Comprehensive instruction manual for the Perlegear PGFS06 Floor TV Stand. This guide provides detailed steps for compatibility checks, assembly, TV mounting, shelf installation, cable management, and adjustments, ensuring a secure and optimal TV setup.</p>
<p>PERLEGEAR</p> <p>テレビスタンド 取扱説明書 Rev00</p> <p>モデル PGFS10/PGFS10W</p>  <p>PERLEGEAR PGFS10/PGFS10W TV Stand Assembly Instructions</p> <p>© 2023 Perlegear.com 1-800-424-0988 www.perlegear.com</p>	<p>PERLEGEAR PGFS10/PGFS10W TV Stand Assembly Instructions</p> <p>Comprehensive guide for assembling the PERLEGEAR PGFS10 and PGFS10W TV stands, including compatibility checks, parts list, and step-by-step instructions with safety precautions.</p>
<p>PERLEGEAR</p> <p>FLOOR TV STAND INSTRUCTION MANUAL Rev00</p> <p>MODEL PGFS09</p>  <p>Perlegear PGFS09 Floor TV Stand Instruction Manual</p> <p>© 2023 Perlegear.com 1-800-424-0988 www.perlegear.com</p>	<p>Perlegear PGFS09 Floor TV Stand Instruction Manual</p> <p>Comprehensive instruction manual for the Perlegear PGFS09 Floor TV Stand, detailing assembly, compatibility checks, and safety guidelines for mounting TVs from 32 to 70 inches.</p>