

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

manuals.plus /

- › [Bulelink](#) /
- › [Bulelink Zenith G10 Cordless Stick Vacuum Cleaner User Manual](#)

Bulelink Zenith G10

Bulelink Zenith G10 Cordless Stick Vacuum Cleaner User Manual

Model: Zenith G10

1. IMPORTANT SAFETY INFORMATION

Please read all instructions carefully before using the Bulelink Zenith G10 Cordless Stick Vacuum Cleaner. Keep this manual for future reference.

- **Electrical Safety:** Do not handle the plug or vacuum cleaner with wet hands. Do not use if the power cord or plug is damaged.
- **Battery Safety:** Use only the original charger provided. Do not expose the battery to high temperatures or direct sunlight. Do not attempt to disassemble the battery pack.
- **Usage Environment:** This appliance is for household use only. Do not vacuum liquids, hot ashes, sharp objects, or flammable/combustible materials. Ensure the dustbin and filters are correctly installed before use.
- **Children and Pets:** Keep the vacuum cleaner out of reach of children and pets. Supervise children to ensure they do not play with the appliance.
- **Maintenance:** Always switch off and unplug the vacuum cleaner before cleaning or performing any maintenance.

2. PRODUCT COMPONENTS

The Bulelink Zenith G10 comes with several components designed for versatile cleaning. Familiarize yourself with each part:



Main Unit and

Accessories: This image displays the complete vacuum cleaner assembly, including the main unit, telescopic tube, motorized brush, and various attachments like the 2-in-1 brush and flat nozzle.



Packaging List: A visual representation of all items included in the box, such as the main unit, battery, telescopic tube, motorized brush, power adapter, wall mount, long crevice tool, 2-in-1 brush, HEPA filter, dustbin, cleaning brush, and user manual.

Included Components:

- Main Unit (Motor and Dustbin)
- Removable Battery
- Telescopic Tube
- Motorized Floor Brush (V-shaped anti-tangle)
- Power Adapter
- Wall Mount
- 2-in-1 Brush
- Long Crevice Tool
- HEPA Filter (additional filter included)
- Cleaning Brush
- Quick Start Guide & User Manual

3. SETUP AND ASSEMBLY

Follow these steps to assemble and prepare your Bulelink Zenith G10 for first use:

1. **Unpack:** Carefully remove all components from the packaging.
2. **Attach Telescopic Tube:** Connect the telescopic tube to the main unit until it clicks into place.
3. **Attach Floor Brush:** Connect the motorized floor brush to the other end of the telescopic tube, ensuring it clicks securely.
4. **Install Battery:** Insert the removable battery into the designated slot on the main unit until it locks.
5. **Initial Charge:** For optimal performance, fully charge the battery before first use. Connect the power

adapter to the charging port on the battery or the wall mount. A full charge takes approximately 4 to 5 hours.

6. **Wall Mount Installation (Optional):** Choose a suitable location near a power outlet. Secure the wall mount to the wall using the provided screws and anchors. The vacuum can be stored and charged on the wall mount.



Wall Mount Charging: The vacuum can be conveniently stored and charged using the included wall mount, keeping it ready for use.

4. OPERATING INSTRUCTIONS

The Bulelink Zenith G10 is designed for powerful and convenient cleaning across various surfaces.

Power On/Off and Suction Modes:

Press the power button to turn the vacuum on. The intelligent OLED touchscreen allows you to easily switch between three suction levels: 25 kPa (Min), 35 kPa (Mid), and 45 kPa (Max). The screen also displays real-time battery status and alerts for blockages.



OLED Touchscreen: The intuitive OLED display provides real-time information on battery level, suction mode, and maintenance alerts.



Powerful Suction:

Equipped with a 550W motor, the vacuum offers up to 45kPa of suction power, effectively cleaning various debris.

Battery Life:

The 2500mAh removable battery provides up to 65 minutes of runtime in low power mode and 30 minutes in high power mode. An optional second battery (sold separately) can double the cleaning time.



Extended Runtime: The 2500mAh battery allows for up to 65 minutes of continuous cleaning, suitable for whole-house cleaning.

Enhanced Floor Brush:

The improved anti-tangle floor brush features integrated soft and stiff bristles, making it suitable for both hard floors and carpets without needing to change rollers. Its V-shaped structure reduces hair entanglement by up to 80%. The 270° swivel head and front LED lights illuminate dark areas, ensuring no dust or dirt is missed.

Brosse Rouleau V Anti-Enchevêtrement

Pois Souples et Rigides Intégrés



Anti-Tangle Brush: The V-shaped brush design with integrated bristles minimizes hair entanglement and features LED lights for improved visibility.



Edge and Corner

Cleaning: The flexible brush head and powerful suction ensure thorough cleaning along edges and in corners.

Versatile Cleaning:

The telescopic tube is adjustable (95 cm ~ 118 cm) to suit users of all heights. The self-standing design allows the vacuum to stand upright independently, providing convenience during cleaning breaks.

Design Autoportant

Rangez-le N'importe Où, Utilisez-le à Tout Moment



Self-Standing Design: The vacuum can stand upright on its own, offering convenient storage and temporary placement during cleaning.

Product Videos:

Your browser does not support the video tag.

Product Demonstration: This video showcases the Bulelink Zenith G10 in action, highlighting its powerful suction, maneuverability, and ease of use on various surfaces.

Your browser does not support the video tag.

Features Overview: This video provides a detailed look at the key features of the Bulelink Zenith G10, including its lightweight

design, LED lights, and efficient cleaning capabilities.

5. MAINTENANCE

Regular maintenance ensures the longevity and optimal performance of your Bulelink Zenith G10.

Emptying the Dustbin:

The 1.6L dustbin allows for extended cleaning sessions without frequent emptying. To empty, simply press the release button to detach the dustbin and dispose of the contents. This one-touch emptying system is designed for quick and effortless disposal.

Grande Capacité 1.6 Litres

Vidange du Bac à Poussière en Une Touche



One-Touch Dustbin Emptying: The large 1.6L dustbin can be emptied easily with a single press of a button, minimizing contact with dirt.

Cleaning the Filtration System:

The 8-layer high-efficiency filtration system captures 99.99% of particles down to 0.3 micrometers. To maintain suction power and air quality, regularly clean the filters. The filter components are washable.

1. **Remove Filters:** Detach the dustbin and carefully remove the HEPA filter and other filter components.
2. **Wash:** Rinse the washable filter components under cold running water until the water runs clear. Do not use detergents.
3. **Dry:** Allow all filter components to air dry completely for at least 24 hours before reassembling. Ensure they are thoroughly dry to prevent mold or damage.

4. **Reassemble:** Once dry, reassemble the filters and reattach the dustbin to the main unit.



High-Efficiency Filtration: The 8-layer system effectively captures fine dust and allergens, purifying the air during cleaning.

Cleaning the Brush Roll:

Periodically check the motorized floor brush for tangled hair or debris. Use the included cleaning brush or scissors to remove any obstructions from the brush roll to ensure smooth operation.

6. TROUBLESHOOTING

If you encounter issues with your Bulelink Zenith G10, refer to the following common problems and solutions:

Problem	Possible Cause	Solution
Vacuum does not turn on	Battery is not charged or not properly installed.	Ensure the battery is fully charged and securely inserted.
Low suction power	Dustbin is full; Filters are clogged; Brush roll is obstructed; Suction inlet is blocked.	Empty the dustbin. Clean or replace filters. Remove any hair or debris from the brush roll. Check for blockages in the telescopic tube or suction inlet.
Brush roll not spinning	Brush roll is jammed by debris; Brush head is not properly attached.	Remove any obstructions from the brush roll. Ensure the brush head is securely connected to the telescopic tube.
Short battery runtime	Battery not fully charged; Using high power mode excessively; Battery life degradation.	Ensure battery is fully charged. Use lower power modes for longer runtime. Consider purchasing a new battery if degradation is significant.
Unusual noise	Blockage in the air path; Loose component.	Check for and remove any blockages in the dustbin, filters, tubes, or brush head. Ensure all components are securely assembled.

If the problem persists after attempting these solutions, please contact Bulelink customer support for assistance.

7. SPECIFICATIONS

Key technical specifications for the Bulelink Zenith G10 Cordless Stick Vacuum Cleaner:

Brand: Bulelink

Model: Zenith G10

Motor Power: 550W

Suction Power: 25 kPa (Min), 35 kPa (Mid), 45 kPa (Max)

Dustbin Capacity: 1.6 Liters

Battery Capacity: 8x2500mAh (Removable)

Runtime: Up to 65 minutes (Min mode), 30 minutes (Max mode)

Charging Time: 4-5 hours

Noise Level: <62 dB

Product Dimensions: 44.5 x 34 x 19 cm

Item Weight: 4.33 Kilograms

Special Features: OLED Touchscreen, Anti-Tangle Brush, LED Headlights, Self-Standing Design, 8-Layer High-Efficiency Filtration, Adjustable Telescopic Tube

Recommended Uses: Pet hair removal, carpets, hard floors, car interiors

8. WARRANTY AND SUPPORT

Bulelink is committed to providing high-quality products and excellent customer service.

Warranty Information:

This product comes with a **3-year warranty service**. Please retain your proof of purchase for warranty claims.

Return and Exchange Policy:

You are eligible for a **30-day return and exchange** period from the date of purchase, subject to the seller's return policy.

Customer Support:

For any assistance, questions, or concerns regarding your Bulelink Zenith G10, please contact our online support. We aim to provide reliable products and services at all times.



Professional After-Sales Service: Bulelink offers a 3-year warranty, 30-day return/exchange, 24-hour online support, and a 100% satisfaction guarantee.