

## Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

manuals.plus /

- › [OMIZN](#) /
- › [OMIZN M5 Walkie Talkie Instruction Manual](#)

## OMIZN M5

# OMIZN M5 Walkie Talkie Instruction Manual

Model: M5

## 1. INTRODUCTION

---

The OMIZN M5 Walkie Talkie is a robust communication device designed for global use, leveraging 4G LTE networks for unlimited range. It features AES256 encryption for secure conversations, intelligent noise reduction for clear audio, and an IP65 rating for durability. This manual provides essential information for the proper setup, operation, and maintenance of your M5 Walkie Talkie.

**Not Affected by Environment, Breaks Distance Limits**  
**Global Walkie-Talkie Without Distance Restrictions**  
**Built-in SIM Card, Works in 172 Countries and Regions**



Figure 1: OMIZN M5 Walkie Talkie, highlighting its global communication capabilities.

## 2. PRODUCT OVERVIEW AND FEATURES

The OMIZN M5 is engineered for reliable and secure communication across vast distances. Key features include:

- **Global Unlimited Range Communication:** Utilizes 4G LTE networks for instant voice transmission across 172 countries.
- **Lifetime Free Data:** Built-in IoT SIM card includes a lifetime data plan with no monthly fees.
- **AES256 Encryption:** Protects operational privacy with end-to-end digital encryption.
- **Noise Reduction:** Integrated intelligent chip filters out 95% of background noise for clear voice.
- **Flexible Group Dispatching System:** Supports one-to-one, group, and all-group calls. Admin mode allows urgent commands.
- **All Day Battery Life:** High-capacity 6000mAh battery supporting 2-4 days of standby.
- **Type-C Charging:** Universal Type-C port for convenient charging.
- **IP65 Durability:** Dustproof and splashproof design for reliable performance.

# AES256 Encryption

Military-grade encryption, unbreakable by brute force, ensuring the security of every call you make.



Figure 2: The M5 Walkie Talkie features AES256 encryption for secure communications.

# Hi-Fi Clear Sound Quality Intelligent Noise Reduction



Figure 3: Intelligent noise reduction ensures clear sound quality even in noisy environments.

### 3. WHAT'S IN THE BOX

Upon unboxing your OMIZN M5 Walkie Talkie, verify that all the following items are included:

- OMIZN M5 Walkie Talkie Unit
- Antenna
- 6000mAh Lithium Battery
- Belt Clip
- Lanyard
- Type-C Charging Cable
- Charger Plug (AC Adapter)

# Product Visual Presentation



Figure 4: All components included in the OMIZN M5 Walkie Talkie package.

Your browser does not support the video tag.

Video 1: An unboxing video for the OMIZN M5 PoC Walkie Talkie, demonstrating the contents of the package and initial handling of the device.

## 4. SETUP

### 4.1 Battery Installation

1. Ensure the device is powered off.
2. Locate the battery compartment cover on the back of the walkie talkie.
3. Slide or unlatch the cover to open it.
4. Insert the 6000mAh Lithium Battery, aligning the contacts correctly.
5. Close the battery compartment cover securely.

### 4.2 SIM Card Installation

The OMIZN M5 comes with a built-in IoT SIM card for lifetime free data. No physical SIM card installation is typically required for

initial use. If you need to use a different SIM card or encounter issues, please contact support.

### 4.3 Antenna Attachment

1. Locate the antenna port on the top of the walkie talkie.
2. Screw the provided antenna clockwise into the port until it is finger-tight. Do not overtighten.

### 4.4 Charging the Battery

Before first use, fully charge the battery.

1. Connect the Type-C charging cable to the charging port on the device.
2. Plug the other end of the cable into the charger plug, then into a standard electrical outlet.
3. The charging indicator will show the charging status. A full charge typically takes approximately 4 hours.
4. Disconnect the charger once charging is complete.

**6000mAh High Capacity**

**60000** mAh

**3-5** Days  
Standby Time

**1-2** Days  
Continuous Usage

**4** Hours  
Type-C Fast Charging

Figure 5: The M5 Walkie Talkie with its high-capacity battery and Type-C charging capability.

## 5. OPERATING INSTRUCTIONS

---

### 5.1 Power On/Off

- **To Power On:** Press and hold the Power button until the screen illuminates.
- **To Power Off:** Press and hold the Power button until the device prompts you to shut down, then confirm.

### 5.2 Volume Adjustment

Use the dedicated volume buttons (usually located on the side or front panel) to increase or decrease the audio output level.

### 5.3 Basic Communication (Push-to-Talk)

1. Ensure you are connected to the network (indicated on the display).
2. Select the desired group or individual contact for communication.
3. Press and hold the Push-to-Talk (PTT) button to transmit your voice.
4. Speak clearly into the microphone.
5. Release the PTT button to listen for a response.

### 5.4 Group and One-to-One Calls

The M5 supports various call types:

- **Group Calls:** Communicate with all members assigned to a specific group.
- **One-to-One Calls:** Initiate a private conversation with a single user.
- **All-Group Dispatching:** An administrator can broadcast messages to all active groups.

Refer to the on-screen menu for selecting and managing groups and contacts. The administrator mode allows for priority interruption for urgent commands.

# Multi-Scenario Applicable

200 groups for easy switching, supports one-on-one private calls, group calls, and one-touch switching.

It works well for dispatching, team management, camping, travel, and more.



Figure 6: The M5 Walkie Talkie is suitable for multiple scenarios, including team management and outdoor use.

## 6. MAINTENANCE

### 6.1 Cleaning

Wipe the device with a soft, damp cloth. Do not use harsh chemicals or abrasive cleaners. Ensure all ports are dry before charging.

### 6.2 Battery Care

- Avoid fully discharging the battery frequently.
- Store the device in a cool, dry place when not in use for extended periods.
- Charge the battery at least once every three months to maintain its health.

### 6.3 Storage

Store the walkie talkie in a dry, dust-free environment, away from direct sunlight and extreme temperatures.

## 7. TROUBLESHOOTING

Problem	Possible Cause	Solution
Device does not power on	Low or depleted battery; improperly installed battery.	Charge the battery; ensure battery is correctly installed.
No network signal	Out of 4G LTE coverage area; SIM card issue.	Move to an area with better signal; contact OMIZN support for SIM card replacement if necessary.
Cannot transmit or receive	Incorrect group/contact selected; PTT button not pressed correctly; network issue.	Verify selected group/contact; ensure PTT button is held during transmission; check network status.
Poor audio quality	High background noise; microphone/speaker obstruction.	Ensure noise reduction is active; clear any obstructions from microphone/speaker.

## 8. SPECIFICATIONS

Feature	Detail
Model Number	M5
Dimensions (H x W x D)	2.99 x 2.2 x 1.3 inches
Item Weight	7 ounces (0.44 Pounds)
Battery Capacity	6000mAh
Standby Time	2-4 days (up to 144 hours)
Charging Time	Approx. 4 hours (Type-C)
Frequency Range	4G LTE (Global)
Number of Channels	200 (groups)
Encryption	AES256
Durability Rating	IP65 (Dustproof and Splashproof)
Display Type	LCD
Voltage	3.7 Volts (DC)

## 9. WARRANTY AND SUPPORT

OMIZN is committed to providing reliable products and customer satisfaction. For any product malfunctions, signal issues, or questions regarding usage, please contact our support team immediately through Amazon. We offer a professional replacement service for SIM card related signal issues to ensure continuous connectivity.

For further assistance, please visit the [OMIZN Store on Amazon](#).

