

[Manuals.plus](#) /

› [JUMMICO](#) /

› JUMMICO Electric Standing Desk with Monitor Stand (Model 0463) - Instruction Manual

JUMMICO 0463

JUMMICO Electric Standing Desk with Monitor Stand - Instruction Manual

Model: 0463

1. IMPORTANT SAFETY INFORMATION

Please read this manual thoroughly before assembly and operation. Retain this manual for future reference.

- Ensure all components are present and undamaged before assembly.
- Keep children and pets away from the desk during operation.
- Avoid placing liquids directly on the control panel or motor components.
- Do not overload the desk beyond its maximum weight capacity of 80 kg (176 lbs).
- Ensure there are no obstructions in the desk's path during height adjustment to prevent damage or injury.
- Only use the provided power adapter.

2. PACKAGE CONTENTS

Verify that all the following parts are included in your package:

- Desktop Sections (3 parts)
- Lifting Columns (Legs)
- Desk Feet
- Control Panel
- Motor and Power Adapter
- Monitor Stand
- Headphone Hook
- Hardware Kit (screws, Allen wrenches, cable ties)

Praktisches Zubehör

Drahtaufnahmeloch



**Verstellbare
Schreibtischfüße**



Kopfhörerhaken



Image: Practical accessories such as a cable management hole, adjustable desk feet, and a headphone hook are included for enhanced usability.



Image: The included monitor stand elevates your screen for ergonomic viewing and provides additional storage space.

3. SETUP AND ASSEMBLY

Assembly is straightforward with pre-drilled holes. Please note that the tabletop consists of three sections.

- 1. Unpack Components:** Carefully remove all parts from the packaging and lay them out on a clean, soft surface to prevent scratches.
- 2. Assemble Desk Frame:** Attach the desk feet to the lifting columns using the provided screws.
- 3. Attach Lifting Columns to Desktop:** Secure the lifting columns to the pre-drilled holes on the underside of the desktop sections. Ensure the three desktop sections are aligned correctly.
- 4. Connect Motor and Control Panel:** Connect the motor cable to the control box and the control panel cable to the control box. Plug the power adapter into the control box and then into a power outlet.
- 5. Install Monitor Stand:** Attach the monitor stand to the designated area on the desktop.
- 6. Install Headphone Hook:** Secure the headphone hook to the side of the desk frame.
- 7. Cable Management:** Use the provided cable ties and cable management holes to organize wires neatly.



Image: A fully assembled JUMMICO Electric Standing Desk, showcasing the monitor stand, ample workspace, and integrated headphone hook.

4. OPERATING INSTRUCTIONS

The JUMMICO Electric Standing Desk features an intuitive control panel for easy height adjustment and memory presets.

4.1. Height Adjustment

- Use the **UP** (▲) and **DOWN** (▼) buttons on the control panel to adjust the desk height.
- The desk can be adjusted from a minimum height of 73 cm (28.7 inches) to a maximum height of 118 cm (46.5 inches).
- The current height is displayed on the digital screen of the control panel.

4.2. Memory Presets

The desk allows you to save two preferred height settings for quick adjustments.

1. Adjust the desk to your desired height using the UP/DOWN buttons.
2. Press the **M** button (if available, or hold the preset button directly) followed by either **1** or **2**. The display will show 'S-' and then the number, indicating the height is saved.
3. To recall a saved height, simply press the corresponding **1** or **2** button. The desk will automatically move to

the saved position.

4.3. Anti-Collision System

The desk is equipped with an intelligent anti-collision system. If the desk encounters an obstruction during height adjustment, it will automatically stop and reverse slightly to prevent damage.



Image: The smart control panel features a digital height display, up/down arrows, and two memory preset buttons (1 and 2) for convenient operation.

Höhenverstellbarer Schreibtisch mit Monitorständer



Image: A user demonstrating the standing position, highlighting the ergonomic benefits of the height-adjustable desk.



Image: Visual representation of the desk's adjustable height range, from 73 cm (sitting) to 118 cm (standing).

5. MAINTENANCE

Regular maintenance ensures the longevity and optimal performance of your JUMMICO Electric Standing Desk.

- **Cleaning:** Wipe the desk surface and frame with a soft, damp cloth. Avoid using abrasive cleaners or harsh chemicals that could damage the finish.
- **Cable Inspection:** Periodically check all cables for any signs of wear, fraying, or damage. Ensure they are securely connected.
- **Screw Tightness:** Occasionally check and tighten any loose screws on the frame or desktop connections.
- **Obstruction Check:** Ensure the area around the desk is clear of obstructions that could interfere with its movement.

6. TROUBLESHOOTING

If you encounter any issues with your desk, refer to the following common troubleshooting steps:

Problem	Possible Cause	Solution
Desk does not move	No power, loose cable connection, motor error	Check power cord connection to outlet and control box. Ensure all motor and control panel cables are securely plugged in. Unplug and replug the power for 10 seconds to reset.
Desk moves unevenly or makes unusual noise	Uneven weight distribution, loose screws, obstruction	Distribute weight evenly on the desktop. Check and tighten all assembly screws. Ensure no objects are obstructing the lifting columns.
Control panel display shows an error code	System malfunction	Refer to the specific error code in a more detailed troubleshooting guide (if available) or contact customer support. Often, a power cycle (unplugging for 10 seconds) can resolve minor errors.
Anti-collision system triggers too easily/not at all	Sensitivity setting (if adjustable), sensor issue	Check if your model allows for anti-collision sensitivity adjustment (refer to advanced settings if applicable). Ensure sensors are clean and unobstructed.

If the problem persists after attempting these solutions, please contact JUMMICO customer support for further assistance.

7. SPECIFICATIONS

Detailed specifications for the JUMMICO Electric Standing Desk (Model 0463):

Feature	Detail
Brand	JUMMICO
Model Number	0463
Shape	Rectangular
Product Dimensions (D x W x H)	30.51"D x 7.09"W x 23.62"H (Packaged)
Desktop Size	160 cm x 70 cm (63 inches x 28 inches)
Color	White
Item Weight	24.4 Kilograms (53.8 lbs)
Minimum Height	73 Centimeters (28.7 inches)
Maximum Height	118 Centimeters (46.5 inches)
Maximum Weight Recommendation	80 Kilograms (176 lbs)
Base Type	Metal
Included Components	Headphone Hook, Monitor Stand

Feature	Detail
Assembly Required	Yes
UPC	788418999955



Image: A comprehensive diagram illustrating the various dimensions of the desk, including desktop size, height range, and monitor stand measurements.

8. WARRANTY AND SUPPORT

JUMMICO products are designed for quality and durability. For information regarding warranty coverage, please refer to the warranty card included with your purchase or visit the official JUMMICO website.

If you require technical assistance, have questions about assembly, or need to report a missing/damaged part, please contact JUMMICO customer service. Provide your model number (0463) and purchase details for efficient support.

You can typically find contact information on the JUMMICO brand store page or through the retailer where you

purchased the product.

ASK A QUESTION ABOUT THIS MANUAL

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. [Privacy details](#).

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

Open the live page

<https://manuals.plus/asin/B0F4RNH2W4>

More documents and user manuals: <https://manuals.plus/>