

manuals.plus /

› [Rapoo](#) /

› [Rapoo 9390M Wireless Multi-Mode Keyboard and Mouse Combo Instruction Manual](#)

Rapoo 9390M

Rapoo 9390M Wireless Multi-Mode Keyboard and Mouse Combo Instruction Manual

INTRODUCTION

Thank you for choosing the Rapoo 9390M Wireless Multi-Mode Keyboard and Mouse Combo. This ultra-slim set offers versatile connectivity options, including 2.4 GHz wireless and Bluetooth 4.0/5.0, allowing seamless switching between multiple devices. Designed for efficiency and comfort, this combo features a full-size QWERTZ keyboard with multimedia keys and an ambidextrous optical mouse.

This manual provides essential information for setting up, operating, and maintaining your new Rapoo 9390M combo. Please read it carefully before use.



Image: The Rapoo 9390M wireless keyboard and mouse combo, showcasing its sleek design and full QWERTZ layout.

SETUP

1. Battery Installation

The Rapoo 9390M combo requires batteries for operation. Ensure correct polarity when inserting.

- **Keyboard:** Requires 2 x AAA alkaline batteries.
- **Mouse:** Requires 1 x AA alkaline battery.

Batteries are included in the package.



Image: Side profile of the Rapoo 9390M keyboard and mouse, illustrating their ultra-slim design. Battery compartments are typically located on the underside of each device.

2. Connecting the Devices

The Rapoo 9390M supports multi-mode connectivity: 2.4 GHz wireless via USB receiver and Bluetooth 4.0/5.0.

2.1. 2.4 GHz Wireless Connection

1. Insert the USB receiver into an available USB Type-A port on your computer or device.
2. Turn on the keyboard and mouse using their respective power switches.
3. The devices should automatically connect to your computer.

2.2. Bluetooth Connection

The keyboard can pair with up to 3 Bluetooth devices, and the mouse with up to 2.

Keyboard Bluetooth Pairing:

1. Turn on the keyboard.
2. Press and hold **Fn + 1**, **Fn + 2**, or **Fn + 3** for 3 seconds to select a Bluetooth channel. The indicator light will flash slowly.
3. Open Bluetooth settings on your device (PC, laptop, tablet, TV).
4. Search for "Rapoo BT3.0 Keyboard" or "Rapoo BT5.0 Keyboard" and select to pair.
5. Once paired, the indicator light will stop flashing.

Mouse Bluetooth Pairing:

1. Turn on the mouse.
2. Press the Bluetooth pairing button on the underside of the mouse. The indicator light will flash slowly.
3. Open Bluetooth settings on your device.
4. Search for "Rapoo BT3.0 Mouse" or "Rapoo BT5.0 Mouse" and select to pair.
5. Once paired, the indicator light will stop flashing.

OPERATING INSTRUCTIONS

1. Switching Between Connected Devices

The Rapoo 9390M allows you to switch between multiple connected devices (up to 4 for keyboard, 3 for mouse, including 2.4 GHz).

- **Keyboard:** Press **Fn + 1**, **Fn + 2**, **Fn + 3** (for Bluetooth devices) or **Fn + 4** (for 2.4 GHz USB receiver) to switch between paired devices.
- **Mouse:** Press the mode switch button on the underside of the mouse to cycle between Bluetooth 1, Bluetooth 2, and 2.4 GHz modes.

2. Keyboard Functions

The keyboard features a full QWERTZ layout with 110 keys, including a numeric keypad and dedicated function keys.

- **Multimedia Keys:** Use the function keys (F1-F12) in combination with the **Fn** key to access multimedia controls (e.g., volume, play/pause, browser).
- **Browser Buttons:** Dedicated keys for browser functions may be present.



Image: Top-down view of the Rapoo 9390M keyboard and mouse, highlighting the QWERTZ key layout and mouse button configuration.

3. Mouse Functions

The optical mouse features 5 buttons, including a scroll wheel, and adjustable DPI.

- **DPI Adjustment:** The mouse supports a DPI range of up to 2400. A dedicated DPI button (often located near the scroll wheel) allows you to cycle through different sensitivity levels.
- **Ambidextrous Design:** The mouse is designed for comfortable use by both right-handed and left-handed users.

MAINTENANCE

1. Cleaning

To ensure optimal performance and longevity, keep your keyboard and mouse clean.

- Use a soft, lint-free cloth slightly dampened with water or a mild cleaning solution.
- Avoid harsh chemicals, abrasive cleaners, or excessive moisture.
- For the keyboard, use compressed air to remove dust and debris from between the keys.

2. Battery Replacement

When the battery indicator light flashes or performance degrades, it's time to replace the batteries.

- Open the battery compartment on the underside of the keyboard (2x AAA) and mouse (1x AA).
- Remove the old batteries and dispose of them responsibly according to local regulations.
- Insert new alkaline batteries, ensuring correct polarity.
- Close the battery compartment securely.

TROUBLESHOOTING

Connection Issues

- **No connection (2.4 GHz):** Ensure the USB receiver is securely plugged into a working USB port. Try a different USB port. Ensure the keyboard and mouse are powered on.
- **No connection (Bluetooth):** Ensure Bluetooth is enabled on your device. Re-initiate the pairing process as described in the Setup section. Ensure the keyboard/mouse is in Bluetooth mode and not 2.4 GHz mode.
- **Intermittent connection:** Move the devices closer to the receiver/device. Avoid placing the devices near

other wireless interference sources (e.g., Wi-Fi routers, other wireless peripherals).

Input Not Registering / Lag

- **Check batteries:** Low batteries can cause performance issues. Replace them if necessary.
- **Switch modes:** Ensure the keyboard and mouse are set to the correct connection mode (2.4 GHz or Bluetooth) for the device you are using.
- **Restart devices:** Turn off and on the keyboard, mouse, and your computer/device.

SPECIFICATIONS

Feature	Description
Model	9390M
Connectivity	2.4 GHz RF (USB Type-A receiver), Bluetooth 4.0, Bluetooth 5.0
Keyboard Layout	QWERTZ (German)
Keyboard Keys	110 keys, Scissor mechanism, Laser engraved keycaps
Keyboard Features	Multimedia keys, Browser buttons, Ultra-slim design, Aluminum base
Mouse Sensor	Optical
Mouse DPI	Up to 2400 DPI
Mouse Buttons	5 buttons (including scroll wheel)
Mouse Design	Ambidextrous, High-quality plastic
Operating Range	Up to 10 meters
OS Compatibility	Windows XP / Vista / 7 / 8 / 10 / 11
Power Source	Battery powered (Alkaline)
Batteries Included	Yes (2x AAA for keyboard, 1x AA for mouse)
Keyboard Dimensions (W x D x H)	42.6 x 14.3 x 2 cm
Keyboard Weight	409 g
Mouse Dimensions (W x D x H)	6.6 x 10.4 x 3.7 cm
Mouse Weight	60 g

WARRANTY AND SUPPORT

For warranty information and technical support, please refer to the warranty card included in your product packaging or visit the official Rapoo website. Keep your proof of purchase for warranty claims.

