

M328

# Generic Advanced M328 Transistor and Component Tester User Manual

Model: M328

## 1. INTRODUCTION

This manual provides detailed instructions for the operation and maintenance of your Generic Advanced M328 Transistor and Component Tester. This device is designed for automatic identification and testing of various electronic components, including transistors, diodes, resistors, capacitors, and inductors. Its color LCD display and built-in rechargeable battery make it a convenient tool for electronics enthusiasts and professionals.

## 2. SAFETY INFORMATION

Please read and understand all safety instructions before using the device. Failure to follow these instructions may result in electric shock, fire, or damage to the device or other property.

- Do not attempt to test components that are still connected to a live circuit. Always ensure components are fully discharged before testing, especially capacitors.
- Do not open the device casing. There are no user-serviceable parts inside.
- Keep the device away from water, moisture, and extreme temperatures.
- Use only the specified charging cable and power adapter (if included) to charge the built-in battery.
- Dispose of the device and its battery according to local regulations.

## 3. PACKAGE CONTENTS

Verify that all items listed below are present in your package.

# What's in the Box



1 pc


The package includes one M328 Transistor and Component Tester.

- M328 Transistor and Component Tester (1 unit)
- Charging Cable (if applicable, not explicitly listed in product description but implied by 'built-in rechargeable battery')

## 4. PRODUCT OVERVIEW AND FEATURES

The M328 Transistor and Component Tester is designed for ease of use and accurate component identification. Key features include:

# Product Details



Detailed view of the M328 tester's interface, including the ZIF socket and display.

- **Automatic Component Detection:** Automatically identifies components, eliminating manual input and increasing testing speed.
- **Multifunctional Testing:** Tests transistors, diodes, resistors, capacitors, and more, suitable for a variety of applications.
- **Colorful LCD Display:** High-contrast color display makes reading results quick and easy.
- **Easy-to-Use Buttons:** Simple interface with buttons for easy operation, suitable for both beginners and experts.
- **Built-in Rechargeable Battery:** Convenient lithium battery power includes a battery indicator for recharging.

## 5. SETUP

### 5.1 Initial Charging

Before first use, ensure the built-in rechargeable battery is fully charged. Connect the device to a suitable USB power source using the provided charging cable. The battery indicator on the display will show the charging status.

## 5.2 Powering On/Off

To power on the device, press the 'TEST' button. The color LCD display will illuminate. To power off, press the 'OFF' button. The device may also automatically power off after a period of inactivity to conserve battery.

## 6. OPERATING INSTRUCTIONS

---

The M328 tester simplifies component testing with its automatic detection capabilities.



User operating the M328 Transistor and Component Tester to test an electronic component.

### 6.1 Connecting Components

The device features a Zero Insertion Force (ZIF) socket for easy component connection. Identify the pins of your component and insert them into the corresponding numbered slots (1, 2, 3) on the ZIF socket. Ensure the component leads are fully inserted and make good contact. For two-lead components, you can use any two of the three available test points.

### 6.2 Initiating a Test

Once the component is securely inserted, press the 'TEST' button. The device will automatically begin the

testing process. It will identify the component type and measure its parameters.

## 6.3 Reading Results

The test results will be displayed on the color LCD screen. The display will show the component type (e.g., NPN transistor, resistor, capacitor), pinout configuration, and measured values such as resistance, capacitance, inductance, forward voltage drop for diodes, and hFE for transistors.

## 7. MAINTENANCE

---

### 7.1 Cleaning

Wipe the device with a soft, dry cloth. Do not use abrasive cleaners or solvents, as these can damage the casing and screen. Ensure no dust or debris accumulates in the ZIF socket.

### 7.2 Battery Care

To prolong battery life, avoid fully discharging the battery frequently. Recharge the battery when the indicator shows low power. If storing the device for an extended period, charge it to approximately 50% and recharge every few months.

### 7.3 Storage

Store the device in a cool, dry place, away from direct sunlight and extreme temperatures. Keep it in its original packaging or a protective case to prevent damage.

## 8. TROUBLESHOOTING

---

- **Device does not power on:** Ensure the battery is charged. Connect to a power source and try again.
- **No component detected:** Check that the component leads are properly inserted into the ZIF socket and make good contact. Ensure the component is not damaged.
- **Incorrect readings:** Verify the component is fully discharged before testing. Ensure there are no short circuits or loose connections.
- **Screen is blank or flickering:** Recharge the battery. If the issue persists, contact customer support.

## 9. SPECIFICATIONS

---

# Product Dimensions



Image showing the physical dimensions of the M328 Transistor and Component Tester.

| Feature             | Specification                                                                                             |
|---------------------|-----------------------------------------------------------------------------------------------------------|
| Product Dimensions  | 5.51 x 3.15 x 1.18 inches                                                                                 |
| Item Weight         | 4.6 ounces                                                                                                |
| Material            | Acrylonitrile Butadiene Styrene (ABS)                                                                     |
| Color               | Black                                                                                                     |
| Display             | Color LCD                                                                                                 |
| Battery             | Built-in Rechargeable Lithium Battery                                                                     |
| Testable Components | Transistors (NPN, PNP, MOSFET, JFET), Diodes, Dual Diodes, Resistors, Capacitors, Inductors, SCRs, Triacs |

## 10. WARRANTY AND SUPPORT

This product comes with a standard manufacturer's warranty. For specific warranty details, please refer to the product packaging or contact your retailer. For technical support or inquiries, please contact the manufacturer or your point of purchase.

Please retain your proof of purchase for warranty claims.