

[Manuals.plus](#) /

> [AROEVE](#) /

> AROEVE DH-JHD03W Smart HEPA Air Purifier User Manual

AROEVE DH-JHD03W

AROEVE DH-JHD03W Smart HEPA Air Purifier

User Manual

INTRODUCTION

Thank you for choosing the AROEVE DH-JHD03W Smart HEPA Air Purifier. This device is designed to improve your indoor air quality by effectively removing various airborne particles. Please read this manual thoroughly before operating the appliance and retain it for future reference.



The AROEVE DH-JHD03W Air Purifier effectively cleans air in large spaces, providing fresh air for your home.

SAFETY INSTRUCTIONS

To reduce the risk of fire, electric shock, or injury, please follow these safety precautions:

- Always unplug the air purifier before moving it, opening the grille, changing filters, or performing any cleaning.
- Do not operate the unit if the power cord or plug is damaged. Contact customer support for assistance.
- Keep the air purifier away from water or other liquids. Do not use it in wet environments like bathrooms.
- Do not insert fingers or foreign objects into the air inlets or outlets.
- Ensure the air purifier is placed on a stable, level surface.
- This appliance is not intended for use by persons (including children) with reduced physical, sensory, or mental capabilities, or lack of experience and knowledge, unless they have been given supervision or instruction concerning use of the appliance by a person responsible for their safety.
- Children should be supervised to ensure they do not play with the appliance.
- The device features a child lock function to prevent accidental changes to settings.

Custodire ogni respiro

Ogni respiro è protetto con cura mentre il nostro purificatore filtra silenziosamente polvere, allergeni e odori quotidiani



Blocco bambini



The child lock feature helps maintain settings and ensures safe operation around children.

PRODUCT OVERVIEW

Components

- Air Purifier Unit
- 4-in-1 HEPA Filter (pre-installed)
- Power Adapter

- User Manual

Control Panel

The control panel is located on the top of the unit and features touch-sensitive buttons and indicators for various functions.

- **Power Button:** Turns the unit on/off.
- **Fan Speed Button:** Adjusts fan speed (Low, Medium, High, Auto).
- **Mode Button:** Selects operating modes (Auto, Sleep).
- **Timer Button:** Sets operating duration (1-24 hours).
- **Aromatherapy Button:** Activates/deactivates the aromatherapy function.
- **Child Lock Button:** Locks/unlocks the control panel.
- **Filter Reset Indicator:** Lights up when filter replacement is needed.
- **Air Quality Indicator:** Displays current air quality (color-coded).

SETUP

1. **Unpack:** Carefully remove the air purifier from its packaging.
2. **Filter Installation:** The 4-in-1 HEPA filter comes pre-installed. Before first use, open the bottom cover, remove the plastic packaging from the filter, and then reinsert the filter and close the cover securely.
3. **Placement:** Place the air purifier on a firm, level surface. Ensure there is at least 30 cm (12 inches) of clear space around all sides for optimal air circulation.
4. **Power Connection:** Plug the power adapter into a standard electrical outlet.

OPERATING INSTRUCTIONS

Turning On/Off

Press the Power Button to turn the air purifier on or off.

Adjusting Fan Speed

Press the Fan Speed Button repeatedly to cycle through Low, Medium, High, and Auto fan speeds.

Auto Mode and Air Quality Indicator

In Auto Mode, the built-in laser sensor detects air quality and automatically adjusts the fan speed. The Air Quality Indicator light changes color to reflect the current air quality:

- **Blue:** Excellent Air Quality
- **Green:** Good Air Quality
- **Yellow:** Moderate Air Quality
- **Red:** Poor Air Quality

Respira la purezza ad ogni respiro

Il display digitale e le luci delicate ti permettono di apprezzare senza sforzo la freschezza e la limpidezza dell'aria



The air purifier automatically adjusts its operation based on detected air quality, indicated by the color display.

Night Mode

Press the Mode Button to activate Night Mode. In this mode, the fan operates at its lowest speed (25 dB) and the display lights are dimmed or turned off to ensure an undisturbed sleep environment.

Riposa sereno, respira liberamente

Luci spente, rumore ridotto – goditi l'aria pulita senza disturbare il tuo sonno



Enjoy quiet operation in Night Mode, with noise levels as low as 25 dB, perfect for bedrooms.

Timer Function

Press the Timer Button to set the operating time for 1 to 24 hours. The unit will automatically turn off once the set time expires.

Aromatherapy Function

The air purifier includes a dedicated pad for essential oils. Add a few drops of water-soluble essential oil to the pad to diffuse a pleasant fragrance into your room.

Vivi la vita con la tua fragranza distintiva

Trasforma ogni momento in un rituale rilassante, donando comfort e carattere al tuo ambiente



Utilize the integrated aromatherapy function by adding essential oils to the dedicated pad.

Smart Control (App & Voice)

The AROEVE DH-JHD03W can be controlled via a smartphone app and voice assistants like Amazon Alexa and Google Assistant. Download the companion app from the App Store or Google Play to:

- Set schedules for operation.
- Control the unit remotely.
- Monitor filter lifespan.
- Use voice commands for hands-free control.

Controllo Intelligente, Cambia come Preferisci



Impostare orari




Timer da 1 a 24 ore



Controllare la durata del filtro



Controllo vocale



Control your air purifier conveniently through the dedicated app, offering scheduling, timer, and filter monitoring features.

Controllo Vocale, in Qualsiasi Momento

"Alexa, accendi il purificatore d'aria"



Integrate with smart home systems for voice control, such as 'Alexa, turn on the air purifier'.

MAINTENANCE

Filter Replacement

The Filter Reset Indicator will illuminate when it's time to replace the filter. The filter typically lasts 6-8 months, depending on usage and air quality.

1. Unplug the air purifier from the power outlet.
2. Turn the unit upside down and twist the bottom cover counter-clockwise to unlock and remove it.

3. Remove the old 4-in-1 HEPA filter.
4. Insert a new AROEVE replacement filter (Model: DH-JHD03W-Filter) into the unit.
5. Replace the bottom cover and twist clockwise to lock it.
6. Plug the air purifier back in.
7. Press and hold the Filter Reset Button (usually the Power Button or a dedicated button, refer to control panel diagram) for 3-5 seconds until the indicator light turns off.

Filtrazione Potente a 4 Strati

99.97%
Tasso di Filtrazione

H13 HEPA
Filtro

Filtrazione HEPA H13
Cattura il 99,97% delle particelle microscopiche fino a 0,3µm, inclusi polvere fine, polline, particelle di fumo e peli di animali

Strato di Filtrazione Rinforzato
Filtra particelle medie come polvere fine, peli di animali e pollini più grandi

Prefiltro
Cattura particelle grandi come polvere, fibre, lanugine, capelli e peli di animali

Filtro a Carboni Attivi
Assorbe fumo, vapori, VOC, odori di animali domestici e odori di cucina

The 4-in-1 HEPA filter system includes a pre-filter, reinforced filter, H13 HEPA filter, and activated carbon filter for comprehensive air purification.



Ensure to use genuine AROEVE replacement filters for optimal performance.

Cleaning the Air Purifier

- Wipe the exterior of the unit with a soft, dry cloth.
- Do not use abrasive cleaners or solvents.
- Clean the air inlet and outlet vents with a soft brush or vacuum cleaner attachment to remove dust buildup.

TROUBLESHOOTING

Problem	Possible Cause	Solution
Unit does not turn on	Not plugged in; Power outlet malfunction; Damaged power cord; Filter not installed correctly.	Ensure power cord is securely plugged in; Try a different outlet; Contact customer support if cord is damaged; Check filter installation and remove plastic packaging.
Weak airflow	Filter is dirty or clogged; Air inlets/outlets are blocked.	Replace the filter; Clear any obstructions from air inlets/outlets.
Unusual noise	Unit not on a level surface; Foreign object inside; Filter not installed correctly.	Place on a flat surface; Unplug and check for foreign objects; Reinstall filter.
Air quality indicator always red/yellow	High pollution levels; Sensor is dirty.	Allow more time for purification; Clean the air quality sensor (refer to specific instructions in the full manual if available).
Aromatherapy not working	No essential oil added; Oil not water-soluble.	Add water-soluble essential oil to the pad; Ensure the aromatherapy function is activated.

SPECIFICATIONS

- **Brand:** AROEVE
- **Model Number:** DH-JHD03W
- **Dimensions (D x W x H):** 23.8 cm x 40.9 cm x 23.8 cm
- **Item Weight:** 2.89 Kilograms

- **Power Source:** Wired Electric
- **Rated Wattage:** 5 Watts
- **Coverage Area:** Up to 120 m²
- **CADR (Clean Air Delivery Rate):** 300 m³/h
- **Filter Type:** 4-in-1 HEPA (H13 Grade)
- **Noise Level:** 25 dB (Night Mode)
- **Control Method:** Touch Panel, App (Smart Control), Voice (Amazon Alexa, Google Assistant)
- **Contaminant Filtration:** Pollen, Dust, Pet Dander, Smoke, VOCs
- **Special Features:** Aromatherapy Function, Automatic Air Quality Detection, Ultra-Quiet Sleep Mode, Child Lock, Timer
- **UPC:** 850070209502
- **Manufacturer:** ANTADI
- **Country of Origin:** China

WARRANTY AND SUPPORT

AROEVE products are manufactured to high-quality standards. For warranty information, technical support, or customer service inquiries, please refer to the contact details provided on the product packaging or the official AROEVE website. Please have your model number (DH-JHD03W) and purchase information ready when contacting support.