

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

[manuals.plus](#) /

› [BrosTrend](#) /

› [BrosTrend AX900 USB WiFi 6 and Bluetooth 5.4 Adapter Instruction Manual](#)

BrosTrend AX900 WiFi 6 and Bluetooth USB Adapter

BrosTrend AX900 USB WiFi 6 and Bluetooth 5.4 Adapter Instruction Manual

MODEL: AX900 WiFi 6 AND BLUETOOTH USB ADAPTER

Brand: BrosTrend

PRODUCT OVERVIEW

The BrosTrend AX900 is a versatile 2-in-1 USB adapter designed to upgrade your PC with both WiFi 6 and Bluetooth 5.4 capabilities. This compact dongle eliminates the need for multiple adapters, providing fast internet connectivity and seamless Bluetooth device pairing. It supports dual-band WiFi 6 for optimal performance and includes a pre-loaded driver for easy installation on Windows 10 and Windows 11 systems.



Image: BrosTrend AX900 USB WiFi 6 and Bluetooth 5.4 Adapter, front view.

Key Features:

- **2-in-1 Functionality:** Integrates WiFi 6 and Bluetooth 5.4 into a single USB adapter.
- **Fast Dual-Band WiFi 6:** Achieves speeds up to 600 Mbps on 5 GHz and 287 Mbps on 2.4 GHz, supporting 1024-QAM and OFDMA for smooth streaming and gaming.
- **Bluetooth 5.4:** Connects up to 5 Bluetooth devices (headphones, mouse, keyboard, speaker, printer) with a stable range of up to 32 feet.

- **Easy Setup:** Features a pre-loaded driver for quick installation on Windows 11/10 without requiring a CD or downloads.
- **Compact Design:** Small form factor (2.04 x 0.78 x 0.35 inches) with dual-side vent holes for efficient heat dissipation and long-term reliability.

Your browser does not support the video tag.

Video: An overview of the BrosTrend AX900 USB WiFi 6 and Bluetooth 5.4 Combo Adapter, highlighting its features and benefits.

SETUP INSTRUCTIONS

Before You Start: Disable Built-in Bluetooth (If Applicable)

If your PC already has a built-in Bluetooth adapter, it is recommended to disable it first in Device Manager. This ensures that your system exclusively uses the BrosTrend adapter for Bluetooth connections, preventing potential conflicts.

1. Right-click on "This PC" icon on your desktop.
2. Select "Manage" or "Show more options" then "Manage".
3. In the Computer Management window, navigate to "Device Manager".
4. Expand the "Bluetooth" section.
5. Right-click on your existing Bluetooth adapter (e.g., "Realtek Bluetooth Adapter") and select "Disable device".
Confirm by clicking "Yes".

Your browser does not support the video tag.

Video: A step-by-step guide on how to set up the BrosTrend AX900 USB WiFi 6 and Bluetooth 5.4 Adapter, including disabling existing Bluetooth adapters and driver installation.

Step 1: Connect the Adapter

Insert the BrosTrend AX900 USB WiFi 6 and Bluetooth 5.4 Adapter into an available USB port on your desktop or laptop computer. The adapter is designed to be compact and will not obstruct adjacent ports.

Quick Initial Setup with Pre-Loaded Driver

The adapter includes a pre-loaded driver—no CD or downloads needed.

Windows 11

Windows 10



Image: The BrosTrend AX900 USB adapter being inserted into a USB port on a desktop computer, illustrating its compact size and ease of connection.

Step 2: Install the Driver

The driver software is pre-loaded directly onto the adapter, eliminating the need for a CD-ROM or external downloads. Once the adapter is inserted, a pop-up notification should appear at the bottom right corner of your screen.

1. Click on the pop-up notification to run the pre-loaded driver installer (e.g., "BrosTrend_WiFi_Bluetooth_Setup.exe").

2. Follow the on-screen prompts to complete the installation.
3. If the pop-up does not appear, open "This PC" (or "My Computer") to locate the "CD Drive (E:) BrosTrend Setup" and double-click to run the driver installer.
4. After successful installation, restart your computer to apply the changes.

OPERATING INSTRUCTIONS

Step 3: Connect to WiFi and Bluetooth

After installing the driver and restarting your computer, you can now connect to WiFi networks and pair Bluetooth devices.

Connecting to WiFi:

1. Click the network icon (usually a globe or WiFi symbol) on the taskbar.
2. Select the desired WiFi network from the list (e.g., "MyWiFi_5GHz" or "MyWiFi_2.4GHz").
3. Click "Connect" and enter the WiFi password if prompted.
4. For best performance, connect your PC to the 5 GHz WiFi band to avoid congestion caused by Bluetooth and WiFi sharing the 2.4 GHz channel.

Fast Dual-Band WiFi 6



Image: A laptop displaying WiFi connectivity, indicating the BrosTrend AX900 adapter is providing fast dual-band WiFi 6 speeds.

Connecting Bluetooth Devices:

1. Right-click the Bluetooth icon on the taskbar (or go to Settings > Bluetooth & devices).
2. Select "Add a Bluetooth Device" or "Add device".
3. Choose "Bluetooth" from the options.
4. Ensure your Bluetooth device is in pairing mode.

5. Select your device from the list and follow any on-screen instructions to complete pairing.

Bluetooth 5.4 Smooth, Lag-Free Connection

Instant Pairing for Headphones, Mouse, Keyboard & More



Note: If your PC has a built-in Bluetooth adapter, disable it in Device Manager to ensure the system uses the BrosTrend adapter for Bluetooth connections.

Image: A laptop with the BrosTrend AX900 adapter connected, showing various Bluetooth devices like headphones, mouse, and keyboard, indicating smooth and lag-free connections.

MAINTENANCE

The BrosTrend AX900 adapter requires minimal maintenance. Keep the device clean and free from dust. Ensure it is not

exposed to extreme temperatures or moisture. Periodically check for driver updates on the BrosTrend official website to ensure optimal performance and compatibility.

TROUBLESHOOTING

- **Adapter Not Recognized:** Try plugging the adapter into a different USB port. Ensure your computer's USB drivers are up to date.
- **WiFi Connection Issues:** Verify that your WiFi network is active and you are entering the correct password. Ensure any built-in WiFi adapters are disabled to prevent conflicts.
- **Bluetooth Pairing Problems:** Confirm that your Bluetooth device is in pairing mode and within range (up to 32 feet). Ensure any built-in Bluetooth adapters are disabled. Restart both your computer and the Bluetooth device.
- **Slow Speeds:** For optimal WiFi performance, connect to a WiFi 6 router and use the 5 GHz band. Ensure there are no physical obstructions or interference sources between the adapter and your router/Bluetooth devices.
- **Driver Installation Failure:** If the pre-loaded driver does not install automatically, manually navigate to "This PC" and run the installer from the virtual CD drive. If issues persist, download the latest driver from the BrosTrend website.

SPECIFICATIONS

Feature	Detail
Model Number	AX900 WiFi 6 and Bluetooth USB Adapter
Product Dimensions	2.04" L x 0.78" W x 0.35" H (5.2 x 2 x 0.9 cm)
Item Weight	0.229 ounces (6.5 Grams)
Hardware Interface	USB 2.0
Data Link Protocol	IEEE802.11ax/ac/n/a 5 GHz, IEEE802.11ax/b/g/n 2.4GHz
Data Transfer Rate	Up to 900 Megabits Per Second (600 Mbps on 5GHz, 287 Mbps on 2.4GHz)
Compatible Operating System	Windows 10, Windows 11 (Mac and Linux NOT supported)
Bluetooth Version	Bluetooth 5.4
Color	Black

WHAT'S IN THE BOX

- 1 x AX900 WiFi 6 and Bluetooth 5.4 Combo USB Adapter
- 1 x Quick Installation Guide

WARRANTY AND SUPPORT

For warranty information and technical support, please refer to the Quick Installation Guide included in the package or visit the official BrosTrend website. If you require assistance, you can send an email to BrosTrend's support team, and they typically respond within 24 hours.

The product is also "Verified by Transparency," meaning each item has a unique code for authenticity verification using the Amazon Shopping app.

