

[Manuals.plus](#) /

› [ALTOUMAN](#) /

› ALTOUMAN Wireless Dog Fence and Training Collar Instruction Manual

ALTOUMAN B0FHW8NZLS

ALTOUMAN Wireless Dog Fence and Training Collar Instruction Manual

Model: B0FHW8NZLS

Brand: ALTOUMAN

1. INTRODUCTION AND OVERVIEW

This manual provides detailed instructions for the ALTOUMAN Wireless Dog Fence and Training Collar. This 2-in-1 system combines a wireless pet containment solution with a remote training collar, designed to help manage your dog's outdoor activities and reinforce desired behaviors. The system offers adjustable boundary settings and multiple training modes to suit various dog temperaments and environments.



Image 1.1: Overview of the ALTOUMAN Wireless Dog Fence and Training Collar system, showing the remote, collar, and a dog.

2. PRODUCT COMPONENTS

The ALTOUMAN Wireless Dog Fence and Training Collar system includes the following items:

- Remote Transmitter: Used to control the training modes and set the wireless fence boundary.
- Receiver Collar: Worn by the dog, it receives signals from the transmitter and delivers corrections.
- Adjustable Collar Strap: For securing the receiver to your dog.
- Charging Cables: For recharging both the remote and the collar.
- Test Light: For verifying the static correction function.
- Contact Points (Short & Long): For different coat lengths.
- Silicone Covers: For comfort and protection over contact points.

Wireless Dog Fence



No App



No Subscription



No SD



No Dig



No Wires



Adjustable range from
30FT-1300FT



When the dog crosses the set area, automatically trigger beep and vibration warnings.



Image 2.1: Visual representation of the wireless fence system in operation, showing the adjustable range from 30ft to 1300ft.

3. SETUP GUIDE

3.1 Charging the Devices

Before initial use, fully charge both the remote transmitter and the receiver collar. A full charge typically takes approximately 2 hours. The remote offers up to 185 hours of standby time, and the collar provides up to 180 hours.

IPX7 Waterproof Collar

Note: The remote is Not waterproof.



Image 3.1: The remote and collar connected to a Type-C charging port, highlighting fast charging and long battery life.

3.2 Fitting the Receiver Collar

1. Select appropriate contact points (short for thin hair, long for thick hair) and attach them to the receiver. Optionally, place silicone covers over the contact points for added comfort.
2. Place the receiver collar around your dog's neck. Ensure the contact points touch the skin.
3. Adjust the strap for a snug fit. You should be able to fit one or two fingers comfortably between the collar and your dog's neck. The collar is adjustable up to 23.6 inches and suitable for dogs weighing 8-110 lbs. Excess strap can be trimmed and sealed with a lighter to prevent fraying.

Adjustable Fit & Easy to Clean



Image 3.2: The adjustable collar shown with different dog sizes, demonstrating its versatility for various breeds and weights.

3.3 Powering On and Pairing

To power on the transmitter and receiver collar, press and hold their respective power buttons. The devices should automatically pair. If not, refer to the detailed pairing instructions in the full user manual.

3.4 Setting the Wireless Fence Boundary

The system allows you to set a circular boundary from 30 to 1300 feet (10 adjustable levels). Position the transmitter in a central location within the desired containment area. Adjust the distance level on the remote to define the perimeter. When your dog approaches or crosses this boundary, the collar will activate warnings.

4. OPERATING INSTRUCTIONS

4.1 Training Modes

The training collar features three modes: Beep, Vibration, and Safety Static. Each mode can be adjusted in intensity:

- **Beep:** An audible warning sound.
- **Vibration:** Adjustable from levels 0-9.
- **Safety Static:** Adjustable from levels 0-10.

It is recommended to begin training with the lowest intensity level and gradually increase it as needed, observing your dog's response. The advanced smart chip ensures a rapid 1-second response for effective training.

Image 4.1: The three effective training modes (Beep, Safe Shock, Vibration) available with the collar.

4.2 Wireless Fence Operation

Once the boundary is set, the system automatically monitors your dog's position. If your dog approaches the set perimeter, the collar will issue a warning (beep, vibration, or static correction) to encourage them to return to the safe zone. This system operates without the need for physical wires or complex installation.

4.3 Flashlight Function

The remote features a dual-function flashlight:

- Press once for a bright white constant beam, useful for general visibility.

- Press twice to activate an attention-getting flashing strobe mode, making your dog easier to spot from a distance, especially in low light conditions.

Fast Charge & Long Lasting



2 Hour
Quick Charge



180 Days
Standby Time

Type-c Charging Port

Easy Charging by Your Power Bank/
Car charger/Laptop/Adapter



Image 4.2: The remote's security lock feature and LED flashlight modes for enhanced safety and visibility.

4.4 Keypad Lock

The remote includes an innovative keypad lock feature to prevent accidental button presses during training sessions, ensuring consistent and controlled operation.

5. MAINTENANCE

5.1 Waterproofing

The receiver collar is IPX7 waterproof, meaning it can withstand rain, splashes, and even accidental submersion. This allows your dog to play freely in various weather conditions. **Note: The remote transmitter is NOT waterproof.**

Security Lock & LED light

Less Accidental Shock



Image 5.1: The IPX7 waterproof collar in action, demonstrating its durability in wet environments.

5.2 Cleaning

Regularly clean the collar and contact points to ensure proper function and hygiene. Remove the receiver from the collar strap for thorough cleaning. Use a damp cloth to wipe down the components. Ensure all parts are dry before reassembly.

5.3 Battery Care

To prolong battery life, avoid extreme temperatures and store the devices in a cool, dry place when not in use. Recharge the devices as needed, typically every few days depending on usage.

6. TROUBLESHOOTING

6.1 Signal Interference

Environmental factors such as large metal objects, dense foliage, or uneven terrain can affect the wireless signal. Ensure the transmitter is placed in an open area, away from obstructions, for optimal performance. The twisted

wires in the system are designed to minimize signal interference, but significant environmental factors can still impact range and consistency.

Your browser does not support the video tag.

Video 6.1: Demonstrates how to test the transmitter and receiver collar, including connecting the boundary wire and verifying the shock mode with a test light. It also illustrates how twisted wires prevent signal interference.

6.2 Collar Not Responding

- Check if both the remote and collar are powered on and fully charged.
- Ensure the devices are properly paired. Refer to the pairing section if necessary.
- Verify that the dog is within the set wireless fence boundary.
- Inspect contact points for proper placement and ensure they are making good contact with the dog's skin.

6.3 Inconsistent Boundary

If the boundary seems inconsistent, try repositioning the transmitter to a more open, central location. Avoid placing it near large metal structures or dense walls that could block the signal. Test the boundary thoroughly before allowing your dog unsupervised access.

7. SPECIFICATIONS

Feature	Detail
Model Number	B0FHW8NZLS
Wireless Fence Range	30 - 1300 feet (10 adjustable levels)
Training Modes	Beep, Vibration (0-9 levels), Safety Static (0-10 levels)
Collar Waterproof Rating	IPX7
Remote Standby Time	185 hours
Collar Standby Time	180 hours
Charging Time	Approximately 2 hours
Adjustable Collar Size	Up to 23.6 inches
Recommended Dog Weight	8 - 110 lbs
Manufacturer	Shenzhen Jingtong Technology Co.,Ltd
UPC	739768930525

8. WARRANTY AND SUPPORT

ALTOUMAN offers a Free Warranty Promise for this product. For any inquiries, technical assistance, or warranty claims, please contact our customer support. We provide 24-hour online customer support and 365 days of after-sale service to ensure your satisfaction.

For further assistance, please refer to the contact information provided with your product packaging or visit the official ALTOUMAN website.

© 2025 ALTOUMAN. All rights reserved.