Saved from manuals.plus.
Open the live page for links to other documents and user manuals.

wolf guard WT4F

Wolf Guard WT4F Smart Home Security Alarm System User Manual

Model: WT4F

1. Introduction

The Wolf Guard WT4F is an advanced smart home security alarm system designed to protect your property. Featuring a 7-inch capacitive touchscreen, dual Wi-Fi/4G network connectivity, and integration with the Tuya Smart Life app, this system offers comprehensive security with remote control capabilities. It supports a wide range of wireless and wired zones, providing flexible protection for various environments.

2. Package Contents

Verify that all items are present in the package:

- Main Control Module with 7" Touchscreen
- 4 x Door/Window Sensors
- 4 x PIR Motion Sensors
- 2 x Remote Controls
- 1 x USB Cable
- 2 x Power Adapters
- Mounting Accessories / Small Screwdriver
- 1 x Wolf Guard Window Sticker
- Quick Start Guide



Image: Wolf Guard WT4F control panel with 7-inch touchscreen display.

3. Product Overview

The WT4F system features a 7-inch RGB capacitive touchscreen for intuitive operation. It utilizes a dual Wi-Fi/4G network for reliable communication, sending notifications via app, SMS, or phone calls. The system supports up to 100 wireless zones and 6 wired zones, each customizable. A built-in backup battery ensures continuous operation during power outages. An integrated RF transmitter allows for expansion with wireless sirens.



Image: Wolf Guard WT4F security system components including control panel, wireless siren, motion detectors, door/window sensors, RFID tags, and remote controls.

4. Setup

The Wolf Guard WT4F alarm kit is designed for easy do-it-yourself installation. No professional technician is required. Follow the provided quick start guides for a straightforward setup process.

4.1 Initial Installation

1. **Power Connection:** Connect the main control module to a power source using the provided power adapter.
2. **SIM Card Insertion (Optional):** If using 4G functionality, insert a 4G SIM card into the designated slot on the main module.
3. **Sensor Placement:** Install door/window sensors on desired entry points and PIR motion sensors in areas requiring detection. Ensure sensors are within range of the main panel.
4. **Pairing Devices:** Follow the on-screen instructions on the 7-inch touchscreen or refer to the quick start guide to pair all wireless sensors and remote controls with the main panel.



Image: Person installing a Wolf Guard WT4F motion sensor on a wall.

4.2 App Configuration (Tuya Smart Life)

For remote control and monitoring, download the "Tuya Smart Life" app from your smartphone's app store (Android/iOS). Register an account and follow the in-app instructions to add your WT4F alarm system. This enables remote arming/disarming, real-time monitoring, and receiving notifications.

5. Operating Instructions

5.1 Arming and Disarming the System

- **Via Touchscreen:** Enter your PIN on the 7-inch touchscreen and select the desired arming mode (Away, Home, Disarm).
- **Via Remote Control:** Use the dedicated buttons on the remote control to arm (Away/Home) or disarm the system.
- **Via Tuya Smart Life App:**Open the app on your smartphone and select the desired arming mode.
- **Via Voice Assistant:** Integrate with Amazon Alexa or Google Assistant to arm or disarm the system using voice

commands (e.g., "Alexa, arm security system").



Image: Wolf Guard WT4F system controlled via Smart Life mobile application, showing arm/disarm options.



Image: Wolf Guard WT4F system integrating with Amazon Alexa and Google Assistant for voice control.

5.2 Alarm Notifications

In case of an alarm trigger, the system will:

- Sound the integrated siren (110dB).
- Send push notifications to the Tuya Smart Life app.
- Send SMS messages to pre-configured phone numbers.
- Initiate phone calls to pre-configured phone numbers.



Image: Wolf Guard WT4F system providing 24/7 home security, showing an intruder being detected.



Image: Wolf Guard WT4F outdoor siren with 110dB sound volume, suitable for indoor and outdoor use, featuring a backup battery.

5.3 Zone Management

The system supports various zone types:

- **24-Hour Zone:** Always active, triggers an alarm immediately.
- **Normal Zone:** Active when the system is armed (Away or Home).
- **Home Zone:** Active when the system is armed in "Home" mode, typically bypassing interior sensors.
- **Delay Zone:** Provides an entry/exit delay before triggering an alarm.

5.4 Multi-Language Support

The WT4F system supports multiple languages for user interface and notifications, including English, French, German, Spanish, Italian, Portuguese, Russian, Dutch, Polish, and Chinese.



Image: Wolf Guard WT4F system supporting multiple languages, including English, French, German, Spanish, Italian, Portuguese, Russian, Dutch, Polish, and Chinese.

6. Maintenance

- **Battery Backup:** The main control module includes a built-in lithium-ion backup battery. This battery automatically activates during a power outage, ensuring continuous operation of the alarm system. Ensure the system is regularly connected to power to keep the backup battery charged.
- **Sensor Batteries:** Periodically check the batteries in your wireless sensors. Replace them as needed to ensure optimal performance. The system may provide low battery alerts.
- **Cleaning:** Clean the touchscreen and sensor surfaces with a soft, dry cloth. Avoid abrasive cleaners or solvents.

7. Troubleshooting

If you encounter issues with your Wolf Guard WT4F system, consider the following:

- **No Power:** Check the power adapter connection and ensure the outlet is functional. If the backup battery is depleted, allow time for it to charge.
- **Sensor Not Triggering:** Verify the sensor's battery level and ensure it is properly paired with the main panel. Check

for obstructions or incorrect placement.

- **No App Notifications:** Ensure your main panel is connected to Wi-Fi or has a working 4G SIM card. Check your smartphone's notification settings for the Tuya Smart Life app.
- **Remote Control Not Working:** Replace the remote control's battery. Re-pair the remote if necessary.
- **False Alarms:** Review sensor placement and sensitivity settings. Ensure pets or environmental factors are not triggering motion sensors.

For further assistance, refer to the detailed user manual or contact Wolf Guard customer support.

8. Specifications

Feature	Specification
Model Number	WT4F
Brand	Wolf Guard
Color	White
Power Source	Electric Cable
Compatible Devices	Smartphone
Item Dimensions (L x W x H)	18.3 x 13.5 x 2.1 cm
Video Recording Resolution	1080p (*Note: This refers to compatible camera resolution, not the panel itself*)
Connectivity Technology	Wireless (Wi-Fi, 4G)
Installation Type	DIY
Alert Type	SMS, Phone Call, Mobile App
Item Weight	1850 Grams
Control Method	Application, Touchscreen, Remote Control
Maximum Range	100 Meters
Noise Level (Siren)	110 Decibels
Sensor Technology	PIR
Recommended Uses	Home Security, Office Security, Warehouse Security
Battery Type	Lithium-ion (Backup)

9. Warranty and Support

Specific warranty details for the Wolf Guard WT4F system are typically provided at the point of purchase or within the product packaging. Please refer to your purchase documentation for warranty terms and conditions.
For technical support, product inquiries, or assistance with troubleshooting, please contact Wolf Guard customer service through their official website or the contact information provided in your product documentation.

© 2024 Wolf Guard. All rights reserved.

Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

Open the live page

https://manuals.plus/asin/B0FL2KLCCG

More documents and user manuals: **https://manuals.plus/**