



[Manuals.plus](#) /

> [SLuB](#) /

> SLuB 6800mAh MagSafe Wireless Power Bank (Model CW12) User Manual

## SLuB CW12

# SLuB 6800mAh MagSafe Wireless Power Bank (Model CW12) User Manual

Model: CW12

## INTRODUCTION

Thank you for purchasing the SLuB 6800mAh MagSafe Wireless Power Bank. This manual provides important information on how to safely and effectively use your device. Please read it thoroughly before use and keep it for future reference.



# ワイヤレス充電 モバイルバッテリー

ケーブル不要、ワイヤレス充電で快適に。



## 6800mAh

大容量 | 超小型 | 高速充電

磁気  
吸着

Image: The SLuB 6800mAh MagSafe Wireless Power Bank, showcasing its compact design and wireless charging capability. The image highlights the purple color variant.

## PRODUCT OVERVIEW

### Key Features

- **MagSafe Compatibility:** Strong magnetic attachment for secure wireless charging with iPhone 12 series and newer.
- **Dual Charging Modes:** Supports both 15W wireless charging and 20W wired (Type-C) fast charging.
- **Simultaneous Charging:** Capable of charging two devices concurrently (one wirelessly, one via Type-C).
- **High Capacity:** 6800mAh battery provides approximately 1.6 charges for an iPhone 17 or 1.5 charges for a Galaxy S25.
- **Compact & Lightweight:** Measures 10.2 x 6.35 x 1 cm and weighs only 116g for easy portability.
- **Integrated Cable/Strap:** A detachable USB-C to USB-C cable that also functions as a convenient carrying strap.
- **LED Power Indicator:** 5-stage LED lights clearly display remaining battery level.
- **Multiple Safety Protections:** PSE certified with safeguards against overcharge, over-discharge, overcurrent, short circuit, high temperature, and surge.
- **Airline Approved:** Meets international aviation standards for safe travel.

磁着バッテリー  
いつでも瞬時に充電

コンパクトで、充電切れなし  
6800mAh [CWI2]

6800 MAH  
大容量 × 機内OK

充電ストラップ  
Type-Cケーブルが  
ストラップに早変わり

残量表示  
充電が見える

Magnetic Wireless Power Bank  
磁気吸着ワイヤレス充電  
モバイルバッテリー

クオリティ4色  
鮮やかなミニマル

磁気吸着デザイン  
在宅ワークの必須アイテム

Image: A visual representation of the strong magnetic attraction feature, ensuring a secure connection for MagSafe-compatible devices.

## SETUP

### Initial Charging of the Power Bank

1. Connect the included USB-C to USB-C cable to the power bank's Type-C port.
2. Connect the other end of the cable to a compatible USB power adapter (not included).
3. The LED indicators will light up to show the charging status. All five LEDs will be solid when fully charged.

It is recommended to fully charge the power bank before its first use.





## ▲ 注意事項

- 1、長期間使用しない場合でも、3ヶ月ごとに1回充電してください。
- 2、使用中、軽い発熱がある場合があります。
- 3、乾燥した場所で保管し、化学洗剤は使用しないでください。
- 4、使用後は家庭ゴミとして捨てず、リサイクル協力店が設置されている「リサイクルBOX」に入れてください。
- 5、子供に単独で使用させないでください。
- 6、不正操作や分解・改造による故障・トラブルには責任を負いません。
- 7、スマホやデジタル端末を充電する前に、互換性を確認してください。

不適切な出力や入力には故障や発火の原因になります。

Image: The power bank and its accessories, including the USB-C cable, illustrating the components provided in the package.

## OPERATING INSTRUCTIONS

---

### Wireless Charging (MagSafe Compatible)

1. Ensure the power bank has sufficient charge.
2. Align your MagSafe-compatible device (e.g., iPhone 12 series or newer) with the magnetic charging area on the power bank. The magnets will automatically snap into place.
3. Charging will begin automatically. The LED indicators on the power bank will show its remaining charge.
4. To stop charging, simply detach your device from the power bank.

**Note:** Using a metal case or a thick protective case on your device may reduce charging efficiency or prevent charging. Remove such cases for optimal performance.

# ワイヤレス充電 便利さの新時代

## ▶ 磁気吸着

磁気吸着で充電宝とデバイスが一体化し、手を解放。  
使用中も滑ったり外れたりしません。

## ▶ ワイヤレス充電技術

テクノロジーの便利さを実感し、  
すべてのiPhoneシリーズに対応。

※ 注意：金属製のケースや厚い保護  
ケースを使うと、充電効率が落ち、  
充電できないことがあります。



## 2つの高速充電方法

ワイヤレス出力

最大  
**15W**

Type-C出力

最大  
**20W**



ワイヤレス充電



Type-C出力



※ 異なるスマートフォンでは、充電速度が異なる場合があります。  
上記のデータは参考値としてご利用ください。

## Wired Charging (Type-C)

1. Ensure the power bank has sufficient charge.
2. Connect your device to the power bank's Type-C port using a compatible USB-C to USB-C cable (included) or another appropriate cable for your device.
3. Charging will begin automatically. The LED indicators on the power bank will show its remaining charge.
4. Disconnect the cable from your device and the power bank when charging is complete.

All you need for travel charging

### 旅の充電、これひとつで十分

MagSafe対応・Type-C急速充電・モバイルバッテリー3in1の超万能デザイン  
ビジネス出張にも、日常の通勤にも、アウトドアの緊急時にも  
—これ1台で手軽に移動、面倒な準備はもう不要!

**充電ストラップ**

Type-Cケーブルが  
ストラップに早変わり



・パープル / Purple

・ブルー / Blue

グリーン / Green

・ホワイト / White

Image: The power bank simultaneously charging two devices, one wirelessly and one through its Type-C port, highlighting its dual-charging capability.

## Checking Battery Level

The power bank features five LED indicators to show the remaining battery capacity:

- 1 LED: 1% - 20%
- 2 LEDs: 21% - 40%
- 3 LEDs: 41% - 60%
- 4 LEDs: 61% - 80%
- 5 LEDs: 81% - 100%



## SPECIFICATIONS

<b>Model Number</b>	CW12
<b>Battery Capacity</b>	6800mAh (3.85V 26.18Wh)
<b>Type-C Input</b>	5V/3A, 9V/2A, 12V/1.5A
<b>Type-C Output</b>	5V/3A, 9V/2.22A, 12V/1.67A
<b>Wireless Output</b>	Max 15W
<b>Battery Type</b>	Polymer Battery
<b>Dimensions (L x W x H)</b>	10.2 x 6.4 x 1 cm
<b>Weight</b>	116g
<b>Operating Temperature</b>	-10°C to 40°C

# 機内持ち込み OK!

## 航空基準を満たす

- ✓ 全日空 (ANA)
- ✓ 日本航空 (JAL)
- ✓ ピーチ航空 (Peach Aviation)
- ✓ ジェットスター・ジャパン (Jetstar Japan)
- ✓ ANAウィングス (ANA Wings)
- ✓ ソラシドエア (Solaseed Air)
- ✓ スカイマーク (SkyMark Airlines)
- ✓ スターフライヤー (StarFlyer)
- ✓ エア・ドゥ (Air Do)



## 製品スペック

製品名:	磁気充電モバイルバッテリー
型番:	CW12
容量:	6800mAh
入力 (Type-C) :	5V-3A / 9V-2A / 12V-1.5A
出力 (Type-C) :	5V-3A / 9V-2.22A / 12V-1.67A
ワイヤレス出力:	最大15W
バッテリー:	ポリマー電池
動作温度範囲:	-10°C~40°C

Image: A summary of the product's technical specifications and a list of airlines that accept the power bank for carry-on.

## **SAFETY PRECAUTIONS**

---

To ensure safe operation and prevent damage, please observe the following:

- If not used for an extended period, charge the power bank once every 3 months.
- Slight heating during use is normal.
- Store in a dry place. Do not use chemical detergents for cleaning.
- After use, dispose of the product as household waste or in designated recycling bins.
- Do not allow children to use the product unsupervised.
- The manufacturer is not responsible for malfunctions or accidents caused by improper operation, disassembly, or modification.
- Before charging smartphones or digital devices, verify compatibility.

## **Integrated Safety Features**

This power bank is equipped with multiple safety protection functions, including:

- Overcharge Protection
- Over-discharge Protection
- Overcurrent Protection
- Short Circuit Protection
- High Temperature Protection
- Overvoltage Protection
- Surge Protection
- Electromagnetic Interference (EMI) Prevention

The product is PSE certified and covered by PL insurance, ensuring reliability and safety for all users.

# 6800

市販のスマホのバッテリー容量



iPhone 15  
3349mAh



iPhone 16  
3561mAh



Xperia 1 VI  
5000mAh



Aquos sense8  
5000mAh

## 高効率の 冷却システム

デバイスを長時間  
安定して動作させます！



過充電保護



過放電保護



過電流保護



短絡保護



温度制御



サージ保護



電磁干渉防護



高品質  
セル保護



PSE認証取得済みで、安心してご使用いただけます。

Image: A series of icons visually representing the comprehensive safety features, such as overcharge, over-discharge, and short-circuit protection.

## TROUBLESHOOTING

---

- **Device not charging wirelessly:**

- Ensure your device is MagSafe compatible and properly aligned with the power bank's charging area.
- Remove any thick or metallic phone cases that might interfere with wireless charging.
- Check if the power bank has sufficient charge.

- **Device not charging via cable:**

- Ensure the cable is securely connected to both the power bank and your device.
- Try using a different USB-C cable to rule out a faulty cable.
- Check if the power bank has sufficient charge.

- **Power bank not charging:**

- Ensure the charging cable is securely connected to the power bank and the power adapter.
- Try using a different power adapter and cable.
- Verify the power adapter is functioning correctly.

- **Power bank feels warm during use:**

- Slight warming during charging or discharging is normal. If it becomes excessively hot, discontinue use and contact support.

## MAINTENANCE

---

- Clean the power bank with a soft, dry cloth. Do not use liquid cleaners or aerosols.
- Avoid exposing the power bank to extreme temperatures, direct sunlight, or high humidity.
- Do not drop, puncture, or disassemble the power bank.
- Store the power bank in a cool, dry place when not in use.

## PACKAGE CONTENTS

---

- SLuB 6800mAh MagSafe Wireless Power Bank (Model CW12)
- USB-C to USB-C Cable (also functions as a strap)
- User Manual

## WARRANTY AND SUPPORT

---

This product is covered by PL insurance (Product Liability Insurance). For any issues or inquiries, please contact SLuB customer support through your purchase platform or the official SLuB website. Please retain your proof of purchase for warranty claims.