

[Manuals.plus](#) /

> [Bewinner](#) /

> Bewinner LED Ceiling Fan Light Kit Instruction Manual

## Bewinner Bewinnergrzqgd4tu-11

# Bewinner LED Ceiling Fan Light Kit Instruction Manual

Model: Bewinnergrzqgd4tu-11

## INTRODUCTION

---

This manual provides instructions for the installation and operation of your Bewinner LED Ceiling Fan Light Kit. This replacement panel features advanced LED chip technology for consistent performance, a convenient memory function for light color settings, and adjustable brightness to suit various lighting needs.



Image: Top view of the Bewinner LED Ceiling Fan Light Kit, showcasing its circular design and LED arrangement.

## SAFETY INFORMATION

---

- **WARNING:** Always disconnect power at the circuit breaker before attempting any installation, maintenance, or servicing of the light kit. Failure to do so may result in electric shock or serious injury.
- If you are unsure about any part of the installation process, consult a qualified electrician.
- Do not use this product with incompatible dimmers. This light kit is designed for use with most LED dimmers on the market (dimmer not included).
- Ensure the product's voltage (120V) is compatible with your existing light fixture's electrical system.
- Handle the LED panel with care to avoid damage to the electronic components.

## PACKAGE CONTENTS

---

The package contains the following item:

- 1 x Bewinner LED Ceiling Fan Light Module

## SPECIFICATIONS

---

<b>Brand</b>	Bewinner
<b>Material</b>	Aluminum + PC
<b>Product Dimensions (L x W x H)</b>	6.29" x 6.29" x 1.18"
<b>Height without Magnetic Part</b>	Approx. 15mm / 0.59in
<b>Height with Magnetic Part</b>	Approx. 24mm / 0.94in
<b>Size</b>	6.3 inch
<b>Power</b>	24W
<b>Color Temperature (CCT)</b>	3000K (Warm), 4000K (Neutral), 6000K (Cool White)
<b>Dimmable</b>	Yes (Dimmer not included)
<b>Voltage</b>	120V
<b>Item Weight</b>	4.6 ounces
<b>Model Number</b>	Bewinnergrzqgd4tu-11

## SETUP AND INSTALLATION

---

This light panel is designed for versatility and is suitable for various fixtures including fan lights, ceiling fans, chandeliers, flush mount lights, and wall sconces, provided they feature a metal base for magnetic attachment. The magnetic design simplifies installation, eliminating the need for drilling.

### Installation Steps:

#### 1. Step 1: Prepare the Wires

Ensure the power to the fixture is disconnected at the circuit breaker. If necessary, strip approximately 1/4 to 1/2 inch of insulation from the ends of the wires from your light fixture.



Image: A close-up view of the wiring terminal on the LED light panel, showing a blue and white wire connected, indicating the connection points.

## 2. Step 2: Connect Wires

Locate the wire terminals on the Bewinner LED light module. Press and hold one end of a terminal. Insert one of the stripped wires from your fixture into the open terminal. Release the terminal to secure the wire connection. Repeat this process for the second wire, ensuring a firm connection for both.



Image: A detailed view of the wire connection process, illustrating how to properly insert a stripped wire into the light module's terminal.

### 3. Step 3: Attach the Panel

Once the wires are securely connected, align the magnetic back of the LED panel with the metal base of your light fixture. The integrated magnets will firmly attach the panel in place, providing a quick and secure setup without the need for additional tools or drilling.



Image: The reverse side of the LED light panel, clearly showing the integrated magnets designed for easy attachment to a metal surface.

## OPERATING INSTRUCTIONS

---

### Power On/Off:

Restore power at the circuit breaker. Use your wall switch or fixture control to turn the light panel on or off.

### Color Temperature Adjustment (3CCT):

The light panel offers three distinct color temperatures: 3000K (Warm Light), 4000K (Neutral Light), and 6000K (Cool White Light). To cycle through these color temperatures, simply turn the light off and then back on within 5 seconds. Each quick toggle will switch to the next available color temperature.

### Memory Function:

The light kit includes a convenient memory function. If the light is turned off for more than 5 seconds, it will automatically recall and revert to the last used color temperature setting when turned back on. This eliminates the need to readjust your preferred setting each time.

### Brightness Adjustment (Dimmable):

This light kit is fully dimmable and compatible with most standard LED dimmer switches (dimmer not included). Connect the light kit to a compatible dimmer to adjust the brightness level from 5% to 100%, allowing you to create the ideal ambiance for any room.

## MAINTENANCE

---

Proper maintenance ensures the longevity and optimal performance of your LED light kit.

- **Cleaning:** Before cleaning, always ensure the power is off and the light panel is cool to the touch. Wipe the surface gently with a soft, dry, or slightly damp cloth. Do not use abrasive cleaners, solvents, or harsh chemicals, as these can damage the finish and electronic components.
- **Inspection:** Periodically inspect the light panel and its connections for any signs of wear, damage, or loose wiring. If any issues are found, disconnect power immediately and consult a qualified professional.

## TROUBLESHOOTING

---

If you encounter any issues with your Bewinner LED Ceiling Fan Light Kit, refer to the following troubleshooting guide:

- **Light does not turn on:**
  - Verify that the power supply to the fixture is connected correctly and securely.
  - Check if the circuit breaker supplying power to the fixture is in the 'ON' position.
  - Ensure that the wires are securely connected to the light module's terminals as per the installation instructions.
- **Light flickers or dims unexpectedly:**
  - Confirm that you are using a compatible LED dimmer switch. Incompatible dimmers can cause flickering or improper dimming.
  - Inspect all wiring connections for any looseness or damage.
  - Ensure the power supply to your home is stable and not experiencing fluctuations.
- **Color temperature does not change:**
  - To change the color temperature, you must cycle the power off and on within 5 seconds. If the light is off for longer than 5 seconds, the memory function will activate, recalling the last setting.

## WARRANTY AND SUPPORT

---

For detailed warranty information, technical assistance, or customer support regarding your Bewinner LED Ceiling Fan Light Kit, please refer to the documentation included with your purchase or visit the official Bewinner website. You may also find contact information for customer service on the product packaging.