

[Manuals.plus](#) /

› [InnoView](#) /

› InnoView 15.6" FHD Dual Portable Monitor (Model INVPM009 05B) User Manual

InnoView INVPM009 05B

InnoView 15.6" FHD Dual Portable Monitor (Model INVPM009 05B) User Manual

Model: INVPM009 05B

1. INTRODUCTION

This manual provides detailed instructions for the setup, operation, and maintenance of your InnoView 15.6" FHD Dual Portable Monitor. Please read this manual thoroughly before using the device to ensure optimal performance and longevity.

The InnoView dual portable monitor is designed to expand your workspace, offering two 15.6-inch 1080P IPS displays. Its foldable design and versatile display modes enhance productivity for various tasks.



Figure 1: InnoView 15.6" FHD Dual Portable Monitor in stacked configuration.

2. WHAT'S IN THE BOX

- InnoView 15.6" FHD Dual Portable Monitor
- HDMI cable
- 30W adapter
- Type-C power cable
- Full-featured Type-C cable

3. SETUP INSTRUCTIONS

3.1 Power Connection

Connect the provided 30W adapter to the monitor using the Type-C power cable. For optimal performance, ensure a 30W or higher power source is used.

3.2 Connecting to Windows Devices

For Windows systems, the monitor is plug-and-play, requiring no driver installation. Connect the monitor to your laptop using the full-featured Type-C cable for both signal transmission and power. This enables extended, split-screen, and duplicate modes.

3.3 Connecting to Mac Devices

For Mac devices, extended mode requires a driver installation. Without the driver, only split-screen and duplicate modes are supported. Ensure your device's Type-C port is full-featured.

Driver Installation Path for Mac:

1. Go to "Menu"
2. Select "Other Settings"
3. Choose "Mac Extend"
4. Set to "On"

Your browser does not support the video tag.

Video 1: Instructions on how to download and install dual monitor display drivers for Mac devices to enable extended mode.

3.4 HDMI Connection

When connecting via HDMI, only duplicate and split-screen modes are available on any system. Extended mode is not supported with HDMI.



4. OPERATING MODES

The InnoView dual portable monitor supports various display configurations to suit your workflow:

- **Extended Mode:** Expands your desktop across both screens, allowing for more workspace. (Requires driver for Mac).
- **Split-Screen Mode:** Divides content across the two screens.
- **Duplicate Mode:** Mirrors the content of your primary display onto the portable monitor.

Multiple Modes Can Be Displayed

Triple screen office
For Type-C Connection: Supports extended display, mirroring, and clone modes. (driver required for Mac)

Sharing Mode
Share meeting materials

Splice Mode
Allows smooth reading of long texts

Portrait Mode
Vertical mode stimulates creativity
* Windows only (manual adjustment required)
For HDMI Connection: Supports mirroring/clone mode only

Figure 3: Visual representation of the multiple display modes available.

4.1 Screen Rotation and Folding

The screens can rotate 0-315° with 180° adjustable stands. Gravity sensors enable automatic screen rotation for optimal viewing when connected to Windows or Mac. This flexibility allows for various configurations, including vertical layouts for programming or document review, and shared viewing for collaboration.

Unlock 6 fun and creative ways to use



Figure 4: Various flexible usage modes of the dual monitor.

Single Cable, Triple Screens

Connect three screens with just one C cable

System	Portrait Mode
Windows	Support 
Macos with Intel chip	Support 
Macos with M1/M2 chip	Support 



Note: ① Mac needs drivers installed. ② Your device's Type-C port needs a full-featured connector.

Figure 5: Effortless screen sharing in a collaborative setting.

5. MAINTENANCE

- Keep the monitor clean by gently wiping the screens with a soft, lint-free cloth. Avoid abrasive cleaners.
- Do not expose the monitor to extreme temperatures or humidity.
- Handle the monitor with care to prevent physical damage, especially to the hinges and screens.
- Store the monitor in its folded position when not in use to protect the screens.

6. TROUBLESHOOTING

6.1 No Display / Black Screen

- Ensure the monitor is properly powered using the original 30W adapter and Type-C power cable.
- Verify that the full-featured Type-C cable (for signal) or HDMI cable is securely connected to both the monitor and

your device.

- Check your device's display settings to ensure the external monitor is detected and configured correctly (e.g., extended or duplicate mode).
- For Mac users, confirm that the necessary drivers are installed for extended mode.

6.2 Incorrect Display Mode on Mac

If your Mac is not displaying in extended mode, ensure the display drivers are installed. Refer to Section 3.3 for driver installation instructions.

6.3 Screen Rotation Issues

The monitor features gravity sensors for automatic rotation. If rotation is not working, ensure the monitor is placed on a stable, flat surface. Check your operating system's display settings for any rotation locks or manual orientation adjustments.

7. SPECIFICATIONS

Feature	Detail
Model Number	INVPM009 05B
Screen Size	15.6 Inches (x2)
Resolution	1920 x 1080 Pixels (FHD 1080p)
Aspect Ratio	16:9
Image Brightness	300 Candela
Screen Surface	Matte
Product Dimensions	8.5 x 14 x 0.85 inches
Item Weight	3.5 pounds
Manufacturer	InnoView

8. WARRANTY AND SUPPORT

InnoView offers a 30-day return policy and an 18-month warranty for this product. For any questions, technical assistance, or warranty claims, please contact our dedicated customer support team.



Figure 6: Warranty information.



Figure 7: Return policy details.

© 2025 InnoView. All rights reserved.

ASK A QUESTION ABOUT THIS MANUAL

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. [Privacy details](#).

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

Answered questions about this manual

Why is my InnoView INVPM009 05B dual monitor displaying 'No Signal' and entering power-saving mode when connected to Windows via USB-C?

If your InnoView INVPM009 05B has suddenly stopped receiving a signal after a year of use, please try the following troubleshooting steps based on the manual: Check Power Supply: Ensure you are using the original...

[Read full answer](#)