

## Marcree B3-8D-1

# Marcree B3-8D-1 Large Capacity Gun Safe User Manual

Model: B3-8D-1

## 1. IMPORTANT SAFETY INFORMATION

Read all instructions carefully before operating the Marcree B3-8D-1 gun safe. Failure to follow these instructions may result in injury, damage to the safe, or unauthorized access.

- Always keep the safe locked when not in use.
- Store emergency keys in a secure location away from the safe and out of reach of children.
- Do not store the emergency keys inside the safe.
- Ensure the safe is securely mounted to prevent tipping or removal.
- Keep children and unauthorized individuals away from the safe.
- This safe is designed for securing firearms and valuables. It is not water resistant.

## 2. PRODUCT OVERVIEW

The Marcree B3-8D-1 is a large capacity gun safe designed for secure storage of rifles, shotguns, handguns, and ammunition. It features a heavy-duty alloy steel construction, an electronic keypad with alarm and silent modes, and multiple access options.

### Key Features:

- Electronic Keypad with Programmable Code
- Emergency Key Access
- External Power Supply for Emergency Access
- Reinforced Locking Bolts
- Anti-Tamper Alarm System
- Silent Mode Operation
- Adjustable Gun Racks and Removable Partitions
- Door Organizer for Handguns and Accessories
- LED Interior Lighting



Image: The Marcee B3-8D-1 gun safe shown in both closed and open configurations, highlighting its internal storage capacity and electronic keypad.

## 20 MINUTES EASY ASSEMBLY

CLICK

Gx1

SECURE

DONE

▲ See the instructions for specific installation steps!!!

Image: Detailed view of the safe's interior, showcasing the net bag on the door, septum, LED light, pistol case, gun bracket clamp, cloth bag under the door, dual alarm system, and mute function.

### 3. SPECIFICATIONS

<b>Brand</b>	Marcree
<b>Model Number</b>	B3-8D-1
<b>Product Dimensions</b>	14.96"D x 17.71"W x 51.96"H
<b>Lock Type</b>	Electronic Combination Lock
<b>Material</b>	Metal (Heavy-duty alloy steel)
<b>Mounting Type</b>	Floor Mount
<b>Special Feature</b>	Alarm System, Silent Mode, LED Lighting
<b>Included Components</b>	Gun safe cabinet, 2x Keys, 4x Expansion Screws, 1x Emergency Battery Box, 1x User Manual
<b>Water Resistance Level</b>	Not Water Resistant

## 10-12 GUN SAFE FOR RIFLES AND PISTOLS



Image: Diagram illustrating the external and internal dimensions of the Marcree B3-8D-1 gun safe, including depth, width, and height measurements.

## 4. SETUP AND INSTALLATION

The Marcree B3-8D-1 gun safe requires assembly and secure mounting. It is recommended that two people perform the assembly and installation.

### 4.1. Assembly

Follow these general steps for assembly. Refer to the included physical user manual for detailed, step-by-step instructions and diagrams.

1. **Unpack Components:** Carefully remove all parts from the packaging. Verify all components listed in the packing list are present.
2. **Assemble Body:** Connect the side panels (A) to the back panel (C) using the provided hardware. Ensure all connections are secure.
3. **Install Top Panel:** Place the top panel (G) onto the assembled body and secure it with the appropriate fasteners.
4. **Attach Door:** Carefully attach the safe door to the main body, ensuring hinges are properly aligned and secured.
5. **Install Interior Components:** Place adjustable gun racks, partitions, and door organizers as desired.



Image: Visual guide showing three main assembly steps: clicking panels together, securing the top, and the final assembled safe. Refer to the full instructions for details.

## 4.2. Mounting

For maximum security, the safe must be securely mounted to a floor or wall. Pre-drilled holes are provided for this purpose.

1. **Choose Location:** Select a discreet and secure location, preferably against a solid wall or in a corner.
2. **Mark Drilling Points:** Position the safe and mark the locations for the mounting holes on the floor or wall.
3. **Drill Holes:** Drill pilot holes using an appropriate drill bit for your mounting surface (wood, concrete, etc.).
4. **Secure Safe:** Align the safe with the drilled holes and secure it using the provided expansion screws or other suitable mounting hardware. Ensure all bolts are tightened firmly.

## 5. OPERATING INSTRUCTIONS

---

The Marcree B3-8D-1 safe offers multiple ways to access its contents.

### 5.1. Electronic Keypad Access

The electronic keypad allows for quick and secure access using a programmable code.

1. **Initial Setup:** Upon first use, you will need to set your personal access code. Refer to the physical manual for specific instructions on programming the code.
2. **Opening the Safe:** Enter your programmed code on the keypad. The safe will emit a confirmation sound (unless in silent mode). Turn the handle to open the door.
3. **Closing the Safe:** Close the door and turn the handle to the locked position. The safe will automatically lock.

### 5.2. Emergency Key Access

In case of battery failure or forgotten code, the safe can be opened using the emergency keys.

1. **Locate Keyhole:** The emergency keyhole is typically concealed behind the keypad or a removable cover.
2. **Insert Key:** Insert the emergency key and turn it to unlock the safe.
3. **Open Door:** Turn the handle to open the door.

### 5.3. External Power Supply

If the internal batteries are depleted and you do not have the emergency keys readily available, an external power supply can be used.

1. **Connect Emergency Battery Box:** Plug the emergency battery box (requires 4 AA batteries, not included) into the external power port on the keypad.
2. **Enter Code:** Enter your programmed code on the keypad.
3. **Open Door:** Turn the handle to open the door. Replace internal batteries immediately after opening.



Image: Illustration demonstrating the three ways to open the safe: using the electronic keypad password, with the emergency keys, or by connecting an external power source to the keypad.

## 5.4. Alarm and Silent Mode

The safe is equipped with an anti-tamper alarm system and a silent mode feature.

- **Alarm Activation:** The alarm will activate if incorrect codes are entered multiple times or if the safe experiences significant impact or tampering.
- **Silent Mode:** Refer to your physical manual for instructions on how to activate and deactivate silent mode, which allows for discreet operation without audible feedback.

## 6. MAINTENANCE

### 6.1. Battery Replacement

The electronic keypad is powered by internal batteries (typically AA batteries). When the battery level is low, the keypad may indicate this with a warning light or sound.

1. **Access Battery Compartment:** Open the safe and locate the battery compartment, usually on the inside of the door or behind the keypad assembly.
2. **Replace Batteries:** Remove old batteries and insert new ones, ensuring correct polarity.

3. **Test Keypad:** Close the safe and test the keypad with your code to ensure proper function.

## 6.2. Cleaning

Clean the exterior of the safe with a soft, damp cloth. Avoid using abrasive cleaners or solvents that could damage the finish.

## 7. TROUBLESHOOTING

Problem	Possible Cause	Solution
Keypad does not respond.	Dead batteries.	Replace internal batteries or use the external power supply.
Safe will not open with code.	Incorrect code entered; batteries low.	Re-enter code carefully. Replace batteries. Use emergency key.
Alarm sounds unexpectedly.	Tampering detected; multiple incorrect code entries.	Enter correct code to disarm. Check for physical impacts.
Door is difficult to close or open.	Obstruction; misalignment; damaged components.	Check for items blocking the door. Ensure safe is level. Contact customer support if issue persists.

## 8. WARRANTY AND CUSTOMER SUPPORT

For warranty information, technical assistance, or any questions regarding your Marcee B3-8D-1 gun safe, please refer to the contact details provided in your original purchase documentation or visit the official Marcee website.

Keep your purchase receipt and model number (B3-8D-1) handy when contacting support.