Saved from manuals.plus.
Open the live page for links to other documents and user manuals.

DAREU LK165D

DAREU LK165D Ultra Slim Full Size Wireless Keyboard

Instruction Manual

Introduction

Thank you for choosing the DAREU LK165D Ultra Slim Full Size Wireless Keyboard. This manual provides detailed instructions for setting up, operating, maintaining, and troubleshooting your new keyboard. Please read this manual carefully before use to ensure optimal performance and longevity of your device.



Image: The DAREU LK165D Ultra Slim Full Size Wireless Keyboard, showcasing its full layout with numeric keypad and media hotkeys.

Product Features

- **Ultra Slim Full Size Design:** Compact yet complete with a numeric keypad.
- **Multi-Mode Connectivity:** Supports 2.4G wireless via USB dongle and three independent Bluetooth channels for connecting up to four devices simultaneously.
- **Wide Compatibility:** Compatible with Windows, macOS, iOS, Android, Chrome OS, and Linux operating systems.
- **Scissor Switch Keys:** Provides a comfortable and quiet typing experience similar to laptop keyboards.
- **Long Battery Life:** Up to 175 hours of continuous use on a single 2-hour charge via USB-C.
- **Ergonomic Stand:** Integrated flip-out legs for adjustable typing angle.
- **Dedicated Media Hotkeys:** Quick access to multimedia controls and system functions.

Setup Guide

1. Charging the Keyboard

Before first use, fully charge the keyboard. Connect the provided USB-C cable to the keyboard's charging port and the other end to a USB power source (e.g., computer USB port, wall adapter). A full charge takes approximately 2 hours and provides up to 175 hours of use.



Image: Close-up of the DAREU LK165D keyboard showing the USB-C charging port with a cable connected.

2. Connecting to Devices

The DAREU LK165D keyboard supports connection to up to four devices: one via 2.4G wireless USB dongle and three via Bluetooth.

2.1. 2.4G Wireless Connection

1. Locate the 2.4G USB dongle, usually stored in a compartment on the keyboard itself.
2. Plug the USB dongle into an available USB port on your computer.

3. Turn on the keyboard. The keyboard should automatically connect to the dongle.
4. Press **Fn + F1** to switch to the 2.4G channel if it doesn't connect automatically.

2.2. Bluetooth Connection (BT1, BT2, BT3)

1. Turn on the keyboard.
2. Press and hold **Fn + F2** (for BT1), **Fn + F3** (for BT2), or **Fn + F4** (for BT3) for 3-5 seconds until the corresponding indicator light flashes rapidly. This indicates the keyboard is in pairing mode.
3. On your device (computer, tablet, phone), go to Bluetooth settings and search for new devices.
4. Select "DAREU LK165D" (or similar name) from the list of available devices to pair.
5. Once paired, the indicator light will stop flashing and remain solid for a few seconds before turning off.



Image: Illustration showing the DAREU LK165D keyboard connecting to a cell phone, tablet, laptop, and desktop computer using its 4-mode connection capabilities.



Image: The DAREU LK165D keyboard displayed with various devices (laptop, tablet, phone) illustrating its wide compatibility across Android, Windows, and Mac/iOS operating systems.

Operating Instructions

1. Switching Between Connected Devices

To switch between your connected devices, simply press the corresponding function key:

- **Fn + F1:** Switch to 2.4G wireless connection.
- **Fn + F2:** Switch to Bluetooth Device 1 (BT1).
- **Fn + F3:** Switch to Bluetooth Device 2 (BT2).
- **Fn + F4:** Switch to Bluetooth Device 3 (BT3).

2. Using Function (Fn) Keys and Media Hotkeys

The keyboard features a dedicated **Fn** key. To activate the secondary functions printed on the F-keys (F1-F12) and other

keys, press and hold the **Fn** key simultaneously with the desired function key.

Common media hotkeys include:

- **Fn + F5:** Previous Track
- **Fn + F6:** Play/Pause
- **Fn + F7:** Next Track
- **Fn + F8:** Mute
- **Fn + F9:** Volume Down
- **Fn + F10:** Volume Up
- **Fn + F11:** Calculator
- **Fn + F12:** Email
- Other keys may have secondary functions for specific operating systems (e.g., Windows/Mac layout).



Image: The DAREU LK165D keyboard highlighting the layout of function keys (F1-F12) and their secondary media hotkey functions.

3. Ergonomic Stand

For improved typing comfort, flip out the integrated stands located on the underside of the keyboard to slightly elevate the rear. This provides a gentle angle for your wrists.



Image: Side view of the DAREU LK165D keyboard demonstrating the ergonomic stand in its deployed position, providing a slight incline.

Maintenance

Proper maintenance ensures the longevity and performance of your keyboard.

- **Cleaning:** Use a soft, dry, lint-free cloth to wipe the keyboard surface. For stubborn dirt, slightly dampen the cloth with water or a mild, non-abrasive cleaner. Avoid excessive moisture. Do not spray cleaners directly onto the keyboard.
- **Keycaps:** The scissor-switch keycaps are low-profile. Avoid attempting to remove them forcefully, as this may cause damage.
- **Battery Care:** To preserve battery life, avoid exposing the keyboard to extreme temperatures (hot or cold). If storing for an extended period, charge the keyboard to about 50% before storage.
- **Storage:** Store the keyboard in a clean, dry environment away from direct sunlight and dust.



Image: Close-up view of the DAREU LK165D keyboard's scissor switch keys, illustrating their low-profile design and mechanism.

Troubleshooting

Problem	Possible Cause	Solution
Keyboard not connecting via 2.4G.	USB dongle not properly inserted, keyboard not in 2.4G mode, low battery.	• Ensure the USB dongle is securely plugged into a working USB port. • Press **Fn + F1** to switch to 2.4G mode. • Charge the keyboard.

Problem	Possible Cause	Solution
Keyboard not connecting via Bluetooth.	Keyboard not in pairing mode, device Bluetooth off, already paired to another channel, low battery.	• Ensure Bluetooth is enabled on your device. • Press and hold **Fn + F2/F3/F4** for 3-5 seconds to enter pairing mode for the desired channel. • Remove previous pairings on your device and re-pair. • Charge the keyboard.
Keys are unresponsive or delayed.	Low battery, interference, keyboard too far from receiver/device.	• Charge the keyboard fully. • Move the keyboard closer to your device/dongle. • Ensure no large metal objects or other wireless devices are causing interference.
Some function keys (F1-F12) are not working as expected.	Fn key not pressed, operating system specific behavior.	• Ensure you are pressing the **Fn** key simultaneously with the desired F-key for secondary functions. • Some functions may behave differently or require specific software/drivers on certain operating systems.

Specifications

Brand	DAREU
Model Number	LK165D
Connectivity Technology	2.4G Wireless, Bluetooth (BT1, BT2, BT3), USB-C (charging)
Keyboard Type	Ultra Slim Full Size Keyboard with Numeric Keypad, Scissor Switch
Compatible Devices	Laptop, Desktop Computer, Tablet, Smartphone
Operating System Compatibility	Windows, macOS, iOS, Android, Chrome OS, Linux
Battery Life	Up to 175 hours of use (after 2-hour charge)
Dimensions (Approx.)	Length: 43.5 cm (17.13 in) Width: 12.5 cm (4.92 in) Thickness: 2 cm (0.78 in)



Image: Diagram illustrating the dimensions of the DAREU LK165D keyboard, showing its length, width, and thickness.

Warranty and Support

For warranty information and technical support, please refer to the warranty card included with your product or visit the official DAREU website. Keep your purchase receipt as proof of purchase for warranty claims.

If you encounter any issues not covered in this manual, please contact DAREU customer support for assistance.

© 2026 DAREU. All rights reserved.

Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

Open the live page

https://manuals.plus/asin/B0FR8V5T7J

More documents and user manuals: **https://manuals.plus/**