

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

manuals.plus /

> [MELONARE](#) /

> [MELONARE MA-1 Mini Guitar Amp Instruction Manual](#)

MELONARE MA-1

MELONARE MA-1 Mini Guitar Amplifier Instruction Manual

Model: MA-1

INTRODUCTION

The MELONARE MA-1 Mini Guitar Amplifier is a versatile and portable 10W electric guitar amplifier designed for practice and recording. It features 30 built-in rhythm patterns, switchable clean and overdrive channels, adjustable reverb, and Bluetooth 5.3 connectivity. Its compact design and long-lasting rechargeable battery make it an ideal companion for musicians on the go.

WHAT'S IN THE BOX

- Guitar Amplifier *1
- Instruction Manual *1
- USB charging cable *1
- Guitar Amplifier packaging bag *1
- Charging cable packaging bag *1

Box Content

- 1 × Electric Guitar Amplifier
- 1 × USB Charging Cable
- 1 × User Manual



Image: The MELONARE MA-1 Mini Guitar Amp shown with its USB charging cable and user manual, indicating the contents of the package.

PRODUCT OVERVIEW AND CONTROLS

Familiarize yourself with the amplifier's front panel controls:

- **INPUT:** 6.35mm jack for connecting your electric guitar.
- **VOLUME:** Adjusts the overall output volume of the amplifier.
- **ON/OFF Switch:** Powers the unit on or off.
- **CLEAN/OVERDRIVE Button:** Toggles between clean and overdrive sound modes.
- **GAIN:** Controls the amount of distortion or overdrive in the signal.
- **TONE:** Shapes the treble and bass frequencies of your sound.
- **TAP (B.T) Button:** Used for tap tempo for rhythms and Bluetooth pairing.
- **REVERB/DRUM VOL/RHYTHM Knob:** This multi-function knob controls reverb depth, drum volume, and selects rhythm patterns.

Built-in Drum Machine

Built-in drum machine offers 30 rhythmic patterns with adjustable tempo, making practice sessions more musical and engaging.

30

Rhythm
Patterns



Full BPM
Control

Shuffle

Swing

Ballad



Image: The front panel of the MA-1 amplifier, highlighting the input, volume, clean/overdrive, gain, tone, tap, and multi-function reverb/rhythm knobs.

SETUP

1. Charging the Battery

The MA-1 features a built-in 2000mAh rechargeable battery, providing approximately 6-7 hours of continuous playtime on a full charge (actual playtime may vary based on volume and mode). To charge, connect the amplifier to a USB power source (power bank, computer, or wall adapter) using the provided USB charging cable. A full charge typically takes about 3 hours.

Flexible Audio Connections

Enjoy stable wireless freedom with Bluetooth 5.3, or plug in directly via 3.5mm AUX. Effortlessly adapt to your environment.



Image: The MA-1 amplifier connected to a charging cable, illustrating its rechargeable battery and long playtime.

2. Connecting Your Guitar

Plug your electric guitar into the **INPUT** 6.35mm jack on the front panel. Ensure the amplifier is powered on using the ON/OFF switch.

3. Bluetooth Connectivity

To stream audio wirelessly from your phone or other Bluetooth-enabled device, press and hold the **TAP (B.T)** button until the indicator light flashes, indicating pairing mode. On your device, search for and select 'MELONARE MA-1' to connect. Once connected, the indicator light will remain solid.

Real-Time Monitoring

Use the 3.5mm headphone output to catch every detail of your playing — ideal for home or outdoor practice.



Image: The MA-1 amplifier demonstrating flexible audio connections, including Bluetooth pairing with a smartphone and AUX input with a laptop.

4. AUX Input

For wired audio input, connect your phone, MP3 player, tablet, or computer to the 3.5mm AUX IN jack located on the rear of the amplifier.

5. Headphone Output

For personal monitoring or quiet practice, plug your 3.5mm headphones into the HEADPHONE OUT jack on the rear of the amplifier. This mutes the main speakers.

Box Content

- 1 × Electric Guitar Amplifier
- 1 × USB Charging Cable
- 1 × User Manual



Image: A user monitoring their playing through headphones connected to the MA-1 amplifier, ideal for quiet practice.

OPERATING THE AMPLIFIER

1. Clean and Overdrive Modes

Press the **CLEAN/OVERDRIVE** button to switch between the two primary sound modes:

- **Clean Mode:** Delivers a clear, transparent sound suitable for daily practice or acoustic-style performances.
- **Overdrive Mode:** Adds a heavy, powerful tone for improvisation or solos.

Adjust the **GAIN** and **TONE** knobs to fine-tune your sound in either mode.

Powerful 10W Full-Range Sound

Dual 1.75" full-range speakers ensure punchy bass and crystal-clear treble.



Image: The MA-1 amplifier's controls, illustrating the selection between Clean and Overdrive modes for varied playing styles.

2. Metronome and Rhythm Patterns

The amplifier includes 30 built-in rhythm patterns. To activate and control them:

- **Select Rhythm:** Push the **REVERB/DRUM VOL/RHYTHM** knob to cycle through the modes. A green LED indicates rhythm selection mode. Turn the knob to choose from the 30 patterns.
- **Adjust Tempo:** Tap the **TAP (B.T)** button three times to set the desired tempo.
- **Adjust Drum Volume:** Push the **REVERB/DRUM VOL/RHYTHM** knob again. A red LED indicates drum volume mode. Turn the knob to adjust the volume of the rhythm pattern independently.

Clean & Overdrive Modes

From crystal-clear tones to roaring rock riffs
— all in one portable amp



Clean Mode

Produces a clear, natural tone with great clarity

Overdrive Mode

Adds warmth and grit for a rich, powerful sound

Image: The MA-1 amplifier showcasing its built-in drum machine with 30 rhythm patterns and adjustable tempo for enhanced practice sessions.

3. Reverb Control

When no LED is lit on the **REVERB/DRUM VOL/RHYTHM** knob, you are in reverb control mode. Turn the knob to fine-tune the depth of the reverb effect, adding space and atmosphere to your sound.

4. Video Demonstration

Video: An official product video from Melonare Audio demonstrating the features and sound of the MA-1 Mini Guitar Amp. This video provides a concise overview of the amplifier's capabilities.

MAINTENANCE

To ensure the longevity and optimal performance of your MELONARE MA-1 Mini Guitar Amplifier, follow these maintenance guidelines:

- **Cleaning:** Use a soft, dry cloth to clean the exterior of the amplifier. Avoid using abrasive cleaners, solvents, or waxes, as these can damage the finish.
- **Storage:** Store the amplifier in a cool, dry place away from direct sunlight, extreme temperatures, and high humidity.
- **Battery Care:** For best battery life, avoid fully discharging the battery frequently. Charge the amplifier

regularly, even if not in use, to maintain battery health. If storing for an extended period, charge the battery to approximately 50% every few months.

- **Handling:** Handle the amplifier with care to prevent drops or impacts, which can damage internal components.

TROUBLESHOOTING

If you encounter issues with your MELONARE MA-1 Mini Guitar Amplifier, refer to the following common troubleshooting steps:

- **No Sound:**
 - Ensure the amplifier is powered on and fully charged.
 - Check that your guitar cable is securely connected to both the guitar and the amplifier's INPUT jack.
 - Verify that the VOLUME knob is turned up.
 - If using headphones, ensure they are properly plugged into the HEADPHONE OUT jack and that the main speakers are muted.
- **Poor Sound Quality/Distortion (in Clean Mode):**
 - Reduce the guitar's volume or the amplifier's GAIN setting.
 - Check for damaged cables or faulty guitar pickups.
- **Bluetooth Connection Issues:**
 - Ensure the amplifier is in Bluetooth pairing mode (flashing blue LED).
 - Disable and re-enable Bluetooth on your device.
 - Move your device closer to the amplifier to ensure a strong signal.
 - Forget the device from your Bluetooth settings and try pairing again.
- **Rhythm Pattern Not Playing:**
 - Ensure the amplifier is in rhythm selection mode (green LED on REVERB/DRUM VOL/RHYTHM knob).
 - Check the drum volume setting.
 - Tap the TAP (B.T) button to start the rhythm.

SPECIFICATIONS

Brand	MELONARE
Model	MA-1
Output Wattage	10 Watts
Item Weight	1.21 pounds
Product Dimensions	5.5 x 3.5 x 1.4 inches
Battery Type	Lithium Ion (2000mAh)
Power Source	Battery Powered
Material Type	Plastic

Color	Turquoise
Connectivity	Bluetooth 5.3, 3.5mm Jack (AUX IN, Headphone OUT), 6.35mm Jack (Guitar INPUT), USB (Charging)

WARRANTY AND SUPPORT

For warranty information and customer support, please refer to the contact details provided on the product packaging or visit the official MELONARE website. Keep your purchase receipt as proof of purchase for any warranty claims.