

Basike B-079S

Basike 30000mAh Universal Portable Power Bank Instruction Manual

Model: B-079S

1. INTRODUCTION

Thank you for choosing the Basike 30000mAh Universal Portable Power Bank. This device is designed to provide reliable and fast charging for your electronic devices on the go. Please read this manual carefully before use to ensure optimal performance and safety.

2. SAFETY INFORMATION

To prevent damage, electric shock, injury, or property damage, please observe the following safety precautions:

- Do not disassemble, open, or attempt to repair the power bank.
- Do not expose the power bank to water, moisture, or extreme temperatures.
- Avoid dropping, hitting, or subjecting the power bank to strong impacts.
- Keep out of reach of children.
- The power bank features intelligent protection against overcharge, overcurrent, short-circuit, overheating, and deep discharge.
- Basike is not responsible for damages caused by improper use of the product or use with an incompatible electrical device.



8 Camadas SmartProtect



Outros



Risco de Inchaço



Risco de Explosão

Image: The Basike Power Bank incorporates 8 layers of SmartProtect technology to prevent issues like battery swelling and explosion, ensuring safe operation.

3. PACKAGE CONTENTS

Please check the package for the following items:

- 1x Basike 30000mAh Power Bank
- 1x USB-C Charging Cable
- 1x User Manual (this document)
- 1x Packaging Box



O Que Você Recebe?



1

Ano

Problemas de Qualidade em até 1 Ano?
Nós Substituímos por um Novo

Basike Cuidado

Image: The package includes the Basike 30000mAh Power Bank, a USB-C charging cable, and the user manual.

4. PRODUCT OVERVIEW

The Basike 30000mAh Power Bank is a high-capacity portable charger designed for extended use. It features multiple charging options and intelligent safety features.

Key Features:

- **High Capacity:** 30000mAh battery for multiple charges.
- **Fast Charging:** Supports Power Delivery (PD) up to 22.5W output and Quick Charge (QC) for rapid device charging.
- **Integrated Cables:** Includes built-in Type-C (22.5W PD) and Lightning (12W) cables for convenience.
- **Multiple Ports:** Equipped with 1 Type-C port (20W output, 18W input, PD) and 1 USB-A port (22.5W QC).
- **Simultaneous Charging:** Capable of charging up to 4 devices concurrently.
- **Digital LED Display:** Provides real-time battery percentage for easy monitoring.



Portátil e Maior Capacidade

30.000mAh



≈ 6.0

Carrega iPhone 17 Pro



≈ 4.6

Carrega Samsung S25



≈ 40

Carrega AirPods Pro



≈ 2.8

Carrega iPad Air



Peso: 580 g

Atenção: Este modelo possui maior capacidade. Confira dimensões e peso antes da compra.



Image: The power bank's 30000mAh capacity can charge an iPhone 17 Pro approximately 6 times, a Samsung S25 4.6 times, AirPods Pro 40 times, and an iPad Air 2.8 times. Dimensions are 147mm x 67mm x 37mm, weighing 580g.



Cabos Duplos Integrados

Pegue. Puxe. Carregue. Sem estresse, sem bagunça.



1

Porta de Entrada USB-C

18W Máx

Suporta PD3.0 / PD2.0 / QC3.0 / QC2.0

1

Porta de Entrada USB-C

20W Máx

Suporta PD3.0 / PD2.0 / QC3.0 / QC2.0

2

Porta de Saída USB-A

22.5W Máx

Suporta / QC3.0 / QC2.0

3

Cabo de Saída USB-C Integrado

22.5W Máx

Suporta PD3.0 / PD2.0 / QC3.0 / QC2.0

4

Cabo de Saída Lightning Integrado

12W Máx

Compatível com Apple 2.4A

Image: Detailed view of the power bank's ports and integrated cables. It features a Type-C input port (18W Max), a Type-C output port (20W Max), a USB-A output port (22.5W Max), an integrated USB-C output cable (22.5W Max), and an integrated Lightning output cable (12W Max).



100+

Dispositivos Compatíveis



Para Celulares

Série iPhone / Série Samsung /
Google Pixel / LG
E Mais...



Para Tablets

Série iPad
E Mais...



Dispositivos de Baixa Potência

E Mais...



Image: The power bank is compatible with over 100 devices, including iPhone, Samsung, Google Pixel, LG cell phones, iPad series tablets, and various low-power devices like headphones.

5. SETUP

Initial Charging of the Power Bank:

1. Before first use, or if the power bank has been inactive for a long period, it may be in a deep discharge state.
2. Connect the power bank to a compatible wall charger using the provided USB-C cable or its integrated Type-C cable.
3. Charge the power bank for 1 to 3 hours. For faster recharging, use a higher-power compatible charger (e.g., 18W or higher).
4. The digital LED display will show the charging progress and current battery percentage.

Protective Film:

Small scratches may be present on the protective film covering the digital display, not on the screen itself. Please remove this film before initial use for a clear view of the display.

6. OPERATING INSTRUCTIONS

Charging Your Devices:

1. Connect your device to the power bank using one of the integrated cables (Type-C or Lightning) or an external cable via the USB-A or Type-C output ports.
2. The power bank will automatically detect the connected device and begin charging.
3. The digital LED display will show the remaining battery percentage of the power bank.
4. For fast charging, ensure your device and cable support PD (Power Delivery) or QC (Quick Charge) protocols. When compatible, fast charging mode will activate automatically.
5. If multiple devices are connected simultaneously, the power bank may automatically exit fast charging mode to ensure stable and safe charging for all devices.



Carrega **4** Dispositivos

2 Saídas por Cabo + 2 Saídas



Display Digital **LED** Inteligente

Permite ver a energia restante em um relance

Image: The power bank is shown charging an iPad, an iPhone, and two other devices simultaneously, demonstrating its multi-device charging capability and digital display.



As Fast as the Original

22.5W Máx
Saída

18W Máx
Entrada



6.0 h Full Recharge



Note: Charging performance requires a charger with 20W or higher output. Charger not included.



Image: The power bank can fast charge an iPad Air to 46% in 30 minutes with 22.5W output. Recharging the power bank fully takes approximately 6 hours with an 18W input.



Energia para o 177A

O Dia Todo

30000mAh do Amanhecer à Noite



Image: Demonstrates the power bank's utility throughout the day, from morning to night, providing continuous power for mobile devices.

7. MAINTENANCE

- Clean the power bank with a soft, dry cloth. Do not use harsh chemicals or abrasive materials.

- Store the power bank in a cool, dry place away from direct sunlight and extreme temperatures.
- If not used for extended periods, recharge the power bank at least once every three months to maintain battery health.

8. TROUBLESHOOTING

Q: The product appears scratched or is larger/heavier than expected.

A: Small scratches may be on the protective film of the display. Please remove this film before first use. This power bank measures 6.7 × 3.7 × 14.7 cm and weighs 0.58 kg. Due to its high capacity (30000mAh), it is naturally larger and heavier than lower capacity models (e.g., 20000mAh).

Q: The power bank does not turn on or display anything.

A: If the product has been inactive for a long time, the battery might have undergone deep discharge and activated its over-discharge protection. Connect the power bank to a charger for 1 to 3 hours. If necessary, use a compatible higher-power charger to reactivate and recharge it faster.

Q: Fast charging is not working or deactivates.

A: Ensure your device and charging cable support fast charging protocols (PD, QC). Fast charging may automatically deactivate if multiple devices are connected simultaneously to maintain overall charging stability and safety.

9. SPECIFICATIONS

Model Name	B-079S
Battery Capacity	30000mAh (3.7V)
Rated Capacity	18000mAh
Type-C Input	DC 5V-3A / 9V-2A / 12V-1.5A (Max 18W)
USB-A Output	DC 5V-3A / 5V-4.5A / 4.5V-5A / 9V-2.5A / 12V-1.87A (Max 22.5W)
Type-C Output	DC 5V-3A / 9V-2.2A / 12V-1.67A (Max 20W)
Integrated Type-C Cable Output	DC 5V-3A / 5V-4.5A / 4.5V-5A / 9V-2.5A / 12V-1.87A (Max 22.5W)
Integrated Lightning Cable Output	DC 5V-2.4A (Max 12W)
Dimensions (L x W x H)	147 x 67 x 37 mm (5.79 x 2.64 x 1.46 inches)
Weight	580g (20.45 oz)
Battery Cell Composition	Lithium-ion
Special Features	Integrated Cables, Fast Charging, Short-circuit Protection, Overcharge Protection, Digital Display

Compatible Devices

Smartphones (iPhone, Samsung, Google Pixel, Android/iOS), Tablets (iPad series), Headphones, Speakers, and other USB-powered devices.

10. WARRANTY AND SUPPORT

Basike provides the following warranty and support for this product:

- **Warranty:** 1-year warranty against manufacturing defects.
- **Customer Support:** 24/7 customer support is available for any inquiries or issues.
- **Disclaimer:** Basike is not responsible for damages caused by improper use of the product or use with an incompatible electrical device.

For warranty claims or technical assistance, please contact Basike customer support through the retailer or official website.

© 2026 Basike. All rights reserved.

ASK A QUESTION ABOUT THIS MANUAL

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. [Privacy details](#).

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

