

[Manuals.plus](#) /

› [TBK](#) /

› TBK TBK568A Heating Pad User Manual for Electronics Repair

TBK TBK568A

TBK568A Heating Pad User Manual

Model: TBK568A

1. INTRODUCTION

The TBK568A Heating Pad is a specialized tool designed for the safe and efficient separation of LCD screens and back covers on various electronic devices, including smartphones, tablets, and other LCD/OLED screens. It features a digital temperature control system to provide precise and stable heating, which is crucial for softening adhesives without causing damage to internal components. This device is suitable for professional repair technicians and electronics enthusiasts seeking reliable performance in their repair tasks.




Figure 1: TBK568A Heating Pad, a specialized mat with an integrated control unit, designed for safe and efficient electronics repair.

2. PACKAGE CONTENTS

Verify that all items are present in the package:

- Heating Pad x 1
- Power Cord x 1

3. SAFETY INFORMATION

- **Voltage Selection:** Before connecting the device to power, ensure the voltage switch (110V/220V) on the control unit is set correctly for your region's power supply. Incorrect voltage selection can damage the unit.
- **Stable Workstation:** Always operate the heating pad on a stable, flat, and heat-resistant surface to prevent accidents.
- **Heat Resistance:** The mat features a non-slip, heat-resistant surface. Avoid placing flammable materials directly on the heated area.
- **Static Prevention:** The mat is designed to help prevent static buildup, but always follow standard ESD (Electrostatic Discharge) precautions when working with sensitive electronics.
- **Supervision:** Do not leave the heating pad unattended while in operation.
- **Ventilation:** Ensure adequate ventilation in your workspace.
- **Children and Pets:** Keep the device out of reach of children and pets.

HIGH-TEMPERATURE RESISTANT SILICONE HEATING PLATE

The design employs a thickened silicone heating plate to ensure uniform heating distribution and avoid localized overheating or underheating.




Figure 2: A close-up view of the TBK568A control unit, highlighting the voltage selection switch (110V/220V) for proper power configuration. Ensure this is set correctly before use.

4. SETUP

1. **Unpack:** Carefully remove the TBK568A Heating Pad and all accessories from its packaging.
2. **Placement:** Place the heating pad on a clean, stable, and heat-resistant workbench.
3. **Voltage Selection:** Locate the voltage selection switch on the side of the control unit. Using a small tool (like tweezers or a thin screwdriver), slide the switch to either **110V** or **220V**, matching your local power supply. **This step is critical to prevent damage to the device.**
4. **Connect Power:** Insert the power cord into the designated port on the control unit, then plug the other end into a suitable power outlet.
5. **Power On:** Press the 'Power' button on the control unit to turn on the device. The digital display will illuminate.

5. FEATURES

- **Professional Heat Pad:** Designed specifically for electronics repair, facilitating safe screen removal by softening adhesives.
- **Digital Temperature Control:** Allows precise heat adjustment from 0°C to 120°C for various repair needs.
- **Even Heat Distribution:** Equipped with a high-efficiency heating system for uniform temperature across the mat, preventing localized overheating.
- **Integrated Dust Inspection Light:** A built-in light helps identify microscopic dust and debris on screens during reassembly, preventing internal scratches.
- **Screw Storage Slots:** Two convenient slots on the control unit provide organized storage for small components during repair.
- **Large Working Area:** The 385 × 250 × 29 mm mat accommodates a wide range of devices, from smartphones to 13-inch laptops.

DUST-DETECTING LIGHTING

Equipped with dust-detecting lighting, it ensures clear visibility of screen details during disassembly, improving work efficiency




Figure 3: The integrated dust inspection light of the TBK568A Heating Pad in operation, revealing microscopic debris on a phone screen for thorough cleaning before reassembly.

2 SCREW STORAGE SLOTS

Convenient for storing screws and other components during work and maintenance.



Figure 4: The TBK568A Heating Pad's control unit featuring two convenient storage slots for organizing small components like screws during repair tasks.

6. OPERATING INSTRUCTIONS

1. **Power On:** After proper setup, press the 'Power' button to turn on the heating pad. The digital display will show the current temperature.
2. **Set Temperature:** Use the '+' and '-' buttons to adjust the desired temperature. The recommended temperature ranges are:
 - **60°C–80°C:** Suitable for smartphones (e.g., iPhone, Samsung) and tablet screens.
 - **80°C–100°C:** Ideal for more stubborn adhesives found in laptops and iPad Pro models.
 - **100°C+:** For specialized tasks such as motherboard pre-heating and professional component soldering.
3. **Heating Process:** Place the device to be repaired onto the heating mat. Allow the device to heat for 3–5 minutes once the set temperature is reached. This duration allows the adhesive to reach its glass transition point, becoming pliable for easier separation.
4. **Screen Separation:** Once the adhesive is softened, carefully begin the screen separation process using appropriate tools. The softened adhesive will allow for a smoother separation without excessive force.
5. **Dust Inspection:** Before reassembly, press the 'Light' button on the control unit to activate the integrated dust inspection light. Use this light to check for any microscopic dust or debris on the screen or internal components, which could cause damage or visual imperfections.

6. **Power Off:** After completing your repair, press the 'Power' button to turn off the heating pad. Allow the unit to cool down before storing.

EVEN HEAT DISTRIBUTION

Equipped with a high-efficiency heating system, the temperature can be raised from 40°C to 120°C in a short time to accelerate disassembly.




Figure 5: A visual representation of the TBK568A Heating Pad's high-efficiency heating system, showing uniform temperature distribution across the mat.

MOBILE PHONE REPAIR IS SIMPLE

Suitable for maintenance engineers or electronic product enthusiasts



Figure 6: An individual performing a phone repair on the TBK568A Heating Pad, demonstrating its use as a stable and heated work surface.

Video 1: This video demonstrates the key features and operation of the TBK568A Heating Pad, including its adjustable voltage, temperature control, dust inspection light, and large working area for various electronics repair tasks.

7. MAINTENANCE

- **Cleaning:** After each use, ensure the heating pad has cooled down completely. Wipe the surface with a soft, dry cloth to remove any debris or adhesive residue. Do not use abrasive cleaners or solvents.
- **Storage:** Store the heating pad in a clean, dry place away from direct sunlight and extreme temperatures.
- **Inspection:** Periodically inspect the power cord and the unit for any signs of damage. If damage is found, discontinue use and contact customer support.

8. TROUBLESHOOTING

- **Device Not Powering On:**
 - Check if the power cord is securely plugged into both the unit and the power outlet.
 - Verify that the power outlet is functional.
 - Ensure the voltage selection switch is set correctly (110V or 220V).
- **Inconsistent Heating:**
 - Ensure the device is placed flat on the heating surface.
 - Allow sufficient time for the unit to reach the set temperature.
 - Avoid placing objects that obstruct heat transfer on the mat.
- **Temperature Display Issues:**
 - If the display is erratic, power off the unit, unplug it, wait a few minutes, and then plug it back in and restart.

If you encounter issues not listed here or if troubleshooting steps do not resolve the problem, please contact customer support.

9. SPECIFICATIONS

Attribute	Value
Model Number	TBK568A
Product Dimensions	15.35 x 9.84 x 1.18 inches
Item Weight	2.04 pounds
Manufacturer	TBK
Temperature Range	0°C to 120°C
Voltage	110V/220V (Adjustable)

10. WARRANTY AND SUPPORT

For warranty information, technical support, or service inquiries, please refer to the documentation provided with your purchase or contact TBK customer service through their official channels. Keep your purchase receipt as proof of purchase for warranty claims.

ASK A QUESTION ABOUT THIS MANUAL

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. [Privacy details.](#)

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

Open the live page

<https://manuals.plus/asin/B0GJ3CXV25>

More documents and user manuals: <https://manuals.plus/>