

Batavia BTC0251-US

BATAVIA Electric Staple Gun 0251 User Manual

Model: BTC0251-US

Brand: Batavia

1. IMPORTANT SAFETY INSTRUCTIONS

Read all safety warnings and instructions before operating this tool. Failure to follow the warnings and instructions may result in electric shock, fire, and/or serious injury.

- Always wear eye protection (safety glasses) when operating the staple gun.
- Keep hands and body parts away from the discharge area of the tool.
- Never point the tool at yourself or others.
- Ensure the contact safety mechanism is engaged before firing.
- Do not operate the tool in explosive atmospheres, such as in the presence of flammable liquids, gases, or dust.
- Keep children and bystanders away while operating a power tool.
- Store idle tools out of reach of children and do not allow persons unfamiliar with the power tool or these instructions to operate the power tool.
- Use the correct power tool for your application. Do not force the tool.

2. PRODUCT OVERVIEW

The BATAVIA Electric Staple Gun 0251 is a versatile 2-in-1 cordless tool designed for both stapling and brad nailing. It features an integrated staple remover for convenience.

Key Features:

- 2-in-1 functionality: Staples and Brad Nails
- Cordless operation for portability
- Integrated staple remover

- Lightweight design
- No-mar tip to protect work surfaces
- Triple safety mechanism
- Bright LED illumination for improved visibility
- Up to 1200+ shots per full charge

Components:



Figure 2.1: Labeled components of the BATAVIA Electric Staple Gun 0251. Key components include the ON/OFF Switch, LED Indicator, Type-C Port, Trigger, TPR Comfort Grip, LED Working Light, Contact Safety, Nail Viewer Window, and Quick Release Magazine.

1. **ON/OFF Switch:** Powers the tool on or off.
2. **LED Indicator:** Shows power status and battery level.
3. **Type-C Port:** For charging the internal battery.
4. **Trigger:** Activates the stapling/nailing mechanism when contact safety is engaged.
5. **TPR Comfort Grip:** Ergonomic handle for comfortable use.

6. **LED Working Light:** Illuminates the work area.
7. **Contact Safety:** Must be pressed against the workpiece for the tool to fire.
8. **Nail Viewer Window:** Allows checking the remaining staples/nails.
9. **Quick Release Magazine:** For easy loading and unloading of fasteners.

3. SETUP

3.1 Charging the Battery

The staple gun is powered by an internal rechargeable battery. Before first use, fully charge the battery.

- Locate the Type-C charging port on the tool.
- Connect a compatible Type-C charging cable to the port and a power source.
- The LED indicator will show the charging status. Refer to the LED indicator section for details.
- A full charge provides over 1200 shots.

3.2 Loading Staples or Brad Nails

This tool is compatible with T50 Staples (1/4"-9/16") and 18GA Brad Nails (9/16"-5/8").

2-IN-1

CORDLESS STAPLER & NAILER



 **T50**
Staple
1/4"-9/16"

 **18GA**
Brad Nail
9/16"-5/8"

Figure 3.1: The BATAVIA Electric Staple Gun 0251 shown with compatible T50 staples (1/4"-9/16") and 18GA brad nails (9/16"-5/8").

1. Ensure the tool is turned OFF.
2. Locate the Quick Release Magazine at the bottom of the tool.
3. Press the release button or lever to open the magazine.
4. Insert a strip of compatible staples or brad nails into the magazine, ensuring they are oriented correctly (points facing forward).
5. Close the magazine securely until it clicks into place.
6. Use the Nail Viewer Window to confirm fasteners are loaded.

4. OPERATING INSTRUCTIONS

4.1 Powering On/Off

- To turn ON the tool, slide the ON/OFF switch to the 'ON' position. The LED indicator will light up.
- To turn OFF the tool, slide the ON/OFF switch to the 'OFF' position. The LED indicator will turn off.

4.2 Firing Staples/Nails



Figure 4.1: Illustration of the triple safety mechanism: 1. ON/OFF Switch, 2. Contact Safety, 3. Trigger.

1. Ensure the tool is loaded with the correct fasteners and powered ON.
2. Place the nose of the tool firmly against the workpiece, ensuring the Contact Safety is fully depressed.
3. Squeeze the Trigger to fire a staple or nail.
4. Release the trigger and lift the tool from the workpiece.

4.3 Using the LED Working Light

BRIGHT LED ILLUMINATION

SEE CLEARLY, FASTEN PERFECTLY



Figure 4.2: The integrated LED working light illuminates the fastening area for improved precision and visibility in low-light conditions.

The integrated LED working light automatically activates when the tool is in operation, providing illumination for precise fastening in dimly lit areas.

4.4 Using the Integrated Staple Remover



Figure 4.3: The integrated staple remover allows for easy and safe removal of staples from various surfaces.

The tool includes a separate, integrated staple remover for correcting mistakes or disassembling projects. To use:

1. Position the remover's prongs under the staple to be removed.
2. Apply gentle leverage to lift the staple from the material.

4.5 Recommended Applications and Limitations

PERFECT FOR

LIGHT DIY & CRAFT PROJECTS



NOT RECOMMENDED!

- Flooring
- Roofing
- Thick Carpet
- Hardwood

Figure 4.4: The BATAVIA Electric Staple Gun 0251 is suitable for light DIY and craft projects, such as upholstery and decorative work.

This tool is ideal for light DIY and craft projects, including:

- Upholstery
- Decorative work
- Light wood assembly
- Fabric fastening

Not Recommended For:

- Flooring
- Roofing
- Thick Carpet
- Hardwood

5. MAINTENANCE

5.1 Cleaning

- Always turn off the tool and remove any fasteners before cleaning.
- Wipe the tool's exterior with a clean, damp cloth. Do not use harsh chemicals or abrasive cleaners.
- Keep the magazine area free of dust and debris to prevent jamming.

5.2 Storage

- Store the tool in a dry, secure location, away from direct sunlight and extreme temperatures.
- Ensure the tool is turned OFF before storing.
- For long-term storage, charge the battery partially (around 50%) to prolong its lifespan.

5.3 Battery Care

- Do not expose the battery to water or excessive heat.
- Only use the provided or a compatible Type-C charger.
- If the tool will not be used for an extended period, recharge the battery every 3-6 months.

6. TROUBLESHOOTING

Problem	Possible Cause	Solution
Tool does not fire	Tool is OFF Battery is low or depleted Magazine is empty Contact safety not fully depressed	Turn ON the tool. Charge the battery. Load fasteners into the magazine. Press the tool firmly against the workpiece.
Fasteners jam in the tool	Incorrect fastener size/type Damaged fasteners Magazine not properly closed Debris in the magazine/firing mechanism	Ensure correct T50 staples or 18GA brad nails are used. Remove and replace damaged fasteners. Securely close the magazine. Clear any debris from the magazine and firing area (ensure tool is OFF and unloaded first).
Fasteners not fully driven	Battery is low Tool not pressed firmly enough Material is too hard for the tool	Recharge the battery. Apply more pressure to the tool against the workpiece. Ensure the material is suitable for this tool (refer to Section 4.5).

7. SPECIFICATIONS

Specification	Detail
Model Number	BTC0251-US
Brand	Batavia
Power Source	4V Rechargeable Battery (1 Nonstandard Battery included)
Compatible Fasteners	T50 Staples (1/4"-9/16"), 18GA Brad Nails (9/16"-5/8")
Operation Mode	Automatic
Material	Plastic
Product Dimensions (L x W x H)	17.78 x 15.24 x 0.25 cm (approximate)
Item Weight	454 g (approximate 1.0 lb)
Manufacturer	BATAVIA

8. WARRANTY AND SUPPORT

For warranty information, technical support, or service inquiries, please refer to the warranty card included with your product or contact Batavia customer service directly.

Please have your model number (BTC0251-US) and purchase date available when contacting support.

ASK A QUESTION ABOUT THIS MANUAL

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page’s manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. [Privacy details](#).

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question