

GOD PTT M77

GOD PTT M77 4G LTE PoC Walkie Talkie Instruction Manual

Model: M77 | Brand: GOD PTT

1. PRODUCT OVERVIEW

The GOD PTT M77 is a 4G LTE Push-to-Talk over Cellular (PoC) two-way radio designed for global communication. It utilizes cellular networks to provide unlimited range and clear voice transmission, making it an ideal tool for professional business communication.

Key Features

- **Global Communication PoC:** Enjoy unlimited range across states or continents with seamless global coverage via 4G-LTE cellular networks. Experience instant, real-time team coordination with crystal-clear HD voice.
- **Lifetime Free Service:** No monthly fees, activation charges, or renewal costs. All service plans are pre-activated before shipment, allowing immediate use.
- **Noise-Canceling Headset Included:** A professional noise-canceling headset is provided to effectively block background noise in loud environments, ensuring clear communication.
- **Power-Efficient Performance:** Equipped with a high-capacity 2500mAh battery, providing a full day of talk time and up to 7 days of standby on a single charge.
- **Effortless Multi-Device & Group Management:** Easily connect multiple devices and create custom groups by contacting customer support with your radio's box code or IMEI number.

Global Walkie-Talkie

4G PoC Enables Unlimited-Distance Two-Way Communication



Image: The GOD PTT M77 Global Walkie-Talkie, highlighting its global intercom, group creation, zero fees, signal boosting, sturdy casing, and one-touch intercom features.

Your browser does not support the video tag.

Video: An official seller video showcasing the 4G Lifetime SIM Card and global radio capabilities, reinforcing the lifetime free service feature.

2. INITIAL SETUP

What's in the Box

- 2 x GODPTT PoC Radio
- 2 x 2500mAh Battery
- 2 x USB Charger Cable & Adapter
- 2 x Belt Clip

- 2 x Hand Strap
- 1 x User Manual

M77 Two-Way Radio / Walkie-Talkie

Complete Package Contents Include



Image: A visual representation of all items included in the GOD PTT M77 package, such as the radios, batteries, charging cables, adapters, belt clips, hand straps, and the user manual.

Your browser does not support the video tag.

Video: An official seller video demonstrating the unboxing process of the M77 walkie-talkie, showing all included components.

Battery Installation

Carefully insert the 2500mAh Lithium-Ion battery into the designated compartment on the back of the radio. Ensure it is oriented correctly and clicks securely into place.

Charging the Device

Connect the radio to the provided USB charger cable and adapter. Plug the adapter into a standard wall outlet. The charging indicator light will show the charging status. A full charge ensures reliable communication for extended periods.



Image: A diagram illustrating the internal 2500mAh high-capacity battery, smart core chip with power saving mode, and Type-C fast charging capability of the M77 radio.

Initial Power-On and Network Connection

Press and hold the power button located at the top of the radio to turn it on. The device will automatically detect and connect to the 4G LTE network using the pre-activated SIM card. Allow approximately one minute for the initial network login and signal acquisition.

3. OPERATING INSTRUCTIONS

Device Layout and Controls



Image: A detailed diagram illustrating the key components and controls of your GOD PTT M77 radio, including the aerial, indicator light, power switch, headphone jack, speaker, LCD display screen, PTT button, side keys, menu, member key, select key, return key, group key, and Type-C port.

- **PTT Button:** Located on the left side. Press and hold to transmit your voice, then release to listen for a response.
- **Power Switch:** Located at the top of the radio. Rotate to turn the device on or off.
- **Volume Buttons:** Use these buttons to adjust the audio output level of the speaker or connected headset.
- **Menu Button:** Press to access the device's settings and configuration options.
- **Select/Navigation Keys:** Use the up/down arrow keys to navigate through menu options and the center key to select.
- **Headphone Jack:** Connect the included noise-canceling headset for private communication.
- **Speaker:** Provides audio output for incoming transmissions.
- **LCD Display Screen:** Shows important information such as network status, current group, member list, date, and time.
- **Side Keys 1 & 2:** These keys can be programmed for quick access to frequently used functions.

- **Return Key:** Press to go back to the previous menu or screen.
- **Group Key:** Use this key to switch between different communication groups.
- **Type-C Port:** Located at the bottom for charging the device.

Push-to-Talk (PTT) Communication

To initiate a conversation, press and hold the PTT button. Speak clearly into the microphone. It is recommended to pause for approximately one second after pressing the PTT button before speaking to ensure your message is transmitted completely. Release the PTT button to end your transmission and listen for a response.

Calling Modes

The M77 supports flexible communication modes:

- **1-on-1 Private Chat:** For direct, private communication with a specific individual within your network.
- **Group Chat Mode:** For broadcasting messages to all members of a pre-defined communication group.



Two Calling Modes

Use different intercom modes for different occasions

**1-on-1
Private Chat**

**Group
Chat Mode**

Management Account Creation Process

By default, we do not proactively create accounts. To protect user privacy, please contact us through Amazon or our official channels. We can create an account for you upon request; however, please provide the IMEI number of your two-way radio.

Image: The GOD PTT M77 radio screen illustrating the availability of two distinct calling modes: 1-on-1 Private Chat for individual conversations and Group Chat Mode for team communication.

Group Management

By default, your radios are configured to a specific group. If you need to connect multiple devices, create custom groups, or personalize radio names, please contact customer support via Amazon Message. Provide the box code printed on the package or the IMEI number of your two-way radio, and our support team will assist in setting up your communication network.

Your browser does not support the video tag.

Video: An official seller video providing a product showcase of the M77, demonstrating its features and functionality.

4. CARE AND MAINTENANCE

Battery Care

The 2500mAh battery is designed for long-lasting performance. To maximize battery life, avoid exposing the device to extreme temperatures (below 14°F or above 131°F). Always fully charge the device before extended use or storage.

Cleaning

To clean your radio, gently wipe the exterior with a soft, damp cloth. Do not use harsh chemicals, abrasive cleaners, or solvents, as these can damage the device. Ensure the charging port and headphone jack are kept free of dust and debris.

Durability

The M77 features a robust, shockproof, and drop-resistant design, providing enhanced protection against accidental falls, bumps, and daily impacts. While durable, it is recommended to handle the device with care to maintain its longevity.

Shockproof & Drop Resistant Design

Ultra Durable Drop Resistant Structure, Shockproof Protection Against Falls, Bumps and Daily Impact



5.0FT
Drop Resistant



Image: The GOD PTT M77 radio highlighted for its ultra-durable, drop-resistant structure and shockproof protection against falls, bumps, and daily impact, shown in an outdoor setting.

5. TROUBLESHOOTING COMMON ISSUES

No Network Connection

- Ensure you are in an area with active 4G LTE cellular service. The radio relies on cellular networks for its global communication capabilities.
- Restart the device by turning it off and then on again.
- If the issue persists, contact customer support for assistance.

Poor Audio Quality

- Check the volume settings on your radio and adjust as needed.
- If using the noise-canceling headset, ensure it is properly connected to the headphone jack.

- When transmitting, remember to pause briefly (about 1 second) after pressing the PTT button before speaking to ensure your message is fully captured.

Radios Not Communicating

- Verify that both radios are powered on and successfully connected to the 4G LTE network.
- Ensure both radios are assigned to the same communication group. If group settings need adjustment, contact customer support.

6. TECHNICAL SPECIFICATIONS

Feature	Specification
Brand	GOD PTT
Model Number	M77
Product Dimensions	1.46"D x 2.36"W x 5.4"H
Item Weight	0.35 Pounds
Number of Channels	200
Frequency Range	4G LTE POC
Talking Range Maximum	Unlimited (via 4G LTE network)
Voltage	3.7 Volts
Battery	2 x 2500mAh Lithium Ion (included)
Battery Average Life	5 days (standby)
Water Resistance Level	Not Water Resistant
Special Features	Active Noise Cancellation, Drop-resistant, Global Intercom, Shockproof
Connectivity Protocol	LTE
Temperature Range	14°F - 131°F (-10°C to +55°C)

7. WARRANTY AND CUSTOMER SUPPORT

Warranty Information

This GOD PTT M77 product comes with a **1-Year Manufacturer Warranty**. Please retain your proof of purchase for any warranty claims. The warranty covers manufacturing defects under normal use conditions.

Customer Support

For technical assistance, inquiries regarding group management, or any other support needs, please contact our dedicated customer support team:

- **Via Amazon Message:** Navigate to your Amazon account, go to "Your Orders", select "Get Help" for your M77 purchase, click "Other", then select "Seller" and send us your message.

- **Dedicated Support:** Our support team can assist with linking multiple devices into one group or creating custom groups upon request. Please provide the IMEI number of your two-way radio for efficient service.

ASK A QUESTION ABOUT THIS MANUAL

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. [Privacy details](#).

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question