

[Manuals.plus](#) /

> [TESSAN](#) /

> TESSAN Power Strip Tower JW402-IT Instruction Manual

TESSAN JW402-IT

TESSAN Power Strip Tower JW402-IT Instruction Manual

Model: JW402-IT

1. PRODUCT OVERVIEW

The TESSAN Power Strip Tower JW402-IT is a versatile power solution designed for home and office use. It features 8 Italian Schuko outlets, 3 USB-A ports, and 1 USB-C port, providing a total of 12 charging options. Equipped with a 5-meter extension cable and independent switches, this power strip offers convenience and safety for multiple devices.

12 IN 1 TORRETTA MULTIPRESA

Carica **12** dispositivi contemporaneamente



8



Presse Schuko
Italiana

3



USB A

1



USB C

2



Interruttore
ON/OFF

5M



Cavo

Image: TESSAN Power Strip Tower, showcasing its 8 Schuko outlets and 4 USB ports, ready to power multiple devices.

Key Features:

- **12-in-1 Power Solution:** 8 Italian Schuko outlets, 3 USB-A ports, and 1 USB-C port.
- **20W PD Fast Charging:** USB-C port and one USB-A port (A3) deliver up to 20W for rapid charging of compatible devices.
- **5-Meter Extension Cable:** Provides extended reach for flexible placement.

- **Independent Switches:** Two separate ON/OFF switches for controlling groups of outlets, enhancing energy efficiency and safety.
- **Comprehensive Safety Protection:** Includes overload protection, short-circuit protection, lightning protection, and over-temperature protection.
- **Space-Saving Design:** Vertical tower design with 45-degree angled outlets prevents plugs from blocking each other.

2. SAFETY INSTRUCTIONS

- Do not exceed the maximum rated power of 2500W (10A, 110-250V~).
- Do not use in wet environments.
- Keep away from children.
- Do not disassemble or modify the product.
- Ensure plugs are fully inserted into the outlets.
- Unplug the power strip from the wall outlet when not in use for extended periods.

PROTEZIONE **CONTINUA 24/7** PER I TUOI DISPOSITIVI



Image: Visual representation of the power strip's continuous 24/7 protection features, including overload, short-circuit, over-temperature, and lightning protection, along with child safety and fire-retardant materials.

3. SETUP

1. **Unpack:** Carefully remove the power strip from its packaging.
2. **Placement:** Place the power strip on a stable, dry surface, away from heat sources and direct sunlight. The 5-meter

cable allows for flexible positioning.

3. **Connect to Wall Outlet:** Plug the power strip's main plug into a grounded wall outlet.

4. **Connect Devices:**

- Insert appliance plugs into the 8 Schuko outlets. The 45-degree angled design helps prevent overcrowding.
- Connect USB-powered devices to the 3 USB-A ports or the 1 USB-C port.



Image: The TESSAN Power Strip with its 5-meter extension cable, demonstrating its reach and flexibility for placement in various scenarios, such as a living room setup.

4. OPERATING INSTRUCTIONS

Powering Devices:

1. After plugging in your devices, press the corresponding ON/OFF switch to activate the outlets. The power strip features two independent switches, allowing you to control different sets of outlets.
2. A red indicator light will illuminate when the power strip is active.



Image: Detail of the two independent ON/OFF switches located on the top of the power strip, allowing for separate control of connected devices.

USB Charging:

- **USB-C Port:** Provides up to 20W Power Delivery (PD) for fast charging compatible smartphones, tablets, and other USB-C devices.
- **USB-A3 Port:** Also provides up to 20W for fast charging compatible devices.
- **USB-A1 & USB-A2 Ports:** Combined output of up to 12W for standard charging of various USB devices.

- Simply connect your device's USB charging cable to the appropriate port.



Image: The TESSAN Power Strip actively charging a tablet via USB-C and other devices, highlighting the 20W PD fast charging capability and the different USB port outputs.

5. MAINTENANCE

- **Cleaning:** Disconnect the power strip from the wall outlet before cleaning. Use a dry, soft cloth to wipe the surface.

Do not use liquid cleaners or abrasive materials.

- **Storage:** When not in use, store the power strip in a cool, dry place, away from dust and moisture.
- **Inspection:** Periodically inspect the power cord and the power strip for any signs of damage. If damage is found, discontinue use and contact customer support.

6. TROUBLESHOOTING

Problem	Possible Cause	Solution
No power to outlets/USB ports.	<ul style="list-style-type: none">• Power strip not plugged in.• ON/OFF switch is off.• Overload protection triggered.• Wall outlet has no power.	<ul style="list-style-type: none">• Ensure the power strip is securely plugged into a live wall outlet.• Press the ON/OFF switch to the 'ON' position.• Unplug some devices, then press the reset button (if available) or cycle the power switch.• Test the wall outlet with another device.
Devices not charging via USB.	<ul style="list-style-type: none">• Incorrect USB cable.• Device not compatible with fast charging.• USB ports overloaded.	<ul style="list-style-type: none">• Use a high-quality, compatible USB cable.• Ensure your device supports the charging protocol (PD for USB-C).• Reduce the number of devices charging simultaneously.
Power strip feels hot.	<ul style="list-style-type: none">• Overloaded.• Poor ventilation.	<ul style="list-style-type: none">• Unplug some devices to reduce the load.• Ensure the power strip is in a well-ventilated area.• If overheating persists, discontinue use immediately.

7. SPECIFICATIONS

Feature	Detail
Model Number	JW402-IT
Brand	TESSAN
AC Outlets	8 Italian Schuko Sockets
USB Ports	3 x USB-A, 1 x USB-C
USB-C Output	20W Max
USB-A3 Output	20W Max
USB-A1 & USB-A2 Combined Output	12W Max
Rated Power	2500W (10A, 110-250V~)
Cable Length	5 Meters
Special Features	Independent ON/OFF Switches, Overload Protection, Short-circuit Protection, Lightning Protection, Over-temperature Protection
Color	Grey

Feature	Detail
Compatible Devices	General electronic devices

8. WARRANTY AND SUPPORT

TESSAN products are designed for reliability and performance. This product typically comes with a standard manufacturer's warranty. Please refer to the warranty information provided with your purchase or visit the official TESSAN website for details regarding warranty terms and conditions.

For technical support, troubleshooting assistance, or warranty claims, please contact TESSAN customer service through their official website or the retailer from whom you purchased the product. Have your model number (JW402-IT) and purchase details ready when contacting support.

Manufacturer: Dongguan JunWei Electronics Co.,Ltd

