

SEDETA Standing Desk

SEDETA L-Shaped Electric Standing Desk User Manual

Model: Standing Desk (Black + Brown)

1. PRODUCT OVERVIEW

This manual provides instructions for the assembly, operation, and maintenance of your SEDETA L-Shaped Electric Standing Desk. This desk is designed to offer a versatile workspace with adjustable height, integrated storage, and convenient power access.

Key Features:

- **Spacious L-Shaped Desktop:** Provides ample surface area for multiple monitors and office equipment.
- **Integrated Storage:** Features 6 large drawers (3 on each side) for organized storage of documents and supplies.
- **Electric Height Adjustment:** Smooth and quiet motor for effortless transitions between sitting and standing positions (28.3" to 47.2").
- **Memory Presets:** Three programmable memory height settings for quick adjustments.
- **Built-in Power Outlets:** Includes 4 AC outlets (120V/12A) and 2 USB ports (5V/2A) with a 6.5-foot power cord.
- **Durable Construction:** Heavy-duty steel frame supports up to 200 lbs, with a scratch-resistant, FSC-certified engineered wood desktop.



Image 1.1: The SEDETA L-Shaped Electric Standing Desk in a home office environment.

2. SAFETY INFORMATION

- Read all instructions carefully before assembly and use.
- Keep children and pets away from the desk during operation.
- Ensure all cables are properly managed to prevent tripping hazards and entanglement during height adjustments.
- Do not overload the desk. The maximum load capacity is 200 lbs (90.7 kg).
- Avoid placing liquids directly on the desk surface, especially near power outlets.
- Do not attempt to disassemble or repair the motor or control system yourself. Contact customer support for assistance.
- Ensure the desk is placed on a level surface.

3. ASSEMBLY INSTRUCTIONS

The SEDETA L-Shaped Electric Standing Desk ships in two boxes and includes all necessary hardware and an installation manual. Follow the detailed instructions provided in the separate installation manual for proper assembly.

3.1. Before You Begin:

- Unpack all components and verify against the parts list in the installation manual.
- Ensure you have adequate space for assembly.
- Gather any additional tools that may be required (e.g., screwdriver, if not included).

3.2. Key Assembly Steps (Refer to separate manual for details):

- 1. Assemble the desk frame components.
- 2. Attach the lifting columns to the frame.
- 3. Mount the desktop sections onto the frame.
- 4. Install the 6 drawers into their respective cabinets.
- 5. Connect the motor and control panel cables.
- 6. Install the built-in power outlet unit.



Image 3.1: Product dimensions and drawer sizes. The desk ships in two boxes.



Heavy Coated Steel Tube Frame



65mm X 45mm industrial
Frame for 200lbs Support



Gap less
than 0.01"



60000+ Lift Tests
Under Full Load

Image 3.2: Detail of the heavy-coated steel tube frame, indicating durability and load capacity.

4. OPERATING INSTRUCTIONS

4.1. Control Panel Overview

The desk features a multi-function control panel for height adjustment and memory presets.

Multi-Function Control Panel



Image 4.1: Multi-Function Control Panel.

- **Digital Screen:** Displays the current desk height.
- **Up/Down Arrows (▲ / ▼):** Press and hold to adjust the desk height manually. Release to stop.
- **Memory Buttons (1, 2, 3):** Store and recall preferred height settings.
- **'S' Button (Set):** Used to save memory presets.
- **'RST' Button (Reset):** Used for resetting the desk (see Troubleshooting).

4.2. Adjusting Desk Height

- **Manual Adjustment:** Press and hold the Up (▲) or Down (▼) arrow button to move the desk to your desired height. Release the button to stop. The desk height ranges from 28.3 inches to 47.2 inches.
- **Using Memory Presets:**
 1. To save a height: Adjust the desk to your desired height using the Up/Down arrows. Press the 'S' button, then press one of the memory buttons (1, 2, or 3) within 3 seconds. The display will show "S-1", "S-2", or "S-3" to confirm the setting is saved.
 2. To recall a height: Simply press the corresponding memory button (1, 2, or 3). The desk will automatically move to the saved height.



Image 4.2: Flexible desk height adjustment from 28.3" to 47.2".

Your browser does not support the video tag.

Video 4.1: Demonstration of the SEDETA L-Shaped Electric Standing Desk's smooth height adjustment and stability.

4.3. Using Built-in Power Outlets

The desk includes an integrated power strip for convenient device charging.



Built-in Power Outlet



4 AC Outlets
120V / 12A



2 USB Ports
5V / 2A



Switch
On / off



Power Cord
6.5-Foot

Image 4.3: Built-in power outlet with 4 AC outlets and 2 USB ports.

- The power strip features 4 standard AC outlets (120V/12A) and 2 USB charging ports (5V/2A).
- Use the integrated switch to turn the power outlets on or off.
- Connect the desk's main power cord (6.5-foot) to a wall outlet.

4.4. Drawer Usage

The desk features 6 spacious drawers for organizing your workspace.



Image 4.4: Organized workspace with open drawers.

- Each side of the L-shaped desk includes three drawers.
- Ensure drawers are closed before adjusting desk height to prevent items from falling.

5. MAINTENANCE

- **Cleaning:** Wipe the desk surface with a damp cloth for general cleaning. For stubborn marks, use a mild cleaner. Dry immediately with a clean, dry cloth.
- **Inspection:** Periodically check all screws and connections to ensure they are tight. Retighten if necessary.
- **Cable Management:** Regularly inspect power cords and cables for any signs of wear or damage. Replace if necessary. Ensure cables are not pinched or stretched during height adjustments.
- **Motor Care:** The electric motor is designed for long-term use. Avoid continuous operation for extended periods without rest.

6. TROUBLESHOOTING

If you encounter issues with your SEDETA Electric Standing Desk, refer to the following common troubleshooting steps:

Problem	Possible Cause	Solution
Desk does not move.	<ul style="list-style-type: none"> Power cable disconnected. Overload protection activated. Control panel error. 	<ul style="list-style-type: none"> Check if the power cable is securely plugged into the wall outlet and the desk. Reduce the weight on the desk. Perform a reset (see below).
Display shows an error code (e.g., E01, E02).	Specific error detected by the control system.	<ul style="list-style-type: none"> Refer to the separate installation manual for specific error code meanings. Try performing a reset. If the error persists, contact customer support.
Desk moves unevenly or makes unusual noises.	<ul style="list-style-type: none"> Loose connections or uneven load. Obstruction in the lifting mechanism. 	<ul style="list-style-type: none"> Check and tighten all assembly screws. Ensure the desk is evenly loaded. Inspect the lifting columns for any obstructions.
Power outlets not working.	<ul style="list-style-type: none"> Power switch off. Desk not plugged in. 	<ul style="list-style-type: none"> Ensure the power switch on the built-in outlet unit is ON. Verify the desk's main power cord is plugged into a live wall outlet.

6.1. Reset Procedure

If the desk is not functioning correctly, a reset may resolve the issue:

1. Press and hold the 'RST' button on the control panel until the desk moves to its lowest position and then slightly rises.
2. Release the button. The desk is now reset.
3. If the reset fails, unplug the desk from the wall outlet for 10-15 minutes, then plug it back in and attempt the reset procedure again.

7. SPECIFICATIONS

Feature	Detail
Brand	SEDETA
Model Name	Standing Desk

Feature	Detail
Color	Black + Brown
Shape	L-Shape
Product Dimensions (D x W x H)	57.1" x 66.9" x 28.3"
Adjustable Height Range	28.3" - 47.2"
Item Weight	162 Pounds (73.5 kg)
Maximum Load Capacity	200 lbs (90.7 kg)
Number of Drawers	6
Base Material	Engineered Wood, Steel Frame
Top Material Type	Engineered Wood (FSC-certified)
Power Outlets	4 AC (120V/12A), 2 USB (5V/2A)
Noise Level (Operation)	<30dB
Assembly Required	Yes (All tools included)

8. WARRANTY AND SUPPORT

SEDETA is committed to providing quality products and customer satisfaction.

- **Warranty:** This product comes with a 3-year service commitment. For detailed warranty terms and conditions, please refer to the documentation included with your purchase or contact customer support.
- **Customer Support:** If you have any questions, require assistance with assembly, or experience any issues with your desk, please contact the seller, goodgoodsstore, through your purchase platform or refer to the contact information provided in your product packaging.
- Please have your purchase details and model number (Standing Desk) ready when contacting support.