

 Crystal Vision  
**CVT Series 3MP IP  
Camera**



# Crystal Vision CVT Series 3MP IP Camera Owner's Manual

[Home](#) » [Crystal Vision](#) » Crystal Vision CVT Series 3MP IP Camera Owner's Manual 

## Contents

- [1 Crystal Vision CVT Series 3MP IP Camera](#)
- [2 General Description](#)
- [3 Add Camera](#)
- [4 Image Setting](#)
- [5 Panic Siren Button](#)
- [6 Two-Way Communication](#)
- [7 Sound Recording](#)
- [8 Specification](#)
- [9 Documents / Resources](#)
  - [9.1 References](#)
- [10 Related Posts](#)




**Crystal Vision CVT Series 3MP IP Camera**






## General Description



1. The camera comes with two major parts; the camera and the power adapter.
2. Please note that the camera cable has two ends: one for the power cable and the other has the Reset button inside.
3. Please make sure all the connections are tight as possible and it is recommended that you secure the connection with electrical tape as you see it.
4. Use the included extension power cable(15ft) if necessary. You may connect up to four 15 ft extension cables(60 ft).


**NOTE:** Please try to protect your power source from moisture and other foreign elements.

## Add Camera



**TIP:** If you are replacing a camera, please delete the camera from the connected camera table first, to make room for a new camera.




1. First, set the camera next to the NVR and power up the camera.
2. Check the status light on the camera to confirm that it is in “sync” mode, indicated by rapid blinking.
3. Click  the button on the menu bar.
4. Click the “Continue” button to start searching for new cameras  
TIP: \* If the system does not find the camera, please press and hold the Reset Button on the camera for about 10 seconds to reset the camera
5. Wait for the NVR to automatically search for cameras for 30 to 40 seconds. your camera should appear in an empty channel in the table.
6. Click the “continue” button to proceed. Check the live view for the newly-added camera to confirm that it is connecting properly

## Image Setting

(For CVT-35WB, CVT23PWBU, CVT-37WPT Cameras Only)


Smart night vision mode allows the camera to detect motion and automatically turn on a bright floodlight when it detects any movement in its range of view.



## Panic Siren Button

(For CVT-35WB, CVT23PWBU, CVT-27WIPT, CVT-37WPT Only)

panic siren button function on a surveillance camera is a feature that allows the camera to emit a loud and attention-grabbing siren in case of an emergency or intrusion.



The Panic Siren Button for all connected cameras is a feature that allows the user to activate a loud siren on all cameras simultaneously by pressing a button on the menu Bar.

## Two-Way Communication


(CVT-35WB, CVT23PWBU, CVT-27WIPT, CVT-37WPT Only)

1. To use the two-way communication function through the Eseecloud app, you need to first connect your system to the app on your smartphone. Once your system is connected, you can select the specific camera you would




like to use to speak.

2. Simply press and hold the talk button in the app while speaking. Once you release the button, you can hear what the person in the scene is saying through the speaker on your phone
3. Once the conversation is over, click the Hang up button to end the communication.



## Sound Recording

(CVT-35WB, CVT23PWBU, CVT-27WIPT, CVT-37WPT only)

1. Click  on Menu Bar> click Camera > Select channel you want to record audio sound > Click Keep Recording > enable Sound Record
2. Click Save changes

## Specification

CVT-30WB

Image Sensor:	3MP 1/3 CMOS
shutter:	Adaptive Shutter
Lens:	4mm F2.0
Night View:	ICR Infraed
Video Compression:	H.265/H.264
Main Stream:	2304x1296@15fps
Sub Stream:	640x480@15fps
WiFi Band:	2.4G
Wireless Standard:	IEEE802.11b,g,n
Operating Temp:	-20 ~50 95% Humidity
Powe supply:	DC12V1A
Protection Level:	IP66

**CVT-35WB / CVT23PWBU**  
**CVT-27WIPT / CVT-37WPT**

## Specification



Image Sensor:	3MP 1/3 CMOS	Smart Siren:	100 Decibel
shutter:	Adaptive Shutter	Recording:	Continuous, Motion-triggered Recording
Lens:	4mm F2.0	Night View:	Smart, Full Color Night View
Night View:	ICR Infraed up to 70ft	Other Alerts:	Push notification to the APP
Video Compression:	H.265/H.264	Main Stream:	2304x1296@15fps
Field of View:	70°	Sub Stream:	640x480@15fps
Min. Illumination:	Color: 0.1Lux, BW: 0.01Lux	Wireless Security:	WPA-PSK/WPA2-PSK
WiFi Band:	2.4G (IEEE802.11b,g,n)	Audio Format:	AAC, G711
Audio:	Built-in Mic and Speaker	Power Consumption:	15W
Operating Temp:	-20 ~50 95% Humidity	CVT-27WIPT Pan, Tilt:	Up to 355° , Up to 75°
Powe supply:	DC12V1A	CVT-37WPT Pan, Tilt:	Up to 263° , Up to 90°
Protection Level:	IP66		

**Our Help Center page offers FAQs, downloads, and a Contact Us section**

For the Help Center Scan the QR Code



## Need More?



Crystal Vision Technology, Inc  
[support@cvtus.com](mailto:support@cvtus.com)

## Documents / Resources

[illegible]

## References

- [User Manual](#)

**Manuals+, Privacy Policy**

This website is an independent publication and is neither affiliated with nor endorsed by any of the trademark owners. The "Bluetooth®" word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. The "Wi-Fi®" word mark and logos are registered trademarks owned by the Wi-Fi Alliance. Any use of these marks on this website does not imply any affiliation with or endorsement.