



## EuroFone S6-1200M Multi-Intercom Helmet Bluetooth Headset User Manual

[Home](#) » [eurofone](#) » EuroFone S6-1200M Multi-Intercom Helmet Bluetooth Headset User Manual 



### S6-1200M Multi-Intercom Helmet Bluetooth Headset User Manual



Thank you for choosing our EUROFONE S8 motorcycle helmet Bluetooth intercom headset. Please carefully read this manual. S6 is a perfect Bluetooth intercom, with a more stylish design and big buttons to operate. After the six Bluetooth headphones are paired separately, they support speaking with the other 5 people respectively. During the cycle operation process, it provides you with a complete communication system to meet all your communication needs. High-quality 40MM speaker and noise reduction filters that will allow you to listen to cell phone MP3 music, GPS voice navigation, and answer cell phone calls. More importantly, it can be compatible with other brands of helmet Bluetooth headset connectivity or normal Bluetooth headset, allowing you to keep in touch with your friends during the ride.

**For People:** Helmet of Motorcycle, bicycle, skiing, electric motorcycle, construction, mining workers, fire fighting, traffic police and so on.

**Main performance and specifications:**

The maximum call distance between the two riders, up to 1200 meters, supports pairing with 5 Bluetooth headphones with full dual wireless communication between any two riders

**maximum noise reduction speed: 120km/ h**

**Automatically answer mobile phone calls and ride safely**

**Bluetooth CSR BC8 CVC8.0 automatic noise reduction scheme**

**Advanced A2DP & EDR Bluetooth features**

**Strong shaking stereo music /audio features (the phone I MP3/GPS using A2DP)**

**DSP noise elimination function**

**The built-in polymer lithium battery is 800mAh**

**Standby time: 400 hours**

**Continuous calls or intercom for more than 22 hours**

**Listen to the music for over 72 hours continuously**

**Charging time is 2.5 hours**

**National Grade 6 waterproof standard**

## Contents

- [1 Buttons Function Introduction](#)
- [2 How to Install It](#)
- [3 Function and Operation Methods](#)
- [4 Pairing with Mobile Phone and Headsets](#)
- [5 Pair with other Brand Helmet Bluetooth Headset](#)
- [6 Battery Description](#)
- [7 Product Specifications](#)
- [8 Bluetooth Status Indication and Prompt](#)
- [9 Documents / Resources](#)
- [10 Related Posts](#)

## Buttons Function Introduction



[Fig.1.

1. Power OcV0fl Button
2. Multi-Function Button /Play Button
3. Volume Up +
4. Volume Down
5. Charging Jack! headphone Jack (Micro Interlace)
6. The A. B, C. D. E intercom Buttons
7. Hard microphone. Soft microphone (replaceable)
8. Stereo Ear Speaker

## How to Install It

**2.1. Screwdrive installation:** Loosen the clip screw clockwise with the provided screwdriver along the arrow, open the fining of the helmet, install the dip on the left, tighten the screw (screw will damage the dip), and slide the Bluetooth host into the slot on the dip holder to ensure that it is firmly locked.for example[Figure1.



(Figure 1.)

**2.2. Installation of the Magic stick clip:** Wipe the helmet, then tear off the white paper on the dip, stick the host to the right left side of the helmet, and then point the Bluetooth headset at the card slot of the dip. and push it in place. (Recommended to stica k 3M Sticker to the helmet for 24 hours). such as (Figure 2)



(Figure 2.)

**2.3. Headphone Installation:** open the helmet lining, find the helmet closest to the ear, and clean the magic patch surface. paste the speaker corresponding to the magic cap patch and arrange the helmet lining. insert the headset plug into the corresponding Bluetooth host headset socket, inert can be metaled. such as (Figure 3).



## Function and Operation Methods

**3.1.1 Power on:** under the shutdown state, press the power button for 2 seconds. you can listen to “power co”. After the device starts and hears the power broadcast, it will automatically switch to Bluetooth pairing mode.

**3.1.11 Power off** in start-up state, press the power button for 5 seconds. hear ‘power off, and the equipment turns off

**3.1.3 Answer the Call:** Press Play briefly to answer the call; automatically after 10 seconds after any operation.

**3.1.4 Rejects a Call:** Press Play for 2 seconds.

**3.1.5 Audio Assistant:** When the headset connects to the phone on standby. Press the Play key for 2 seconds (this function requires the phone to support voice dialing)

**3.1.6 Termination:** Press Play briefly during the call.

**3.1.7 End Radial:** In connected. double-click Play.

**3.1.8 Music Play/Pause:** Mobile phone music. short press Play, music pause. the repeated operation, music play.

**3.1.9 Up Next:** Volume-, last sang, Volume +. next song.

**3.1.10 Increase/Decrease Volume:** In musk, press the volume +, and make the volume up. Press the volume -, and the volume decreases. The volume moves to maximum or maximum and a lick’ is heard.

**3.1.11. Initiate and End Intercom Mode:** in pairing state. briefly press A, B, C, 0, and E to initiate Intercom; in intercom mode. briefly press the Play key to end the intercom. **3.1.12 Phone. Intercom, Musk switch:** when listening to music or Bluetooth intercom, call wit automatically switch to the phone state. when the call. automatically restore the phone state; want to talk to A. press A button, went to speak to B. press B button.. (must pair with MEACW.AE first), will enter the intercom slate, and then press Play button, intercom end, press more Play button, the music automatically resins playback;

**Note:** It takes about 5 seconds to swltdi between each state.

**3.1.13. Chinon and English Language Switch:** in pairing mode, double-ack the volume Up + and volume Down- (Customize other languages, the customer provide the language voice List).

**3.1.14. Restore factory settings:** In pelting mode, press volume • and Play for 5 seconds.

## Pairing with Mobile Phone and Headsets

### 4.1. Pairing with Mobile phone

**4.1.1** The needs a paired Bluetooth headset within 1 meter away from the phone with Bluetooth.

**4.1.2 In shutdown state.** Press the power button for 5 seconds, and the red and blue lights flash

**4.1.3** Turns on the phone with Bluetooth, and the phone automatically searches for Bluetooth headset devices.

**4.1.4.** Selects “S6’ Bluetooth device and matches, and will hear the voice of Bluetooth is connected”. The Bluetooth headset is successfully paired with the mobile phone, which can bare\* and answer the mobile phone through the Bluetooth headset

### 4.2. Two Bluetooth Intercom Pairing

**4.2.1** Two Bluetooth headphones to be paired are placed within a visual range of 1 meter apart.

**4.2.2** Press the Power On button for 2 seconds. blue light. name automatically play after power. Into the red and blue light flash, and press the A button of any Bluetooth headset, and the Bluetooth headset flash for about 3 seconds. enter the intercom peering mode. Power on another Bluetooth headset and pairing mode. no operation, to be searched, the red and blue light flashing and hear the Intercom connected prompt, that is Into the Intercom mode (intercom pairing for 120 seconds. intercom pairing will automatically exit the intercom paining mode and pro, not connection timeout).



## 2 Bluetooth Headset Pairing

4.2.3 In intercom mode, the ear opportunity has the intercom prompt voice: the intercom is connected", which means that Bluetooth pairs connect the headset successfully, so you can make the intercom. Press Play short to close the Intercom.

4.2.4. intercom: after the intercom or two paired Bluetooth headsets restart, want to speak again, just press the A button once (must remember which button paired, press which button), the main opportunity to prompt voice: "start Intercom", two Bluetooth can hear "Intercom already connected", then can speak.

### 4.3. 6 Bluetooth Headsets Pairing

The S6 supports 6 Bluetooth headphones to be paired with each other and realize the switch pair between every two knights. The matching method is to take a Bluetooth headset as the host. The host must be paired with the other five Bluetooth headphones respectively. The steps are as follows:



( 6 Bluetooth Headsets Pairing )

4.3.1. Paired with A, two Headsets power on to pairing state, press A button of A machine and PLAY key, enter Intercom mode for 3 seconds. Short press the PLAY button. finish the Intercom and turn off the A.

4.3.2. Paired with B. two Headsets power on to pairing state. Press the B button of the B machine and the PLAY key. enter intercom mode for 3 seconds. Short press the PLAY button, finish the intercom and turn off the B.

4.3.3. Paired with C. two Headsets Power on to pairing state, press the C Button of C, and enter intercom mode for 3 seconds. Short press the PLAY button to finish the intercom and shut off C.

4.3.4. Paired with D, two Bluetooth power on to pairing state, press D key of D machine and PLAY key, and enter Intercom mode for 3 seconds. Short press the PLAY button to finish the intercom and turn off the D.

4.3.5. Paired with E. two Bluetooth power on to the pairing state. and press the E key and PLAY button of the E machine, and enter the intercom mode for 3 seconds, you can speak.

4.3.6. After the host is paired with A. B. C. D. E 5 Bluetooth headsets, press A. B. C. D, for 3 seconds. Power on all



of them. When the host wants to talk to A. only press A: want to speak to B. only press B, and so on.

4.3.7. If A wants to speak to B, C, D, E, A must be paired with the 8, C, D, E like as the first host. The same for B. C. D. E. operating with the matching method of the fast host.

## Pair with other Brand Helmet Bluetooth Headset

### For Example: Paired with V6-1200

5.1.1. S6 and any other brand of Bluetooth intercom headset are placed within 1 meter apart



5.1.2. Press the V8-1200 Power button. long until the red light flashes and loose. Bluetooth on. long-press any B. C. D. E on the host panel, and red and blue lights flash to enter the paid® mode.

5.1.3 long-press the S6 power button for 3 seconds to see the blue light for 2 seconds to lose, will listen to the POWER ON prompt, and then play power. such as connected to the phone, cannot find the phone and turn to the red-blue light flashing, Into the pairing state, now press A and Play for 3 SeCOnds. Play button with blue light flashing. into intercom pairing mode, about 120 seconds. V6-1200 blue light, two Bluetooth headsets pairing successfully. S8 will have a prompt voice: ' the intercom is connected', directly Into the intercom mode, you can call the Intercom. The V8-1200 has no voice prompt.



**5.1.4. Briefly Press the SS Play Key to End the Intercom:** to speak again, press the B key of Se (which key to press the intercom. V6-1200 can not actively initiate or end poking with other Bluetooth headphones. so it does not support pairing with other brands of Bluetooth headset).

## Battery Description

Using a polymer battery, make sure to place it in a dry place. If not used for more than three months, charge it once a month to ensure the service life of the product.

## Product Specifications

Bluetooth Version: 5.1V  
Bluetooth protocol Profile:HSP,HFP,A2DP,AGHSP  
People Intercom Distance: 12.00m  
Standby time: 400 hours  
Working hours:22 hours  
Charging time: 2.5 hours  
Charging Interface/headphone Interface: Android universal plug  
Battery type: Rechargeable lithium polymer battery.800mAh  
Poway supply requirements:5V=1A  
Operating temperature: -4F~131F-(10°C~55°C)  
Storage tomponetuee: -4F-140F (-20°C~60°C)

### Codification: CE, CE-UK, ROHS, FCC. TELEC (available)

• The actual time may vary depending on the type of phone and usage state. If the working distance of \* is without obstacles, some deviation occurs due to environment and climate.

### Notes

- 8.1. The applicable storage temperature of this product is-20 °C to 60 °C, do not store in too high a temperature or too low an environment, otherwise, it will affect the service life of the product;  
8.2. Do not Expose this Product to an Open Fire to Avoid Explosion;  
8.3. If the Product is not Used for a Long Time, Please Store it in a Dry Place and Charge the Product Regularly (once in three months) to Ensure That the Product Works Normally.

## Bluetooth Status Indication and Prompt

- 9.1. Turn on ("Bluetooth connected" when Bluetooth is connected, and the blue indicator flashes once every 10 seconds);  
9.2. When Bluetooth disconnects from the phone, you hear "pairing mode" and the red and blue lights flash alternately.  
9.3. Low power alarm (prompt "Low battery power, please charge" every 60 seconds)  
9.4. Charging state (the red light is long when charging, the red light of the blue light is often lit.Out in 8 seconds.  
).  
9.5. Power on power voice prompt Please charge from 100% power to 10%.

## product quality warranty card

<b>Customer Nerve: Canoed Address:</b>	<b>Contact telephone number: Product model:</b>
<b>Problem description:</b>	

### Warranty Description:

Thank you for purchasing S6 products, to ensure your legitimate interests, please read the following:  
This card is the product warranty certification. When the product needs maintenance, please provide the card together with the product. This card is only valid for products under the warranty, as shown below:

1. Products of the Company obtained through legal and formal channels;
2. Non-human damaged products include, but are not limited to the case of improper disassembly and use of natural disasters, not within the scope of warranty;
3. Not exceeding the product warranty period; Notes include, and are not limited to, the above. The Company reserves the right of final interpretation.

FCC Statement This equipment has been tested and found to comply with the limits for a Class Rdigiud device. pursuant to part I5 of the FCC Rules. These limits are designed to provide reasonable protection against h: until interference in a residential installation. This equipment generates. uses and can radiate radio frequency energy and. if not installed and used in accordance with the instructions. may cause harmful interference to radio communications. However. there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception. which can be determined by turning the equipment off and on. the user is encouraged to try to correct the interference by one or more of the following measures

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

**Caution:** Any changes or modifications to this device not explicitly approved by the manufacturer could void your authority to operate this equipment. This device complies with pan 15 of the FCC Rules. Operation is subject to the following two conditions

1. This device may not cause harmful interference. and
2. this device must accept any interference received. including interference that may cause undesired operation.

**RF Exposure Information**

The device has been evaluated to meet general RF exposure requirements. The device can be used in portable exposure conditions without restriction.

CE CE-UK ROHS FCC BQ

**Documents / Resources**

	<p><a href="#">EuroFone S6-1200M Multi-Intercom Helmet Bluetooth Headset</a> [pdf] User Manual S6-S2, S6S2, 2A68V-S6-S2, 2A68VS6S2, S6-1200M, Multi-Intercom Helmet Bluetooth Headset, S6-1200M Multi-Intercom Helmet Bluetooth Headset</p>
---	---