




HANNSpree HE247HFB Smart LED Monitor User Manual

[Home](#) » [HANNSpree](#) » HANNSpree HE247HFB Smart LED Monitor User Manual 

Contents

- 1 HANNSpree HE247HFB Smart LED Monitor
- 2 RECYCLING INFORMATION
- 3 SAFETY NOTICE
- 4 SPECIAL NOTES ON LCD MONITORS
- 5 BEFORE YOU OPERATE THE MONITOR
- 6 POWER
- 7 SETTING THE MONITOR ON THE WALL
- 8 MAKING CONNECTIONS
- 9 OPERATING INSTRUCTIONS
- 10 FRONT PANEL CONTROL
- 11 HOW TO ADJUST A SETTINGS
- 12 PLUG AND PLAY
- 13 TECHNICAL SUPPORT (FAQ)
- 14 ERROR MESSAGE & POSSIBLE SOLUTIONS
- 15 APPENDIX SPECIFICATIONS
- 16 Documents / Resources
- 17 Related Posts



HANNSpree HE247HFB Smart LED Monitor



- Before operating the monitor, please read this manual thoroughly. This manual should be retained for future reference.
- This device complies with requirement of EMC directive 2014/30/EU with regard to Electromagnetic Compatibility, and 2014/35/EU and 93/68/EEC with regard to Low Voltage directive.
- Socket-outlet shall be near the equipment and shall be accessible.
- **Trademark Notice:**
 - HANNSpree products incorporate High-Definition Multimedia Interface (HDMI TM) technology.
 - The terms HDMI and HDMI High-Definition Multimedia Interface, and the HDMI Logo are trademarks or registered trademarks of HDMI Licensing LLC in the United States and other countries.

RECYCLING INFORMATION

- We, at HANNSpree care very much about our environment protection strategy and firmly believe that it helps us have healthier earth via appropriate treatment and recycling of industrial technology devices at the end-of-life.
- These devices contain recyclable materials, which can be re-decomposed and re-integrated into brand-new marvels. On the contrary, other material can be classified to hazardous and poisoned substances. We strongly encourage you to contact the provided information to recycle this product.
- For more information, please visit <http://www.hannspree.eu/>

SAFETY NOTICE

1. The changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.
2. Shielded interface cables and AC power cord, if any, must be used in order to comply with the emission limits.
3. The manufacturer is not responsible for any radio or TV interference caused by unauthorized modification to this equipment. It is the responsibilities of the user to correct such interference.
4. Only use attachments/accessories specified by the manufacturer.

WARNING:

To prevent fire or shock hazard, do not expose the monitor to rain or moisture. Dangerously high voltages are

present inside the monitor. Do not open the cabinet. Refer servicing to qualified personnel only.

PRECAUTIONS

- Do not use the monitor near water, e.g. near a bathtub, washbowl, kitchen sink, laundry tub, swimming pool or in a wet basement.
- Do not place the monitor on an unstable cart, stand, or table. If the monitor falls, it can injure a person and cause serious damage to the appliance. Use only a cart or stand recommended by the manufacturer or sold with the monitor. If you mount the monitor on a wall or shelf, use a mounting kit approved by the manufacturer and follow the kit instructions.
- Slots and openings in the back and bottom of the cabinet are provided for ventilation. To ensure reliable operation of the monitor and to protect it from overheating, be sure these openings are not blocked or covered. Do not place the monitor on a bed, sofa, rug, or similar surface. Do not place the monitor near or over a radiator or heat register. Do not place the monitor in a bookcase or cabinet unless proper ventilation is provided.
- The monitor should be operated only from the type of power source indicated on the label. If you are not sure of the type of power supplied to your home, consult your dealer or local power company.
- Unplug the unit during a lightning storm or when it will not be used for long period of time. This will protect the monitor from damage due to power surges.
- Do not overload power strips and extension cords. Overloading can result in fire or electric shock.
- Never push any object into the slot on the monitor cabinet. It could short circuit parts causing a fire or electric shock. Never spill liquids on the monitor.
- Do not attempt to service the monitor by yourself; opening or removing covers can expose you to dangerous voltages and other hazards. Please refer all servicing to qualified service personnel.
- The wall socket shall be installed near the equipment and shall be easily accessible.

SPECIAL NOTES ON LCD MONITORS

The following symptoms are normal with LCD monitor and do not indicate a problem.

- Due to the nature of the fluorescent light, the screen may flicker during initial use. Turn off the Power Switch and then turn it on again to make sure the flicker disappears.
- You may find slightly uneven brightness on the screen depending on the desktop pattern you use.
- The LCD screen has effective pixels of 99.99% or more. It may include blemishes of 0.01% or less such as a missing pixel or a pixel lit all of the time.
- Due to the nature of the LCD screen, an afterimage of the previous screen may remain after switching the image, when the same image is displayed for hours. In this case, the screen is recovered slowly by changing the image or turning off the Power Switch for hours.
- If the screen suddenly flashes erratically or the backlighting fails, please contact your dealer or service center for repair. Do not attempt to repair the monitor yourself.


BEFORE YOU OPERATE THE MONITOR

FEATURES

- 59,8cm / 23.6" Wide Screen TFT Color LCD Monitor
- Crisp, Clear Display
- Ergonomic Design
- Space Saving, Compact Case Design


CHECKING THE CONTENTS OF THE PACKAGE

The product package should include the following items:



INSTALLATION INSTRUCTIONS

INSTALL



REMOVE




Figure.1. Installing and Removing the Base

POWER


POWER SOURCE:

1. Make sure that the power cord is the correct type required in your area.
2. This LCD monitor has an External universal power adaptor supply that allows operation in either 100/120V AC or 220/240V AC voltage area (No user adjustment is required.)
3. Connect the DC-power adaptor one end to your LCD monitor's DC-input port, the other end to wall-outlet.

SETTING THE MONITOR ON THE WALL

DISSEMBLING THE STAND BASE:


1. Disconnect all the cables and cords from the Monitor to prevent breakage.
2. Carefully place the Monitor face down on a soft and flat surface (blanket, foam, cloth, etc) to prevent any damage to the Monitor.
3. Press the clips on the base that holds the monitor in place.
4. Gently remove the stand base.



(For reference only)

WALL MOUNTING THE MONITOR:

1. Purchase a VESA compatible wall bracket: VESA 100×100, 4 holes, M4, 10mm, 8kg.
2. Locate your ideal Monitor position on the wall.
3. Fix the wall bracket firmly on the wall.
4. Secure the Monitor to the bracket using the 4 mount holes on the back and center of the Monitor.



NOTE:

- Please read the instructions of your specific wall bracket to properly wall mount the Monitor.
- The pitch of the mounting holes is 100mm horizontally and 100mm vertically.
- The screws type required is metric: M4, 10mm length.
- The Monitor stand base can be screwed on a table or a hard surface using the hole on the back of the stand base.
- For use only with UL listed wall mount bracket.
- Installing the LCD Monitor requires special skill that should only be performed by qualified service personnel. Customers should not attempt to do the work themselves. Hannspree bears no responsibility for improper mounting or mounting that results in accident or injury. You can ask a qualified service personnel about using an optional bracket to mount the Monitor to the wall.

MAKING CONNECTIONS

CONNECTING TO A PC

Turn off your computer before performing the procedure below.

- Connect one end of the HDMI cable to the back of the monitor and connect the other end to the computer's HDMI port.
- Connect one end of the VGA cable (optional) to the back of the monitor and connect the other end to the computer's VGA port.
- Connect one end of the HDMI to DVI cable (optional) to the back of the monitor and connect the other end to the computer's DVI port.
- Connect the audio cable between the monitor's audio input and the PC's audio output (green port).
- Plug one end of the DC power adaptor to the LCD monitor's DC input port, and the other end to Wall outlet.
- Turn on your monitor and computer.




Figure.2. Connecting to a PC

1. Power DC Input
2. Earphone
3. VGA Input
4. HDMI Input

ADJUSTING THE VIEWING ANGLE

- For optimal viewing it is recommended to look at the full face of the monitor, then adjust the monitor's angle to your own preference.
- Hold the stand so you do not topple the monitor when you change the monitor's angle.
- You are able to adjust the monitor's angle from -5to 15




Figure.3. Monitor Angle

NOTES:

- Do not touch the LCD screen when you change the angle. It may cause damage or break the LCD screen.
- Be careful not to place fingers or hands near the hinges when tilting the monitor, otherwise pinching can result.

OPERATING INSTRUCTIONS

GENERAL INSTRUCTIONS

Press the power button to turn the monitor on or off. The other control buttons are located on the front panel of the monitor (See Figure 4). By changing these settings, the picture can be adjusted to your personal preferences.

- The power adaptor should be connected.
- Connect the Signal cable from the monitor to the HDMI card.

- Press the power button to turn on the monitor. The power indicator will light up.
/ Return Auto adjustment(Analog Only, Hold on 3 sec)



Input source



[] Volume adjustment button (HDMI Input Models)



[] Brightness adjustment button






Menu / Enter



Power Button

FRONT PANEL CONTROL

- **Power Button:**
 - Press this button to switch ON/OFF of monitor's power.
- **Power Indicator:**
 - Green — Power On mode.
 - Green flicker — Power Saving mode.
- **MENU / ENTER:**
 - Turn the OSD menu on/off or enter to the previous menu
- **Adjust ▼ ▲ :**
 1. Adjust Brightness and volume when the OSD is off.
 2. Navigate through adjustment icons when OSD is ON or adjust a function when function is activated.
-  **Button:** Analog Input Models
 1. The OSD menu is used as confirmation function during start-up.
 2. The Auto adjustment function works only for VGA input. (The auto adjustment function is used to optimize the horizontal position , vertical position , clock ,and phase .)
-  **Button:** Digital Input Models
 - Press  to enter Source selections. (Selections include HDMI, etc. The actual selections may vary depending on the models. This function is only available in models with digital inputs)
 - The OSD menu is used as confirmation function during start-up.
 - Press and hold this button more than 3 seconds will start Auto Adjust function when using VGA input only. (The auto adjustment function is used to optimize the horizontal position , vertical position , clock ,and phase .)

NOTES:

- Do not install the monitor in a location near heat sources such as radiators or air ducts, or in a place subject to direct sunlight, or excessive dust or mechanical vibration or shock.
- Save the original shipping box and packing materials, as they will come in handy if you ever have to ship your monitor.
- For maximum protection, repackage your monitor as it was originally packed at the factory.
- To keep the monitor looking new, periodically clean it with a soft cloth. Stubborn stains may be removed with a cloth lightly dampened with a mild detergent solution. Never use strong solvents such as thinner, benzene, or abrasive cleaners, since these will damage the cabinet. As a safety precaution, always unplug the monitor before cleaning it.

HOW TO ADJUST A SETTINGS

BRIGHTNESS	
BRIGHTNESS	Adjust the brightness value of the display according to your preference. Select BRIGHTNESS option to adjust the brightness value..
CONTRAST	Adjust the contrast value of the display according to your preference. Select CONTRAST option to adjust the contrast value.
PRESET MODE	Select the preset mode according to your preference: PC/ MOVIE/ GAME/ ECO [The availability of this function depends upon the selected model]
ACTIVE CONTRAST	Optimal setting for high contrast images or videos. The dark and light areas of the image are automatically detected, and the contrast is enhanced to provide a clearer, sharper image. Also, you may select the ACTIVE CONTRAST option.
OVERDRIVE	Setup the display response time through the Response time function. Available settings are ON , and OFF . [This feature is limited to specific models only.]
IMAGE SETUP	
H-POSITION	Select the H-POSITION option to shift the screen image to the left or right. Enter the option and adjust the level. [For VGA only]
V-POSITION	Select the V-POSITION option to shift the screen image up or down. Enter the option and adjust the level. [For VGA only]
CLOCK	Select the CLOCK option to reduce the vertical flicker of characters on the screen. Enter the option and adjust the level. [For VGA only]
PHASE	Select the PHASE option to reduce the horizontal flicker of characters on the screen. Enter the option and adjust the level. [For VGA only]
IMAGE RATIO	When the aspect ratio of screen is distorted, you may make adjustments by using this function. WIDE indicates full screen display, which does not ensure the image is shown as is or in initial scale. 4:3 indicates scaling by the proportion of original images, which may cause the screen showing black bands. [The availability of this function depends upon the selected model]
COLOR SETUP	

5500K 6500K 9300K Low Blue Mode	Adjust the color temperature value of the display according to your preference: 5500 / 6500/ 9300 / Low Blue Mode.
USER	<p>Move the cursor to the User option and select it,</p> <ol style="list-style-type: none"> 1. To adjust the red, enter the R option and adjust the level. 2. To adjust the green, enter the G option and adjust the level. 3. To adjust the blue, enter the B option and adjust the level.

LOW BLUE MODE	Move the cursor to the Low Blue Mode option and select it.
OSD SET UP	
LANGUAGE	Select LANGUAGE option to change the language of the OSD. Enter the option and select a language. [Reference only, the OSD Language depends on the selected model]
H-POSITION	Select H-POSITION option to adjust the horizontal position of the OSD. Enter the option and adjust the level.
V-POSITION	Select V-POSITION option to adjust the vertical position of the OSD. Enter the option and adjust the level.
TIME OUT	Select TIMEOUT option to set the OSD time out from 5 to 120 seconds. Enter the option and adjust the level.
TRANSPARENCY	Select TRANSPARENCY option to adjust the transparency of the OSD. Enter the option and adjust the level(0,25,50,75,100).
RESET	
AUTO CONFIG	The auto config function is used to optimize the H-POSITION , V-POSITION , CLOCK ,and PHASE . [For VGA Input only]
AUTO COLOR	The auto color function is used to optimize the COLOR . [For VGA Input only]

RESET	Select the RESET option to reset to the monitor's default setting. This will erase the current settings. Enter the option and select On or Off.
EXTRA	
INPUT SELECT	The input select function is to enter Source selections. (Selections include VGA, HDMI, etc. The actual selections may vary depending on the models. This function is only available in models with digital inputs)
MUTE	Select the MUTE option to switch the function On or Off. [The availability of this function depends upon the selected model. Adjusting the volume while muted cancels Mute mode.]
VOLUME	Select the VOLUME option to change the volume level. Enter the option and adjust the level. [This function applies only to models with incorporated audio.] ● By high volume, risk of hearing damage exists.
DDC/CI	Select the DDC/CI option to switch the function On or Off.[Dual input mode optional]

PLUG AND PLAY

Plug & Play DDC2B Feature

- This monitor is equipped with VESA DDC2B capabilities according to the VESA DDC STANDARD.
- It allows the monitor to inform the host system of its identity and, depending on the level of DDC used, communicate additional information about its display capabilities. The DDC2B is a bidirectional data channel based on the I²C protocol. The host can request EDID information over the DDC2B channel.

THIS MONITOR WILL APPEAR TO BE NON-FUNCTIONAL IF THERE IS NO VIDEO INPUT SIGNAL. IN ORDER FOR THIS MONITOR TO OPERATE PROPERLY, THERE MUST BE A VIDEO INPUT SIGNAL.

TECHNICAL SUPPORT (FAQ)

Q & A FOR GENERAL PROBLEMS

PROBLEM & QUESTION	POSSIBLE SOLUTION
Power LED is not on	*Check if the Power Switch is in the ON position. *Power Adaptor should be connected.
No Plug & Play	*Check if the PC system is Plug & Play compatible. *Check if the Video Card is Plug & Play compatible. *Check if any plug pins on the VGA or HDMI connector is bent.
The display is too dark or too bright.	*Adjust the Contrast and Brightness Controls.
Picture bounces or a wave pattern is present in the picture	*Move electrical devices that may cause electrical interference.
The power LED is ON (Green Flicker) but there's no video or no picture.	*Computer Power Switch should be in the ON position. *Computer Video Card should be snugly seated in its slot. *Make sure monitor's video cable is properly connected to the computer. *Inspect monitor's video cable and make sure none of the pins are bent. *Make sure computer is operational by hitting the CAPS LOCK key on the keyboard while observing the CAPS LOCK LED. The LED should either turn ON or OFF after hitting the CAPS LOCK key.
Missing one of the primary colors (RED, GREEN, or BLUE)	*Inspect the monitor's video cable and make sure that none of the pins are bent.
Screen image is not centered or sized properly.	* Adjust pixel frequency CLOCK and PHASE.
Picture has color defects (White does not look white)	*Adjust RGB color or select color temperature.
The screen resolution needs to be adjusted	*Use Windows 7/ Windows 8/ Windows 10 Right click anywhere on desktop and select Properties>Settings>Screen Resolution . Use the slider to adjust the resolution and click Apply .

Addendum related to Windows 7 / Windows 8 / Windows 10

When you encounter display problem under Windows 7/ Windows 8/ Windows 10, you need to do the following:

1. Make sure your PC computer (Hardware requirement) can support Windows 7/ Windows 8/ Windows 10.
2. Make sure your video card can run Windows 7/ Windows 8/ Windows 10.
3. If your video card can support Windows 7/ Windows 8/ Windows 10, need to install the latest Windows 7/ Windows 8/ Windows 10 driver of your video card.

Suggest to do the following:

1. Install the latest Windows 7/ Windows 8/ Windows 10 video driver of your video card.
2. Try to use the recommended display resolution that is supported by the monitor.
3. If the recommended display resolution is not working, try the second recommended display resolution.

		1	2	
	35,56cm / 14" (16:9)	1366×768@60Hz	1366×768@50Hz	
	39,6cm / 15.6" (16:9)	1366×768@60Hz	1366×768@75Hz	
	40,64cm / 16" (16:9)	1366×768@60Hz	1366×768@50Hz	
	43,2cm / 17" (16:10)	1440×900@60Hz	1440×900@75Hz	
	47cm / 18.5" (16:9)	1366×768@60Hz	1366×768@75Hz	
	48,3cm / 19" (5:4)	1280×1024@60Hz	1280×1024@75Hz	
	48,3cm / 19" (16:10)	1440×900@60Hz	1440×900@75Hz	
	51cm / 20" (16:9)	1600×900@60Hz	1600×900@50Hz	
	56cm / 22" (16:10)	1680×1050@60Hz	1680×1050@50Hz	
	54,6cm / 21.5" (16:9)	1920×1080@60Hz	1920×1080@50Hz	
	58,4cm / 23" (16:9)			
	60cm / 23.6" (16:9)			
	62,5cm / 24.6 (16:9)			
	68,6cm / 27 " (16:9)			
	70cm / 27.5" (16:10)	1920×1200@60Hz	1920×1200@50Hz	

And if you still have display problem after doing the above procedure, please visit Hannspree support and Service Website: <http://www.hannspree.eu/en/monitors> Windows is a registered trademark of Microsoft Corporation.

ERROR MESSAGE & POSSIBLE SOLUTIONS

• CABLE NOT CONNECTED:

1. Check that the signal-cable is properly connected, if the connector is loose, tighten the connector's screws.
2. Check the signal-cable's connection pins for damage.

- **INPUT NOT SUPPORT :**

1. Your computer has been set to unsuitable display mode, set the computer to display mode given in the following table.

FACTORY PRESET TIMING TABLE:

MODE	RESOLUTION	HORIZONTAL FREQUENCY (KHz)	VERTICAL FREQUENCY (Hz)
1	640×400 @70Hz	31.469	70.087
2	640×480 @60Hz	31.469	59.940
3	640×480 @70Hz	36.052	70.004
4	640×480 @67Hz	35.000	66.667
5	640×480 @72Hz	37.861	72.809
6	640×480 @75Hz	37.500	75.000
7	720×400 @70Hz	31.469	70.087
8	800×600 @56Hz	35.156	56.250
9	800×600 @60Hz	37.879	60.317
10	800×600 @72Hz	48.077	72.188
11	800×600 @75Hz	46.875	75.000
12	832×624 @75Hz	49.725	75.000
13	1024×768 @60Hz	48.363	60.004
14	1024×768 @70Hz	56.476	70.069
15	1024×768 @75Hz	60.023	75.029
16	1152×870 @75Hz	68.681	75.062
17	1152×864 @75Hz	67.500	75.000
18	1280×720 @60Hz	45.000	60.000
19	1280×960 @60Hz	60.000	60.000
20	1280×960 @75Hz	74.592	74.443
21	1280×768 @60Hz	47.776	59.870
22	1280×768 @75Hz	60.289	74.893
23	1280×1024 @60Hz	63.981	60.020
24	1280×1024 @75Hz	79.976	75.025
25	1360×768 @60Hz	47.712	60.015
26	1366×768 @60Hz	47.852	59.964
27	1440×900 @60Hz	55.469	59.901
28	1440×900 @75Hz	70.635	74.984

29	1400×1050 @60Hz	64.744	59.948
30	1600×900 @60Hz	55.540	59.978
31	1680×1050 @60Hz	65.290	59.954
32	1920×1080 @60Hz	67.500	60.000

(Video mode)

MODE	RESOLUTION
1	640×480p @60Hz
2	720×480i @60Hz
3	720×480p @60Hz
4	720×576i @50Hz
5	720×576p @50Hz
6	1280×720p @60Hz
7	1920×1080i @50Hz
8	1920×1080i @60Hz
9	1920×1080p @50Hz
10	1920×1080p @60Hz

We ensure that the monitor can be lighted under interlace signal mode, but we can not guarantee the image

quality.

APPENDIX SPECIFICATIONS

LCD Panel	Driving system	TFT Color LCD
	Size	59,8cm / 23.6" Diagonal
	Pixel pitch	0.2715mm(H) ×0.2715mm(V)
Video	H-Frequency	30KHz – 83KHz
	V-Frequency	56Hz – 75Hz
Display Colors		16.7M Colors
Max. Resolution		1920 × 1080 @60Hz
Plug & Play		VESA DDC2BTM
Power consumption	ON Mode	18 W (Max)
	Power Saving Mode	≤ 0.5 W
	OFF Mode	≤ 0.3 W
Audio output		Rated Power 2.0 W rms (Per channel)
Input Terminal		VGA HDMI
Maximum Screen Size		Hor. : 521.28mm Ver. : 293.22mm
Power Source		AC Power: 100–240V 50–60Hz DC Adaptor: 12V, 2.5A
Environmental Considerations		Operating Temp:5° to 35°C Storage Temp.: -20° to 60°C Operating Humidity: 10% to 85%
Dimensions		538.83 (W)×408.06 (H)×149.71 (D) mm 21.2 "(W)×16.0"(H)×5.9 "(D)
Weight (NW)		3.1 kg (6.8 lb)

The above specification is subject to actual product specification and is subject to change without prior notice.

NOTES:

The Maximum Resolution will depends on the display card supporting. Related issue can refer to <http://www.hannspree.eu/en/monitors>. FAQ section.

Documents / Resources



[HANNspree HE247HFB Smart LED Monitor](#) [pdf] User Manual
HE247HFB Smart LED Monitor, HE247HFB, Smart LED Monitor

User's Manual