







# HUAWEI MERC-1300W-P Smart Module Controller Owner's Manual

[Home](#) » [Huawei](#) » HUAWEI MERC-1300W-P Smart Module Controller Owner's Manual 



SMART MODULE  
CONTROLLER  
Model MERC-1100/1300W-P



			
Higher Yields Module-level Optimization Increases System Energy Yield by 5% to 30%	Flexible Design Long String Design to Reduce BOS	Active Safety Firefighting and O&M Safety with Module-level Rapid Shutdown	Smart O&M Pinpointing Open Fault for Quick Troubleshooting



MERC-1100/1300W-P

**Contents**

- [1 Technical Specification](#)
- [2 Documents / Resources](#)
- [2.1 References](#)

**Technical Specification**

Technical Specification	1100W-P	MERC-1300W-P
Input		
Rated input DC power <sup>1</sup>	1100 W	1300 W
Absolute max. input voltage	125 V	
MPPT operating voltage range	12.5–105 V	
Max. short-circuit current (Isc)	20 A	
Max. efficiency	99.5%	
Weighted efficiency	99.0%	
Overvoltage category	II	
Output		
Max. output voltage	80 V	
Max. output current	22 A	
Output bypass <sup>2</sup>	Yes	
Safety output voltage <sup>3</sup>	1 V	
Standards Compliance		
Safety	IEC62109-1 (class II safety)	
RoHS	Yes	
General Specification		
Dimensions (W X H X D)	149 mm x 104 mm x 48.8 mm (5.9 in. x 4.1 in. x 1.9 in.)	
Weight (including wires)	1.0 kg (2.2 lb.)	
Installation kit (optional)	PV Module Frame Plate/T-shaped Bolt <sup>4</sup>	
Input connector	Staubli MC4	
Input wire length	0.1 m (+/-) (short-input-cable version) <sup>5</sup>	
Output connector	Staubli MC4	
Output wire length	0.1 m (+), 5.1 m (-) (short-input-cable version) <sup>5</sup>	
Operating temperature	–40°C to +85°C <sup>6</sup>	
Relative humidity	0%–100%	
IP rating	IP68	
Compatible inverters	SUN2000-12-25K-MB0, SUN2000-12-25KTL-M5, SUN2000-30-40KTL-M3, SUN2000-50KTL-M3, SUN5000-150K-MG0	

PV System Design <sup>7/8/9</sup>	SUN2000- 1 2~25K-MB0	SUN2000- 1 2~25KTL-M5	SUN2000- 3 0~40KTL-M3	SUN2000- 5 0KTL-M3	SUN5000- 150K-MG0
Min. string length (power optimizers )	8	8	8	8	12
Max. string length (power optimizers)	25	25	25	20	20
Max. DC power per string	20,000 W	20,000 W	20,000 W	20,000 W	20,000 W



1. The maximum power of PV module at STC shall NOT exceed the “Rated input DC power” of MERC-1100/1300W-P. PV Modules with up to  $\pm 10\%$  power tolerance are allowed.
2. Any power optimizer, which is connected to an operating inverter in a PV string, will be bypassed when it fails.
3. When the MERC-1100/1300W-P is disconnected from inverter or when the inverter is off, its output voltage will become 1 V.
4. It is for PV module frame/extruded aluminum profile racking system installation.
5. Pay attention to the PV module wire length. To match PV modules with a split junction box and short output wire, the long-input-cable version (input wire: 1.3 m (+/-); output wire: 0.1 m (+)/2.9 m (-)) of MERC-1100/1300W-P is available upon request.
6. When the operating temperature of the MERC-1100/1300W-P reaches 70 °C to 85 °C, it may shut down due to over-temperature protection and report an over-temperature alarm.  
After the temperature decreases, it can automatically resume working without causing any damage.
7. Each PV module under the same inverter must be equipped with a MERC-1100/1300W-P.
8. 8SUN2000-450W-P2/600W-P and MERC-1100/1300W-P can NOT be used in mixture under the same Smart Energy/PV Controller.
9. It is recommended that strings under the same inverter have an equal capacity. If this is not feasible, the capacity difference between strings under the same inverter must not exceed 2 kW. Otherwise, the energy yield will be reduced.

**Disclaimer:** The preceding values are measured by an internal laboratory of Huawei in a specific environment. The actual values may vary with products, software versions, usage conditions, and environmental factors.





[HUAWEI MERC-1300W-P Smart Module Controller](#) [pdf] Owner's Manual  
MERC-1300W-P Smart Module Controller, MERC-1300W-P, Smart Module Controller, Module Controller, Controller

References

- [User Manual](#)

Manuals+. [Privacy Policy](#)

This website is an independent publication and is neither affiliated with nor endorsed by any of the trademark owners. The "Bluetooth®" word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. The "Wi-Fi®" word mark and logos are registered trademarks owned by the Wi-Fi Alliance. Any use of these marks on this website does not imply any affiliation with or endorsement.