



iclever IC-BK03 Tri-folding Universal Magnetic Control Bluetooth Keyboard Instruction Manual

[Home](#) » [iclever](#) » iclever IC-BK03 Tri-folding Universal Magnetic Control Bluetooth Keyboard Instruction Manual



Contents

- 1 [iclever IC-BK03 Tri-folding Universal Magnetic Control Bluetooth Keyboard](#)
- 2 [Product Information](#)
- 3 [Special Features and Options](#)
- 4 [Package Contents](#)
- 5 [Indicator Lights Description](#)
- 6 [Specification](#)
- 7 [Important Notification](#)
- 8 [Bluetooth Keyboard Function](#)
- 9 [Bluetooth Keyboard Characteristics](#)
- 10 [Bluetooth Keyboard Pairing](#)
- 11 [Charge the keyboard](#)
- 12 [Energy Saving Sleep Mode](#)
- 13 [Safety Caution](#)
- 14 [Cleaning and Maintenance](#)
- 15 [Troubleshooting](#)
- 16 [FAQ](#)
 - 16.1 [Q: How do I know if the keyboard is fully charged?](#)
 - 16.2 [Q: How do I switch between capital and small letters?](#)
- 17 [Documents / Resources](#)
 - 17.1 [References](#)
- 18 [Related Posts](#)

INSTRUCTION MANUAL

IC-BK03

www.iclever.us

Product Information

The Tri-folding Universal Magnetic Control Bluetooth Keyboard, model IC-BK03, is a versatile keyboard that can be used with various devices. It features indicator lights for power, charging, Caps Lock, and Bluetooth status. The keyboard has a micro charging port for easy charging.

Special Features and Options

The keyboard is very convenient in storage and carrying, also the protective case can protect it conveniently.

Package Contents

- 1 x Bluetooth Keyboard
- 1 x USB Charging Cable
- 1 x Protective Case
- 1 x User Manual
- 1 x One Year Warranty Card

Indicator Lights Description



① **Power indicator:** Unfold the keyboard, green power indicator will be on for 3s and then turns off.

Charging indicator: The red charging indicator will be stably on when charging it. It automatically turns off after being fully charged.

② **Caps Lock indicator:** Press Caps Lock key to switch capital and small letters. The blue Caps Lock indicator is on when you're inputting capital letters.

Bluetooth Status indicator: Press Fn + C keys, this indicator will flash. It turns off until the keyboard well connects with your device.

③ **Micro charging port:** Used for charging the keyboard.




















Specification

1. Standard Micro interface
2. Operating distance is up to 10 meters
3. Modulation system: GFSK
4. Operating voltage: 3.0-4.2V
5. Operating current: 2.5mA
6. Standby current < 0.3mA
7. Sleep current < 40uA
8. Charging current $\geq 200\text{mA}$
9. Standby time > 218 days
10. Charging time < 2 hours
11. Lithium battery capacity: 210mA
12. Uninterrupted working time: 84 hours
13. Lithium battery life: 3 years
14. Key force: $60 \pm 10\text{g}$
15. Key lifespan: 3 million strokes
16. Operating temperature: $10 \pm 55^{\circ}\text{C}$
17. Keyboard unfold size: 251.7 x 89.6 x 6.6 mm

Important Notification

1. 3 in 1 keyboard: After connecting with the device, you must press Fn + relative OS key(Q for Android, W for Windows, E for IOS) to select operating system, otherwise all these keys' function are invalid.
2. When use the keyboard again, unfold the left and right keyboard area, and then press any key to make it automatically connect with your device again.
3. You can only use these functions by pressing Fn and the same color key together.
4. Press Fn + C key to let the keyboard ready for pairing and press them again to disconnect its ready pairing condition.

Bluetooth Keyboard Function

Key icon	Fn + key icon function in IOS system	Fn + key icon function in Android system	Fn + key icon function in Windows system	Fn+Shift+key icon function in Windows system
	Home	Home	ESC	Web browser
	Search	Search	F1	Search
	Select all	Select all	F2	Select all
	Copy	Copy	F3	Copy
	Paste	Paste	F4	Paste
	Cut	Cut	F5	Cut
	Previous track	Previous track	F6	Previous track
	Play/pause	Play/pause	F7	Play/pause
	Next track	Next track	F8	Next track
	Volume down	Volume down	F9	Volume down
	Volume up	Volume up	F10	Volume up
	No function	No function	F11	No function
	No function	No function	F12	
	Virtual keyboard	Virtual keyboard	No function	
	First line	Page heading	Page heading	
	Page heading	Page up	Page up	
	Page footing	Page down	Page down	
	End of line	Page footing	Page footing	
	Function Combination key	Function Combination key	Function Combination key	

Bluetooth Keyboard Characteristics

1. Built-in USA BROADCOM Bluetooth module 3.0
2. Suitable for Android & Windows & IOS systems tablets, smartphones etc.
3. Full automatic power on/off design, easy and flexible to operate
4. Micro interface, easy to charge
5. Energy saving keyboard with sleep mode
6. Built-in rechargeable lithium battery
7. Front: plastic; Backboard: aluminum alloy
8. Tri-fold design, convenient to carry
9. Light weight, quiet keystrokes
10. Ergonomic design greatly improves touch feeling
11. Proper protective case protects your device perfectly. It can be used as a great stand too.

Bluetooth Keyboard Pairing

Pairing with IOS system

1. Unfold the keyboard, green power indicator will be on for 3s and then turns off.
2. Press Fn + C key, Bluetooth indicator will flash.
3. Open the Bluetooth App of tablet, the tablet will automatically or manually search Bluetooth enabled devices. Find the keyboard name(iClever IC-BK03 Keyboard) and click to automatically connect them.
4. It will display success connection and Bluetooth indicator in the keyboard will automatically turn off.

Pairing with Android system (e.g. Samsung)

1. Unlock the tablet, log in “home page” or “application” interface.
2. Click “Setting” icon to step into setting interface, and then slide “Bluetooth switch” icon to make it green. The tablet goes into “searching for pairing” condition.
3. Unfold the left and right keyboard area to power on the keyboard, and then press connection keys(Fn +C) to step into pairing condition.
4. The tablet will display keyboard name(iClever IC-BK03 Keyboard), click this device’s name.
5. It’s no need to input password. Bluetooth keyboard name displays in blue color to show it is well connected with your tablet.

Pairing with Windows system (e.g. Surface)

1. Unlock the tablet and log in “start” interface.
2. Use fingers to touch the black edge of screen and slide from right to left, then click “Setting” icon.
3. After stepping into “Setting” menu, click the bottom right icon of menu “change computer setting”.
4. Step into computer’s setting interface and click “device”, then click “add device” in the “device” interface. The tablet goes into “searching for pairing” condition.
5. Unfold the left and right keyboard area to power on the keyboard, and then press connection keys(Fn +C) to step into pairing condition.
6. The tablet will display keyboard name(iClever IC-BK03 Keyboard), click this device’s name.
7. It’s no need to input password. Bluetooth keyboard name displays in blue color to show it is well connected with your tablet.

Charge the keyboard

- To charge this keyboard, please connect it to a free USB port on your PC or USB AC adapter via the USB charging cable. (Output: DC 5V/500mA)
- The red charging indicator will be stably on when charging it. It automatically turns off after being fully charged.

Energy Saving Sleep Mode

The keyboard will enter sleep mode after being idle for about 15 minutes. You can press and hold any key for 3s to activate it.

Safety Caution

1. Keep the keyboard away from sharp objects.
2. Keep it away from microwave radiation source.
3. Do not place heavy object on the keyboard.
4. Do not force or distort the keyboard.
5. Keep it away from oil, chemical or any other organic liquid.

Cleaning and Maintenance

- Clean the keyboard with alcohol or alcohol based disinfectant via a dry cloth.
- In order to extend battery lifespan, only charge the keyboard while its power indicator flashes.
- You must charge the keyboard via its original power line when it is working, or it may cause messy code and malfunction.

Troubleshooting

A. Unable to connect

1. Make sure the keyboard is on.
2. Make sure the keyboard is in operating distance(within 10 minutes).
3. Make sure the battery can work(Power indicator is blinking red, which shows you need to charge the keyboard).
4. Make sure the tablet and keyboard Bluetooth is turned on.

B. Unable to charge the keyboard

1. Make sure the USB cable is connected correctly to the keyboard and the power source.
2. Make sure the wall charger is plugged into the power outlet.

Warm tip: The output voltage and current of power adapter can't surpass DC 5V/500mA, or it will damage the battery and keyboard.

FAQ


Q: How do I know if the keyboard is fully charged?

A: The red charging indicator will turn off automatically after the keyboard is fully charged.

Q: How do I switch between capital and small letters?

A: Press the Caps Lock key to switch between capital and small letters. The blue Caps Lock indicator will be on when inputting capital letters.

Documents / Resources

	<p>iclever IC-BK03 Tri-folding Universal Magnetic Control Bluetooth Keyboard [pdf] Instruction Manual</p> <p>IC-BK03 Tri-folding Universal Magnetic Control Bluetooth Keyboard, IC-BK03, Tri-folding Universal Magnetic Control Bluetooth Keyboard, Universal Magnetic Control Bluetooth Keyboard, Magnetic Control Bluetooth Keyboard, Control Bluetooth Keyboard, Bluetooth Keyboard, Keyboard</p>
---	--

References

-  [Manual-Hub.com - Free PDF manuals!](#)
- [User Manual](#)

[Manuals+.](#) [Privacy Policy](#)

This website is an independent publication and is neither affiliated with nor endorsed by any of the trademark owners. The "Bluetooth®" word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. The "Wi-Fi®" word mark and logos are registered trademarks owned by the Wi-Fi Alliance. Any use of these marks on this website does not imply any affiliation with or endorsement.