



idx Firmware Instruction Manual

[Home](#) » [idx](#) » idx Firmware Instruction Manual 

idx Firmware

VL-2000S Technical Bulletin

May 1, 2019

Contents

- [1 Firmware Update \(Compatibility w/ IPL Series\)](#)
 - [1.1 Firmware Update Needed \(Serial Number\):](#)
- [2 Hardware Requirements:](#)
- [3 Firmware Update Instruction:](#)
- [4 Documents / Resources](#)
- [5 Related Posts](#)

Firmware Update (Compatibility w/ IPL Series)

The new PowerLink technology in both IPL-98 & IPL-150 allows for up to four battery series to be stacked charged when used with the VL-2000S charger. To take advantage of this new feature, current owners of the VL-2000S charger will have to install the newest firmware.

* Update not required for serial numbers starting with VDXCA91.



Firmware Update Needed (Serial Number):

VDXCA81*****

A71*****

A61*****

Hardware Requirements:

- Windows PC with at least 1x USB port
- USB Flash Drive (blank)

Firmware Update Instruc on:

1. Download firmware (.zip) from the link provided.
2. Unzip and copy the 2 files to the root folder of the blank USB flash drive.
3. Remove all ba series and the AC cable from the charger and wait for all LEDs to turn off.
4. Insert the USB flash drive with the firmware into the USB port on the side of the charger.
5. Plug in the AC cable.
6. The charger will boot up with all LED lit solid for 3 sec, and then will blink during the install.
Do not remove the USB flash drive during installation (LED blinking)
7. A er a few seconds, LED will turn off, and then the install on is complete.
8. VL-2000S can now stack charge!


For more information, please contact IDX customer service at (310) 328-2850.



Torrance, CA 90501
t: (310) 328-2850 f: (310) 328-8202 e: idx.usa@idx.tv



Documents / Resources

	<p>idx Firmware [pdf] Instruction Manual Firmware, 2000S</p>
---	--