



Contents [[hide](#)]

- 1 [iskydance V1 Plus RT1 Single Color LED Controller Kit](#)
- 2 [Feature](#)
- 3 [Technical Parameters](#)
- 4 [Mechanical Structures and Installations](#)
- 5 [Wiring Diagram](#)
- 6 [Remote function](#)
- 7 [Match Remote Control \(two match ways\)](#)
- 8 [Light on/off fade time](#)
- 9 [Dimming Curve](#)
- 10 [Malfunctions analysis & troubleshooting](#)
- 11 [Safety information](#)
- 12 [Documents / Resources](#)
 - 12.1 [References](#)
- 13 [Related Posts](#)


iskydance

iskydance V1 Plus RT1 Single Color LED Controller Kit



Model No.: V1 + RT1

channels constant voltage/Touch color wheel/Step-less dimming/Wireless remote, 30m distance



FC CE RoHS EMC RED

Feature

- Remote control or connected with an external push switch to achieve on/off and dimming functions
- Ultra-sensitive brightness adjustment touch wheel
- Smooth dimming and switching without any flickering
- 4 scene memory
- Auto-transmitting function: The Controller automatically transmits a signal to another controller with a 30m control distance
- Light on/off fade time 3s selectable

Technical Parameters

LED Receiver's Input and Output	
Input voltage	5-36VDC
Input current	8.5A
Output voltage	5-36VDC
Output current	1CH,8A
Output power	40W/96W/192W/288W (5V/12V/24V/36V)
Output type	Constant voltage

Dimming data	
Dimming level	4096 levels
Dimming range	0 -100%
Dimming curve	Logarithmic
PWM Frequency	2000Hz

Warranty and Protection	
Warranty	5 years
Protection	Reverse Polarity


LED Remote's Input and Output	
Output signal	RF(2.4GHz)
Working voltage	3VDC(AAAx2)
Working current	5mA
Standby current	10μA
Standby time	2 year
Remote distance	30m

Safety and EMC	
EMC standard (EMC)	ETSI EN 301 489-1 V2.2.3 ETSI EN 301 489-17 V3.2.4
Safety standard(LVD)	EN 62368-1:2020+A11:2020
Radio Equipment(RED)	ETSI EN 300 328 V2.2.2
Certification	CE, EMC, LVD, RED


Environment	
Operation temperature	Ta: -30 OC ~ +55 OC

Case temperature (Max.Tc	c: +85OC
IP rating	IP20

Mechanical Structures and Installations













Wiring Diagram



Remote function



-  : Turn on/off light.
-  : Touch to change brightness.
-   : Adjust brightness, short press 10 levels, long press 1-6s for continuous 256 levels adjustment.
-  : Small night brightness (10%).
-  : Turn off light after 30s, long press 2s will turn off light after 60s.
-     : 25%, 50%, 75%, 100% brightness.
-     : Short press recall the scene, long press 2s save current brightness into S1/2/3/4. the LED indicator display green when save OK.

Match Remote Control (two match ways)

The end user can choose the suitable match/delete methods. Two options are offered for selection:

Use the controller's Match key

Match:

Short-press-press press match key, immediately press the on/off key of the remote.

Delete:

Switch off the power, then switch on the power, repeat. Immediately short-press-press press on/off key 5 times on the remote.

The light blinks 5 times means all matched remotes were deleted.

Use Power Restart

Match:

Switch off the power, then switch on the power, repeat.

Immediately short-press-press press on/off key 3 times on the remote.

The light blinks 3 times means the match is successful.

Delete:


Press and hold the match key for 5 seconds to delete all matches. The light blinks 5 times means all matched remotes were deleted.

Light on/off fade time

Long press match key 5s, then short press match key 3 times, the light on/off time will be set to 3s, the indicator light blink 3 times.

Long press match key 10s, restore factory default parameter, the light on/off time also restore to 0.5s.

Dimming Curve



Malfunctions analysis & troubleshooting

Malfunctions	Causes	Troubleshooting
No light	<ol style="list-style-type: none">1. No power.2. Wrong connection or insecure.	<ol style="list-style-type: none">1. Check the power.2. Check the connection.
Uneven intensity between front and rear, with a voltage drop	<ol style="list-style-type: none">1. The output cable is too long.2. Wire diameter is too small.3. Overload beyond power supply capability.4. Overload beyond controller capability.	<ol style="list-style-type: none">1. Reduce cable or loop supply.2. Change wider wire.3. Replace the higher power supply.4. Add power repeater.


No response from the remote	<ol style="list-style-type: none"> 1. The battery has no power. 2. Beyond controllable distance. 3. The controller did not match the remote. 	<ol style="list-style-type: none"> 1. Replace the battery. 2. Reduce remote distance. 3. Re-match the remote.
-----------------------------	---	--

Safety information

1. The product shall be installed and serviced by a qualified person.
2. The product is non-waterproof. Please avoid the sun and rain.
3. Good heat dissipation will prolong the working life of the controller. Please ensure good ventilation.
4. Please check if the output voltage of any power supplies used comply with the working voltage of the product.
5. Ensure all wire connections and polarities are correct and secure before applying power to avoid any damages to the LED lights.
6. If a fault occurs, please return the product to your supplier. Do not attempt to fix this product by yourself.

User Manual Ver 1.0.4 V1+ RT1 Single Color LED Controller Kit

Documents / Resources


	iskydance V1 Plus RT1 Single Color LED Controller Kit [pdf] Owner's Manual V1 Plus RT1 Single Color LED Controller Kit, V1 Plus RT1, Single Color LED Controller Kit, LED Controller Kit, Controller Kit
---	---

References

- [User Manual](#)

Related Posts

[5W Single Color LED Controller Owner's Manual](#)



DIM - Z SINGLE COLOR LED CONTROLLER Control
Single Color LED Strip PRODUCT PARAMETERS
PRODUCT NAME single Color...

[iskydance V1-W Single Color LED Mini RF Controller Instruction Manual](#)



iskydance V1-W Single Color LED Mini RF Controller
Model List Model Photo Power Connector LED

Connector V1-W Red/Black...



[iled CUIL.SC11 Dual Color LED Controller Kit Instruction Manual](#)

iled CUIL.SC11 Dual Color LED Controller Kit Product
Information: The product is a LED light with a color...

[iskydance V1 Single Color LED Controller Instruction Manual](#)



iskydance V1 Single Color LED Controller Features 4096
levels 0-100% dimming smoothly without any flash.

Match with RF...

■ iskydance

◆ Controller Kit, iskydance, LED Controller Kit, Single Color LED Controller Kit, V1 Plus RT1, V1 Plus RT1 Single Color LED Controller Kit

Leave a comment

Your email address will not be published. Required fields are marked *

Comment *

Name

Email

Website

☐ Save my name, email, and website in this browser for the next time I comment.

Post Comment

Search:

e.g. whirlpool wrf535swhz

Search

Manuals+ | Upload | Deep Search | Privacy Policy | @manuals.plus | YouTube

This website is an independent publication and is neither affiliated with nor endorsed by any of the trademark owners. The "Bluetooth®" word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. The "Wi-Fi®" word mark and logos are registered trademarks owned by the Wi-Fi Alliance. Any use of these marks on this website does not imply any affiliation with or endorsement.