

JUNIPER
NETWORKS
JSA 7.5.0 Update
Package 7 Interim
Fix 06 Software



Juniper JSA 7.5.0 Update Package 7 Interim Fix 06 Software User Guide

[Home](#) » [JUNIPer](#) » Juniper JSA 7.5.0 Update Package 7 Interim Fix 06 Software User Guide 

Contents

- 1 Juniper JSA 7.5.0 Update Package 7 Interim Fix 06 Software
- 2 Product Information
- 3 Product Usage Instructions
- 4 Frequently Asked Questions
- 5 06 Software Update
- 6 Installation Wrap-up
- 7 Clearing the Cache
- 8 Known Issues and Limitations
- 9 Resolved Issues
- 10 Documents / Resources
 - 10.1 References
- 11 Related Posts

JUNIPER
NETWORKS

Juniper JSA 7.5.0 Update Package 7 Interim Fix 06 Software



Product Information

Specifications:

- Product Name: JSA 7.5.0 Update Package 7 Interim Fix 06 SFS
- Published Date: 2024-03-12
- System Requirements: SSH access, 5 GB free space in /store/tmp
- Compatibility: JSA versions at JSA 7.3.x and later

Product Usage Instructions

Installing the JSA 7.5.0 Update Package 7 Interim Fix 06 Software Update:

1. Visit [Juniper Support Downloads](#).
2. Using SSH, log into your system as the root user.
3. Verify you have at least 5 GB of space in /store/tmp for the JSA Console.

Installation Wrap-up:

1. After the patch completes and you exit the installer, type: `umount /media/updates`

Clearing the Cache:

1. On your desktop, select Start > Control Panel.
2. Double-click the Java icon.
3. In the Temporary Internet Files pane, click View.
4. Select all Deployment Editor entries in the Java Cache Viewer window, then click Delete.
5. Close the window and click OK.
6. Open your web browser and clear the cache.
7. Log in to JSA.

Known Issues and Limitations:

If the interface admin password fails to be set correctly, follow these steps:

1. Change the admin account password in the command-line interface.
2. To change the admin user password, use SSH to log in to the JSA Console as the root user.
3. Type: `/opt/qradar/support/changePasswd.sh -a`
4. Follow the prompts to enter and confirm the new password.
5. To restart the user interface, type: `systemctl restart tomcat`

Frequently Asked Questions

- **Q: How can I check if my system meets the space requirements for JSA Console?**
 - A: You can verify you have enough space (5 GB) in /store/tmp by using SSH to log in and checking the available disk space.
- **Q: What should I do if the admin password is not set correctly?**
 - A: If the admin password is not set correctly, change it using the command-line interface and restart the Tomcat service as instructed in the manual.

Installing the JSA 7.5.0 Update Package 7 Interim Fix

06 Software Update

JSA 7.5.0 Update Package 7 Interim Fix 06 resolves reported issues from users and administrators from previous JSA versions. This cumulative software update fixes known software issues in your JSA deployment. JSA software updates are installed by using an SFS file. The software update can update all appliances attached to the JSA Console.

The 7.5.0.20240225123426.sfs file can upgrade the following JSA version to JSA 7.5.0 Update Package 7 Interim Fix 06:

- JSA 7.5.0 Update Package 7
- JSA 7.5.0 Update Package 7 Interim Fix 01
- JSA 7.5.0 Update Package 7 Interim Fix 02
- JSA 7.5.0 Update Package 7 Interim Fix 03
- JSA 7.5.0 Update Package 7 Interim Fix 04
- JSA 7.5.0 Update Package 7 Interim Fix 05

This document does not cover all the installation messages and requirements, such as changes to appliance memory requirements or browser requirements for JSA. For more information, see the [Juniper Secure Analytics Upgrading JSA to 7.5.0](#).

Ensure that you take the following precautions:

- Back up your data before you begin any software upgrade. For more information about backup and recovery, see the [Juniper Secure Analytics Administration Guide](#).
- To avoid access errors in your log file, close all open JSA webUI sessions.
- The software update for JSA cannot be installed on a managed host that is at a different software version from the Console. All appliances in the deployment must be at the same software revision to update the entire deployment.
- Verify that all changes are deployed on your appliances. The update cannot install on appliances that have changes that are not deployed.

To install the JSA 7.5.0 Update Package 7 Interim Fix 06 software update:

1. Download the 7.5.0.20240225123426.sfs from the Juniper Customer Support website.
<https://support.juniper.net/support/downloads/>
2. Using SSH, log into your system as the root user.
3. To verify you have enough space (5 GB) in /store/tmp for the JSA Console, type the following command: `df -h /tmp /startup /store/transient | tee diskchecks.txt`
 - Best directory option: /storetmp It is available on all appliance types at all versions. In JSA 7.5.0 versions /store/tmp is a symlink to the /storetmp partition.
4. To create the /media/updates directory, type the following command: `mkdir -p /media/updates`
5. Using SCP, copy the files to the JSA Console to the /startup directory or a location with 5 GB of disk space.

6. Change to the directory where you copied the patch file.

For example, cd /storetmp

7. Unzip the file in the /storetmp directory using the bunzip utility: bunzip2 7.5.0.20240225123426.sfs.bz2

8. To mount the patch file to the /media/updates directory, type the following command: mount -o loop -t squashfs /storetmp/7.5.0.20240225123426.sfs /media/updates

9. To run the patch installer, type the following command: /media/updates/installer

10. Using the patch installer, select all.

- The all option updates the software on all appliances in the following order:
- Console
- No order required for remaining appliances. All remaining appliances can be updated in any order the administrator requires.
- If you do not select the all option, you must select your console appliance. If your Secure Shell (SSH) session is disconnected while the upgrade is in progress, the upgrade continues. When you reopen your SSH session and rerun the installer, the patch installation resumes.

Installation Wrap-up

1. After the patch completes and you have exited the installer, type the following command: umount /media/updates
2. Clear your browser cache before logging in to the Console.
3. Delete the SFS file from all appliances.

Results

A summary of the software update installation advises you of any managed host that were not updated. If the software update fails to update a managed host, you can copy the software update to the host and run the installation locally. After all hosts are updated, administrators can send an email to their team to inform them that they will need to clear their browser cache before logging in to the JSA.

Clearing the Cache

After you install the patch, you must clear your Java cache and your web browser cache before you log into the JSA appliance.

Before you begin

Ensure that you have only one instance of your browser open. If you have multiple versions of your browser open, the cache might fail to clear. Ensure that the Java Runtime Environment is installed on the desktop system that you use to view the user interface. You can download Java version 1.7 from the Java website: <http://java.com/>.

About this task

If you use the Microsoft Windows 7 operating system, the Java icon is typically located under the Programs pane.

To clear the cache:

1. Clear your Java cache:
 - a. On your desktop, select Start > Control Panel.
 - b. Double-click the Java icon.
 - c. In the Temporary Internet Files pane, click View.
 - d. On the Java Cache Viewer window, select all Deployment Editor entries.
 - e. Click the Delete icon.
 - f. Click Close.
 - g. Click OK.
2. Open your web browser.
3. Clear the cache of your web browser. If you use the Mozilla Firefox web browser, you must clear the cache in the Microsoft Internet Explorer and Mozilla Firefox web browsers.
4. Log in to JSA.

Known Issues and Limitations

The known issue addressed in the JSA 7.5.0 Update Package 7 Interim Fix 06 are listed below:

- When a JSA system is being built and a reboot occurs during the install configuration, the User Interface admin password can sometimes fail to be set correctly.

Workaround:

Change the admin account password in the command-line interface.

NOTE: This procedure requires that you restart the Tomcat service and deploy changes, resulting in a temporary loss of access to the JSA user interface while services restart. Administrators can complete this procedure during a scheduled maintenance window as users are logged out, exports in the process are interrupted, and scheduled reports might need to be restarted manually.

If you do not have access to the admin account from the user interface, it can be necessary to change the admin password from the command-line interface.

1. Using SSH, log in to the JSA Console as the root user.
2. To change the admin user password, type: `/opt/radar/support/changePasswd.sh -a`
3. Enter the new password as prompted.
4. Confirm the new password.

```
[root@qr750-3199-29271 ~]# /opt/qradar/support/changePasswd.sh -a
Please enter the new admin password.
Password:
```

```
Confirm password:
The admin password has been changed.
```

5. To restart the user interface, type:

systemctl restart tomcat

NOTE: This command works on JSA versions at JSA 7.3.x and later

6. Log in to the user interface as an administrator.

7. Click Admin tab > Advanced > Deploy Full Configuration.

Important:

Performing a Deploy Full Configuration results in services being restarted. While services are restarting, event processing stops until services restart. Scheduled reports that are in progress need to be manually restarted by users. Administrators with strict outage policies are advised to complete the Deploy Full Configuration step during a scheduled maintenance window for their organization.

Results:

After the service restarts, the admin account password is changed.

- Managed WinCollect 7 agents cannot receive updates from encrypted JSA Managed Hosts with JSA 7.5.0 Update Package 7 Interim Fix 05 or later.


Resolved Issues

The resolved issues addressed in the JSA 7.5.0 Update Package 7 Interim Fix 06 are listed below:

- False Positive offenses are produced where rules use reference sets not conditions.
- Dropped events in log source protocol queue after upgrade to JSA 7.5.0 Update Package 7.
- Qualys and Nessus scans won't run after installing JSA 7.5.0 Update Package 7 Interim Fix 03.

Juniper Networks, the Juniper Networks logo, Juniper, and Junos are registered trademarks of Juniper Networks, Inc. in the United States and other countries. All other trademarks, service marks, registered marks, or registered service marks are the property of their respective owners. Juniper Networks assumes no responsibility for any inaccuracies in this document. Juniper Networks reserves the right to change, modify, transfer, or otherwise revise this publication without notice. Copyright © 2024 Juniper Networks, Inc. All rights reserved

Documents / Resources

 Release Notes <small>JSA 7.5.0 Update Package 7 Interim Fix 06 05/2024</small>	Juniper JSA 7.5.0 Update Package 7 Interim Fix 06 Software [pdf] User Guide JSA 7.5.0 Update Package 7 Interim Fix 06 Software, 7.5.0 Update Package 7 Interim Fix 06 Software, Update Package 7 Interim Fix 06 Software, Package 7 Interim Fix 06 Software, 7 Interim Fix 06 Software, Fix 06 Software, Software
--	--

References

- [Downloads](#)
- [Juniper Secure Analytics Administration Guide | JSA 7.5.0 | Juniper Networks](#)
- [Upgrading Juniper Secure Analytics to 7.5.0 | JSA 7.5.0 | Juniper Networks](#)
- [User Manual](#)

[Manuals+](#), [Privacy Policy](#)

This website is an independent publication and is neither affiliated with nor endorsed by any of the trademark owners. The "Bluetooth®" word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. The "Wi-Fi®" word mark and logos are registered trademarks owned by the Wi-Fi Alliance. Any use of these marks on this website does not imply any affiliation with or endorsement.